
PyPCAPKit

Release 0.15.1.post1

Jarry Shaw

Jun 19, 2020

CONTENTS

1	Stream PCAP File Extractor	3
1.1	Library Foundation	3
1.2	User Interface	21
1.3	Protocol Family	23
1.4	Reassembly Packets & Datagrams	232
1.5	Core Utilities	243
1.6	Dump Utilities	248
1.7	Compatibility Tools	250
1.8	Utility Functions & Classes	256
1.9	Constant Enumerations	266
1.10	Web Crawlers for Constant Enumerations	337
1.11	Library Index	366
2	Command Line Interface	367
3	About	369
3.1	Module Structure	369
3.2	Engine Comparison	370
4	Installation	371
5	Samples	373
5.1	Usage Samples	373
5.2	CLI Samples	374
6	Indices and tables	375
	Python Module Index	377
	Index	381

The *PyPCAPKit* project is an open source Python program focus on PCAP parsing and analysis, which works as a stream PCAP file extractor. With support of *DictDumper*, it shall support multiple output report formats.

Important: The whole project supports **Python 3.4** or later.

STREAM PCAP FILE EXTRACTOR

pcapkit is an independent open source library, using only *DictDumper* as its formatted output dumper.

There is a project called *jspcap* works on *pcapkit*, which is a command line tool for PCAP extraction.

Unlike popular PCAP file extractors, such as *Scapy*, *DPKT*, *PyShark*, and etc, *pcapkit* uses streaming strategy to read input files. That is to read frame by frame, decrease occupation on memory, as well as enhance efficiency in some way.

1.1 Library Foundation

pcapkit.foundation is a collection of foundations for *pcapkit*, including PCAP file extraction tool Extrator, application layer protocol analyser Analysis, and TCP flow tracer TraceFlow.

1.1.1 Analyser for Application Layer

pcapkit.foundation.analysis works as a header quarter to analyse and match application layer protocol. Then, call corresponding modules and functions to extract the attributes.

`pcapkit.foundation.analysis._analyse_ftp(file, *args, seekset=0, **kw)`
Analyse FTP packet.

Parameters

- **file** (*io.BytesIO*) – source data stream
- **length** (*Optional[int]*) – packet length

Keyword Arguments **seekset** (*int*) – original file offset

Returns If the packet is FTP, returns *True* and parsed FTP packet; otherwise returns *False* and *None*.

Return type *Tuple[bool, Optional[HTTPv1]]*

`pcapkit.foundation.analysis._analyse_httpv1(file, *args, seekset=0, **kw)`
Analyse HTTP/1.* packet.

Parameters

- **file** (*io.BytesIO*) – source data stream
- **length** (*Optional[int]*) – packet length

Keyword Arguments **seekset** (*int*) – original file offset

Returns If the packet is HTTP/1.*, returns `True` and parsed HTTP/1.* packet; otherwise returns `False` and `None`.

Return type `Tuple[bool, Optional[HTTPv1]]`

`pcapkit.foundation.analysis._analyse_httpv2` (*file*, **args*, *seekset=0*, ***kw*)
Analyse HTTP/2 packet.

Parameters

- **file** (*io.BytesIO*) – source data stream
- **length** (*Optional[int]*) – packet length

Keyword Arguments **seekset** (*int*) – original file offset

Returns If the packet is HTTP/2, returns `True` and parsed HTTP/2 packet; otherwise returns `False` and `None`.

Return type `Tuple[bool, Optional[HTTPv1]]`

`pcapkit.foundation.analysis.analyse` (*file*, *length=None*, *, *termination=False*)
Analyse application layer packets.

Parameters

- **file** (*io.BytesIO*) – source data stream
- **length** (*Optional[int]*) – packet length

Keyword Arguments **termination** (*bool*) – If terminate parsing application layer protocol.

Returns Parsed application layer protocol.

Return type *Protocol*

Notes

Currently, the analysis processes in following order:

1. *FTP*
2. *HTTP/1.**
3. *HTTP/2*

and *Raw* as the fallback result.

1.1.2 Extractor for PCAP Files

`pcapkit.foundation.extraction` contains *Extractor* only, which synthesises file I/O and protocol analysis, coordinates information exchange in all network layers, extracts parameters from a PCAP file.

Todo: Implement engine support for `pypcap` & `pypcapfile`.

```
class pcapkit.foundation.extraction.Extractor (fin=None,      fout=None,      for-
                                              mat=None,      auto=True,      exten-
                                              sion=True,      store=True,      files=False,
                                              nofile=False,      verbose=False,      en-
                                              gine=None, layer=None, protocol=None,
                                              ip=False,      ipv4=False,      ipv6=False,
                                              tcp=False,      strict=True,      trace=False,
                                              trace_fout=None,      trace_format=None,
                                              trace_byteorder='little',
                                              trace_nanosecond=False)
```

Bases: `object`

Extractor for PCAP files.

For supported engines, please refer to corresponding driver method for more information:

- Default drivers:
 - Global header: `record_header()`
 - Packet frames: `record_frames()`
- DPKT driver: `_run_dpkt()`
- Scapy driver: `_run_scapy()`
- PyShark driver: `_run_pyshark()`
- Multiprocessing driver:
 - Pipeline model: `_run_pipeline()`
 - Server model: `_run_server()`

`_ifnm: str`

Input file name.

`_ofnm: str`

Output file name.

`_fext: str`

Output file extension.

`_flag_a: bool`

Auto extraction flag (as the `auto` parameter).

`_flag_d: bool`

Data storing flag (as the `store` parameter).

`_flag_e: bool`

EOF flag.

`_flag_f: bool`

Split output into files flag (as the `files` parameter).

`_flag_m: bool`

Multiprocessing engine flag.

`_flag_q: bool`

No output flag (as the `nofile` parameter).

`_flag_t: bool`

TCP flow tracing flag (as the `trace` parameter).

_flag_v: Union[bool, Callable[[*pcapkit.foundation.extraction.Extractor*, *pcapkit.proto*]]
A bool value or a function takes the `Extract` instance and current parsed frame (depends on the engine selected) as parameters to print verbose output information (as the `verbose` parameter).

_vfunc: Union[NotImplemented, Callable[[*pcapkit.foundation.extraction.Extractor*, *pcap*]]
If the `verbose` parameter is a callable, then it will be assigned as `self._vfunc`; otherwise, it keeps `NotImplemented` as a placeholder and has specific function for each engine.

_frnum: int
Current frame number.

_frame: List[*pcapkit.protocols.pcap.frame.Frame*]
Frame records storage.

_proto: *pcapkit.corekit.protochain.ProtoChain*
Current frame's protocol chain.

_reasm: List[Optional[*pcapkit.reassembly.ipv4.Ipv4_Reassembly*], Optional[*pcapkit.reasse*]]
Reassembly buffers.

_trace: Optional[*pcapkit.foundation.traceflow.TraceFlow*]
TCP flow tracer.

_ipv4: bool
IPv4 reassembly flag (as the `ipv4` and/or `ip` flag).

_ipv6: bool
IPv6 reassembly flag (as the `ipv6` and/or `ip` flag).

_tcp: bool
TCP reassembly flag (as the `tcp` parameter).

_exptl: str
Extract til protocol flag (as the `protocol` parameter).

_exlyr: str
Extract til layer flag (as the `layer` parameter).

_exeng: str
Extraction engine (as the `engine` parameter).

_ifile: io.BufferedReader
Source PCAP file (opened in binary mode).

_ofile: Optional[Union[*dictdumper.dumper.Dumper*, Type[*dictdumper.dumper.Dumper*]]]
Output dumper. If `self._flag_f` is `True`, it is the `Dumper` object, otherwise it is an initialised `Dumper` instance.

Note: We customised the `object_hook()` method to provide generic support of `enum.Enum`, `ipaddress.IPv4Address`, `ipaddress.IPv6Address` and `Info`.

See also:

When the output format is unsupported, we uses `NotImplementedIO` as a fallback solution.

_gbhdr: *pcapkit.protocols.pcap.header.Header*
Parsed PCAP global header instance.

_vinfo: *pcapkit.corekit.version.VersionInfo*
The version info of the PCAP file (as the `self._gbhdr.version` property).

`_dlink:` `pcapkit.const.reg.linktype.LinkType`
Protocol type of data link layer (as the `self._gbhdr.protocol` property).

`_nnsec:` `bool`
Nanosecond PCAP file flag (as the `self._gbhdr.nanosecond` property).

`_type:` `str`
Output format (as the `self._ofile.kind` property).

`_expkg:` `types.ModuleType`
Extraction engine module.

`_extmp:` `Iterator[Any]`
Temporary storage for frame parsing iterator.

`_mpprc:` `List[multiprocessing.Process]`
List of active child processes.

`_mpfdp:` `DefaultDict[multiprocessing.Queue]`
File pointer (offset) queue for each frame.

`_mpmng:` `multiprocessing.sharedctypes.multiprocessing.Manager`
Multiprocessing manager context.

`_mpkit:` `multiprocessing.managers.SyncManager.Namespace`
Multiprocessing utility namespace.

`_mpkit.counter:` `int`
Number of active workers.

`_mpkit.pool:` `int`
Number of prepared workers.

`_mpkit.current:` `int`
Current processing frame number.

`_mpkit.eof:` `bool`
EOF flag.

`_mpkit.frames:` `Dict[int, pcapkit.protocols.pcap.frame.Frame]`
Frame storage.

`_mpkit.trace:` `Optional[pcapkit.foundation.traceflow.TraceFlow]`
TCP flow tracer.

`_mpkit.reassembly:` `List[Optional[pcapkit.reassembly.ipv4.Ipv4_Reassembly], Optional[pcapkit.reassembly.ipv6.Ipv6_Reassembly]]`
Reassembly buffers.

`_mpsrv:` `multiprocessing.Process`
Server process for frame analysis and processing.

`_mpbuf:` `Union[multiprocessing.managers.SyncManager.dict, Dict[int, pcapkit.protocols.pcap.frame.Frame]]`
Multiprocessing buffer for parsed PCAP frames.

`_mpfrm:` `Union[multiprocessing.managers.SyncManager.list, List[pcapkit.protocols.pcap.frame.Frame]]`
Multiprocessing storage for processed PCAP frames.

`_mprsm:` `Union[multiprocessing.managers.SyncManager.list, List[Optional[pcapkit.reassembly.Reassembly]]]`
Multiprocessing storage for reassembly buffers.

`__call__` `()`
Works as a simple wrapper for the iteration protocol.

Raises `IterableError` – If `self._flag_a` is `True`, as iteration is not applicable.

`__enter__()`

Uses *Extractor* as a context manager.

`__exit__(exc_type, exc_value, traceback)`

Close the input file when exits.

`__init__(fin=None, fout=None, format=None, auto=True, extension=True, store=True, files=False, nofile=False, verbose=False, engine=None, layer=None, protocol=None, ip=False, ipv4=False, ipv6=False, tcp=False, strict=True, trace=False, trace_fout=None, trace_format=None, trace_byteorder='little', trace_nanosecond=False)`

Initialise PCAP Reader.

Parameters

- **fin** (*Optional[str]*) – file name to be read; if file not exist, raise `FileNotFound`
- **fout** (*Optional[str]*) – file name to be written
- **format** (*Optional[Literal['plist', 'json', 'tree']]*) – file format of output
- **auto** (*bool*) – if automatically run till EOF
- **extension** (*bool*) – if check and append extensions to output file
- **store** (*bool*) – if store extracted packet info
- **files** (*bool*) – if split each frame into different files
- **nofile** (*bool*) – if no output file is to be dumped
- **(Union[bool, Callable[[pcapkit.foundation.extraction.Extractor, (verbose) – pcapkit.protocol.pcap.frame.Frame]]])**: a *bool* value or a function takes the `Extract` instance and current parsed frame (depends on engine selected) as parameters to print verbose output information
- **engine** (*Optional[Literal['default', 'pcapkit', 'dpkt', 'scapy', 'pyshark', 'server', 'pipeline']]*) – extraction engine to be used
- **layer** (*Optional[Literal['Link', 'Internet', 'Transport', 'Application']]*) – extract til which layer
- **protocol** (*Optional[Union[str, Tuple[str], Type[Protocol]]]*) – extract til which protocol
- **ip** (*bool*) – if record data for IPv4 & IPv6 reassembly
- **ipv4** (*bool*) – if perform IPv4 reassembly
- **ipv6** (*bool*) – if perform IPv6 reassembly
- **tcp** (*bool*) – if perform TCP reassembly
- **strict** (*bool*) – if set strict flag for reassembly
- **trace** (*bool*) – if trace TCP traffic flows
- **trace_fout** (*Optional[str]*) – path name for flow tracer if necessary
- **trace_format** (*Optional[Literal['plist', 'json', 'tree', 'pcap']]*) – output file format of flow tracer
- **trace_byteorder** (*Literal['little', 'big']*) – output file byte order
- **trace_nanosecond** (*bool*) – output nanosecond-resolution file flag

Warns `FormatWarning` – Warns under following circumstances:

- If using PCAP output for TCP flow tracing while the extraction engine is PyShark.
- If output file format is not supported.

`__iter__()`

Iterate and parse PCAP frame.

Raises `IterableError` – If `self._flag_a` is `True`, as such operation is not applicable.

`__next__()`

Iterate and parse next PCAP frame.

It will call `__read_frame()` to parse next PCAP frame internally, until the EOF reached; then it calls `__cleanup()` for the aftermath.

`__aftermathmp()`

Aftermath for multiprocessing.

The method will *join* all child processes forked/spawned as in `self._mpprc`, and will *join* `self._mpsrv` server process if using multiprocessing server engine.

For multiprocessing server engine, it will

- assign `self._mpfrm` to `self._frame`
- assign `self._mprsm` to `self._reasm`
- copy `self._mpkit.trace` to `self._trace`

For multiprocessing pipeline engine, it will

- restore `self._frame` from `self._mpkit.frames`
- copy `self._mpkit.reassembly` to `self._reasm`
- copy `self._mpkit.trace` to `self._trace`

After restoring attributes, it will *shutdown* multiprocessing manager context `self._mpmng`, delete all multiprocessing attributes (i.e. starts with `_mp`), and deduct the frame number `self._frnum` by 2 (*hacking solution*).

Notes

If `self._flag_e` is already set as `True`, do nothing.

Raises `UnsupportedCall` – If `self._flag_m` is `False`, as such operation is not applicable.

`__cleanup()`

Cleanup after extraction & analysis.

The method clears the `self._expkg` and `self._extmp` attributes, sets `self._flag_e` as `True` and closes the input file.

`__default_read_frame(*, frame=None, mpkit=None)`

Read frames with default engine.

This method performs following operations:

- extract frames and each layer of packets;
- make `Info` object out of frame properties;

- write to output file with corresponding dumper;
- reassemble IP and/or TCP datagram;
- trace TCP flows if any;
- record frame *Info* object to frame storage.

Keyword Arguments

- **frame** (*Optional*[*pcapkit.protocols.pcap.frame.Frame*]) – The fall-back frame data (for multiprocessing engines).
- **mpkit** (*multiprocessing.managers.SyncManager.Namespace*) – The multiprocess data kit.

Returns Parsed frame instance.

Return type *Optional*[*pcapkit.protocols.pcap.frame.Frame*]

`_dpkt_read_frame()`

Read frames with DPKT engine.

Returns Parsed frame instance.

Return type *dpkt.dpkt.Packet*

See also:

Please refer to *_default_read_frame()* for more operational information.

`_pipeline_read_frame(*, mpfdp, mpkit)`

Extract frame with multiprocessing pipeline engine.

The method calls *Frame* to parse the PCAP frame data. Should *EOFError* raised, it will toggle *self._mpkit.eof* as *True*. Finally, it will decendant *self.mpkit.counter* by 1 and closes the input source file (as the child process exits).

For the parsed *Frame* instance, the instant will first wait until *self.mpkit.current* is the same as *self._frnum*, i.e. it's now time to process the parsed frame as in a linear sequential order.

It will proceed by calling *_default_read_frame()*, whilst temporarily assigning *self.mpkit.trace* to *self._trace* and *self.mpkit.reassembly* to *self._reasm* then put back.

Keyword Arguments

- **mpfdp** (*multiprocessing.Queue*) – *Queue* for multiprocessing file pointer (offset).
- **mpkit** (*multiprocessing.managers.SyncManager.Namespace*) – Namespace instance as *self._mpkit*.

Raise:

EOFError: If *self._flag_e* is *True*, as the parsing had finished.

`_pyshark_read_frame()`

Read frames with PyShark engine.

Returns Parsed frame instance.

Return type *pyshark.packet.packet.Packet*

Notes

This method inserts `packet2dict()` to the parsed frame instance as `packet2dict()` method.

See also:

Please refer to `_default_read_frame()` for more operational information.

`_read_frame()`

Headquarters for frame reader.

This method is a dispatcher for parsing frames.

- For Scapy engine, calls `_scapy_read_frame()`.
- For DPkt engine, calls `_dpkt_read_frame()`.
- For PyShark engine, calls `_pyshark_read_frame()`.
- For default (PyPCAPKit) engine, calls `_default_read_frame()`.

Returns The parsed frame instance.

`_run_dpkt(dpkt)`

Call `dpkt.pcap.Reader` to extract PCAP files.

This method assigns `self._expkg` as `dpkt` and `self._extmp` as an iterator from `dpkt.pcap.Reader`.

Parameters `dpkt` (`types.ModuleType`) – The `dpkt` module.

Warns `AttributeWarning` – If `self._exlyr` and/or `self._exptl` is provided as the DPkt engine currently does not support such operations.

`_run_pipeline(multiprocessing)`

Use pipeline multiprocessing to extract PCAP files.

Notes

The basic concept of multiprocessing pipeline engine is that we parse the PCAP file as a pipeline. Each frame per worker. Once the length of a frame is known, i.e. the PCAP frame header is parsed, then we can start a new working and start parsing the next frame concurrently.

However, as the datagram reassembly and TCP flow tracing require linear sequential processing, we still need to *wait* for the completion of analysis on previous frames before proceeding on such operations.

This method assigns `self._expkg` as `multiprocessing`, creates a file pointer storage as `self._mpfdp`, manager context as `self._mpmng` and namespace as `self._mpkit`.

In the namespace, we initiate number of (on duty) workers as `counter`, pool of (ready) workers as `pool`, current frame number as `current`, EOF flag as `eof`, frame storage as `frames`, TCP flow tracer `self._trace` as `trace` and the reassembly buffers `self._reasm` as `reassembly`.

After initial setup, the method calls `record_header()` to parse the PCAP global header and *put* the file offset to `self._mpfdp` as the start of first frame. Then it starts the parsing of each PCAP frame.

During this phrase, it's a `while` clause until `self._mpkit.eof` is set as `True` then it calls `_update_eof()` and breaks. In the `while` clause, it maintains a `multiprocessing.pool.Pool` like worker pool. It checks the `self._mpkit.pool` for available workers and `self._mpkit.counter` for active workers.

When starts a new worker, it first update the input file offset to the file offset as specified in `self._mpfdp`. Then creates a child process running `_pipeline_read_frame()` with keyword arguments `mpkit` as `self._mpkit` and `mpfdp` as corresponding `Queue` from `self._mpfdp`. Later, it decrements the `self._mpkit.pool` and increments the `self._mpkit.counter`, both by 1. The child process will be appended to `self._mpprc`.

When the number of active workers is greater than or equal to `CPU_CNT`, it waits and `join` the leading child processes in `self._mpprc` then removes their reference.

Parameters multiprocessing (`types.ModuleType`) – The `multiprocessing` module.

Warns AttributeWarning – If `self._flag_q` is `False`, as multiprocessing engines do not support output.

Raises UnsupportedCall – If `self._flag_m` is `False`, as such operation is not applicable.

`_run_pyshark` (`pyshark`)

Call `pyshark.FileCapture` to extract PCAP files.

This method assigns `self._expkg` as `pyshark` and `self._extmp` as an iterator from `pyshark.FileCapture`.

Parameters pyshark (`types.ModuleType`) – The `pyshark` module.

Warns AttributeWarning – Warns under following circumstances:

- if `self._exlyr` and/or `self._exptl` is provided as the PyShark engine currently does not support such operations.
- if reassembly is enabled, as the PyShark engine currently does not support such operation.

`_run_scapy` (`scapy.all`)

Call `scapy.all.sniff()` to extract PCAP files.

This method assigns `self._expkg` as `scapy.all` and `self._extmp` as an iterator from `scapy.all.sniff()`.

Parameters scapy_all (`types.ModuleType`) – The `scapy.all` module.

Warns AttributeWarning – If `self._exlyr` and/or `self._exptl` is provided as the Scapy engine currently does not support such operations.

`_run_server` (`multiprocessing`)

Use server multiprocessing to extract PCAP files.

Notes

The basic concept of multiprocessing server engine is that we further separate the logic of PCAP frame parsing and analysis/processing, comparing to the multiprocessing pipeline engine (c.f. `_run_pipeline()`).

We starts a `server` process to perform the datagram reassembly and TCP flow tracing, etc. of all parsed PCAP frames, whilst parsing each PCAP frame in the same manner as in multiprocessing pipeline engine, i.e. each frame per worker.

This method assigns `self._expkg` as `multiprocessing`, creates a file pointer storage as `self._mpfdp`, manager context as `self._mpmng` and namespace as `self._mpkit`. We will also maintain the active process list `self._mpprc` as in `_run_pipeline()`.

It will also creates a `dict` as `self._mpbuf`, frame buffer (temporary storage) for the server process to obtain the parsed frames; a `list` as `self._mpfrm`, eventual frame storage; and another `list` as `self._mprsm`, storing the reassembly buffers `self._reasm` before the server process exits.

In the namespace, we initiate number of (on duty) workers as `counter`, pool of (ready) workers as `pool`, current frame number as `current`, EOF flag as `eof`, frame storage as `frames`, and trace for storing TCP flow tracer `self._trace` before the server process exits.

After initial setup, the method calls `record_header()` to parse the PCAP global header and *put* the file offset to `self._mpfdp` as the start of first frame. It will then starts the server process `self._mpsrv` from `_server_analyse_frame()`. Finally, it starts the parsing of each PCAP frame.

During this phrase, it's a `while` clause until `self._mpkit.eof` is set as `True` then it calls `_update_eof()` and breaks. In the `while` clause, it maintains a `multiprocessing.pool.Pool` like worker pool. It checks the `self._mpkit.pool` for available workers and `self._mpkit.counter` for active workers.

When starts a new worker, it first update the input file offset to the file offset as specified in `self._mpfdp`. Then creates a child process running `_server_extract_frame()` with keyword arguments `mpkit` as `self._mpkit`, `mpbuf` as `self._mpbuf` and `mpfdp` as corresponding `Queue` from `self._mpfdp`. Later, it decendants the `self._mpkit.pool` and increments the `self._mpkit.counter`, both by 1. The child process will be appended to `self._mpprc`.

When the number of active workers is greater than or equal to `CPU_CNT`, it waits and *join* the leading child processes in `self._mpprc` then removes their reference.

Parameters `multiprocessing` (`types.ModuleType`) – The `multiprocessing` module.

Warns `AttributeWarning` – If `self._flag_q` is `False`, as multiprocessing engines do not support output.

Raises `UnsupportedCall` – If `self._flag_m` is `False`, as such operation is not applicable.

`_scapy_read_frame()`

Read frames with Scapy engine.

Returns Parsed frame instance.

Return type `scapy.packet.Packet`

See also:

Please refer to `_default_read_frame()` for more operational information.

`_server_analyse_frame` (`*`, `mpkit`, `mpfrm`, `mprsm`, `mpbuf`)

Analyse frame using multiprocessing server engine.

This method starts a `while` clause. For each round, it will *pop* the frame `self._frnum` from `mpbuf` then calls `_default_read_frame()` to perform datagram reassembly and TCP flow tracing, etc.

Once the frame popped is `EOFError`, i.e. the frame parsing had finished, it breaks from the clause and updates `mpfrm` with `self._frame`, `mprsm` with `self._reasm`, and `mpkit.trace` with `self._trace`.

Keyword Arguments

- **`mpkit`** (`multiprocessing.managers.SyncManager.Namespace`) – Namespace instance as `_mpkit`.
- **`mpfrm`** (`multiprocessing.managers.SyncManager.list`) – Frame storage.

- **mpprsm** (*multiprocessing.managers.SyncManager.list*) – Reassembly buffers.
- **mpbuf** (*multiprocessing.managers.SyncManager.dict*) – Frame buffer (temporary storage) for the server process *self._mpsrv* to obtain the parsed frames.

_server_extract_frame (*, *mpfdp*, *mpkit*, *mpbuf*)

Extract frame using multiprocessing server engine.

The method calls `Frame` to parse the PCAP frame data. The parsed frame will be saved to *mpbuf* under the corresponding frame number *self._frnum*.

Should `EOFError` raised, it will toggle *self._mpkit.eof* as `True`, and save `EOFError` object to *mpbuf* under the corresponding frame number *self._frnum*.

Finally, it will decendant *self.mpkit.counter* by 1 and closes the input source file (as the child process exits).

Parameters

- **mpfdp** (*multiprocessing.Queue*) – Queue for multiprocessing file pointer (offset).
- **mpkit** (*multiprocessing.managers.SyncManager.Namespace*) – Namespace instance as *_mpkit*.
- **mpbuf** (*multiprocessing.managers.SyncManager.dict*) – Frame buffer (temporary storage) for the server process *self._mpsrv* to obtain the parsed frames.

Raise:

EOFError: If *self._flag_e* is `True`, as the parsing had finished.

_update_eof ()

Update EOF flag.

This method calls *_aftermathmp* () to cleanup multiprocessing stuff, closes the input file and toggle *self._flag_e* as `True`.

check ()

Check layer and protocol thresholds.

Warns

- **LayerWarning** – If *self._exlyr* is not recognised.
- **ProtocolWarning** – If *self._exptl* is not recognised.

See also:

- List of available layers: `LAYER_LIST`
- List of available protocols: `PROTO_LIST`

static import_test (*engine*, *, *name=None*)

Test import for extractcion engine.

Parameters *engine* (*str*) – Extraction engine module name.

Keyword Arguments *name* (*Optional[str]*) – Extraction engine display name.

Warns **EngineWarning** – If the engine module is not installed.

Returns If succeeded, returns `True` and the module; otherwise, returns `False` and `None`.

Return type Tuple[bool, Optional[ModuleType]]

classmethod `make_name` (*fin*, *fout*, *fmt*, *extension*, *, *files*=False, *nofile*=False)

Generate input and output filenames.

The method will perform following processing:

1. sanitise *fin* as the input PCAP filename; *in.pcap* as default value and append *.pcap* extension if needed and *extension* is `True`; as well as test if the file exists;
2. if *nofile* is `True`, skips following processing;
3. if *fmt* provided, then it presumes corresponding output file extension;
4. if *fout* not provided, it presumes the output file name based on the presumptive file extension; the stem of the output file name is set as *out*; should the file extension is not available, then it raises `FormatError`;
5. if *fout* provided, it presumes corresponding output format if needed; should the presumption cannot be made, then it raises `FormatError`;
6. it will also append corresponding file extension to the output file name if needed and *extension* is `True`.

Parameters

- **fin** (*Optional[str]*) – Input filename.
- **fout** (*Optional[str]*) – Output filename.
- **fmt** (*str*) – Output file format.
- **extension** (*bool*) – If append *.pcap* file extension to the input filename if *fin* does not have such file extension; if check and append extensions to output file.

Keyword Arguments

- **files** (*bool*) – If split each frame into different files.
- **nofile** (*bool*) – If no output file is to be dumped.

Returns

Generated input and output filenames:

0. input filename
1. output filename / directory name
2. output format
3. output file extension (without *.*)
4. if split each frame into different files

Return type Tuple[str, str, str, str, bool]

Raises

- **FileNotFound** – If input file does not exists.
- **FormatError** – If output format not provided and cannot be presumed.

record_frames ()

Read packet frames.

The method calls `_read_frame()` to parse each frame from the input PCAP file; and calls `_cleanup()` upon complision.

Notes

Under non-auto mode, i.e. `self._flag_a` is `False`, the method performs no action.

record_header()

Read global header.

The method will parse the PCAP global header and save the parsed result as `self._gbhdr`. Information such as PCAP version, data link layer protocol type, nanosecond flag and byteorder will also be save the current `Extractor` instance.

If TCP flow tracing is enabled, the nanosecond flag and byteorder will be used for the output PCAP file of the traced TCP flows.

For output, the method will dump the parsed PCAP global header under the name of `Global Header`.

run()

Start extraction.

We uses `import_test()` to check if a certain engine is available or not. For supported engines, each engine has different driver method:

- Default drivers:
 - Global header: `record_header()`
 - Packet frames: `record_frames()`
- DPKT driver: `_run_dpkt()`
- Scapy driver: `_run_scapy()`
- PyShark driver: `_run_pyshark()`
- Multiprocessing driver:
 - Pipeline model: `_run_pipeline()`
 - Server model: `_run_server()`

Warns EngineWarning – If the extraction engine is not available. This is either due to dependency not installed, number of CPUs is not enough, or supplied engine unknown.

property engine

PCAP extraction engine.

Return type `str`

property format

Format of output file.

Raises `UnsupportedCall` – If `self._flag_q` is set as `True`, as output is disabled by initialisation parameter.

Return type `str`

property frame

Extracted frames.

Raises `UnsupportedCall` – If `self._flag_d` is `True`, as storing frame data is disabled.

Return type `Tuple[Info[DataType_Frame]]`

property header

Global header.

Raises *UnsupportedCall* – If `self._exeng` is 'scapy' or 'pyshark', as such engines does not reserve such information.

Return type `Info[DataType_Header]`

property info

Version of input PCAP file.

Raises *UnsupportedCall* – If `self._exeng` is 'scapy' or 'pyshark', as such engines does not reserve such information.

Return type `VersionInfo`

property input

Name of input PCAP file.

Return type `str`

property length

Frame number (of current extracted frame or all).

Return type `int`

property output

Name of output file.

Raises *UnsupportedCall* – If `self._flag_q` is set as `True`, as output is disabled by initialisation parameter.

Return type `str`

property protocol

Protocol chain of current frame.

Raises *UnsupportedCall* – If `self._flag_a` is `True`, as such attribute is not applicable.

Return type `ProtoChain`

property reassembly

Frame record for reassembly.

- `ipv6` – tuple of TCP payload fragment (`IPv4_Reassembly`)
- `ipv4` – tuple of TCP payload fragment (`IPv6_Reassembly`)
- `tcp` – tuple of TCP payload fragment (`TCP_Reassembly`)

Return type `Info`

property trace

Index table for traced flow.

Raises *UnsupportedCall* – If `self._flag_t` is `True`, as TCP flow tracing is disabled.

Return type `Tuple[Info]`

`pcapkit.foundation.extraction.CPU_CNT`: `int`

Number of available CPUs. The value is used as the maximum concurrent workers in multiprocessing engines.

`pcapkit.foundation.extraction.LAYER_LIST` = {'Application', 'Internet', 'Link', 'None', 'Tr

List of layers.

```
pcapkit.foundation.extraction.PROTO_LIST = {'ah', 'application', 'arp', 'drarp', 'ethernet'}
```

List of protocols.

1.1.3 Trace TCP Flows

`pcapkit.foundation.traceflow` is the interface to trace TCP flows from a series of packets and connections.

Note: This was implemented as the demand of my mate @gousaiyang.

Data Structure

trace.packet Data structure for TCP flow tracing (`dump()`) is as following:

```
tract_dict = dict(
    protocol=data_link,          # data link type from global header
    index=frame.info.number,     # frame number
    frame=frame.info,           # extracted frame info
    syn=tcp.flags.syn,           # TCP synchronise (SYN) flag
    fin=tcp.flags.fin,           # TCP finish (FIN) flag
    src=ip.src,                  # source IP
    dst=ip.dst,                  # destination IP
    srcport=tcp.srcport,         # TCP source port
    dstport=tcp.dstport,         # TCP destination port
    timestamp=frame.info.time_epoch, # frame timestamp
)
```

trace.buffer Data structure for internal buffering when performing reassembly algorithms (`_buffer`) is as following:

```
(dict) buffer --> memory buffer for reassembly
|--> (tuple) BUFID : (dict)
|   |--> ip.src      |
|   |--> ip.dst      |
|   |--> tcp.srcport |
|   |--> tcp.dstport |
|   |--> 'fpout' : (dictdumper.dumper.Dumper) output dumper_
->object
|   |--> 'index': (list) list of frame index
|   |-->         |--> (int) frame index
|   |--> 'label': (str) flow label generated from ``BUFID``
|--> (tuple) BUFID ...
```

trace.index Data structure for TCP flow tracing (element from `index tuple`) is as following:

```
(tuple) index
|--> (Info) data
|   |--> 'fpout' : (Optional[str]) output filename if exists
|   |--> 'index': (tuple) tuple of frame index
|   |   |--> (int) frame index
|   |--> 'label': (str) flow label generated from ``BUFID``
|--> (Info) data ...
```

Implementation

class pcapkit.foundation.traceflow.**TraceFlow** (*fout=None, format=None, byte-order='little', nanosecond=False*)

Bases: `object`

Trace TCP flows.

__call__ (*packet*)

Dump frame to output files.

Parameters **packet** (*Dict[str, Any]*) – a flow packet (*trace.packet*)

__init__ (*fout=None, format=None, byteorder='little', nanosecond=False*)

Initialise instance.

Parameters

- **fout** (*Optional[str]*) – output path
- **format** (*Optional[str]*) – output format
- **byteorder** (*str*) – output file byte order
- **nanosecond** (*bool*) – output nanosecond-resolution file flag

dump (*packet*)

Dump frame to output files.

Parameters **packet** (*Dict[str, Any]*) – a flow packet (*trace.packet*)

static make_fout (*fout='./tmp', fmt='pcap'*)

Make root path for output.

Positional arguments: fout (str): root path for output fmt (str): output format

Returns dumper of specified format and file extension of output file

Return type `Tuple[Type[dictdumper.dumper.Dumper], str]`

Warns

- **FormatWarning** – If fmt is not supported.
- **FileWarning** – If fout exists and fmt is `None`.

Raises **FileExists** – If fout exists and fmt is **NOT** `None`.

submit ()

Submit traced TCP flows.

Returns traced TCP flow (*trace.buffer*)

Return type `Tuple[Info]`

trace (*packet, *, check=True, output=False*)

Trace packets.

Parameters **packet** (*Dict[str, Any]*) – a flow packet (*trace.packet*)

Keyword Arguments

- **check** (*bool*) – flag if run validations
- **output** (*bool*) – flag if has formatted dumper

Returns If `output` is `True`, returns the initiated `Dumper` object, which will dump data to the output file named after the flow label; otherwise, returns the flow label itself.

Return type `Union[dictdumper.dumper.Dumper, str]`

Notes

The flow label is formatted as following:

```
f' {packet.src}_{packet.srcport}-{packet.dst}_{info.dstport}-{packet.timestamp}'
```

_buffer

Buffer field (*trace.buffer*).

Type `dict`

_endian

Output file byte order.

Type `Literal['little', 'big']`

_fdpext

Output file extension.

Type `str`

_foutio

Dumper class.

Type `Type[dictdumper.dumper.Dumper]`

_fproot

Output root path.

Type `str`

_newflg

New packet flag.

Type `bool`

_nnsecd

Output nanosecond-resolution file flag.

Type `bool`

_stream

Stream index (*trace.index*).

Type `list`

property index

Index table for traced flow.

Return type `Tuple[Info]`

1.2 User Interface

`pcapkit.interface` defines several user-oriented interfaces, variables, and etc. These interfaces are designed to help and simplify the usage of `pcapkit`.

1.2.1 PCAP Extration

```
pcapkit.interface.extract (fin=None, fout=None, format=None, auto=True, extension=True, store=True, files=False, nofile=False, verbose=False, engine=None, layer=None, protocol=None, ip=False, ipv4=False, ipv6=False, tcp=False, strict=True, trace=False, trace_fout=None, trace_format=None, trace_byteorder='little', trace_nanosecond=False)
```

Extract a PCAP file.

Parameters

- **fin** (*Optional[str]*) – file name to be read; if file not exist, raise `FileNotFound`
- **fout** (*Optional[str]*) – file name to be written
- **format** (*Optional[Literal['plist', 'json', 'tree']]*) – file format of output
- **auto** (*bool*) – if automatically run till EOF
- **extension** (*bool*) – if check and append extensions to output file
- **store** (*bool*) – if store extracted packet info
- **files** (*bool*) – if split each frame into different files
- **nofile** (*bool*) – if no output file is to be dumped
- **verbose** (*bool*) – if print verbose output information
- **engine** (*Optional[Literal['default', 'pcapkit', 'dpkt', 'scapy', 'pyshark', 'server', 'pipeline']]*) – extraction engine to be used
- **layer** (*Optional[Literal['Link', 'Internet', 'Transport', 'Application']]*) – extract til which layer
- **protocol** (*Optional[Union[str, Tuple[str], Type[Protocol]]]*) – extract til which protocol
- **ip** (*bool*) – if record data for IPv4 & IPv6 reassembly
- **ipv4** (*bool*) – if perform IPv4 reassembly
- **ipv6** (*bool*) – if perform IPv6 reassembly
- **tcp** (*bool*) – if perform TCP reassembly
- **strict** (*bool*) – if set strict flag for reassembly
- **trace** (*bool*) – if trace TCP traffic flows
- **trace_fout** (*Optional[str]*) – path name for flow tracer if necessary
- **trace_format** (*Optional[Literal['plist', 'json', 'tree', 'pcap']]*) – output file format of flow tracer
- **trace_byteorder** (*Literal['little', 'big']*) – output file byte order

- **trace_nanosecond** (*bool*) – output nanosecond-resolution file flag

Returns *Extractor* – an *Extractor* object

1.2.2 Application Layer Analysis

`pcapkit.interface.analyse` (*file*, *length=None*)

Analyse application layer packets.

Parameters

- **file** (*Union[bytes, io.BytesIO]*) – packet to be analysed
- **length** (*Optional[int]*) – length of the analysing packet

Returns an *Analysis* object

Return type *Analysis*

1.2.3 Payload Reassembly

`pcapkit.interface.reassemble` (*protocol*, *strict=False*)

Reassemble fragmented datagrams.

Parameters

- **protocol** (*Union[str, Type[Protocol]]*) –
- **strict** (*bool*) – if return all datagrams (including those not implemented) when submit

Returns a *Reassembly* object of corresponding protocol

Return type *Union[IPv4_Reassembly, IPv6_Reassembly, TCP_Reassembly]*

Raises *FormatError* – If protocol is **NOT** any of IPv4, IPv6 or TCP.

1.2.4 TCP Flow Tracing

`pcapkit.interface.trace` (*fout=None*, *format=None*, *byteorder='little'*, *nanosecond=False*)

Trace TCP flows.

Parameters

- **fout** (*str*) – output path
- **format** (*Optional[str]*) – output format
- **byteorder** (*str*) – output file byte order
- **nanosecond** (*bool*) – output nanosecond-resolution file flag

Returns a *TraceFlow* object

Return type *TraceFlow*

1.2.5 Output File Formats

```
pcapkit.interface.TREE = 'tree'  
pcapkit.interface.JSON = 'json'  
pcapkit.interface.PLIST = 'plist'  
pcapkit.interface.PCAP = 'pcap'
```

1.2.6 Layer Thresholds

```
pcapkit.interface.RAW = 'None'  
pcapkit.interface.LINK = 'Link'  
pcapkit.interface.INET = 'Internet'  
pcapkit.interface.TRANS = 'Transport'  
pcapkit.interface.APP = 'Application'
```

1.2.7 Extration Engines

```
pcapkit.interface.DPKT = 'dpkt'  
pcapkit.interface.Scapy = 'scapy'  
pcapkit.interface.PCAPKit = 'default'  
pcapkit.interface.PyShark = 'pyshark'  
pcapkit.interface.MPServer = 'server'  
pcapkit.interface.MPPipeline = 'pipeline'
```

1.3 Protocol Family

pcapkit.protocols is collection of all protocol families, with detailed implementation and methods.

1.3.1 PCAP File Headers

pcapkit.protocols.pcap contains header descriptions for PCAP files, including global header (*Header*) and frame header (*Frame*).

Global Header

pcapkit.protocols.pcap.header contains *Header* only, which implements extractor for global headers*⁰ of PCAP, whose structure is described as below:

⁰ https://wiki.wireshark.org/Development/LibpcapFileFormat#Global_Header

```
typedef struct pcap_hdr_s {
    quint32 magic_number;    /* magic number */
    quint16 version_major;   /* major version number */
    quint16 version_minor;  /* minor version number */
    gint32  thiszone;        /* GMT to local correction */
    quint32 sigfigs;         /* accuracy of timestamps */
    quint32 snaplen;         /* max length of captured packets, in octets */
    quint32 network;         /* data link type */
} pcap_hdr_t;
```

class pcapkit.protocols.pcap.header.**Header** (*file=None, length=None, **kwargs*)

Bases: [pcapkit.protocols.protocol.Protocol](#)

PCAP file global header extractor.

classmethod `__index__()`

Numeral registry index of the protocol.

Raises [UnsupportedCall](#) – This protocol has no registry entry.

`__len__()`

Total length of corresponding protocol.

Return type [Literal](#)[24]

`__length_hint__()`

Return an estimated length for the object.

Return type [Literal](#)[24]

`__post_init__` (*file=None, length=None, **kwargs*)

Post initialisation hook.

Parameters

- **file** (*Optional*[[io.BytesIO](#)]) – Source packet stream.
- **length** (*Optional*[[int](#)]) – Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to [make\(\)](#).

`_decode_next_layer` (**args, **kwargs*)

Decode next layer protocol.

Parameters ***args** – arbitrary positional arguments

Keyword Arguments ****kwargs** – arbitrary keyword arguments

Raises [UnsupportedCall](#) – This protocol doesn't support `_decode_next_layer()`.

`_import_next_layer` (**args, **kwargs*)

Import next layer extractor.

Parameters ***args** – arbitrary positional arguments

Keyword Arguments ****kwargs** – arbitrary keyword arguments

Raises [UnsupportedCall](#) – This protocol doesn't support `_import_next_layer()`.

`_make_magic` (***kwargs*)

Generate magic number.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Magic number and little-endian flag.

Return type Tuple[bytes, bool]

_read_protos (*size*)

Read next layer protocol type.

Parameters **size** (*int*) –

Returns link layer protocol enumeration

Return type *pcapkit.const.reg.linktype.LinkType*

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments

- **byteorder** (*str*) – header byte order
- **lilendian** (*bool*) – little-endian flag
- **bigendian** (*bool*) – big-endian flag
- **nanosecond** (*bool*) – nanosecond-resolution file flag (default: `False`)
- **version** (Tuple[*int*, *int*]) – version information (default: (2, 4))
- **version_major** (*int*) – major version number (default: 2)
- **version_minor** (*int*) – minor version number (default: 4)
- **thiszone** (*int*) – GMT to local correction (default: 0)
- **sigfigs** (*int*) – accuracy of timestamps (default: 0)
- **snaplen** (*int*) – max length of captured packets, in octets (default: 262_144)
- **network** (Union[*pcapkit.const.reg.linktype.LinkType*, *enum.IntEnum*, *str*, *int*]) – data link type (default: `DLT_NULL`)
- **network_default** (*int*) – default value for unknown data link type
- **network_namespace** (Union[*pcapkit.const.reg.linktype.LinkType*, *enum.IntEnum*, Dict[*str*, *int*], Dict[*int*, *str*]) – data link type namespace (default: `LinkType`)
- **network_reversed** (*bool*) – if namespace is `str -> int` pairs (default: `False`)
- ****kwargs** – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type bytes

read (*length=None, **kwargs*)

Read global header of PCAP file.

Notes

PCAP file has **four** different valid magic numbers.

- d4 c3 b2 a1 – Little-endian microsecond-timestamp PCAP file.
- a1 b2 c3 d4 – Big-endian microsecond-timestamp PCAP file.

- 4d 3c b2 a1 – Little-endian nanosecond-timestamp PCAP file.
 - a1 b2 3c 4d – Big-endian nano-timestamp PCAP file.
-

Parameters `length` (*Optional[int]*) – Length of packet data.

Keyword Arguments `**kwargs` – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_Header*

Raises *FileError* – If the magic number is invalid.

property `byteorder`

Header byte order.

Return type `Literal['big', 'little']`

property `length`

Header length of corresponding protocol.

Return type `Literal[24]`

property `name`

Name of corresponding protocol.

Return type `Literal['Global Header']`

property `nanosecond`

Nanosecond-resolution flag.

Return type `bool`

property `payload`

Payload of current instance.

Raises *UnsupportedCall* – This protocol doesn't support *payload*.

property `protochain`

Protocol chain of current instance.

Raises *UnsupportedCall* – This protocol doesn't support *protochain*.

property `protocol`

Data link type.

Return type *pcapkit.const.reg.linktype.LinkType*

property `version`

Version information of input PCAP file.

Return type *pcapkit.corekit.version.VersionInfo*

```
pcapkit.protocols.pcap.header._MAGIC_NUM = {('big', False): b'\xa1\xb2\xc3\xd4', ('big', True): b'\xa1\xb2\xc3\xd4'}
```

Mapping of PCAP file magic numbers.

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

class pcapkit.protocols.pcap.header.DataType_Header

Bases TypedDict

PCAP global header.

magic_number: **DataType_MagicNumber**
magic number

version_major: **int**
major version number

version_minor: **int**
minor version number

thiszone: **int**
GMT to local correction

sigfigs: **int**
accuracy of timestamps

snaplen: **int**
max length of captured packets, in octets

network: *pcapkit.const.reg.linktype.LinkType*
data link type

class pcapkit.protocols.pcap.header.DataType_MagicNumber

Bases TypedDict

PCAP magic number.

data: **bytes**
original magic number

byteorder: **str**
byte order (big / little)

nanosecond: **bool**
nanosecond-timestamp support

Frame Header^{*0}

**pcapkit.protocols.pcap.frame* contains *Frame* only, which implements extractor for frame headers of PCAP, whose structure is described as below:

```
typedef struct pcaprec_hdr_s {
    quint32 ts_sec;      /* timestamp seconds */
    quint32 ts_usec;    /* timestamp microseconds */
    quint32 incl_len;    /* number of octets of packet saved in file */
    quint32 orig_len;    /* actual length of packet */
} pcaprec_hdr_t;
```

⁰ https://wiki.wireshark.org/Development/LibpcapFileFormat#Record_28Packet.29_Header

class pcapkit.protocols.pcap.frame.**Frame** (*file=None, length=None, **kwargs*)

Bases: *pcapkit.protocols.protocol.Protocol*

Per packet frame header extractor.

__proto__: **DefaultDict**[**int**, **Tuple**[**str**, **str**]]

Protocol index mapping for decoding next layer, c.f. *self._decode_next_layer* & *self._import_next_layer*. The values should be a tuple representing the module name and class name.

Code	Module	Class
1	<i>pcapkit.protocols.link.ethernet</i>	<i>Ethernet</i>
228	<i>pcapkit.protocols.link.internet.ipv4</i>	IPv4
229	<i>pcapkit.protocols.link.internet.ipv6</i>	IPv6

__contains__ (*name*)

Returns if name is in *self._info* or in the frame packet *self._protos*.

Parameters **name** (*Any*) – name to search

Returns if name exists

Return type **bool**

__getitem__ (*key*)

Subscription (*getitem*) support.

This method fist checks if *key* exists in *self._info*. If so, returns the corresponding value, else calls the original *__getitem__()* method.

Parameters **key** (*Union[str, Protocol, Type[Protocol]]*) – Indexing key.

Returns

- If key exists in *self._info*, returns the value of the key;
- else returns the sub-packet from the current packet of indexed protocol.

__index__ ()

Index of the protocol.

Returns If the object is initiated, i.e. *self._fnum* exists, returns the frame index number of itself; else raises *UnsupportedCall*.

Return type **int**

Raises *UnsupportedCall* – This protocol has no registry entry.

__length_hint__ ()

Return an estimated length for the object.

Return type **Literal**[16]

__post_init__ (*file=None, length=None, *, num, proto, nanosecond, **kwargs*)

Initialisation.

Parameters

- **file** (*Optional[io.BytesIO]*) – Source packet stream.
- **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments

- **num** (*int*) – Frame index number (*self._fnum*).

- **proto** (`pcapkit.const.reg.linktype.LinkType`) – Next layer protocol index (`self._prot`).
- **nanosecond** (`bool`) – Nanosecond-timestamp PCAP flag (`self._nsec`).
- **mpfdp** (`multiprocessing.Queue`) – Multiprocessing file descriptor queue (`self._mpfdp`).
- **mpkit** (`multiprocessing.Namespace`) – Multiprocessing auxiliaries (`self._mpkt`).
- ****kwargs** – Arbitrary keyword arguments.

For *multiprocessing* related parameters, please refer to `pcapkit.foundation.extraction.Extrator` for more information.

See also:

For construction argument, please refer to `make()`.

`_decode_next_layer` (`data`, `length=None`)
Decode next layer protocol.

Positional arguments: `data` (dict): info buffer `length` (int): valid (*non-padding*) length

Returns current protocol with packet extracted

Return type dict

`_import_next_layer` (`proto`, `length`, `error=False`)
Import next layer extractor.

This method currently supports following protocols as registered in *LinkType*:

proto	Protocol
1	<i>Ethernet</i>
228	<i>IPv4</i>
229	<i>IPv6</i>

Parameters

- **proto** (`pcapkit.const.reg.linktype.LinkType`) – next layer protocol index
- **length** (`int`) – valid (*non-padding*) length

Keyword Arguments **error** (`bool`) – if function called on error

Returns instance of next layer

Return type `pcapkit.protocols.protocol.Protocol`

`_make_timestamp` (`**kwargs`)
Make timestamp.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Second and microsecond/nanosecond value of timestamp.

Return type Tuple[int, int]

`index` (`name`)
Call `ProtoChain.index`.

Parameters **name** (*Union[str, Protocol, Type[Protocol]]*) – name to be searched

Returns first index of name

Return type *int*

Raises *IndexNotFound* – if name is not present

make (***kwargs*)

Make frame packet data.

Keyword Arguments

- **timestamp** (*float*) – UNIX-EPOCH timestamp
- **ts_sec** (*int*) – timestamp seconds
- **ts_usec** (*int*) – timestamp microseconds
- **incl_len** (*int*) – number of octets of packet saved in file
- **orig_len** (*int*) – actual length of packet
- **packet** (*bytes*) – raw packet data (default: `b''`)
- **nanosecond** (*bool*) – nanosecond-resolution file flag (default: `False`)
- ****kwargs** – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type *bytes*

read (*length=None, **kwargs*)

Read each block after global header.

Parameters **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_Frame*

Raises *EOFError* – If `self._file` reaches EOF.

property length

Header length of corresponding protocol.

Return type *Literal[16]*

property name

Name of corresponding protocol.

Return type *str*

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

```
class pcapkit.protocols.pcap.frame.DataType_Frame
    Bases TypedDict
    PCAP frame header.
    frame_info: DataType_FrameInfo
        PCAP frame information
    time: datetime.datetime
        timestamp
    number: int
        frame index number
    time_epoch: float
        EPOCH timestamp
    len: int
        captured packet length
    cap_len: int
        actual packet length
    packet: bytes
        packet raw data
    protocols: pcapkit.corekit.protochain.ProtoChain
        protocol chain
    error: typing.Optional[str]
        error message (optional)

class pcapkit.protocols.pcap.frame.DataType_FrameInfo
    Bases TypedDict
    Frame information.
    ts_sec: int
        timestamp seconds
    ts_usec: int
        timestamp microseconds/nanoseconds
    incl_len: int
        number of octets of packet saved in file
    orig_len: int
        actual length of packet
```

1.3.2 Link Layer Protocols

`pcapkit.protocols.link` is collection of all protocols in link layer, with detailed implementation and methods.

ARP/InARP - (Inverse) Address Resolution Protocol

`pcapkit.protocols.link.arp` contains *ARP* only, which implements extractor for (Inverse) Address Resolution Protocol (ARP/InARP)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>arp.htype</code>	Hardware Type
2	16	<code>arp.ptype</code>	Protocol Type
4	32	<code>arp.hlen</code>	Hardware Address Length
5	40	<code>arp.plen</code>	Protocol Address Length
6	48	<code>arp.oper</code>	Operation
8	64	<code>arp.sha</code>	Sender Hardware Address
14	112	<code>arp.spa</code>	Sender Protocol Address
18	144	<code>arp.tha</code>	Target Hardware Address
24	192	<code>arp.tpa</code>	Target Protocol Address

class `pcapkit.protocols.link.arp.ARP` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.link.link.Link`

This class implements all protocols in ARP family.

- Address Resolution Protocol (ARP) [[RFC 826](#)]
- Reverse Address Resolution Protocol (RARP) [[RFC 903](#)]
- Dynamic Reverse Address Resolution Protocol (DRARP) [[RFC 1931](#)]
- Inverse Address Resolution Protocol (InARP) [[RFC 2390](#)]

`__acnm:` `Literal['ARP', 'InARP', 'RARP', 'DRARP']`

Acronym of corresponding protocol.

The value is based on operation type (*oper*).

`__name:` `Literal['Dynamic Reverse Address Resolution Protocol', 'Inverse Address Resolution Protocol']`

Name of current protocol.

The value is based on operation type (*oper*).

`classmethod __index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in [IANA](#).

Return type `pcapkit.const.reg.ethertype.EtherType`

`__length_hint__()`

Return an estimated length for the object.

Return type `Literal[28]`

`__read_addr_resolve` (*length, htype*)

Resolve hardware address according to protocol.

Parameters

⁰ http://en.wikipedia.org/wiki/Address_Resolution_Protocol

- **length** (*int*) – Hardware address length.
- **htype** (*int*) – Hardware type.

Returns Hardware address. If *htype* is 1, i.e. MAC address, returns : seperated *hex* encoded MAC address.

Return type *str*

`__read_proto_resolve` (*length*, *pctype*)

Resolve protocol address according to protocol.

Positional arguments: *length* (*int*): Protocol address length. *pctype* (*int*): Protocol type.

Returns Protocol address. If *pctype* is 0x0800, i.e. IPv4 address, returns an *IPv4Address* object; if *pctype* is 0x86dd, i.e. IPv6 address, returns an *IPv6Address* object; otherwise, returns a raw *str* representing the protocol address.

Return type Union[ipaddress.IPv4Address, ipaddress.IPv6Address, str]

classmethod **`id`** ()

Index ID of the protocol.

Returns Index ID of the protocol.

Return type Tuple[Literal['ARP'], Literal['InARP']]

See also:

pcapkit.protocols.protocol.Protocol.__getitem__()

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments *****kwargs*** – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type *bytes*

read (*length=None*, ***kwargs*)

Read Address Resolution Protocol [RFC 826].

Parameters ***length*** (*Optional[int]*) – Length of packet data.

Keyword Arguments *****kwargs*** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_ARP*

property **`alias`**

Acronym of corresponding protocol.

Return type Literal['ARP', 'InARP', 'RARP', 'DRARP']

property **`dst`**

Target hardware & protocol address.

Return type Tuple[str, Union[ipaddress.IPv4Address, ipaddress.IPv6Address, str]]

property **`length`**

Header length of current protocol.

Return type *int*

property name

Name of current protocol.

Return type Literal['Dynamic Reverse Address Resolution Protocol', 'Inverse Address Resolution Protocol', 'Reverse Address Resolution Protocol', 'Address Resolution Protocol']

property src

Sender hardware & protocol address.

Return type Tuple[str, Union[ipaddress.IPv4Address, ipaddress.IPv6Address, str]]

property type

Hardware & protocol type.

Return type Tuple[pcapkit.const.arp.hardware.Hardware, pcapkit.const.reg.ethertype.EtherType]

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

```
class pcapkit.protocols.link.arp.DataType_ARP
```

Bases TypedDict

ARP header [RFC 826].

htype: pcapkit.const.arp.Headware
hardware type

pctype: Union[pcapkit.const.reg.ethertype.EtherType, str]
protocol type

hlen: int
headware address length

plen: int
protocol address length

oper: pcapkit.const.arp.operation.Operation
operation

sha: str
sender hardware address

Ethernet Protocol

pcapkit.protocols.link.ethernet contains *Ethernet* only, which implements extractor for Ethernet Protocol*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	eth.dst	Destination MAC Address
1	8	eth.src	Source MAC Address
2	16	eth.type	Protocol (Internet Layer)

⁰ <https://en.wikipedia.org/wiki/Ethernet>

class pcapkit.protocols.link.ethernet.**Ethernet** (*file=None, length=None, **kwargs*)

Bases: *pcapkit.protocols.link.link.Link*

This class implements Ethernet Protocol.

classmethod `__index__()`

Numeral registry index of the protocol.

Raises *UnsupportedCall* – This protocol has no registry entry.

`__length_hint__()`

Return an estimated length for the object.

Return type *Literal[14]*

`__read_mac_addr()`

Read MAC address.

Returns Colon (:) seperated *hex* encoded MAC address.

Return type *str*

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type *bytes*

read (*length=None, **kwargs*)

Read Ethernet Protocol [[RFC 7042](#)].

Parameters *length* (*Optional[int]*) – Length of packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_Ethernet*

property *dst*

Destination mac address.

Return type *str*

property *length*

Header length of current protocol.

Return type *Literal[14]*

property *name*

Name of current protocol.

Return type *Literal['Ethernet Protocol']*

property *protocol*

Name of next layer protocol.

Return type *pcapkit.const.reg.ethertype.EtherType*

property *src*

Source mac address.

Return type *str*

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

class pcapkit.protocols.link.ethernet.DataType_Ethernet

Bases TypedDict

Ethernet header.

dst: *str*
destination MAC address

src: *str*
source MAC address

type: *pcapkit.const.reg.ethertype.EtherType*
protocol (Internet layer)

L2TP - Layer Two Tunnelling Protocol

pcapkit.protocols.link.l2tp contains *L2TP* only, which implements extractor for Layer Two Tunnelling Protocol (L2TP)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<i>l2tp.flags</i>	Flags and Version Info
0	0	<i>l2tp.flags.type</i>	Type (control / data)
0	1	<i>l2tp.flags.len</i>	Length
0	2		Reserved (must be zero x00)
0	4	<i>l2tp.flags.seq</i>	Sequence
0	5		Reserved (must be zero x00)
0	6	<i>l2tp.flags.offset</i>	Offset
0	7	<i>l2tp.flags.prio</i>	Priority
1	8		Reserved (must be zero x00)
1	12	<i>l2tp.ver</i>	Version (2)
2	16	<i>l2tp.length</i>	Length (optional by <i>len</i>)
4	32	<i>l2tp.tunnelid</i>	Tunnel ID
6	48	<i>l2tp.sessionid</i>	Session ID
8	64	<i>l2tp.ns</i>	Sequence Number (optional by <i>seq</i>)
10	80	<i>l2tp.nr</i>	Next Sequence Number (optional by <i>seq</i>)
12	96	<i>l2tp.offset</i>	Offset Size (optional by <i>offset</i>)

class pcapkit.protocols.link.l2tp.L2TP (*file=None, length=None, **kwargs*)

Bases: *pcapkit.protocols.link.link.Link*

This class implements Layer Two Tunnelling Protocol.

classmethod *__index__*()
Numeral registry index of the protocol.

Raises *UnsupportedCall* – This protocol has no registry entry.

⁰ https://en.wikipedia.org/wiki/Layer_2_Tunneling_Protocol

__length_hint__()

Return an estimated length for the object.

Return type Literal[16]

make (**kwargs)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.


Returns Constructed packet data.

Return type bytes

read (length=None, **kwargs)

Read Layer Two Tunnelling Protocol.

Structure of L2TP header [RFC 2661]:



Parameters **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_L2TP*

property length

Header length of current protocol.

Return type int

property name

Name of current protocol.

Return type Literal['Layer 2 Tunnelling Protocol']

property type

L2TP type.

Return type Literal['Control', 'Data']

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

```
class pcapkit.protocols.link.l2tp.DataType_L2TP
```

```
    Bases TypedDict
```

```
    L2TP header.
```

```
    flags: DataType_Flags
```

```
        flags & versioin info
```

```
    version: Literal[2]
```

```
        version (2)
```

```
    length: Optional[int]
```

```
        length (optional by len)
```

```
    tunnelid: int
```

```
        tunnel ID
```

```
    sessionid: int
```

```
        session ID
```

```
    ns: Optional[int]
```

```
        sequence number (optional by seq)
```

```
    nr: Optional[int]
```

```
        next sequence number (optional by seq)
```

```
    offset: Optional[int]
```

```
        offset (optional by offset)
```

```
class pcapkit.protocols.link.l2tp.DataType_Flags
```

```
    Bases TypedDict
```

```
    Flags and version info.
```

```
    type: Literal['Control', 'Data']
```

```
        type (control / data)
```

```
    len: bool
```

```
        length
```

```
    seq: bool
```

```
        sequence
```

```
    offset: bool
```

```
        offset
```

```
    prio: bool
```

```
        priority
```

OSPF - Open Shortest Path First

`pcapkit.protocols.link.ospf` contains *OSPF* only, which implements extractor for Open Shortest Path First (OSPF)⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ospf.version</code>	Version Number
0	0	<code>ospf.type</code>	Type
0	1	<code>ospf.len</code>	Packet Length (header included)
0	2	<code>ospf.router_id</code>	Router ID
0	4	<code>ospf.area_id</code>	Area ID
0	6	<code>ospf.chksum</code>	Checksum
0	7	<code>ospf.autype</code>	Authentication Type
1	8	<code>ospf.auth</code>	Authentication

class `pcapkit.protocols.link.ospf.OSPF` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.link.link.Link`

This class implements Open Shortest Path First.

classmethod `__index__()`

Numeral registry index of the protocol.

Raises *UnsupportedCall* – This protocol has no registry entry.

`__length_hint__()`


Return an estimated length for the object.

Return type `Literal[24]`

`__read_encrypt_auth()`

Read Authentication field when Cryptographic Authentication is employed, i.e. `autype` is 2.

Structure of Cryptographic Authentication [[RFC 2328](#)]:



Parameters `length` (*int*) – packet length

Returns

Parsed packet data.

class `Auth(TypedDict):` `"""Cryptographic authentication."""`

#: key ID `key_id: int` #: authentication data length `len: int` #: cryptographic sequence number `seq: int`

Return type `DataType_Auth`

`__read_id_numbers()`

Read router and area IDs.

⁰ https://en.wikipedia.org/wiki/Open_Shortest_Path_First

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

```
class pcapkit.protocols.link.ospf.DataType_OSPF
    Bases TypedDict
    OSPF header.
    version: int
        version number
    type: pcapkit.const.ospf.packet.Packet
        type
    len: int
        packet length (header included)
    router_id: ipaddress.IPv4Address
        router ID
    area_id: ipaddress.IPv4Address
        area ID
    chksum: bytes
        checksum
    autype: pcapkit.const.ospf.authentication.Authentication
        authentication type
    auth: Union[bytes, DataType_Auth]
        authentication
```

Cryptographic Authentication Information

For cryptographic authentication information as described in [RFC 2328](#), its structure is described as below:

Octets	Bits	Name	Description
0	0		Reserved (must be zero \x00)
0	0	ospf.auth.key_id	Key ID
0	1	ospf.auth.len	Authentication Data Length
0	2	ospf.auth.seq	Cryptographic Sequence Number

```
class pcapkit.protocols.link.ospf.DataType_Auth
    Bases TypedDict
    Cryptographic authentication.
    key_id: int
        key ID
    len: int
        authentication data length
    seq: int
        cryptographic sequence number
```

RARP/DRARP - (Dynamic) Reverse Address Resolution Protocol

`pcapkit.protocols.link.rarp` contains *RARP* only, which implements extractor for (Dynamic) Reverse Address Resolution Protocol (RARP/DRARP)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>rarp.htype</code>	Hardware Type
2	16	<code>rarp.ptype</code>	Protocol Type
4	32	<code>rarp.hlen</code>	Hardware Address Length
5	40	<code>rarp.plen</code>	Protocol Address Length
6	48	<code>rarp.oper</code>	Operation
8	64	<code>rarp.sha</code>	Sender Hardware Address
14	112	<code>rarp.spa</code>	Sender Protocol Address
18	144	<code>rarp.tha</code>	Target Hardware Address
24	192	<code>rarp.tpa</code>	Target Protocol Address

class `pcapkit.protocols.link.rarp.RARP` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.link.arp.ARP`

This class implements Reverse Address Resolution Protocol.

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in *IANA*.

Return type `pcapkit.const.reg.ethertype.EtherType`

classmethod `id()`

Index ID of the protocol.

Returns Index ID of the protocol.

Return type `Tuple[Literal['RARP'], Literal['DRARP']]`

See also:

`pcapkit.protocols.protocol.Protocol.__getitem__()`

`_acnm = 'RARP'`

Acronym of corresponding protocol.

`_name = 'Reverse Address Resolution Protocol'`

Name of corresponding protocol.

VLAN - 802.1Q Customer VLAN Tag Type

`pcapkit.protocols.link.vlan` contains *VLAN* only, which implements extractor for 802.1Q Customer VLAN Tag Type*⁰, whose structure is described as below:

Octets	Bits	Name	Description
1	0	<code>vlan.tci</code>	Tag Control Information
1	0	<code>vlan.tci.pcp</code>	Priority Code Point
1	3	<code>vlan.tci.dei</code>	Drop Eligible Indicator
1	4	<code>vlan.tci.vid</code>	VLAN Identifier
3	24	<code>vlan.type</code>	Protocol (Internet Layer)

⁰ http://en.wikipedia.org/wiki/Address_Resolution_Protocol

⁰ https://en.wikipedia.org/wiki/IEEE_802.1Q

class pcapkit.protocols.link.vlan.VLAN (*file=None, length=None, **kwargs*)

Bases: *pcapkit.protocols.link.link.Link*

This class implements 802.1Q Customer VLAN Tag Type.

classmethod `__index__()`

Numeral registry index of the protocol.

Raises *UnsupportedCall* – This protocol has no registry entry.

`__length_hint__()`

Return an estimated length for the object.

Return type *Literal[4]*

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type *bytes*

read (*length=None, **kwargs*)

Read 802.1Q Customer VLAN Tag Type.

Parameters *length* (*Optional[int]*) – Length of packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_VLAN*

property *alias*

Acronym of corresponding protocol.

Return type *Literal['802.1Q']*

property *length*

Header length of current protocol.

Return type *Literal[4]*

property *name*

Name of current protocol.

Return type *Literal['802.1Q Customer VLAN Tag Type']*

property *protocol*

Name of next layer protocol.

Return type *pcapkit.const.reg.ethertype.EtherType*

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

```
class pcapkit.protocols.link.vlan.DataType_VLAN
    Bases TypedDict
    IEEE 802.1Q customer VLAN tag type [RFC 7042].
    tci: DataType_TCI
        Tag control information.
    type: pcapkit.const.reg.ethertype.EtherType
        Protocol (internet layer).
class pcapkit.protocols.link.vlan.DataType_TCI
    Bases TypedDict
    Tag control information.
    pcp: pcapkit.const.vlan.priority_level.PriorityLevel
        Priority code point.
    dei: bool
        Drop eligible indicator.
    vid: int
        VLAN identifier.
```

Base Protocol

`pcapkit.protocols.link.link` contains `Link`, which is a base class for link layer protocols, e.g. ARP/InARP, Ethernet, L2TP, OSPF, RARP/DRARP and etc.

```
class pcapkit.protocols.link.link.Link (file=None, length=None, **kwargs)
    Bases: pcapkit.protocols.protocol.Protocol
    Abstract base class for link layer protocol family.
    __layer__ = 'Link'
        Layer of protocol.
    __proto__: DefaultDict[int, Tuple[str, str]]
        Protocol index mapping for decoding next layer, c.f. self._decode_next_layer & self._import_next_layer. The values should be a tuple representing the module name and class name.
```

Code	Module	Class
0x0806	<code>pcapkit.protocols.link.arp</code>	ARP
0x8035	<code>pcapkit.protocols.link.rarp</code>	RARP
0x8100	<code>pcapkit.protocols.link.vlan</code>	VLAN
0x0800	<code>pcapkit.protocols.internet.ipv4</code>	IPv4
0x86DD	<code>pcapkit.protocols.internet.ipv6</code>	IPv6
0x8137	<code>pcapkit.protocols.internet.ipx</code>	IPX

`_import_next_layer` (*proto*, *length=None*)

Import next layer extractor.

This method currently supports following protocols as registered in *EtherType*:

proto	Protocol
0x0806	<i>ARP</i>
0x8035	<i>RARP</i>
0x8100	<i>VLAN</i>
0x0800	<i>IPv4</i>
0x86DD	<i>IPv6</i>
0x8137	<i>IPX</i>

Parameters

- **`proto`** (*int*) – next layer protocol index
- **`length`** (*int*) – valid (*non-padding*) length

Returns instance of next layer

Return type *pcapkit.protocols.protocol.Protocol*

`_read_protos` (*size*)

Read next layer protocol type.

Parameters **`size`** (*int*) – buffer size

Returns next layer's protocol enumeration

Return type *pcapkit.const.reg.ethertype.EtherType*

`property layer`

Protocol layer.

Return type `Literal['Link']`

1.3.3 Internet Layer Protocols

pcapkit.protocols.internet is collection of all protocols in internet layer, with detailed implementation and methods.

AH - Authentication Header

pcapkit.protocols.internet.ah contains AH only, which implements extractor for Authentication Header (AH)⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ah.next</code>	Next Header
1	8	<code>ah.length</code>	Payload Length
2	16		Reserved (must be zero)
4	32	<code>sah.spi</code>	Security Parameters Index (SPI)
8	64	<code>sah.seq</code>	Sequence Number Field
12	96	<code>sah.icv</code>	Integrity Check Value (ICV)

⁰ <https://en.wikipedia.org/wiki/IPsec>

```
class pcapkit.protocols.internet.ah.AH (file=None, length=None, **kwargs)
```

Bases: `pcapkit.protocols.internet.ipsec.IPsec`

This class implements Authentication Header.

```
classmethod __index__()
```

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in IANA.

Return type `pcapkit.const.reg.transype.TransType`

```
__length_hint__()
```

Return an estimated length for the object.

Return type `Literal[20]`

```
__post_init__(file, length=None, *, version=4, extension=False, **kwargs)
```

Post initialisation hook.

Parameters

- **file** (`io.BytesIO`) – Source packet stream.
- **length** (`Optional[int]`) – Length of packet data.

Keyword Arguments

- **version** (`Literal[4, 6]`) – IP protocol version.
- **extension** (`bool`) – If the protocol is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to `make()`.

```
classmethod id()
```

Index ID of the protocol.

Returns Index ID of the protocol.

Return type `Literal['AH']`

```
make(**kwargs)
```

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.


Returns Constructed packet data.

Return type `bytes`

```
read(length=None, *, version=4, extension=False, **kwargs)
```


Read Authentication Header.

Structure of AH header [RFC 4302]:



(continues on next page)

(continued from previous page)



Parameters `length` (*Optional*[`int`]) – Length of packet data.

Keyword Arguments

- **version** (*Literal*[4, 6]) – IP protocol version.
- **extension** (*bool*) – If the protocol is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_AH*

property `length`

Info dict of current instance.

Return type `int`

property `name`

Name of corresponding protocol.

Return type *Literal*['Authentication Header']

property `payload`

Payload of current instance.

Raises *UnsupportedCall* – if the protocol is used as an IPv6 extension header

Return type *pcapkit.protocols.protocol.Protocol*

property `protocol`

Name of next layer protocol.

Return type *pcapkit.const.reg.transtype.TransType*

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

class `pcapkit.protocols.internet.ah.DataType_AH`

Bases `TypedDict`

Authentication header [RFC 4302].

next: *pcapkit.const.reg.transtype.TransType*

Next header.

length: `int`

Payload length.

spi: `int`
Security parameters index (SPI).

seq: `int`
Sequence number field.

icv: `int`
Integrity check value (ICV).

HIP - Host Identity Protocol

`pcapkit.protocols.internet.hip` contains *HIP* only, which implements extractor for Host Identity Protocol (HIP)⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hip.next</code>	Next Header
1	8	<code>hip.length</code>	Header Length
2	16		Reserved (<code>\x00</code>)
2	17	<code>hip.type</code>	Packet Type
3	24	<code>hip.version</code>	Version
3	28		Reserved
3	31		Reserved (<code>\x01</code>)
4	32	<code>hip.chksum</code>	Checksum
6	48	<code>hip.control</code>	Controls
8	64	<code>hip.shit</code>	Sender's Host Identity Tag
24	192	<code>hip.rhit</code>	Receiver's Host Identity Tag
40	320	<code>hip.parameters</code>	HIP Parameters

class `pcapkit.protocols.internet.hip.HIP` (*file=None, length=None, **kwargs*)
Bases: `pcapkit.protocols.internet.internet.Internet`

This class implements Host Identity Protocol.

classmethod `__index__()`
Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in *IANA*.

Return type `pcapkit.const.reg.transype.TransType`

`__length_hint__()`
Return an estimated length for the object.

Return type `Literal[40]`

`__post_init__(file, length=None, *, extension=False, **kwargs)`
Post initialisation hook.

Parameters

- **file** (`io.BytesIO`) – Source packet stream.
- **length** (`Optional[int]`) – Length of packet data.

Keyword Arguments

- **extension** (`bool`) – If the protocol is used as an IPv6 extension header.

⁰ https://en.wikipedia.org/wiki/Host_Identity_Protocol

- ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to `make()`.

`_read_hip_para` (*length*, *, *version*)

Read HIP parameters.

Parameters *length* (*int*) – length of parameters

Keyword Arguments *version* (*Literal*[1, 2]) – HIP version

Returns extracted HIP parameters


Return type `Tuple[Tuple[pcapkit.const.hip.parameter.Parameter], DataType_Parameter]`

Raises *ProtocolError* – if packet length threshold check failed

`_read_para_ack` (*code*, *cbit*, *clen*, *, *desc*, *length*, *version*)

Read HIP ACK parameter.

Structure of HIP ACK parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (*pcapkit.const.hip.parameter.Parameter*) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_ACK*

Raises *ProtocolError* – If *clen* is **NOT** 4 modulo.

`_read_para_ack_data` (*code*, *cbit*, *clen*, *, *desc*, *length*, *version*)

Read HIP ACK_DATA parameter.

Structure of HIP ACK_DATA parameter [RFC 6078]:



(continues on next page)

(continued from previous page)

```

+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
|                                     Acked Sequence number                               /
/                                                                              /
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+

```

Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.**Return type** *DataType_Param_ACK_Data***Raises** *ProtocolError* – If clen is **NOT** 4 modulo.**_read_para_cert** (*code, cbit, clen, *, desc, length, version*)

Read HIP CERT parameter.

Structure of HIP CERT parameter [RFC 7401]:

```

0                               1                               2                               3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
|                                     Type                                     | Length |
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
| CERT group | CERT count | CERT ID | CERT type |
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
|                                     Certificate                               /
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
/                                     | Padding (variable length) |
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+

```

Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments


- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.**Return type** *DataType_Param_Cert*

`_read_para_dh_group_list` (*code, cbit, clen, *, desc, length, version*)

Read HIP DH_GROUP_LIST parameter.

Structure of HIP DH_GROUP_LIST parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version


Returns Parsed parameter data.

Return type `DataType_Param_DH_Group_List`

`_read_para_diffie_hellman` (*code, cbit, clen, *, desc, length, version*)

Read HIP DIFFIE_HELLMAN parameter.

Structure of HIP DIFFIE_HELLMAN parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type

- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version


Returns Parsed parameter data.

Return type `DataType_Param_Diffie_Hellman`

`_read_para_echo_request_signed` (*code, cbit, clen, *, desc, length, version*)

Read HIP ECHO_REQUEST_SIGNED parameter.

Structure of HIP ECHO_REQUEST_SIGNED parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version


Returns Parsed parameter data.

Return type `DataType_Param_Echo_Request_Signed`

`_read_para_echo_request_unsigned` (*code, cbit, clen, *, desc, length, version*)

Read HIP ECHO_REQUEST_UNSIGNED parameter.

Structure of HIP ECHO_REQUEST_UNSIGNED parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version


Returns Parsed parameter data.

Return type `DataType_Param_Echo_Request_Unsigned`

`_read_para_echo_response_signed` (`code, cbit, clen, *, desc, length, version`)

Read HIP ECHO_RESPONSE_SIGNED parameter.

Structure of HIP ECHO_RESPONSE_SIGNED parameter [RFC 7401]:



Parameters

- **code** (`int`) – parameter code
- **cbit** (`bool`) – critical bit
- **clen** (`int`) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version


Returns Parsed parameter data.

Return type `DataType_Param_Echo_Response_Signed`

`_read_para_echo_response_unsigned` (`code, cbit, clen, *, desc, length, version`)

Read HIP ECHO_RESPONSE_UNSIGNED parameter.

Structure of HIP ECHO_RESPONSE_UNSIGNED parameter [RFC 7401]:



Parameters

- **code** (`int`) – parameter code
- **cbit** (`bool`) – critical bit
- **clen** (`int`) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version


Returns Parsed parameter data.

Return type `DataType_Param_Echo_Response_Unsigned`

`_read_para_encrypted` (`code, cbit, clen, *, desc, length, version`)

Read HIP ENCRYPTED parameter.

Structure of HIP ENCRYPTED parameter [RFC 7401]:

**Parameters**

- **code** (`int`) – parameter code
- **cbit** (`bool`) – critical bit
- **clen** (`int`) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version


Returns Parsed parameter data.

Return type `DataType_Param_Encrypted`

`_read_para_esp_info` (`code, cbit, clen, *, desc, length, version`)


Read HIP ESP_INFO parameter.

Structure of HIP ESP_INFO parameter [RFC 7402]:



(continues on next page)

(continued from previous page)

**Parameters**

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents


Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.**Return type** *DataType_Param_ESP_Info***Raises** *ProtocolError* – If clen is NOT 12.**`_read_para_esp_transform`** (*code, cbit, clen, *, desc, length, version*)

Read HIP ESP_TRANSFORM parameter.

Structure of HIP ESP_TRANSFORM parameter [RFC 7402]:

**Parameters**

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Transform_Format_List*

Raises *ProtocolError* – If clen is NOT 2 modulo.

`_read_para_from` (*code, cbit, clen, *, desc, length, version*)

Read HIP FROM parameter.

Structure of HIP FROM parameter [RFC 8004]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (*pcapkit.const.hip.parameter.Parameter*) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal[1, 2]*) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_From*

Raises *ProtocolError* – If clen is NOT 16.

`_read_para_hip_cipher` (*code, cbit, clen, *, desc, length, version*)

Read HIP HIP_CIPHER parameter.

Structure of HIP HIP_CIPHER parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code

- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Cipher*

Raises *ProtocolError* – If clen is NOT a 2 modulo.

_read_para_hip_mac (*code, cbit, clen, *, desc, length, version*)

Read HIP HIP_MAC parameter.

Structure of HIP HIP_MAC parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_HMAC*

_read_para_hip_mac_2 (*code, cbit, clen, *, desc, length, version*)


Read HIP HIP_MAC_2 parameter.

Structure of HIP HIP_MAC_2 parameter [RFC 7401]:



(continues on next page)

(continued from previous page)



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_HMAC_2*

_read_para_hip_signature (*code, cbit, clen, *, desc, length, version*)

Read HIP `HIP_SIGNATURE` parameter.

Structure of HIP HIP_SIGNATURE parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_Signature*

`_read_para_hip_signature_2` (*code, cbit, clen, *, desc, length, version*)

Read HIP HIP_SIGNATURE_2 parameter.

Structure of HIP HIP_SIGNATURE_2 parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version


Returns Parsed parameter data.

Return type `DataType_Param_Signature_2`

`_read_para_hip_transform` (*code, cbit, clen, *, desc, length, version*)

Read HIP HIP_TRANSFORM parameter.

Structure of HIP HIP_TRANSFORM parameter [RFC 5201]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length

- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Transform*

Raises *ProtocolError* – The parameter is **ONLY** supported in HIPv1.

`_read_para_hip_transport_mode` (*code, cbit, clen, *, desc, length, version*)

Read HIP HIP_TRANSPORT_MODE parameter.

Structure of HIP HIP_TRANSPORT_MODE parameter [RFC 6261]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Transport_Mode*

Raises *ProtocolError* – If clen is **NOT** 2 modulo.

`_read_para_hit_suite_list` (*code, cbit, clen, *, desc, length, version*)

Read HIP HIT_SUITE_LIST parameter.

Structure of HIP HIT_SUITE_LIST parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_HIT_Suite_List*

`_read_para_host_id` (*code, cbit, clen, *, desc, length, version*)

Read HIP HOST_ID parameter.

Structure of HIP HOST_ID parameter [[RFC 7401](#)]:

**Parameters**

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_Host_ID*

`_read_para_locator_set` (*code, cbit, clen, *, desc, length, version*)

Read HIP LOCATOR_SET parameter.

Structure of HIP LOCATOR_SET parameter [[RFC 8046](#)]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Locator_Set*

Raises *ProtocolError* – If locator data is malformed.

```
_read_para_nat_traversal_mode(code, cbit, clen, *, desc, length, version)
```


Read HIP NAT_TRAVERSAL_MODE parameter.

Structure of HIP NAT_TRAVERSAL_MODE parameter [RFC 5770]:



(continues on next page)

(continued from previous page)



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_NET_Traversal_Mode*

Raises *ProtocolError* – If clen is **NOT** a 2 modulo.

```
_read_para_notification (code, cbit, clen, *, desc, length, version)
```

Read HIP NOTIFICATION parameter.

Structure of HIP NOTIFICATION parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Notification*

Raises *ProtocolError* – Unregistered notify message type.

`_read_para_overlay_id` (*code, cbit, clen, *, desc, length, version*)

Read HIP OVERLAY_ID parameter.

Structure of HIP OVERLAY_ID parameter [RFC 6079]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal[1, 2]*) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_Overlay_ID*

`_read_para_overlay_ttl` (*code, cbit, clen, *, desc, length, version*)

Read HIP OVERLAY_TTL parameter.

Structure of HIP OVERLAY_TTL parameter [RFC 6078]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type

- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Relay_To*

Raises *ProtocolError* – If clen is NOT 4.

`_read_para_payload_mic` (*code, cbit, clen, *, desc, length, version*)

Read HIP PAYLOAD_MIC parameter.

Structure of HIP PAYLOAD_MIC parameter [RFC 6078]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (*pcapkit.const.hip.parameter.Parameter*) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_Payload_MIC*

`_read_para_puzzle` (*code, cbit, clen, *, desc, length, version*)


Read HIP PUZZLE parameter.

Structure of HIP PUZZLE parameter [RFC 5201][RFC 7401]:



(continues on next page)

(continued from previous page)



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Puzzle*

Raises *ProtocolError* – The parameter is **ONLY** supported in HIPv1.

```
_read_para_r1_counter (code, cbit, clen, *, desc, length, version)
```

Read HIP R1_COUNTER parameter.

Structure of HIP R1_COUNTER parameter [RFC 5201][RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_R1_Counter*

Raises *ProtocolError* – If `clen` is **NOT** 12 or the parameter is **NOT** used in HIPv1.

`_read_para_reg_failed` (*code, cbit, clen, *, desc, length, version*)

Read HIP REG_FAILED parameter.

Structure of HIP REG_FAILED parameter [RFC 8003]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type `DataType_Param_Reg_Failed`

Raises `ProtocolError` – If the registration type is invalid.

`_read_para_reg_from` (*code, cbit, clen, *, desc, length, version*)

Read HIP REG_FROM parameter.

Structure of HIP REG_FROM parameter [RFC 5770]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit

- `clen` (*int*) – length of contents

Keyword Arguments

- `desc` (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- `length` (*int*) – remaining packet length
- `version` (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type `DataType_Param_Reg_From`

Raises `ProtocolError` – If `clen` is NOT 20.

`_read_para_reg_info` (*code, cbit, clen, *, desc, length, version*)

Read HIP REG_INFO parameter.

Structure of HIP REG_INFO parameter [RFC 8003]:



Parameters

- `code` (*int*) – parameter code
- `cbit` (*bool*) – critical bit
- `clen` (*int*) – length of contents

Keyword Arguments

- `desc` (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- `length` (*int*) – remaining packet length
- `version` (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type `DataType_Param_Reg_Info`

Raises `ProtocolError` – If the registration type is invalid.

`_read_para_reg_request` (*code, cbit, clen, *, desc, length, version*)

Read HIP REG_REQUEST parameter.

Structure of HIP REG_REQUEST parameter [RFC 8003]:



(continues on next page)

(continued from previous page)

```

+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
| Lifetime | Reg Type #1 | Reg Type #2 | Reg Type #3 |
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
| ... | ... | Reg Type #n |
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
|                                     Padding
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+

```

Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.**Return type** *DataType_Param_Reg_Request***Raises** *ProtocolError* – If the registration type is invalid.**_read_para_reg_response** (*code, cbit, clen, *, desc, length, version*)

Read HIP REG_RESPONSE parameter.

Structure of HIP REG_RESPONSE parameter [RFC 8003]:

```

0                               1                               2                               3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
|                                     Type                                     |
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
| Lifetime | Reg Type #1 | Reg Type #2 | Reg Type #3 |
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
| ... | ... | Reg Type #n |
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
|                                     Padding
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+

```

Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Reg_Response*

Raises *ProtocolError* – If the registration type is invalid.

`_read_para_relay_from` (*code, cbit, clen, *, desc, length, version*)

Read HIP RELAY_FROM parameter.

Structure of HIP RELAY_FROM parameter [RFC 5770]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (*pcapkit.const.hip.parameter.Parameter*) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal[1, 2]*) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Relay_From*

Raises *ProtocolError* – If clen is NOT 20.

`_read_para_relay_hmac` (*code, cbit, clen, *, desc, length, version*)

Read HIP RELAY_HMAC parameter.

Structure of HIP RELAY_HMAC parameter [RFC 5770]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_Relay_HMAC*

`_read_para_relay_to` (*code, cbit, clen, *, desc, length, version*)

Read HIP RELAY_TO parameter.

Structure of HIP RELAY_TO parameter [RFC 5770]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Relay_To*

Raises *ProtocolError* – If clen is NOT 20.

`_read_para_route_dst` (*code, cbit, clen, *, desc, length, version*)

Read HIP ROUTE_DST parameter.

Structure of HIP ROUTE_DST parameter [RFC 6028]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (`int`) – remaining packet length
- **version** (`Literal[1, 2]`) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Route_Dst*

Raises *ProtocolError* – If the parameter is malformed.

_read_para_route_via (*code, cbit, clen, *, desc, length, version*)


Read HIP ROUTE_VIA parameter.

Structure of HIP ROUTE_VIA parameter [RFC 6028]:



(continues on next page)

(continued from previous page)



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Route_Via*

Raises *ProtocolError* – If the parameter is malformed.

`_read_para_rvs_hmac` (*code, cbit, clen, *, desc, length, version*)

Read HIP RVS_HMAC parameter.

Structure of HIP RVS_HMAC parameter [RFC 8004]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version


Returns Parsed parameter data.

Return type *DataType_Param_RVS_HMAC*

`_read_para_seq` (*code*, *cbit*, *clen*, *, *desc*, *length*, *version*)

Read HIP SEQ parameter.

Structure of HIP SEQ parameter [RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_SEQ*

Raises *ProtocolError* – If *clen* is NOT 4.

`_read_para_seq_data` (*code*, *cbit*, *clen*, *, *desc*, *length*, *version*)

Read HIP SEQ_DATA parameter.

Structure of HIP SEQ_DATA parameter [RFC 6078]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length

- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_SEQ_Data*

Raises *ProtocolError* – If clen is NOT 4.

`_read_para_solution` (*code, cbit, clen, *, desc, length, version*)

Read HIP SOLUTION parameter.

Structure of HIP SOLUTION parameter [RFC 5201][RFC 7401]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (*pcapkit.const.hip.parameter.Parameter*) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal*[1, 2]) – HIP protocol version

Returns Parsed parameter data.


Return type *DataType_Param_Solution*

Raises *ProtocolError* – The parameter is **ONLY** supported in HIPv1.

`_read_para_transaction_id` (*code, cbit, clen, *, desc, length, version*)

Read HIP TRANSACTION_ID parameter.

Structure of HIP TRANSACTION_ID parameter [RFC 6078]:






`_read_para_via_rvs` (*code, cbit, clen, *, desc, length, version*)

Read HIP VIA_RVS parameter.

Structure of HIP VIA_RVS parameter [RFC 6028]:



Parameters

- **code** (*int*) – parameter code
- **cbit** (*bool*) – critical bit
- **clen** (*int*) – length of contents

Keyword Arguments

- **desc** (`pcapkit.const.hip.parameter.Parameter`) – parameter type
- **length** (*int*) – remaining packet length
- **version** (*Literal[1, 2]*) – HIP protocol version

Returns Parsed parameter data.

Return type `DataType_Param_Route_Via`

Raises `ProtocolError` – If `clen` is NOT 16 modulo.

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.


Returns Constructed packet data.

Return type `bytes`

read (*length=None, *, extension=False, **kwargs*)

Read Host Identity Protocol.

Structure of HIP header [RFC 5201][RFC 7401]:



(continues on next page)

```

| Next Header | Header Length | 0 | Packet Type | Version | RES. | 1 |
+-----+-----+-----+-----+-----+-----+-----+
| Checksum | Controls |
+-----+-----+-----+-----+-----+-----+-----+
| Sender's Host Identity Tag (HIT) |
| |
| |
| |
+-----+-----+-----+-----+-----+-----+-----+
| Receiver's Host Identity Tag (HIT) |
| |
| |
| |
+-----+-----+-----+-----+-----+-----+-----+
| |
/ HIP Parameters /
/ /
| |
+-----+-----+-----+-----+-----+-----+-----+

```

Keyword Arguments

- Returns** Parsed packet data.

Raises *ProtocolError* – If the packet is malformed.

Acronym of corresponding protocol.

```
property length
```

Return type `int`

Name of current protocol.

property payload

Raises *UnsupportedCall* – if the protocol is used as an IPv6 extension header

Return type *pcapkit.protocols.protocol.Protocol*

Name of next layer protocol.

Return type *pcapkit.const.reg.transtype.TransType*

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

```
class pcapkit.protocols.internet.hip.DataType_HIP
    Bases TypedDict
    HIP header [RFC 5201][RFC 7401].
    next: pcapkit.const.reg.transtype.TransType
        Next header.
    length: int
        Header length.
    type: pcapkit.const.hip.packet.Packet
        Packet type.
    version: Literal[1, 2]
        Version.
    chksum: bytes
        Checksum.
    control: DataType_Control
        Controls.
    shit: int
        Sender's host identity tag.
    rhit: int
        Receiver's host identity tag.
    parameters: Optional[Tuple[pcapkit.const.hip.parameter.Parameter]]
        HIP parameters.

class pcapkit.protocols.internet.hip.DataType_Control
    Bases TypedDict
    HIP controls.
    anonymous: bool
        Anonymous.

class pcapkit.protocols.internet.hip.DataType_Parameter
    Bases TypedDict
    HIP parameters.
    type: pcapkit.const.hip.parameter.Parameter
        Parameter type.
    critical: bool
        Critical bit.
    length: int
        Length of contents.
```

HIP Unassigned Parameters

For HIP unassigned parameters as described in [RFC 5201](#) and [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	para.type	Parameter Type
1	15	para.critical	Critical Bit
2	16	para.length	Length of Contents
4	32	para.contents	Contents Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Unassigned
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP unassigned parameters [RFC 5201][RFC 7401].
```

```
    contents: bytes
        Contents.
```

HIP ESP_INFO Parameter

For HIP ESP_INFO parameter as described in [RFC 7402](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	esp_info.type	Parameter Type
1	15	esp_info.critical	Critical Bit
2	16	esp_info.length	Length of Contents
4	32		Reserved
6	48	esp_info.index	KEYMAT Index
8	64	esp_info.old_spi	OLD SPI
12	96	esp_info.new_spi	NEW SPI

```
class pcapkit.protocols.internet.hip.DataType_Param_ESP_Info
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP ESP_INFO parameter [RFC 7402].
```

```
    index: int
        KEYMAT index.
```

```
    old_spi: int
        Old SPI.
```

```
    new_spi: int
        New SPI.
```

HIP R1_COUNTER Parameter

For HIP R1_COUNTER parameter as described in [RFC 5201](#) and [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ri_counter.type	Parameter Type
1	15	ri_counter.critical	Critical Bit
2	16	ri_counter.length	Length of Contents
4	32		Reserved
8	64	ri_counter.count	Generation of Valid Puzzles

```
class pcapkit.protocols.internet.hip.DataType_Param_R1_Counter
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP R1_COUNTER parameter [RFC 5201][RFC 7401].
```

```
    count: int
           Generation of valid puzzles.
```

HIP LOCATOR_SET Parameter

For HIP LOCATOR_SET parameter as described in [RFC 8046](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	locator_set.type	Parameter Type
1	15	locator_set.critical	Critical Bit
2	16	locator_set.length	Length of Contents
?	?
4	32	locator.traffic	Traffic Type
5	40	locator.type	Locator Type
6	48	locator.length	Locator Length
7	56		Reserved
7	63	locator.preferred	Preferred Locator
8	64	locator.lifetime	Locator Lifetime
12	96	locator.object	Locator
?	?

```
class pcapkit.protocols.internet.hip.DataType_Param_Locator_Set
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP LOCATOR_SET parameter [RFC 8046].
```

```
    locator: Tuple[DataType_Locator]
            Locator set.
```

```
class pcapkit.protocols.internet.hip.DataType_Locator
```

```
    Bases: TypedDict
```

```
    Locator.
```

```
    traffic: int
            Traffic type.
```

```

    type: int
        Locator type.

    length: int
        Locator length.

    preferred: int
        Preferred length.

    lifetime: int
        Locator lifetime.

    object: DataType_Locator_Dict
        Locator.

class pcapkit.protocols.internet.hip.DataType_Locator_Dict
    Bases TypedDict

    Locator type 2.

    spi: int
        SPI.

    ip: ipaddress.IPv4Address

```

HIP PUZZLE Parameter

For HIP PUZZLE parameter as described in [RFC 5201](#) and [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	puzzle.type	Parameter Type
1	15	puzzle.critical	Critical Bit
2	16	puzzle.length	Length of Contents
4	32	puzzle.number	Number of Verified Bits
5	40	puzzle.lifetime	Lifetime
6	48	puzzle.opaque	Opaque
8	64	puzzle.random	Random Number

```

class pcapkit.protocols.internet.hip.DataType_Param_Puzzle
    Bases DataType_Parameter

    Structure of HIP PUZZLE parameter [RFC 5201][RFC 7401].

    number: int
        Number of verified bits.

    lifetime: int
        Lifetime.

    opaque: bytes
        Opaque.

    random: int
        Random number.

```

HIP SOLUTION Parameter

For HIP SOLUTION parameter as described in [RFC 5201](#) and [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	solution.type	Parameter Type
1	15	solution.critical	Critical Bit
2	16	solution.length	Length of Contents
4	32	solution.number	Number of Verified Bits
5	40	solution.lifetime	Lifetime
6	48	solution.opaque	Opaque
8	64	solution.random	Random Number
?	?	solution.solution	Puzzle Solution

```
class pcapkit.protocols.internet.hip.DataType_Param_Solution
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP SOLUTION parameter [RFC 5201][RFC 7401].
```

```
    number: number
        Number of verified bits.
```

```
    lifetime: int
        Lifetime.
```

```
    opaque: bytes
        Opaque.
```

```
    random: int
        Random number.
```

```
    solution: int
        Puzzle solution.
```

HIP SEQ Parameter

For HIP SEQ parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	seq.type	Parameter Type
1	15	seq.critical	Critical Bit
2	16	seq.length	Length of Contents
4	32	seq.id	Update ID

```
class pcapkit.protocols.internet.hip.DataType_Param_SEQ
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP SEQ parameter [RFC 7401].
```

```
    id: int
        Update ID.
```


HIP ACK Parameter

For HIP ACK parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ack.type	Parameter Type
1	15	ack.critical	Critical Bit
2	16	ack.length	Length of Contents
4	32	ack.id	Peer Update ID

```
class pcapkit.protocols.internet.hip.DataType_Param_ACK
```

```
    Bases: DataType_Parameter
```

```
    id: Tuple[int]
```

```
        Array of peer update IDs.
```

HIP DH_GROUP_LIST Parameter

For HIP DH_GROUP_LIST parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	dh_group_list.type	Parameter Type
1	15	dh_group_list.critical	Critical Bit
2	16	dh_group_list.length	Length of Contents
4	32	dh_group_list.id	DH GROUP ID

```
class pcapkit.protocols.internet.hip.DataType_Param_DH_Group_List
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP DH_GROUP_LIST parameter [RFC 7401].
```

```
    id: Tuple[pcapkit.const.hip.group.Group]
```

```
        Array of DH group IDs.
```

HIP DEFFIE_HELLMAN Parameter

For HIP DEFFIE_HELLMAN parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	diffie_hellman.type	Parameter Type
1	15	diffie_hellman.critical	Critical Bit
2	16	diffie_hellman.length	Length of Contents
4	32	diffie_hellman.id	Group ID
5	40	diffie_hellman.pub_len	Public Value Length
6	48	diffie_hellman.pub_val	Public Value
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Deffie_Hellman
```

```
    Bases: DataType_Parameter
```

Structure of HIP DEFFIE_HELLMAN parameter [RFC 7401].

id: `pcapkit.const.hip.group.Group`
Group ID.

pub_len: `int`
Public value length.

pub_val: `bytes`
Public value.

HIP HIP_TRANSFORM Parameter

For HIP HIP_TRANSFORM parameter as described in RFC 5201, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hip_transform.type</code>	Parameter Type
1	15	<code>hip_transform.critical</code>	Critical Bit
2	16	<code>hip_transform.length</code>	Length of Contents
4	32	<code>hip_transform.id</code>	Group ID
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Transform
```

Bases `DataType_Parameter`

Structure of HIP HIP_TRANSFORM parameter [RFC 5201].

id: `Tuple[pcapkit.const.hip.suite.Suite]`
Array of group IDs.

HIP HIP_CIPHER Parameter

For HIP HIP_CIPHER parameter as described in RFC 7401, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hip_cipher.type</code>	Parameter Type
1	15	<code>hip_cipher.critical</code>	Critical Bit
2	16	<code>hip_cipher.length</code>	Length of Contents
4	32	<code>hip_cipher.id</code>	Cipher ID
?	?
?	?	.	Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Cipher
```

Bases `DataType_Parameter`

Structure of HIP HIP_CIPHER parameter [RFC 7401].

id: `Tuple[pcapkit.const.hip.cipher.Cipher]`
Array of cipher IDs.

HIP NAT_TRAVERSAL_MODE Parameter

For HIP NAT_TRAVERSAL_MODE parameter as described in [RFC 5770](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	nat_traversal_mode.type	Parameter Type
1	15	nat_traversal_mode.critical	Critical Bit
2	16	nat_traversal_mode.length	Length of Contents
4	32		Reserved
6	48	nat_traversal_mode.id	Mode ID
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_NET_Traversal_Mode
```

```
    Bases: DataType_Parameter
```

Structure of HIP NAT_TRAVERSAL_MODE parameter [\[RFC 5770\]](#).

```
    id: Tuple[pcapkit.const.hip.nat_traversal.NETTraversal]
        Array of mode IDs.
```

HIP TRANSACTION_PACING Parameter

For HIP TRANSACTION_PACING parameter as described in [RFC 5770](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	transaction_pacing.type	Parameter Type
1	15	transaction_pacing.critical	Critical Bit
2	16	transaction_pacing.length	Length of Contents
4	32	transaction_pacing.min_ta	Min Ta

```
class pcapkit.protocols.internet.hip.DataType_Param_Transaction_Pacing
```

```
    Bases: DataType_Parameter
```

Structure of HIP TRANSACTION_PACING parameter [\[RFC 5770\]](#).

```
    min_ta: int
        Min Ta.
```

HIP ENCRYPTED Parameter

For HIP ENCRYPTED parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	encrypted.type	Parameter Type
1	15	encrypted.critical	Critical Bit
2	16	encrypted.length	Length of Contents
4	32		Reserved
8	48	encrypted.iv	Initialization Vector
?	?	encrypted.data	Encrypted data
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Encrypted
```

```
    Bases: DataType_Parameter
```

Structure of HIP ENCRYPTED parameter [RFC 7401].

```
    raw: bytes
```

Raw content data.

HIP HOST_ID Parameter

For HIP HOST_ID parameter as described in RFC 7401, its structure is described as below:

Octets	Bits	Name	Description
0	0	host_id.type	Parameter Type
1	15	host_id.critical	Critical Bit
2	16	host_id.length	Length of Contents
4	32	host_id.id_len	Host Identity Length
6	48	host_id.di_type	Domain Identifier Type
6	52	host_id.di_len	Domain Identifier Length
8	64	host_id.algorithm	Algorithm
10	80	host_id.host_id	Host Identity
?	?	host_id.domain_id	Domain Identifier
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Host_ID
```

```
    Bases: DataType_Parameter
```

Structure of HIP HOST_ID parameter [RFC 7401].

```
    id_len: int
```

Host identity length.

```
    di_type: pcapkit.const.hip.di_type.DIType
```

Domain identifier type.

```
    di_len: int
```

Domain identifier length.

```
    algorithm: pcapkit.const.hip.hi_algorithm.HIAlgorithm
```

Algorithm.

```
    host_id: Union[bytes, DataType_Host_ID_ECDSA_Curve, DataType_Host_ID_ECDSA_LOW_Curve]
```

Host identity.

```
    domain_id: bytes
```

Domain identifier.

```
class pcapkit.protocols.internet.hip.DataType_Host_ID_ECDSA_Curve
```

```
    Bases: TypedDict
```

Host identity data.

```
    curve: pcapkit.const.hip.ecdsa_curve.ECDSACurve
```

ECDSA curve.

```
    pubkey: bytes
```

Public key.

```
class pcapkit.protocols.internet.hip.DataType_Host_ID_ECDSA_LOW_Curve
```

Bases TypedDict

Host identity data.

curve: `pcapkit.const.hip.ecdsa_low_curve.ECDSALowCurve`
ECDSA_Low curve.

pubkey: `bytes`
Public key.

HIP HIT_SUITE_LIST Parameter

For HIP HIT_SUITE_LIST parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hit_suite_list.type	Parameter Type
1	15	hit_suite_list.critical	Critical Bit
2	16	hit_suite_list.length	Length of Contents
4	32	hit_suite_list.id	HIT Suite ID
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_HIT_Suite_List
```

Bases DataType_Parameter

Structure of HIP HIT_SUITE_LIST parameter [[RFC 7401](#)].

id: `Tuple[pcapkit.const.hip.hit_suite.HITSuite]`
Array of HIT suite IDs.

HIP CERT Parameter

For HIP CERT parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	cert.type	Parameter Type
1	15	cert.critical	Critical Bit
2	16	cert.length	Length of Contents
4	32	cert.group	CERT Group
5	40	cert.count	CERT Count
6	48	cert.id	CERT ID
7	56	cert.cert_type	CERT Type
8	64	cert.certificate	Certificate
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Cert
```

Bases DataType_Parameter

Structure of HIP CERT parameter [[RFC 7401](#)].

group: `pcapkit.const.hip.group.Group`
CERT group.

```
count: int
    CERT count.

id: int
    CERT ID.

cert_type: pcapkit.const.hip.certificate.Certificate

certificate: bytes
    Certificate.
```

HIP NOTIFICATION Parameter

For HIP NOTIFICATION parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	notification.type	Parameter Type
1	15	notification.critical	Critical Bit
2	16	notification.length	Length of Contents
4	32		Reserved
6	48	notification.msg_type	Notify Message Type
8	64	notification.data	Notification Data
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Notification
```

```
    Bases: DataType_Parameter
```

Structure of HIP NOTIFICATION parameter [[RFC 7401](#)].

```
msg_type: pcapkit.const.hip.notify_message.NotifyMessage
    Notify message type.
```

```
data: bytes
    Notification data.
```

HIP ECHO_REQUEST_SIGNED Parameter

For HIP ECHO_REQUEST_SIGNED parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	echo_request_signed.type	Parameter Type
1	15	echo_request_signed.critical	Critical Bit
2	16	echo_request_signed.length	Length of Contents
4	32	echo_request_signed.data	Opaque Data

```
class pcapkit.protocols.internet.hip.DataType_Param_Echo_Request_Signed
```

```
    Bases: DataType_Parameter
```

Structure of HIP ECHO_REQUEST_SIGNED parameter [[RFC 7401](#)].

```
data: bytes
    Opaque data.
```

HIP REG_INFO Parameter

For HIP REG_INFO parameter as described in [RFC 8003](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	reg_info.type	Parameter Type
1	15	reg_info.critical	Critical Bit
2	16	reg_info.length	Length of Contents
4	32	reg_info.lifetime	Lifetime
4	32	reg_info.lifetime.min	Min Lifetime
5	40	reg_info.lifetime.max	Max Lifetime
6	48	reg_info.reg_type	Reg Type
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Reg_Info
    Bases: DataType_Parameter
    Structure of HIP REG_INFO parameter [RFC 8003].
    lifetime:   DataType_Lifetime
                Lifetime.
    reg_type:   Tuple[pcapkit.const.hip.registration.Registration]
                Array of registration type.

class pcapkit.protocols.internet.hip.DataType_Lifetime
    Bases: NamedTuple
    Lifetime.
    min: int
        Minimum lifetime.
    maz: int
        Maximum lifetime.
```

HIP REG_REQUEST Parameter

For HIP REG_REQUEST parameter as described in [RFC 8003](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	reg_request.type	Parameter Type
1	15	reg_request.critical	Critical Bit
2	16	reg_request.length	Length of Contents
4	32	reg_request.lifetime	Lifetime
4	32	reg_request.lifetime.min	Min Lifetime
5	40	reg_request.lifetime.max	Max Lifetime
6	48	reg_request.reg_type	Reg Type
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Reg_Request
```

Bases `DataType_Parameter`

Structure of HIP `REG_REQUEST` parameter [RFC 8003].

lifetime: `DataType_Lifetime`

Lifetime.

reg_type: `Tuple[pcapkit.const.hip.registration.Registration]`

Array of registration type.

HIP `REG_RESPONSE` Parameter

For HIP `REG_RESPONSE` parameter as described in RFC 8003, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>reg_response.type</code>	Parameter Type
1	15	<code>reg_response.critical</code>	Critical Bit
2	16	<code>reg_response.length</code>	Length of Contents
4	32	<code>reg_response.lifetime</code>	Lifetime
4	32	<code>reg_response.lifetime.min</code>	Min Lifetime
5	40	<code>reg_response.lifetime.max</code>	Max Lifetime
6	48	<code>reg_response.reg_type</code>	Reg Type
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Reg_Response
```

Bases `DataType_Parameter`

Structure of HIP `REG_RESPONSE` parameter [RFC 8003].

lifetime: `DataType_Lifetime`

Lifetime.

reg_type: `Tuple[pcapkit.const.hip.registration.Registration]`

Array of registration type.

HIP `REG_FAILED` Parameter

For HIP `REG_FAILED` parameter as described in RFC 8003, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>reg_failed.type</code>	Parameter Type
1	15	<code>reg_failed.critical</code>	Critical Bit
2	16	<code>reg_failed.length</code>	Length of Contents
4	32	<code>reg_failed.lifetime</code>	Lifetime
4	32	<code>reg_failed.lifetime.min</code>	Min Lifetime
5	40	<code>reg_failed.lifetime.max</code>	Max Lifetime
6	48	<code>reg_failed.reg_type</code>	Reg Type
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Reg_Failed
```


Bases `DataType_Parameter`

Structure of HIP `REG_FAILED` parameter [RFC 8003].

lifetime: `DataType_Lifetime`

Lifetime.

reg_type: `Tuple[pcapkit.const.hip.registration.Registration]`

Array of registration type.

HIP `REG_FROM` Parameter

For HIP `REG_FROM` parameter as described in RFC 5770, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>reg_from.type</code>	Parameter Type
1	15	<code>reg_from.critical</code>	Critical Bit
2	16	<code>reg_from.length</code>	Length of Contents
4	32	<code>reg_from.port</code>	Port
6	48	<code>reg_from.protocol</code>	Protocol
7	56		Reserved
8	64	<code>reg_from.ip</code>	Address (IPv6)

```
class pcapkit.protocols.internet.hip.DataType_Param_Reg_From
```

Bases `DataType_Parameter`

Structure of HIP `REG_FROM` parameter [RFC 5770].

port: `int`

Port.

protocol: `pcapkit.const.reg.transtype.TransType`

Protocol.

ip: `ipaddress.IPv6Address`

IPv6 address.

HIP `ECHO_RESPONSE_SIGNED` Parameter

For HIP `ECHO_RESPONSE_SIGNED` parameter as described in RFC 7401, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>echo_response_signed.type</code>	Parameter Type
1	15	<code>echo_response_signed.critical</code>	Critical Bit
2	16	<code>echo_response_signed.length</code>	Length of Contents
4	32	<code>echo_response_signed.data</code>	Opaque Data

```
class pcapkit.protocols.internet.hip.DataType_Param_Echo_Response_Signed
```

Bases `DataType_Parameter`

Structure of HIP `ECHO_RESPONSE_SIGNED` parameter [RFC 7401].

data: `bytes`

Opaque data.

HIP TRANSPORT_FORMAT_LIST Parameter

For HIP TRANSPORT_FORMAT_LIST parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	transport_format_list.type	Parameter Type
1	15	transport_format_list.critical	Critical Bit
2	16	transport_format_list.length	Length of Contents
4	32	transport_format_list.tf_type	TF Type
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Transform_Format_List
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP TRANSPORT_FORMAT_LIST parameter [RFC 7401].
```

```
    tf_type: Tuple[int]
```

```
        Array of TF types.
```

HIP ESP_TRANSFORM Parameter

For HIP ESP_TRANSFORM parameter as described in [RFC 7402](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	esp_transform.type	Parameter Type
1	15	esp_transform.critical	Critical Bit
2	16	esp_transform.length	Length of Contents
4	32		Reserved
6	48	esp_transform.id	Suite ID
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_ESP_Transform
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP ESP_TRANSFORM parameter [RFC 7402].
```

```
    id: Tuple[pcapkit.const.hip.esp_transform_suite.ESPTransformSuite]
```

```
        Array of suite IDs.
```

HIP SEQ_DATA Parameter

For HIP SEQ_DATA parameter as described in [RFC 6078](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	seq_data.type	Parameter Type
1	15	seq_data.critical	Critical Bit
2	16	seq_data.length	Length of Contents
4	32	seq_data.seq	Sequence number

```
class pcapkit.protocols.internet.hip.DataType_Param_SEQ_Data
```

```
    Bases DataType_Parameter
```

Structure of HIP SEQ_DATA parameter [RFC 6078].

```
seq: int
    Sequence number.
```

HIP ACK_DATA Parameter

For HIP ACK_DATA parameter as described in RFC 6078, its structure is described as below:

Octets	Bits	Name	Description
0	0	ack_data.type	Parameter Type
1	15	ack_data.critical	Critical Bit
2	16	ack_data.length	Length of Contents
4	32	ack_data.ack	Acked Sequence number

```
class pcapkit.protocols.internet.hip.DataType_Param_ACK_Data
```

```
    Bases DataType_Parameter
```

Structure of HIP ACK_DATA parameter [RFC 6078].

```
ack: Tuple[int]
    Array of ACKed sequence number.
```

HIP PAYLOAD_MIC Parameter

For HIP PAYLOAD_MIC parameter as described in RFC 6078, its structure is described as below:

Octets	Bits	Name	Description
0	0	payload_mic.type	Parameter Type
1	15	payload_mic.critical	Critical Bit
2	16	payload_mic.length	Length of Contents
4	32	payload_mic.next	Next Header
5	40		Reserved
8	64	payload_mic.data	Payload Data
12	96	payload_mic.value	MIC Value
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Payload_MIC
```

```
    Bases DataType_Parameter
```

Structure of HIP PAYLOAD_MIC parameter [RFC 6078].

```
next: pcapkit.const.reg.transtype.TransType
    Next header.
```

```
data: bytes
    Payload data.
```

```
value: bytes
    MIC value.
```

HIP TRANSACTION_ID Parameter

For HIP TRANSACTION_ID parameter as described in [RFC 6078](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	transaction_id.type	Parameter Type
1	15	transaction_id.critical	Critical Bit
2	16	transaction_id.length	Length of Contents
4	32	transaction_id.id	Identifier

```
class pcapkit.protocols.internet.hip.DataType_Param_Transaction_ID
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP TRANSACTION_ID parameter [RFC 6078].
```

```
    id: int
        Identifier.
```

HIP OVERLAY_ID Parameter

For HIP OVERLAY_ID parameter as described in [RFC 6079](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	overlay_id.type	Parameter Type
1	15	overlay_id.critical	Critical Bit
2	16	overlay_id.length	Length of Contents
4	32	overlay_id.id	Identifier

```
class pcapkit.protocols.internet.hip.DataType_Param_Overlay_ID
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP OVERLAY_ID parameter [RFC 6079].
```

```
    id: int
        Identifier.
```

HIP ROUTE_DST Parameter

For HIP ROUTE_DST parameter as described in [RFC 6079](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	route_dst.type	Parameter Type
1	15	route_dst.critical	Critical Bit
2	16	route_dst.length	Length of Contents
4	32	route_dst.flags	Flags
4	32	route_dst.flags.symmetric	SYMMETRIC [RFC 6028]
4	33	route_dst.flags.must_follow	MUST_FOLLOW [RFC 6028]
6	48		Reserved
8	64	route_dst.ip	HIT
?	?

```
class pcapkit.protocols.internet.hip.DataType_Param_Route_Dst
```

```
    Bases DataType_Parameter
```

```
    Structure of HIP ROUTE_DST parameter [RFC 6028].
```

```
    flags:   DataType_Flags
```

```
        Flags.
```

```
    ip:   Tuple[ipaddress.IPv6Address]
```

```
        Array of HIT addresses.
```

```
class pcapkit.protocols.internet.hip.DataType_Flags
```

```
    Bases TypedDict
```

```
    Flags.
```

```
    symmetric:   bool
```

```
        SYMMETRIC flag [RFC 6028].
```

```
    must_follow:   bool
```

```
        MUST_FOLLOW flag [RFC 6028].
```

HIP HIP_TRANSPORT_MODE Parameter

For HIP HIP_TRANSPORT_MODE parameter as described in [RFC 6261](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hip_transport_mode.type	Parameter Type
1	15	hip_transport_mode.critical	Critical Bit
2	16	hip_transport_mode.length	Length of Contents
4	32	hip_transport_mode.port	Port
6	48	hip_transport_mode.id	Mode ID
?	?
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Transport_Mode
```

```
    Bases DataType_Parameter
```

```
    Structure of HIP HIP_TRANSPORT_MODE parameter [RFC 6261].
```

```
    port:   int
```

```
        Port.
```

```
    id:   Tuple[pcapkit.const.hip.transport.Transport]
```

```
        Array of transport mode IDs.
```

HIP HIP_MAC Parameter

For HIP HIP_MAC parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hip_mac.type	Parameter Type
1	15	hip_mac.critical	Critical Bit
2	16	hip_mac.length	Length of Contents
4	32	hip_mac.hmac	HMAC
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_HMAC
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP HIP_MAC parameter [RFC 7401].
```

```
    hmac: bytes
           HMAC.
```

HIP HIP_MAC_2 Parameter

For HIP HIP_MAC_2 parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hip_mac_2.type	Parameter Type
1	15	hip_mac_2.critical	Critical Bit
2	16	hip_mac_2.length	Length of Contents
4	32	hip_mac_2.hmac	HMAC
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_HMAC_2
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP HIP_MAC_2 parameter [RFC 7401].
```

```
    hmac: bytes
           HMAC.
```

HIP HIP_SIGNATURE_2 Parameter

For HIP HIP_SIGNATURE_2 parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hip_signature_2.type	Parameter Type
1	15	hip_signature_2.critical	Critical Bit
2	16	hip_signature_2.length	Length of Contents
4	32	hip_signature_2.algorithm	SIG Algorithm
6	48	hip_signature_2.signature	Signature
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Signature_2
```

Bases `DataType_Parameter`

Structure of HIP `HIP_SIGNATURE_2` parameter [RFC 7401].

algorithm: `pcapkit.const.hip.hi_algorithm.HIAlgorithm`
SIG algorithm.

signature: `bytes`
Signature.

HIP `HIP_SIGNATURE` Parameter

For HIP `HIP_SIGNATURE` parameter as described in RFC 7401, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hip_signature.type</code>	Parameter Type
1	15	<code>hip_signature.critical</code>	Critical Bit
2	16	<code>hip_signature.length</code>	Length of Contents
4	32	<code>hip_signature.algorithm</code>	SIG Algorithm
6	48	<code>hip_signature.signature</code>	Signature
?	?		Padding

class `pcapkit.protocols.internet.hip.DataType_Param_Signature`

Bases `DataType_Parameter`

Structure of HIP `HIP_SIGNATURE` parameter [RFC 7401].

algorithm: `pcapkit.const.hip.hi_algorithm.HIAlgorithm`
SIG algorithm.

signature: `bytes`
Signature.

HIP `ECHO_REQUEST_UNSIGNED` Parameter

For HIP `ECHO_REQUEST_UNSIGNED` parameter as described in RFC 7401, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>echo_request_unsigned.type</code>	Parameter Type
1	15	<code>echo_request_unsigned.critical</code>	Critical Bit
2	16	<code>echo_request_unsigned.length</code>	Length of Contents
4	32	<code>echo_request_unsigned.data</code>	Opaque Data

class `pcapkit.protocols.internet.hip.DataType_Param_Echo_Request_Unsigned`

Bases `DataType_Parameter`

Structure of HIP `ECHO_REQUEST_UNSIGNED` parameter [RFC 7401].

data: `bytes`
Opaque data.

HIP ECHO_RESPONSE_UNSIGNED Parameter

For HIP ECHO_RESPONSE_UNSIGNED parameter as described in [RFC 7401](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	echo_response_unsigned.type	Parameter Type
1	15	echo_response_unsigned.critical	Critical Bit
2	16	echo_response_unsigned.length	Length of Contents
4	32	echo_response_unsigned.data	Opaque Data

```
class pcapkit.protocols.internet.hip.DataType_Param_Echo_Response_Unsigned
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP ECHO_RESPONSE_UNSIGNED parameter [RFC 7401].
```

```
    data: bytes
           Opaque data.
```

HIP RELAY_FROM Parameter

For HIP RELAY_FROM parameter as described in [RFC 5770](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	relay_from.type	Parameter Type
1	15	relay_from.critical	Critical Bit
2	16	relay_from.length	Length of Contents
4	32	relay_from.port	Port
6	48	relay_from.protocol	Protocol
7	56		Reserved
8	64	relay_from.ip	Address (IPv6)

```
class pcapkit.protocols.internet.hip.DataType_Param_Relay_From
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP RELAY_FROM parameter [RFC 5770].
```

```
    port: int
           Port.
```

```
    protocol: pcapkit.const.reg.transtype.TransType
              Protocol.
```

```
    ip: ipaddress.IPv6Address
        IPv6 address.
```


HIP RELAY_TO Parameter

For HIP RELAY_TO parameter as described in [RFC 5770](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	relay_to.type	Parameter Type
1	15	relay_to.critical	Critical Bit
2	16	relay_to.length	Length of Contents
4	32	relay_to.port	Port
6	48	relay_to.protocol	Protocol
7	56		Reserved
8	64	relay_to.ip	Address (IPv6)

```
class pcapkit.protocols.internet.hip.DataType_Param_Relay_To
```

```
    Bases: DataType_Parameter
```

Structure of HIP RELAY_TO parameter [[RFC 5770](#)].

```
    port: in
        Port.
```

```
    protocol: pcapkit.const.reg.transtype.TransType
        Protocol.
```

```
    ip: ipaddress.IPv6Address
        IPv6 address.
```

HIP OVERLAY_TTL Parameter

For HIP OVERLAY_TTL parameter as described in [RFC 6078](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	overlay_ttl.type	Parameter Type
1	15	overlay_ttl.critical	Critical Bit
2	16	overlay_ttl.length	Length of Contents
4	32	overlay_ttl.ttl	TTL
6	48		Reserved

```
class pcapkit.protocols.internet.hip.DataType_Param_Overlay_TTL
```

```
    Bases: DataType_Parameter
```

```
    ttl: int
        TTL.
```

HIP ROUTE_VIA Parameter

For HIP ROUTE_VIA parameter as described in [RFC 6028](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	route_via.type	Parameter Type
1	15	route_via.critical	Critical Bit
2	16	route_via.length	Length of Contents
4	32	route_via.flags	Flags
4	32	route_via.flags.symmetric	SYMMETRIC [RFC 6028]
4	33	route_via.flags.must_follow	MUST_FOLLOW [RFC 6028]
6	48	.	Reserved
8	64	route_dst.ip	HIT
?	?

```
class pcapkit.protocols.internet.hip.DataType_Param_Route_Via
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP ROUTE_VIA parameter \[RFC 6028\].
```

```
    flags: DataType_Flags
```

```
        Flags.
```

```
    ip: Tuple[ipaddress.IPv6Address]
```

```
        Array of HITs.
```

HIP FROM Parameter

For HIP FROM parameter as described in [RFC 8004](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	from.type	Parameter Type
1	15	from.critical	Critical Bit
2	16	from.length	Length of Contents
4	32	from.ip	Address

```
class pcapkit.protocols.internet.hip.DataType_Param_From
```

```
    Bases: DataType_Parameter
```

```
    Structure of HIP FROM parameter \[RFC 8004\].
```

```
    ip: ipaddress.IPv6Address
```

```
        IPv6 address.
```

HIP RVS_HMAC Parameter

For HIP RVS_HMAC parameter as described in [RFC 8004](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>rvs_hmac.type</code>	Parameter Type
1	15	<code>rvs_hmac.critical</code>	Critical Bit
2	16	<code>rvs_hmac.length</code>	Length of Contents
4	32	<code>rvs_hmac.hmac</code>	HMAC
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_RVS_HMAC
```

```
    Bases DataType_Parameter
```

```
    Structure of HIP RVS_HMAC parameter [RFC 8004].
```

```
    hmac: bytes
           HMAC.
```

HIP VIA_RVS Parameter

For HIP VIA_RVS parameter as described in [RFC 6028](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>via_rvs.type</code>	Parameter Type
1	15	<code>via_rvs.critical</code>	Critical Bit
2	16	<code>via_rvs.length</code>	Length of Contents
4	32	<code>via_rvs.ip</code>	Address
?	?

```
class pcapkit.protocols.internet.hip.DataType_Param_Via_RVS
```

```
    Bases DataType_Parameter
```

```
    Structure of HIP VIA_RVS parameter [RFC 6028].
```

```
    ip: Tuple[ipaddress.IPv6]
         Array of IPv6 addresses.
```

HIP RELAY_HMAC Parameter

For HIP RELAY_HMAC parameter as described in [RFC 5770](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>relay_hmac.type</code>	Parameter Type
1	15	<code>relay_hmac.critical</code>	Critical Bit
2	16	<code>relay_hmac.length</code>	Length of Contents
4	32	<code>relay_hmac.hmac</code>	HMAC
?	?		Padding

```
class pcapkit.protocols.internet.hip.DataType_Param_Relay_HMAC
```

Bases: `DataType_Parameter`

hmac: `bytes`
HMAC.

HOPOPT - IPv6 Hop-by-Hop Options

`pcapkit.protocols.internet.hopopt` contains *HOPOPT* only, which implements extractor for IPv6 Hop-by-Hop Options header (HOPOPT)⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hopopt.next</code>	Next Header
1	8	<code>hopopt.length</code>	Header Extensive Length
2	16	<code>hopopt.options</code>	Options

class `pcapkit.protocols.internet.hopopt.HOPOPT` (*file=None, length=None, **kwargs*)
Bases: `pcapkit.protocols.internet.internet.Internet`

This class implements IPv6 Hop-by-Hop Options.

classmethod `__index__()`
Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in *IANA*.

Return type `pcapkit.const.reg.transype.TransType`

`__length_hint__()`
Return an estimated length for the object.

Return type `Literal[2]`

`__post_init__(file, length=None, *, extension=False, **kwargs)`
Post initialisation hook.

Parameters

- **file** (`io.BytesIO`) – Source packet stream.
- **length** (`Optional[int]`) – Length of packet data.

Keyword Arguments

- **extension** (`bool`) – If the protocol is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to `make()`.


`__read_hopopt_options(length)`
Read HOPOPT options.

Positional arguments: `length` (`int`): length of options

Returns `Tuple[Tuple[pcapkit.const.ipv6.option.Option], Dict[str, DataType_Option]]`: extracted HOPOPT options

Raises `ProtocolError` – If the threshold is **NOT** matching.

⁰ https://en.wikipedia.org/wiki/IPv6_packet#Hop-by-hop_options_and_destination_options



Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description


Returns parsed option data

Return type *DataType_Opt_ILNP*

`_read_opt_ip_dff` (*code*, *, *desc*)

Read HOPOPT IP_DFF option.

Structure of HOPOPT IP_DFF option [RFC 6971]:



Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data


Return type *DataType_Opt_IP_DFF*

Raises *ProtocolError* – If `hopopt.ip_dff.length` is NOT 2.

`_read_opt_jumbo` (*code*, *, *desc*)

Read HOPOPT Jumbo Payload option.

Structure of HOPOPT Jumbo Payload option [RFC 2675]:



Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data


Return type *DataType_Opt_Jumbo*

Raises *ProtocolError* – If `hopopt.jumbo.length` is NOT 4.

`_read_opt_lio (code, *, desc)`

Read HOPOPT Line-Identification option.

Structure of HOPOPT Line-Identification option [RFC 6788]:



Parameters `code (int)` – option type value

Keyword Arguments `desc (str)` – option description


Returns parsed option data

Return type `DataType_Opt_LIO`

`_read_opt_mpl (code, *, desc)`

Read HOPOPT MPL option.

Structure of HOPOPT MPL option [RFC 7731]:



Parameters `code (int)` – option type value

Keyword Arguments `desc (str)` – option description

Returns parsed option data


Return type `DataType_Opt_MPL`

Raises `ProtocolError` – If the option is malformed.

`_read_opt_none (code, *, desc)`

Read HOPOPT unassigned options.

Structure of HOPOPT unassigned options [RFC 8200]:



Parameters `code (int)` – option type value

Keyword Arguments `desc (str)` – option description

Returns parsed option data

Return type `DataType_Opt_None`

`_read_opt_pad(code, *, desc)`

Read HOPOPT padding options.

Structure of HOPOPT padding options [RFC 8200]:

- Pad1 option:

```

+---+---+---+---+---+---+
|           0           |
+---+---+---+---+---+---+

```

- PadN option:

```

+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
|           1           | Opt Data Len | Option Data
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+

```

Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data

Return type Union[*DataType_Opt_Pad1*, *DataType_Opt_PadN*]

Raises *ProtocolError* – If code is NOT 0 or 1.

`_read_opt_pdm(code, *, desc)`

Read HOPOPT PDM option.

Structure of HOPOPT PDM option [RFC 8250]:

```

0          1          2          3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
| Option Type | Option Length | ScaleDTLR | ScaleDTLS |
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
| PSN This Packet | PSN Last Received |
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+
| Delta Time Last Received | Delta Time Last Sent |
+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+---+

```

Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data

Return type *DataType_Opt_PDM*

Raises *ProtocolError* – If `hopopt.pdm.length` is NOT 10.

`_read_opt_qs(code, *, desc)`

Read HOPOPT Quick Start option.

Structure of HOPOPT Quick-Start option [RFC 4782]:

- A Quick-Start Request:

0										1										2										3									
0	1	2	3	4	5	6	7	8	9	0	1	2	3	4	5	6	7	8	9	0	1	2	3	4	5	6	7	8	9	0	1								
																				+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+																			
																				Option Type Opt Data Len																			
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+																																							

(continued from previous page)

O R F 0 0 0 0 0	RPLInstanceID		SenderRank	
+---				
	(sub-TLVs)			
+---				

Parameters **code** (*int*) – option type value

Keyword Arguments **desc** (*str*) – option description

Returns parsed option data

Return type *DataType_Opt_RPL*

Raises *ProtocolError*—If `hopopt.rpl.length` is **LESS THAN** 4.

```
_read_opt_smf_dpd(code, *, desc)
```

Read HOPOPT SMF_DPD option.

Structure of HOPOPT SMF_DPD option [RFC 5570]:

- IPv6 SMF_DPD option header in **I-DPD** mode

[illegible]

- IPv6 SMF_DPD option header in **H-DPD** mode

[illegible]

Parameters **code** (*int*) – option type value

Keyword Arguments `desc (str)` – option description

Returns

parsed option data

Return type Union[*DataType_Opt_SMF_I_PDP*, *DataType_Opt_SMF_H_PDP*]

Raises *ProtocolError* – If the option is malformed.

read_opt_tun (*code*, *, *desc*)

Read HOPOPT Tunnel Encapsulation Limit option.

Structure of HOPOPT Tunnel Encapsulation Limit option [RFC 2473]:

```

+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
| Next Header |Hdr Ext Len = 0| Opt Type = 4 |Opt Data Len=1 |
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
| Tun Encap Lim |PadN Opt Type=1|Opt Data Len=1 |          0          |
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+

```

Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data

Return type *DataType_Opt_TUN*

Raises *ProtocolError* – If `hopopt.tun.length` is NOT 1.

`_read_opt_type` (*kind*)

Read option type field.

Parameters `kind` (*int*) – option kind value

Returns extracted HOPOPT option type field

Return type *DataType_Option_Type*

`make` (***kwargs*)

Make (construct) packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type *bytes*

`read` (*length=None, *, extension=False, **kwargs*)

Read IPv6 Hop-by-Hop Options.

Structure of HOPOPT header [RFC 8200]:

```

+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
| Next Header | Hdr Ext Len |                                     |
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
|                                     |                                     |
|                                     |                                     |
|                                     |                                     |
|                                     |                                     |
|                                     |                                     |
|                                     |                                     |
|                                     |                                     |
|                                     |                                     |
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+

```

Parameters `length` (*Optional[int]*) – Length of packet data.

Keyword Arguments

- **`extension`** (*bool*) – If the packet is used as an IPv6 extension header.
- **`**kwargs`** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_HOPOPT*

`property length`

Header length of current protocol.

Return type `int`

property name

Name of current protocol.

Return type `Literal['IPv6 Hop-by-Hop Options']`

property payload

Payload of current instance.

Raises `UnsupportedCall` – if the protocol is used as an IPv6 extension header

Return type `pcapkit.protocols.protocol.Protocol`

property protocol

Name of next layer protocol.

Return type `pcapkit.const.reg.transype.TransType`

`pcapkit.protocols.internet.hopopt._HOPOPT_ACT: Dict[str, str]`

HOPOPT unknown option actions.

Code	Action
00	skip over this option and continue processing the header
01	discard the packet
10	discard the packet and, regardless of whether or not the packet's Destination Address was a multicast address, send an ICMP Parameter Problem, Code 2, message to the packet's Source Address, pointing to the unrecognized Option Type
11	discard the packet and, only if the packet's Destination Address was not a multicast address, send an ICMP Parameter Problem, Code 2, message to the packet's Source Address, pointing to the unrecognized Option Type

`pcapkit.protocols.internet.hopopt._HOPOPT_OPT: Dict[int, Tuple[str, str]]`

HOPOPT options.

Code	Acronym	Option	Reference
0x00	pad	Pad1	[RFC 8200] 0
0x01	pad	PadN	[RFC 8200]
0x04	tun	Tunnel Encapsulation Limit	[RFC 2473] 1
0x05	ra	Router Alert	[RFC 2711] 2
0x07	calipso	Common Architecture Label IPv6 Security Option	[RFC 5570]
0x08	smf_dpd	Simplified Multicast Forwarding	[RFC 6621]
0x0F	pdm	Performance and Diagnostic Metrics	[RFC 8250] 10
0x26	qs	Quick-Start	[RFC 4782][RFC Errata 2034] 6
0x63	rpl	Routing Protocol for Low-Power and Lossy Networks	[RFC 6553]
0x6D	mpl	Multicast Protocol for Low-Power and Lossy Networks	[RFC 7731]
0x8B	ilnp	Identifier-Locator Network Protocol Nonce	[RFC 6744]
0x8C	lio	Line-Identification Option	[RFC 6788]
0xC2	jumbo	Jumbo Payload	[RFC 2675]
0xC9	home	Home Address	[RFC 6275]
0xEE	ip_dff	Depth-First Forwarding	[RFC 6971]

`pcapkit.protocols.internet.hopopt._HOPOPT_NULL: Dict[int, str]`
 HOPOPT unknown option descriptions.

Code	Description	Reference
0x1E	RFC3692-style Experiment	[RFC 4727]
0x3E	RFC3692-style Experiment	[RFC 4727]
0x4D	Deprecated	[RFC 7731]
0x5E	RFC3692-style Experiment	[RFC 4727]
0x7E	RFC3692-style Experiment	[RFC 4727]
0x8A	Endpoint Identification	DEPRECATED
0x9E	RFC3692-style Experiment	[RFC 4727]
0xBE	RFC3692-style Experiment	[RFC 4727]
0xDE	RFC3692-style Experiment	[RFC 4727]
0xFE	RFC3692-style Experiment	[RFC 4727]

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

class `pcapkit.protocols.internet.hopopt.DataType_HOPOPT`

Bases TypedDict

Structure of HOPOPT header [RFC 8200].

next: `pcapkit.const.reg.transtype.TransType`
 Next header.

length: `int`
 Header extensive length.

options: `Tuple[pcapkit.const.ipv6.option.Option]`
 Array of option acronyms.

packet: `bytes`
 Packet data.

class `pcapkit.protocols.internet.hopopt.DataType_Option`

Bases TypedDict

HOPOPT option.

desc: `str`
 Option description.

type: `DataType_Option_Type`
 Option type.

length: `int`
 Option length.

Note: This attribute is **NOT** the length specified in the HOPOPT optiona data, rather the *total* length of the current option.

HOPOPT Option Type

For HOPOPT option type field as described in [RFC 791](#), its structure is described as below:

Octets	Bits	Name	Descriptions
0	0	<code>hopopt.opt.type.value</code>	Option Number
0	0	<code>hopopt.opt.type.action</code>	Action (00-11)
0	2	<code>hopopt.opt.type.change</code>	Change Flag (0/1)

```
class pcapkit.protocols.internet.hopopt.DataType_Option_Type
```

```
    Bases TypedDict
```

```
    Structure of option type field [RFC 791].
```

```
    value: int
        Option number.
```

```
    action: str
        Action.
```

```
    change: bool
        Change flag.
```

HOPOPT Unassigned Options

For HOPOPT unassigned options as described in [RFC 8200](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hopopt.opt.type</code>	Option Type
0	0	<code>hopopt.opt.type.value</code>	Option Number
0	0	<code>hopopt.opt.type.action</code>	Action (00-11)
0	2	<code>hopopt.opt.type.change</code>	Change Flag (0/1)
1	8	<code>hopopt.opt.length</code>	Length of Option Data
2	16	<code>hopopt.opt.data</code>	Option Data

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_None
```

```
    Bases DataType_Option
```

```
    Structure of HOPOPT unassigned options [RFC 8200].
```

```
    data: bytes
        Option data.
```

HOPOPT Padding Options

Pad1 Option

For HOPOPT `Pad1` option as described in [RFC 8200](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hopopt.pad.type</code>	Option Type
0	0	<code>hopopt.pad.type.value</code>	Option Number
0	0	<code>hopopt.pad.type.action</code>	Action (00)
0	2	<code>hopopt.pad.type.change</code>	Change Flag (0)

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_Pad1
```

```
    Bases DataType_Option
```

```
    Structure of HOPOPT padding options [RFC 8200].
```

```
    length: Literal[1]
```

```
        Option length.
```

PadN Option

For HOPOPT `PadN` option as described in [RFC 8200](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hopopt.pad.type</code>	Option Type
0	0	<code>hopopt.pad.type.value</code>	Option Number
0	0	<code>hopopt.pad.type.action</code>	Action (00)
0	2	<code>hopopt.pad.type.change</code>	Change Flag (0)
1	8	<code>hopopt.opt.length</code>	Length of Option Data
2	16	<code>hopopt.pad.padding</code>	Padding

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_PadN
```

```
    Bases DataType_Option
```

```
    Structure of HOPOPT padding options [RFC 8200].
```

```
    padding: bytes
```

```
        Padding data.
```

HOPOPT Tunnel Encapsulation Limit Option

For HOPOPT Tunnel Encapsulation Limit option as described in [RFC 2473](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hopopt.tun.type</code>	Option Type
0	0	<code>hopopt.tun.type.value</code>	Option Number
0	0	<code>hopopt.tun.type.action</code>	Action (00)
0	2	<code>hopopt.tun.type.change</code>	Change Flag (0)
1	8	<code>hopopt.tun.length</code>	Length of Option Data
2	16	<code>hopopt.tun.limit</code>	Tunnel Encapsulation Limit

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_TUN
```

```
    Bases: DataType_Option
```

Structure of HOPOPT Tunnel Encapsulation Limit option [RFC 2473].

```
    limit: int
```

Tunnel encapsulation limit.

HOPOPT Router Alert Option

For HOPOPT Router Alert option as described in RFC 2711, its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.ra.type	Option Type
0	0	hopopt.ra.type.value	Option Number
0	0	hopopt.ra.type.action	Action (00)
0	2	hopopt.ra.type.change	Change Flag (0)
1	8	hopopt.opt.length	Length of Option Data
2	16	hopopt.ra.value	Value

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_RA
```

```
    Bases: DataType_Option
```

Structure of HOPOPT Router Alert option [RFC 2711].

```
    value: int
```

Router alert code value.

```
    alert: pcapkit.const.ipv6.router_alter.RouterAlert
```

Router alert enumeration.

HOPOPT CALIPSO Option

For HOPOPT CALIPSO option as described in RFC 5570, its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.calipso.type	Option Type
0	0	hopopt.calipso.type.value	Option Number
0	0	hopopt.calipso.type.action	Action (00)
0	2	hopopt.calipso.type.change	Change Flag (0)
1	8	hopopt.calipso.length	Length of Option Data
2	16	hopopt.calipso.domain	CALIPSO Domain of Interpretation
6	48	hopopt.calipso.cmpt_len	Cmpt Length
7	56	hopopt.calipso.level	Sens Level
8	64	hopopt.calipso.chksum	Checksum (CRC-16)
9	72	hopopt.calipso.bitmap	Compartment Bitmap

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_CALIPSO
```

```
    Bases: DataType_Option
```

Structure of HOPOPT CALIPSO option [RFC 5570].


```

domain: int
    CALIPSO domain of interpretation.

cmpt_len: int
    Compartment length.

level: int
    Sene level.

chksum: bytes
    Checksum (CRC-16).

bitmap: Tuple[str]
    Compartment bitmap.

```

HOPOPT SMF_DPD Option

I-DPD Mode

For IPv6 SMF_DPD option header in I-DPD mode as described in [RFC 5570](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.smf_dpd.type	Option Type
0	0	hopopt.smf_dpd.type.value	Option Number
0	0	hopopt.smf_dpd.type.action	Action (00)
0	2	hopopt.smf_dpd.type.change	Change Flag (0)
1	8	hopopt.smf_dpd.length	Length of Option Data
2	16	hopopt.smf_dpd.dpd_type	DPD Type (0)
2	17	hopopt.smf_dpd.tid_type	TaggerID Type
2	20	hopopt.smf_dpd.tid_len	TaggerID Length
3	24	hopopt.smf_dpd.tid	TaggerID
?	?	hopopt.smf_dpd.id	Identifier

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_I_PDP
```

```
    Bases: DataType_Option
```

Structure of HOPOPT SMF_DPD option in **I-DPD** mode [[RFC 5570](#)].

```

dpd_type: Literal['I-DPD']
    DPD type.

tid_type: pcapkit.const.ipv6.tagger_id.TaggerID
    TaggerID type.

tid_len: int
    TaggerID length.

tid: int
    TaggerID.

id: bytes
    Identifier.

```

H-DPD Mode

For IPv6 SMF_DPD option header in H-DPD mode as described in [RFC 5570](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.smf_dpd.type	Option Type
0	0	hopopt.smf_dpd.type.value	Option Number
0	0	hopopt.smf_dpd.type.action	Action (00)
0	2	hopopt.smf_dpd.type.change	Change Flag (0)
1	8	hopopt.smf_dpd.length	Length of Option Data
2	16	hopopt.smf_dpd.dpd_type	DPD Type (1)
2	17	hopopt.smf_dpd.hav	Hash Assist Value

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_H_PDP
```

```
    Bases: DataType_Option
```

```
    Structure of HOPOPT SMF_DPD option in H-DPD mode [RFC 5570].
```

```
    dpd_type: Literal['H-DPD']
        DPD type.
```

```
    hav: str
        Hash assist value (as binary string).
```

HOPOPT PDM Option

For HOPOPT PDM option as described in [RFC 8250](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.pdm.type	Option Type
0	0	hopopt.pdm.type.value	Option Number
0	0	hopopt.pdm.type.action	Action (00)
0	2	hopopt.pdm.type.change	Change Flag (0)
1	8	hopopt.pdm.length	Length of Option Data
2	16	hopopt.pdm.scaledt1r	Scale Delta Time Last Received
3	24	hopopt.pdm.scaledt1s	Scale Delta Time Last Sent
4	32	hopopt.pdm.psntp	Packet Sequence Number This Packet
6	48	hopopt.pdm.psn1r	Packet Sequence Number Last Received
8	64	hopopt.pdm.deltat1r	Delta Time Last Received
10	80	hopopt.pdm.deltat1s	Delta Time Last Sent

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_PDM
```

```
    Bases: DataType_Option
```

```
    Structure of HOPOPT PDM option [RFC 8250].
```

```
    scaledt1r: datetime.timedelta
        Scale delta time last received.
```

```
    scaledt1s: datetime.timedelta
        Scale delta time last sent.
```

```
    psntp: int
        Packet sequence number this packet.
```

psnlr: `int`
 Packet sequence number last received.

deltatlr: `datetime.timedelta`
 Delta time last received.

deltatls: `datetime.timedelta`
 Delta time last sent.

HOPOPT Quick Start Option

For HOPOPT Quick Start option as described in [RFC 4782](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hopopt.qs.type</code>	Option Type
0	0	<code>hopopt.qs.type.value</code>	Option Number
0	0	<code>hopopt.qs.type.action</code>	Action (00)
0	2	<code>hopopt.qs.type.change</code>	Change Flag (1)
1	8	<code>hopopt.qs.length</code>	Length of Option Data
2	16	<code>hopopt.qs.func</code>	Function (0/8)
2	20	<code>hopopt.qs.rate</code>	Rate Request / Report (in Kbps)
3	24	<code>hopopt.qs.ttl</code>	QS TTL / <code>None</code>
4	32	<code>hopopt.qs.nounce</code>	QS Nounce
7	62		Reserved

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_QS
    Bases DataType_Option

    Structure of HOPOPT Quick Start option [RFC 8250].

    func: pcapkit.const.ipv6.qs_function.QSFunction
        Function.

    rate: float
        Rate request and/or report (in Kbps).

    ttl: Optional[int]
        QS TTL.

    nounce: int
        QS nounce.
```

HOPOPT RPL Option

For HOPOPT RPL option as described in [RFC 6553](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.rpl.type	Option Type
0	0	hopopt.rpl.type.value	Option Number
0	0	hopopt.rpl.type.action	Action (01)
0	2	hopopt.rpl.type.change	Change Flag (1)
1	8	hopopt.rpl.length	Length of Option Data
2	16	hopopt.rpl.flags	RPL Option Flags
2	16	hopopt.rpl.flags.down	Down Flag
2	17	hopopt.rpl.flags.rank_error	Rank-Error Flag
2	18	hopopt.rpl.flags.fwd_error	Forwarding-Error Flag
3	24	hopopt.rpl.id	RPL Instance ID
4	32	hopopt.rpl.rank	SenderRank
6	48	hopopt.rpl.data	Sub-TLVs

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_RPL
```

```
    Bases: DataType_Option
```

```
    Structure of HOPOPT RPL option [RFC 6553].
```

```
    flags: DataType_RPL_Flags
```

```
        RPL option flags.
```

```
    id: int
```

```
        RPL instance ID.
```

```
    rank: int
```

```
        Sender rank.
```

```
    data: Optional[bytes]
```

```
        Sub-TLVs (if hopopt.rpl.length is GREATER THAN 4).
```

```
class pcapkit.protocols.internet.hopopt.DataType_RPL_Flags
```

```
    Bases: TypedDict
```

```
    RPL option flags.
```

```
    down: bool
```

```
        Down flag.
```

```
    rank_error: bool
```

```
        Rank-Error flag.
```

```
    fwd_error: bool
```

```
        Forwarding-Error flag.
```

HOPOPT MPL Option

For HOPOPT MPL option as described in [RFC 7731](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.mpl.type	Option Type
0	0	hopopt.mpl.type.value	Option Number
0	0	hopopt.mpl.type.action	Action (01)
0	2	hopopt.mpl.type.change	Change Flag (1)
1	8	hopopt.mpl.length	Length of Option Data
2	16	hopopt.mpl.seed_len	Seed-ID Length
2	18	hopopt.mpl.flags	MPL Option Flags
2	18	hopopt.mpl.max	Maximum SEQ Flag
2	19	hopopt.mpl.verification	Verification Flag
2	20		Reserved
3	24	hopopt.mpl.seq	Sequence
4	32	hopopt.mpl.seed_id	Seed-ID

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_MPL
```

Bases `DataType_Option`

Structure of HOPOPT MPL option [[RFC 7731](#)].

seed_len: `pcapkit.const.ipv6.seed_id.SeedID`
Seed-ID length.

flags: `DataType_MPL_Flags`
MPL option flags.

seq: `int`
Sequence.

seed_id: `Optional[int]`
Seed-ID.

```
class pcapkit.protocols.internet.hopopt.DataType_MPL_Flags
```

Bases `TypedDict`

MPL option flags.

max: `bool`
Maximum sequence flag.

verification: `bool`
Verification flag.

HOPOPT ILNP Nounce Option

For HOPOPT ILNP Nounce option as described in [RFC 6744](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.ilnp.type	Option Type
0	0	hopopt.ilnp.type.value	Option Number
0	0	hopopt.ilnp.type.action	Action (10)
0	2	hopopt.ilnp.type.change	Change Flag (0)
1	8	hopopt.ilnp.length	Length of Option Data
2	16	hopopt.ilnp.value	Nonce Value

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_ILNP
```

```
    Bases: DataType_Option
```

```
    Structure of HOPOPT ILNP Nonce option [RFC 6744].
```

```
    value: bytes
```

```
        Nonce value.
```

HOPOPT Line-Identification Option

For HOPOPT Line-Identification option as described in [RFC 6788](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.lio.type	Option Type
0	0	hopopt.lio.type.value	Option Number
0	0	hopopt.lio.type.action	Action (10)
0	2	hopopt.lio.type.change	Change Flag (0)
1	8	hopopt.lio.length	Length of Option Data
2	16	hopopt.lio.lid_len	Line ID Length
3	24	hopopt.lio.lid	Line ID

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_LIO
```

```
    Bases: DataType_Option
```

```
    Structure of HOPOPT Line-Identification option [RFC 6788].
```

```
    lid_len: int
```

```
        Line ID length.
```

```
    lid: bytes
```

```
        Line ID.
```

HOPOPT Jumbo Payload Option

For HOPOPT Jumbo Payload option as described in [RFC 2675](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	hopopt.jumbo.type	Option Type
0	0	hopopt.jumbo.type.value	Option Number
0	0	hopopt.jumbo.type.action	Action (11)
0	2	hopopt.jumbo.type.change	Change Flag (0)
1	8	hopopt.jumbo.length	Length of Option Data
2	16	hopopt.jumbo.payload_len	Jumbo Payload Length

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_Jumbo
```

```
    Bases: DataType_Option
```

```
    Structure of HOPOPT Jumbo Payload option [RFC 2675].
```

```
    payload_len: int
```

```
        Jumbo payload length.
```

HOPOPT Home Address Option

For HOPOPT Home Address option as described in [RFC 6275](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hopopt.home.type</code>	Option Type
0	0	<code>hopopt.home.type.value</code>	Option Number
0	0	<code>hopopt.home.type.action</code>	Action (11)
0	2	<code>hopopt.home.type.change</code>	Change Flag (0)
1	8	<code>hopopt.home.length</code>	Length of Option Data
2	16	<code>hopopt.home.ip</code>	Home Address

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_Home
```

```
    Bases: DataType_Option
```

Structure of HOPOPT Home Address option [[RFC 6275](#)].

```
ip:    ipaddress.IPv6Address
       Home address.
```

HOPOPT IP_DFF Option

For HOPOPT IP_DFF option as described in [RFC 6971](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>hopopt.ip_dff.type</code>	Option Type
0	0	<code>hopopt.ip_dff.type.value</code>	Option Number
0	0	<code>hopopt.ip_dff.type.action</code>	Action (11)
0	2	<code>hopopt.ip_dff.type.change</code>	Change Flag (1)
1	8	<code>hopopt.ip_dff.length</code>	Length of Option Data
2	16	<code>hopopt.ip_dff.version</code>	Version
2	18	<code>hopopt.ip_dff.flags</code>	Flags
2	18	<code>hopopt.ip_dff.flags.dup</code>	DUP Flag
2	19	<code>hopopt.ip_dff.flags.ret</code>	RET Flag
2	20		Reserved
3	24	<code>hopopt.ip_dff.seq</code>	Sequence Number

```
class pcapkit.protocols.internet.hopopt.DataType_Opt_IP_DFF
```

```
    Bases: DataType_Option
```

Structure of HOPOPT IP_DFF option [[RFC 6971](#)].

```
version: int
         Version.
```

```
flags:   DataType_IP_DFF_Flags
         Flags.
```

```
seq:     int
         Sequence number.
```

```
class pcapkit.protocols.internet.hopopt.DataType_IP_DFF_Flags
```

```
    Bases: TypedDict
```

Flags.

dup: `bool`
DUP flag.

ret: `bool`
RET flag.

IP - Internet Protocol

`pcapkit.protocols.internet.ip` contains *IP* only, which is a base class for Internet Protocol (IP) protocol family⁰, eg. *IPv4*, *IPv6*, and *IPsec*.

class `pcapkit.protocols.internet.ip.IP` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.internet.internet.Internet`

This class implements all protocols in IP family.

- Internet Protocol version 4 (*IPv4*) [**RFC 791**]
- Internet Protocol version 6 (*IPv6*) [**RFC 2460**]
- Authentication Header (*AH*) [**RFC 4302**]
- Encapsulating Security Payload (ESP) [**RFC 4303**]

classmethod `id()`

Index ID of the protocol.

Returns Index ID of the protocol.

Return type `Tuple[Literal['IPv4'], Literal['IPv6']]`

property `dst`

Destination IP address.

Return type `Union[ipaddress.IPv4Address, ipaddress.IPv6Address]`

property `src`

Source IP address.

Return type `Union[ipaddress.IPv4Address, ipaddress.IPv6Address]`

IPsec - Internet Protocol Security

`pcapkit.protocols.internet.ipsec` contains *IPsec* only, which is a base class for Internet Protocol Security (IPsec) protocol family⁰, eg. *AH* and *ESP*^{†0}.

class `pcapkit.protocols.internet.ipsec.IPsec` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.internet.ip.IP`

Abstract base class for IPsec protocol family.

- Authentication Header (*AH*) [**RFC 4302**]
- Encapsulating Security Payload (ESP) [**RFC 4303**]

classmethod `id()`

Index ID of the protocol.

⁰ https://en.wikipedia.org/wiki/Internet_Protocol

⁰ <https://en.wikipedia.org/wiki/IPsec>

⁰ ESP is currently **NOT** implemented.

Returns Index ID of the protocol.

Return type Tuple[Literal['AH'], Literal['ESP']]

property dst

Destination IP address.

Raises *UnsupportedCall* – This protocol doesn't support *dst*.

property src

Source IP address.

Raises *UnsupportedCall* – This protocol doesn't support *src*.

IPv4 - Internet Protocol version 4

`pcapkit.protocols.internet.ipv4` contains *IPv4* only, which implements extractor for Internet Protocol version 4 (IPv4)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ip.version</code>	Version (4)
0	4	<code>ip.hdr_len</code>	Internal Header Length (IHL)
1	8	<code>ip.dsfield.dscp</code>	Differentiated Services Code Point (DSCP)
1	14	<code>ip.dsfield.ecn</code>	Explicit Congestion Notification (ECN)
2	16	<code>ip.len</code>	Total Length
4	32	<code>ip.id</code>	Identification
6	48		Reserved Bit (must be \x00)
6	49	<code>ip.flags.df</code>	Don't Fragment (DF)
6	50	<code>ip.flags.mf</code>	More Fragments (MF)
6	51	<code>ip.frag_offset</code>	Fragment Offset
8	64	<code>ip.ttl</code>	Time To Live (TTL)
9	72	<code>ip.proto</code>	Protocol (Transport Layer)
10	80	<code>ip.checksum</code>	Header Checksum
12	96	<code>ip.src</code>	Source IP Address
16	128	<code>ip.dst</code>	Destination IP Address
20	160	<code>ip.options</code>	IP Options (if IHL > 5)

class `pcapkit.protocols.internet.ipv4.IPv4` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.internet.ip.IP`

This class implements Internet Protocol version 4.

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in IANA.

Return type `pcapkit.const.reg.transtype.TransType`

`__length_hint__()`

Return an estimated length for the object.

Return type Literal[20]

`_read_ipv4_addr()`

Read IP address.

⁰ <https://en.wikipedia.org/wiki/IPv4>

Returns Parsed IP address.

Return type `ipaddress.IPv4Address`

`_read_ipv4_options` (*size=None*)

Read IPv4 option list.

Parameters *size* (*Optional[int]*) – buffer size

Returns Tuple[Tuple[pcapkit.const.ipv4.option_number.OptionNumber], Dict[str, Union[DataType_Opt, Tuple[DataType_Opt]]]]: IPv4 option list and extracted IPv4 options

`_read_mode_donone` (*size, kind*)

Read options require no process.

Parameters

- **`size`** (*int*) – length of option
- **`kind`** (*int*) – option kind value

Returns extracted option

Return type `DataType_Opt_Do_None`


Raises `ProtocolError` – If *size* is LESS THAN 3.

`_read_mode_qs` (*size, kind*)


Read Quick Start option.

Structure of Quick-Start (QS) option [RFC 4782]:

- A Quick-Start Request



- Report of Approved Rate



Parameters

- **`size`** (*int*) – length of option
- **`kind`** (*Literal[25]*) – option kind value (QS)

Returns extracted Quick Start option

Return type `DataType_Opt_QuickStart`

Raises *ProtocolError* – If the option is malformed.

`_read_mode_route` (*size*, *kind*)

Read options with route data.

Structure of these options [RFC 791]:

- Loose Source Route

```
+-----+-----+-----+-----+//-----+
|10000011| length | pointer|      route data    |
+-----+-----+-----+-----+//-----+
```

- Strict Source Route

```
+-----+-----+-----+-----+//-----+
|10001001| length | pointer|      route data    |
+-----+-----+-----+-----+//-----+
```

- Record Route

```
+-----+-----+-----+-----+//-----+
|00000111| length | pointer|      route data    |
+-----+-----+-----+-----+//-----+
```

Parameters

- **`size`** (*int*) – length of option
- **`kind`** (*Literal*[7, 131, 137]) – option kind value (RR/LSR/SSR)

Returns extracted option with route data

Return type *DataType_Opt_Route_Data*

Raises *ProtocolError* – If the option is malformed.

`_read_mode_rsralt` (*size*, *kind*)

Read Router Alert option.

Structure of Router Alert (RTRALT) option [RFC 2113]:

```
+-----+-----+-----+-----+
|10010100|00000100|  2 octet value  |
+-----+-----+-----+-----+
```

Parameters

- **`size`** (*int*) – length of option
- **`kind`** (*Literal*[140]) – option kind value (RTRALT)

Returns extracted option with security info

Return type *DataType_Opt_RouterAlert*

Raises *ProtocolError* – If `size` is NOT 4.

`_read_mode_sec` (*size*, *kind*)

Read options with security info.

Structure of these options [RFC 1108]:

- Security (SEC)

10000010	XXXXXXXX	SSSSSSSS	AAAAAAA[1]	AAAAAAA0
			[0]	
TYPE = 130	LENGTH	CLASSIFICATION LEVEL	PROTECTION AUTHORITY FLAGS	

- Extended Security (ESEC)

+-----+-----+-----+-----+ 10000101 000LLLLL AAAAAAAA add sec info
+-----+-----+-----+-----+
TYPE = 133 LENGTH ADDITIONAL SECURITY INFO ADDITIONAL FORMAT CODE INFO

c

```
_read_mode_tr(size, kind)
```

Read Traceroute option.

Structure of Traceroute (TR) option [RFC 6814]:

0		8		16		24	
F	C	Number	Length	ID Number			
Outbound Hop Count				Return Hop Count			
Originator IP Address							

Parameters

- **size** (*int*) – length of option
- **kind** (*Literal*[82]) – option kind value (TR)

Returns extracted Traceroute option

Return type *DataType_Opt_Traceroute*

Raises *ProtocolError* – If size is **NOT** 12.

`_read_mode_ts` (*size*, *kind*)

Read Time Stamp option.

Structure of Timestamp (TS) option [RFC 791]:

```

+-----+-----+-----+-----+
|01000100| length | pointer|oflw|flg|
+-----+-----+-----+-----+
|          internet address          |
+-----+-----+-----+-----+
|          timestamp                  |
+-----+-----+-----+-----+
|          .                          |
+-----+-----+-----+-----+

```

(continues on next page)

<ul style="list-style-type: none"> • •
--

Parameters

- **size** (*int*) – length of option
- **kind** (*Literal*[68]) – option kind value (TS)

Returns extracted Time Stamp option

Return type *DataType_Opt_TimeStamp*

Raises *ProtocolError* – If the option is malformed.

_read_mode_unpack (*size, kind*)

Read options require unpack process.

Parameters

- **size** (*int*) – length of option
- **kind** (*int*) – option kind value

Returns extracted option

Return type *DataType_Opt_Unpack*

Raises *ProtocolError* – If size is **LESS THAN 3**.

_read_opt_type (*kind*)

Read option type field.

Parameters `kind` (*int*) – option kind value

Returns extracted IPv4 option

Return type *DataType_IPv4_Option_Type*

```
classmethod id()
```

Index ID of the protocol.

Returns Index ID of the protocol.**Return type** Literal['IPv4']

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type bytes

```
read (length=None, **kwargs)
```


Read Internet Protocol version 4 (IPv4).

Structure of IPv4 header [RFC 791]:

[illegible]

(continues on next page)

(continued from previous page)



Parameters `length` (*Optional*[`int`]) – Length of packet data.

Keyword Arguments `**kwargs` – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type `DataType_IpV4`

property `length`

Header length of corresponding protocol.

Return type `int`

property `name`

Name of corresponding protocol.

Return type `Literal['Internet Protocol version 4']`

property `protocol`

Name of next layer protocol.

Return type `pcapkit.const.reg.trans_type.TransType`

`pcapkit.protocols.internet.ipv4.IPv4_OPT: DataType_IpV4_OPT`

IPv4 option `dict` parsing mapping.

copy	class	number	kind	length	process	name
0	0	0	0			[RFC 791] End of Option List
0	0	1	1			[RFC 791] No-Operation
0	0	7	7	?	2	[RFC 791] Record Route
0	0	11	11	4	1	[RFC 1063][RFC 1191] MTU Probe
0	0	12	12	4	1	[RFC 1063][RFC 1191] MTU Reply
0	0	25	25	8	3	[RFC 4782] Quick-Start
0	2	4	68	?	4	[RFC 791] Time Stamp
0	2	18	82	?	5	[RFC 1393][RFC 6814] Traceroute
1	0	2	130	?	6	[RFC 1108] Security
1	0	3	131	?	2	[RFC 791] Loose Source Route
1	0	5	133	?	6	[RFC 1108] Extended Security
1	0	8	136	4	1	[RFC 791][RFC 6814] Stream ID
1	0	9	137	?	2	[RFC 791] Strict Source Route
1	0	17	145	?	0	[RFC 1385][RFC 6814] Ext. Inet. Protocol
1	0	20	148	4	7	[RFC 2113] Router Alert

See also:

`pcapkit.protocols.internet.ipv4.DataType_IPv4_OPT`

`pcapkit.protocols.internet.ipv4.process_opt: Dict[int, Callable[[pcapkit.protocols.internet`
Process method for IPv4 options.

Code	Method	Description
0	<code>_read_mode_donone()</code>	do nothing
1	<code>_read_mode_unpack()</code>	unpack according to size
2	<code>_read_mode_route()</code>	unpack route data options
3	<code>_read_mode_qs()</code>	unpack Quick-Start
4	<code>_read_mode_ts()</code>	unpack Time Stamp
5	<code>_read_mode_tr()</code>	unpack Traceroute
6	<code>_read_mode_sec()</code>	unpack (Extended) Security
7	<code>_read_mode_rsralt()</code>	unpack Router Alert

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

class `pcapkit.protocols.internet.ipv4.DataType_IPv4`

Bases: `TypedDict`

Structure of IPv4 header [RFC 791].

version: `Literal[4]`

Version (4).

hdr_len: `int`

Internal header length (IHL).

dsfield: `DataType_DS_Field`

Type of services.

len: `int`

Total length.

id: `int`

Identification.

flags: `DataType_IPv4_Flags`

Flags.

frag_offset: `int`

Fragment offset.

ttl: `int`

Time to live (TTL).

proto: `pcapkit.const.reg.transtype.TransType`

Protocol (transport layer).

checksum: `bytes`

Header checksum.

src: `ipaddress.IPv4Address`

Source IP address.

```
    dst: ipaddress.IPv4Address
        Destination IP address.

    opt: Tuple[pcapkit.const.ipv4.option_number.OptionNumber]
        Tuple of option acronyms.

    packet: bytes
        Rase packet data.

class pcapkit.protocols.internet.ipv4.DataType_DS_Field
    Bases TypedDict

    IPv4 DS fields.

    dscp: DataType_IPv4_DSCP
        Differentiated services code point (DSCP).

    ecn: pcapkit.const.ipv4.tos_ecn.ToSECN
        Explicit congestion notification (ECN).

class pcapkit.protocols.internet.ipv4.DataType_IPv4_DSCP
    Bases TypedDict

    Differentiated services code point (DSCP).

    pre: pcapkit.const.ipv4.tos_pre.ToSPrecedence
        ToS precedence.

    del: pcapkit.const.ipv4.tos_del.ToSDelay
        ToS delay.

    thr: pcapkit.const.ipv4.tos_thr.ToSThroughput
        ToS throughput.

    rel: pcapkit.const.ipv4.tos_rel.ToSReliability
        ToS reliability.

class pcapkit.protocols.internet.ipv4.DataType_IPv4_Flags
    Bases TypedDict

    IPv4 flags.

    df: bool
        Dont's fragment (DF).

    mf: bool
        More fragments (MF).

class pcapkit.protocols.internet.ipv4.DataType_Opt
    Bases TypedDict

    IPv4 option data.

    kind: int
        Option kind.

    type: DataType_IPv4_Option_Type
        Option type info.

    length: int
        Option length.

class pcapkit.protocols.internet.ipv4.DataType_IPv4_OPT
```


Bases TypedDict

IPv4 option dict parsing mapping.

flag: `bool`
If the length of option is **GREATER THAN** 1.

desc: `str`
Description string, also attribute name.

proc: `Optional[int]`
Process method that data bytes need (when *flag* is `True`).

See also:

`pcapkit.protocols.internet.ipv4.process_opt`

IPv4 Option Type

For IPv4 option type field as described in **RFC 791**, its structure is described as below:

Octets	Bits	Name	Descriptions
0	0	<code>ip.opt.type.copy</code>	Copied Flag (0/1)
0	1	<code>ip.opt.type.class</code>	Option Class (0-3)
0	3	<code>ip.opt.type.number</code>	Option Number

class `pcapkit.protocols.internet.ipv4.DataType_IpV4_Option_Type`

Bases TypedDict

Structure of option type field [**RFC 791**].

copy: `bool`
Copied flag.

class: `pcapkit.const.ipv4.option_class.OptionClass`
Option class.

number: `int`
Option number.

IPv4 Miscellaneous Options

1-Byte Options

class `pcapkit.protocols.internet.ipv4.DataType_Opt_1_Byte`

Bases `DataType_Opt`

1-byte options.

length: `Literal[1]`
Option length.

Permission Options

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_Permission
```

```
    Bases: DataType_Opt
```

```
    Permission options (length is 2).
```

```
    length: Literal[2]
```

```
        Option length.
```

```
    flag: Literal[True]
```

```
        Permission flag.
```

No Process Options

For IPv4 options require no process, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ip.opt.kind</code>	Kind
0	0	<code>ip.opt.type.copy</code>	Copied Flag
0	1	<code>ip.opt.type.class</code>	Option Class
0	3	<code>ip.opt.type.number</code>	Option Number
1	8	<code>ip.opt.length</code>	Length
2	16	<code>ip.opt.data</code>	Kind-specific Data

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_Do_None
```

```
    Bases: DataType_Opt
```

```
    Structure of IPv4 options.
```

```
    data: bytes
```

```
        Kind-specific data.
```

Unpack Process Options

For IPv4 options require unpack process, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ip.opt.kind</code>	Kind
0	0	<code>ip.opt.type.copy</code>	Copied Flag
0	1	<code>ip.opt.type.class</code>	Option Class
0	3	<code>ip.opt.type.number</code>	Option Number
1	8	<code>ip.opt.length</code>	Length
2	16	<code>ip.opt.data</code>	Kind-specific Data

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_Unpack
```

```
    Bases: DataType_Opt
```

```
    Structure of IPv4 options.
```

```
    data: int
```

```
        Kind-specific data.
```

IPv4 Options with Route Data

For IPv4 options with route data as described in [RFC 791](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ip.opt.kind	Kind (7/131/137)
0	0	ip.opt.type.copy	Copied Flag (0)
0	1	ip.opt.type.class	Option Class (0/1)
0	3	ip.opt.type.number	Option Number (3/7/9)
1	8	ip.opt.length	Length
2	16	ip.opt.pointer	Pointer (4)
3	24	ip.opt.data	Route Data

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_Route_Data
```

```
    Bases: DataType_Opt
```

Structure of IPv4 options with route data [[RFC 791](#)].

```
    pointer: int
```

Pointer.

```
    data: Optional[Tuple[ipaddress.IPv4Address]]
```

Route data.

IPv4 Quick Start Options

For IPv4 Quick Start options as described in [RFC 4782](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ip.qs.kind	Kind (25)
0	0	ip.qs.type.copy	Copied Flag (0)
0	1	ip.qs.type.class	Option Class (0)
0	3	ip.qs.type.number	Option Number (25)
1	8	ip.qs.length	Length (8)
2	16	ip.qs.func	Function (0/8)
2	20	ip.qs.rate	Rate Request / Report (in Kbps)
3	24	ip.qs.ttl	QS TTL / None
4	32	ip.qs.nounce	QS Nounce
7	62		Reserved (\x00\x00)

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_QuickStart
```

```
    Bases: DataType_Opt
```

Structure of Quick-Start (QS) option [[RFC 4782](#)].

```
    func: pcapkit.const.ipv4.qs_function.QSFunction
```

Function.

```
    rate: int
```

Rate request / report (in Kbps).

```
    ttl: Optional[int]
```

QS TTL.

nounce: `int`
QS nounce.

IPv4 Time Stamp Option

For IPv4 Time Stamp option as described in [RFC 791](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ip.ts.kind</code>	Kind (25)
0	0	<code>ip.ts.type.copy</code>	Copied Flag (0)
0	1	<code>ip.ts.type.class</code>	Option Class (0)
0	3	<code>ip.ts.type.number</code>	Option Number (25)
1	8	<code>ip.ts.length</code>	Length (40)
2	16	<code>ip.ts.pointer</code>	Pointer (5)
3	24	<code>ip.ts.overflow</code>	Overflow Octets
3	28	<code>ip.ts.flag</code>	Flag
4	32	<code>ip.ts.ip</code>	Internet Address
8	64	<code>ip.ts.timestamp</code>	Timestamp

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_TimeStamp
```

```
    Bases DataType_Opt
```

Structure of Timestamp (TS) option [[RFC 791](#)].

pointer: `int`
Pointer.

overflow: `int`
Overflow octets.

flag: `int`
Flag.

ip: `Optional[Tuple[ipaddress.IPv4Address]]`
Array of Internet addresses (if *flag* is 1/3).

timestamp: `Optional[Tuple[datetime.datetime]]`
Array of timestamps (if *flag* is 0/1/3).

data: `Optional[bytes]`
Timestamp data (if *flag* is unknown).

IPv4 Traceroute Option

For IPv4 Traceroute option as described in [RFC 6814](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ip.tr.kind	Kind (82)
0	0	ip.tr.type.copy	Copied Flag (0)
0	1	ip.tr.type.class	Option Class (0)
0	3	ip.tr.type.number	Option Number (18)
1	8	ip.tr.length	Length (12)
2	16	ip.tr.id	ID Number
4	32	ip.tr.ohc	Outbound Hop Count
6	48	ip.tr.rhc	Return Hop Count
8	64	ip.tr.ip	Originator IP Address

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_Traceroute
```

```
    Bases: DataType_Opt
```

Structure of Traceroute (TR) option [RFC 6814].

```
    id: int
```

ID number.

```
    ohc: int
```

Outbound hop count.

```
    rhc: int
```

Return hop count.

```
    ip: ipaddress.IPv4Address
```

Originator IP address.

IPv4 Options with Security Info

For IPv4 options with security info as described in RFC 1108, its structure is described as below:

Octets	Bits	Name	Description
0	0	ip.sec.kind	Kind (130/133)
0	0	ip.sec.type.copy	Copied Flag (1)
0	1	ip.sec.type.class	Option Class (0)
0	3	ip.sec.type.number	Option Number (2)
1	8	ip.sec.length	Length (3)
2	16	ip.sec.level	Classification Level
3	24	ip.sec.flags	Protection Authority Flags

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_Security_Info
```

```
    Bases: DataType_Opt
```

Structure of IPv4 options with security info [RFC 791].

```
    level: pcapkit.const.ipv4.classification_level.ClassificationLevel
```

Classification level.

```
    flags: Tuple[DataType_SEC_Flags]
```

Array of protection authority flags.

```
class pcapkit.protocols.internet.ipv4.DataType_SEC_Flags
```

```
    Bases: pcapkit.corekit.infoclass.Info
```

Protection authority flags, as mapping of protection authority bit assignments *enumeration* and `bool` flags.

IPv4 Traceroute Option

For IPv4 Router Alert option as described in **RFC 2113**, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ip.rsralt.kind</code>	Kind (148)
0	0	<code>ip.rsralt.type.copy</code>	Copied Flag (1)
0	1	<code>ip.rsralt.type.class</code>	Option Class (0)
0	3	<code>ip.rsralt.type.number</code>	Option Number (20)
1	8	<code>ip.rsralt.length</code>	Length (4)
2	16	<code>ip.rsralt.alert</code>	Alert
2	16	<code>ip.rsralt.code</code>	Alert Code

```
class pcapkit.protocols.internet.ipv4.DataType_Opt_RouterAlert
```

```
    Bases: DataType_Opt
```

Structure of Router Alert (RTRALT) option [**RFC 2113**].

```
    alert: pcapkit.const.ipv4.router_alert.RouterAlert
           Alert.
```

```
    code: int
           Alert code.
```

IPv6-Frag - Fragment Header for IPv6

`pcapkit.protocols.internet.ipv6_frag` contains *IPv6_Frag* only, which implements extractor for Fragment Header for IPv6 (IPv6-Frag)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>frag.next</code>	Next Header
1	8		Reserved
2	16	<code>frag.offset</code>	Fragment Offset
3	29		Reserved
3	31	<code>frag.mf</code>	More Flag
4	32	<code>frag.id</code>	Identification

```
class pcapkit.protocols.internet.ipv6_frag.IPv6_Frag (file=None, length=None,
                                                    **kwargs)
```

```
    Bases: pcapkit.protocols.internet.internet.Internet
```

This class implements Fragment Header for IPv6.

```
    classmethod __index__ ()
           Numeral registry index of the protocol.
```

Returns Numeral registry index of the protocol in **IANA**.

Return type *pcapkit.const.reg.transtype.TransType*

⁰ https://en.wikipedia.org/wiki/IPv6_packet#Fragment

`__length_hint__()`

Return an estimated length for the object.

Return type `Literal[8]`

`__post_init__(file, length=None, *, extension=False, **kwargs)`

Post initialisation hook.

Parameters

- **file** (`io.BytesIO`) – Source packet stream.
- **length** (`Optional[int]`) – Length of packet data.

Keyword Arguments

- **extension** (`bool`) – If the protocol is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to `make()`.

make (`**kwargs`)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type `bytes`

read (`length=None, *, extension=False, **kwargs`)

Read Fragment Header for IPv6.

Structure of IPv6-Frag header [[RFC 8200](#)]:

```

+-----+-----+-----+-----+-----+-----+-----+-----+
| Next Header | Reserved | Fragment Offset | Res|M|
+-----+-----+-----+-----+-----+-----+-----+-----+
|                                     Identification                                     |
+-----+-----+-----+-----+-----+-----+-----+-----+

```

Parameters **length** (`Optional[int]`) – Length of packet data.

Keyword Arguments

- **extension** (`bool`) – If the packet is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type `DataType_IPv6_Frag`

property alias

Acronym of corresponding protocol.

Return type `Literal['IPv6-Frag']`

property length

Header length of current protocol.

Return type `int`

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in [IANA](#).

Return type `pcapkit.const.reg.transype.TransType`

__length_hint__()

Return an estimated length for the object.

Return type `Literal[2]`

__post_init__(file, length=None, *, extension=False, **kwargs)

Post initialisation hook.

Parameters

- **file** (`io.BytesIO`) – Source packet stream.
- **length** (`Optional[int]`) – Length of packet data.

Keyword Arguments

- **extension** (`bool`) – If the protocol is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to `make()`.

__read_ipv6_opts_options(length)

Read IPv6-Opts options.

Positional arguments: `length (int)`: length of options

Returns `Tuple[Tuple[pcapkit.const.ipv6.option.Option], Dict[str, DataType_Option]]`: extracted IPv6-Opts options

Raises `ProtocolError` – If the threshold is **NOT** matching.

__read_opt_calipso(code, *, desc)

Read IPv6-Opts CALIPSO option.

Structure of IPv6-Opts CALIPSO option [[RFC 5570](#)]:

Next Header	Hdr Ext Len	Option Type	Option Length
+-----+			
CALIPSO Domain of Interpretation			
+-----+			
Cmppt Length	Sens Level	Checksum (CRC-16)	
+-----+			
Compartment Bitmap (Optional; variable length)			
+-----+			

Parameters **code** (`int`) – option type value

Keyword Arguments **desc** (`str`) – option description

Returns parsed option data


Return type `DataType_Dest_Opt_CALIPSO`

Raises `ProtocolError` – If the option is malformed.

_read_opt_home (*code*, *, *desc*)

Read IPv6-Opts Home Address option.

Structure of IPv6-Opts Home Address option [RFC 6275]:



Parameters `code` (*int*) – option type value

Keyword Arguments **desc** (*str*) – option description

Returns parsed option data


Return type *DataType_Dest_Opt_Home*

Raises *ProtocolError* – If `ipv6_opts.jumbo.length` is **NOT** 16.

```
_read_opt_ilnp (code, *, desc)
```

Read IPv6-Opts ILNP Nonce option.

Structure of IPv6-Opts | LNP Nonce option [RFC 6744]:



Parameters `code` (*int*) – option type value

Keyword Arguments `desc (str)` – option description


Returns parsed option data

Return type *DataType_Dest_Opt_ILNP*

```
_read_opt_ip_dff (code, *, desc)
```

Read IPv6-Opts IP_DFF option.

Structure of IPv6-Opts IP_DFF option [RFC 6971]:




(continues on next page)

VER D R 0 0 0 0	Sequence Number		Pad1	
+--+				


Raises *ProtocolError*—If `ipv6_opts.ip_dff.length` is **NOT** 2.

Structure of IPv6-Opts Jumbo Payload option [RFC 2675]:




Raises *ProtocolError*—If `ipv6_opts.jumbo.length` is **NOT** 4.

Structure of IPv6-Opts Line-Identification option [RFC 6788]:



Return type *DataType_Dest_Opt_LIO*

Structure of IPv6-Opts MPL option [RFC 7731]:



Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data


Return type *DataType_Dest_Opt_MPL*

Raises *ProtocolError* – If the option is malformed.

`_read_opt_none` (*code*, *, *desc*)

Read IPv6-Opts unassigned options.

Structure of IPv6-Opts unassigned options [RFC 8200]:



Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data


Return type *DataType_Dest_Opt_None*

`_read_opt_pad` (*code*, *, *desc*)


Read IPv6-Opts padding options.

Structure of IPv6-Opts padding options [RFC 8200]:

- Pad1 option:



- PadN option:



Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data


Return type Union[*DataType_Dest_Opt_Pad1*, *DataType_Dest_Opt_PadN*]

Raises *ProtocolError* – If code is NOT 0 or 1.

`_read_opt_pdm(code, *, desc)`

Read IPv6-Opts PDM option.

Structure of IPv6-Opts PDM option [RFC 8250]:



Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data

Return type *DataType_Dest_Opt_PDM*


Raises *ProtocolError* – If `ipv6_opts.pdm.length` is **NOT** 10.

`_read_opt_qs(code, *, desc)`


Read IPv6-Opts Quick Start option.

Structure of IPv6-Opts Quick-Start option [RFC 4782]:

- A Quick-Start Request:



- Report of Approved Rate:



Parameters `code` (*int*) – option type value

Keyword Arguments `desc` (*str*) – option description

Returns parsed option data

Return type *DataType_Dest_Opt_QS*

Raises *ProtocolError* – If the option is malformed.

`_read_opt_ra (code, *, desc)`

Read IPv6-Opts Router Alert option.

Structure of IPv6-Opts Router Alert option [RFC 2711]:

```

+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
| 0 0 0 | 0 1 0 1 | 0 0 0 0 0 1 0 |           Value (2 octets)           |
+-----+-----+-----+-----+-----+-----+-----+-----+

```

Parameters `code (int)` – option type value

Keyword Arguments `desc (str)` – option description

Returns parsed option data

Return type `DataType_Dest_Opt_RA`

Raises `ProtocolError` – If `ipv6_opts.tun.length` is **NOT** 2.

`_read_opt_rpl (code, *, desc)`

Read IPv6-Opts RPL option.

Structure of IPv6-Opts RPL option [RFC 6553]:

```

0                               1                               2                               3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1
                                     +-----+-----+-----+-----+
                                     | Option Type | Opt Data Len |
+-----+-----+-----+-----+-----+-----+-----+-----+
| O | R | F | 0 | 0 | 0 | 0 | 0 | RPLInstanceID |           SenderRank           |
+-----+-----+-----+-----+-----+-----+-----+-----+
|                                     (sub-TLVs)                                     |
+-----+-----+-----+-----+-----+-----+-----+-----+

```

Parameters `code (int)` – option type value

Keyword Arguments `desc (str)` – option description

Returns parsed option data

Return type `DataType_Dest_Opt_RPL`

Raises `ProtocolError` – If `ipv6_opts.rpl.length` is **LESS THAN** 4.

`_read_opt_smf_dpd (code, *, desc)`

Read IPv6-Opts SMF_DPD option.


Structure of IPv6-Opts SMF_DPD option [RFC 5570]:

- IPv6 SMF_DPD option header in **I-DPD** mode

```

0                               1                               2                               3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1
+-----+-----+-----+-----+-----+-----+-----+-----+
...                                     | 0 | 0 | 0 | 0 | 0 1000 | Opt. Data Len |
+-----+-----+-----+-----+-----+-----+-----+-----+
| 0 | TidTy | TidLen |                               TaggerID (optional) ...                               |
+-----+-----+-----+-----+-----+-----+-----+-----+
|                                     Identifier ...                                     |
+-----+-----+-----+-----+-----+-----+-----+-----+

```

Parameters `length` (*Optional*[`int`]) – Length of packet data.

Keyword Arguments

- **extension** (`bool`) – If the packet is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type `DataType_IPv6_Opts`

property alias

Acronym of corresponding protocol.

Return type `Literal['IPv6-Opts']`

property length

Header length of current protocol.

Return type `int`

property name

Name of current protocol.

Return type `Literal['Destination Options for IPv6']`

property payload

Payload of current instance.

Raises `UnsupportedCall` – if the protocol is used as an IPv6 extension header

Return type `pcapkit.protocols.protocol.Protocol`

property protocol

Name of next layer protocol.

Return type `pcapkit.const.reg.trans_type.TransType`

`pcapkit.protocols.internet.ipv6_opts._IPv6_Opts_ACT: Dict[str, str]`

IPv6-Opts unknown option actions.

Code	Action
00	skip over this option and continue processing the header
01	discard the packet
10	discard the packet and, regardless of whether or not the packet's Destination Address was a multicast address, send an ICMP Parameter Problem, Code 2, message to the packet's Source Address, pointing to the unrecognized Option Type
11	discard the packet and, only if the packet's Destination Address was not a multicast address, send an ICMP Parameter Problem, Code 2, message to the packet's Source Address, pointing to the unrecognized Option Type

`pcapkit.protocols.internet.ipv6_opts._IPv6_Opts_OPT: Dict[int, Tuple[str, str]]`
 IPv6-Opts options.

Code	Acronym	Option	Reference
0x00	pad	Pad1	[RFC 8200] 0
0x01	pad	PadN	[RFC 8200]
0x04	tun	Tunnel Encapsulation Limit	[RFC 2473] 1
0x05	ra	Router Alert	[RFC 2711] 2
0x07	calipso	Common Architecture Label IPv6 Security Option	[RFC 5570]
0x08	smf_dpd	Simplified Multicast Forwarding	[RFC 6621]
0x0F	pdm	Performance and Diagnostic Metrics	[RFC 8250] 10
0x26	qs	Quick-Start	[RFC 4782][RFC Errata 2034] 6
0x63	rpl	Routing Protocol for Low-Power and Lossy Networks	[RFC 6553]
0x6D	mpl	Multicast Protocol for Low-Power and Lossy Networks	[RFC 7731]
0x8B	ilnp	Identifier-Locator Network Protocol Nonce	[RFC 6744]
0x8C	lio	Line-Identification Option	[RFC 6788]
0xC2	jumbo	Jumbo Payload	[RFC 2675]
0xC9	home	Home Address	[RFC 6275]
0xEE	ip_dff	Depth-First Forwarding	[RFC 6971]

`pcapkit.protocols.internet.ipv6_opts._IPv6_Opts_NULL: Dict[int, str]`
 IPv6-Opts unknown option descriptions.

Code	Description	Reference
0x1E	RFC3692-style Experiment	[RFC 4727]
0x3E	RFC3692-style Experiment	[RFC 4727]
0x4D	Deprecated	[RFC 7731]
0x5E	RFC3692-style Experiment	[RFC 4727]
0x7E	RFC3692-style Experiment	[RFC 4727]
0x8A	Endpoint Identification	DEPRECATED
0x9E	RFC3692-style Experiment	[RFC 4727]
0xBE	RFC3692-style Experiment	[RFC 4727]
0xDE	RFC3692-style Experiment	[RFC 4727]
0xFE	RFC3692-style Experiment	[RFC 4727]

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

`class pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts`

Bases TypedDict

Structure of IPv6-Opts header [RFC 8200].

next: `pcapkit.const.reg.trans_type.TransType`

Next header.

length: `int`
Header extensive length.

options: `Tuple[pcapkit.const.ipv6.option.Option]`
Array of option acronyms.

packet: `bytes`
Packet data.

class `pcapkit.protocols.internet.ipv6_opts.DataType_Option`

Bases TypedDict

IPv6_Opts option.

desc: `str`
Option description.

type: `DataType_IPv6_Opts_Option_Type`
Option type.

length: `int`
Option length.

Note: This attribute is **NOT** the length specified in the IPv6-Opts optiona data, rather the *total* length of the current option.

IPv6-Opts Option Type

For IPv6-Opts option type field as described in [RFC 791](#), its structure is described as below:

Octets	Bits	Name	Descriptions
0	0	<code>ipv6_opts.opt.type.value</code>	Option Number
0	0	<code>ipv6_opts.opt.type.action</code>	Action (00-11)
0	2	<code>ipv6_opts.opt.type.change</code>	Change Flag (0/1)

class `pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts_Option_Type`

Bases TypedDict

Structure of option type field [[RFC 791](#)].

value: `int`
Option number.

action: `str`
Action.

change: `bool`
Change flag.

IPv6-Opts Unassigned Options

For IPv6-Opts unassigned options as described in [RFC 8200](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.opt.type	Option Type
0	0	ipv6_opts.opt.type.value	Option Number
0	0	ipv6_opts.opt.type.action	Action (00-11)
0	2	ipv6_opts.opt.type.change	Change Flag (0/1)
1	8	ipv6_opts.opt.length	Length of Option Data
2	16	ipv6_opts.opt.data	Option Data

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_None
```

```
    Bases: DataType_Option
```

Structure of IPv6-Opts unassigned options [[RFC 8200](#)].

```
    data: bytes
```

```
        Option data.
```

IPv6-Opts Padding Options

Pad1 Option

For IPv6-Opts Pad1 option as described in [RFC 8200](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.pad.type	Option Type
0	0	ipv6_opts.pad.type.value	Option Number
0	0	ipv6_opts.pad.type.action	Action (00)
0	2	ipv6_opts.pad.type.change	Change Flag (0)

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_Pad1
```

```
    Bases: DataType_Option
```

Structure of IPv6-Opts padding options [[RFC 8200](#)].

```
    length: Literal[1]
```

```
        Option length.
```

PadN Option

For IPv6-Opts PadN option as described in [RFC 8200](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.pad.type	Option Type
0	0	ipv6_opts.pad.type.value	Option Number
0	0	ipv6_opts.pad.type.action	Action (00)
0	2	ipv6_opts.pad.type.change	Change Flag (0)
1	8	ipv6_opts.opt.length	Length of Option Data
2	16	ipv6_opts.pad.padding	Padding

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PadN
    Bases: DataType_Option
    Structure of IPv6-Opts padding options [RFC 8200].
    padding: bytes
        Padding data.
```

IPv6-Opts Tunnel Encapsulation Limit Option

For IPv6-Opts Tunnel Encapsulation Limit option as described in [RFC 2473](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.tun.type	Option Type
0	0	ipv6_opts.tun.type.value	Option Number
0	0	ipv6_opts.tun.type.action	Action (00)
0	2	ipv6_opts.tun.type.change	Change Flag (0)
1	8	ipv6_opts.tun.length	Length of Option Data
2	16	ipv6_opts.tun.limit	Tunnel Encapsulation Limit

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_TUN
    Bases: DataType_Option
    Structure of IPv6-Opts Tunnel Encapsulation Limit option [RFC 2473].
    limit: int
        Tunnel encapsulation limit.
```

IPv6-Opts Router Alert Option

For IPv6-Opts Router Alert option as described in [RFC 2711](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.ra.type	Option Type
0	0	ipv6_opts.ra.type.value	Option Number
0	0	ipv6_opts.ra.type.action	Action (00)
0	2	ipv6_opts.ra.type.change	Change Flag (0)
1	8	ipv6_opts.opt.length	Length of Option Data
2	16	ipv6_opts.ra.value	Value

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_RA
    Bases: DataType_Option
    Structure of IPv6-Opts Router Alert option [RFC 2711].
    value: int
        Router alert code value.
    alert: pcapkit.const.ipv6.router_alter.RouterAlert
        Router alert enumeration.
```

IPv6-Opts CALIPSO Option

For IPv6-Opts CALIPSO option as described in [RFC 5570](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.calipso.type	Option Type
0	0	ipv6_opts.calipso.type.value	Option Number
0	0	ipv6_opts.calipso.type.action	Action (00)
0	2	ipv6_opts.calipso.type.change	Change Flag (0)
1	8	ipv6_opts.calipso.length	Length of Option Data
2	16	ipv6_opts.calipso.domain	CALIPSO Domain of Interpretation
6	48	ipv6_opts.calipso.cmpt_len	Cmpt Length
7	56	ipv6_opts.calipso.level	Sens Level
8	64	ipv6_opts.calipso.chksum	Checksum (CRC-16)
9	72	ipv6_opts.calipso.bitmap	Compartment Bitmap

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_CALIPSO
```

```
    Bases: DataType_Option
```

Structure of IPv6-Opts CALIPSO option [[RFC 5570](#)].

```
domain: int
    CALIPSO domain of interpretation.
```

```
cmpt_len: int
    Compartment length.
```

```
level: int
    Sene level.
```

```
chksum: bytes
    Checksum (CRC-16).
```

```
bitmap: Tuple[str]
    Compartment bitmap.
```

IPv6-Opts SMF_DPD Option

I-DPD Mode

For IPv6 SMF_DPD option header in I-DPD mode as described in [RFC 5570](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.smf_dpd.type	Option Type
0	0	ipv6_opts.smf_dpd.type.value	Option Number
0	0	ipv6_opts.smf_dpd.type.action	Action (00)
0	2	ipv6_opts.smf_dpd.type.change	Change Flag (0)
1	8	ipv6_opts.smf_dpd.length	Length of Option Data
2	16	ipv6_opts.smf_dpd.dpd_type	DPD Type (0)
2	17	ipv6_opts.smf_dpd.tid_type	TaggerID Type
2	20	ipv6_opts.smf_dpd.tid_len	TaggerID Length
3	24	ipv6_opts.smf_dpd.tid	TaggerID
?	?	ipv6_opts.smf_dpd.id	Identifier

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_SMF_I_PDP
    Bases: DataType_Option
    Structure of IPv6-Opts SMF_DPD option in I-DPD mode [RFC 5570].
    dpd_type: Literal['I-DPD']
        DPD type.
    tid_type: pcapkit.const.ipv6.tagger_id.TaggerID
        TaggerID type.
    tid_len: int
        TaggerID length.
    tid: int
        TaggerID.
    id: bytes
        Identifier.
```

H-DPD Mode

For IPv6 SMF_DPD option header in H-DPD mode as described in [RFC 5570](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ipv6_opts.smf_dpd.type</code>	Option Type
0	0	<code>ipv6_opts.smf_dpd.type.value</code>	Option Number
0	0	<code>ipv6_opts.smf_dpd.type.action</code>	Action (00)
0	2	<code>ipv6_opts.smf_dpd.type.change</code>	Change Flag (0)
1	8	<code>ipv6_opts.smf_dpd.length</code>	Length of Option Data
2	16	<code>ipv6_opts.smf_dpd.dpd_type</code>	DPD Type (1)
2	17	<code>ipv6_opts.smf_dpd.hav</code>	Hash Assist Value

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_SMF_H_PDP
    Bases: DataType_Option
    Structure of IPv6-Opts SMF_DPD option in H-DPD mode [RFC 5570].
    dpd_type: Literal['H-DPD']
        DPD type.
    hav: str
        Hash assist value (as binary string).
```

IPv6-Opts PDM Option

For IPv6-Opts PDM option as described in [RFC 8250](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.pdm.type	Option Type
0	0	ipv6_opts.pdm.type.value	Option Number
0	0	ipv6_opts.pdm.type.action	Action (00)
0	2	ipv6_opts.pdm.type.change	Change Flag (0)
1	8	ipv6_opts.pdm.length	Length of Option Data
2	16	ipv6_opts.pdm.scaledtlr	Scale Delta Time Last Received
3	24	ipv6_opts.pdm.scaledtls	Scale Delta Time Last Sent
4	32	ipv6_opts.pdm.psntp	Packet Sequence Number This Packet
6	48	ipv6_opts.pdm.psnlr	Packet Sequence Number Last Received
8	64	ipv6_opts.pdm.deltatlr	Delta Time Last Received
10	80	ipv6_opts.pdm.deltatls	Delta Time Last Sent

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PDM
```

Bases `DataType_Option`

Structure of IPv6-Opts PDM option [[RFC 8250](#)].

scaledtlr: `datetime.timedelta`

Scale delta time last received.

scaledtls: `datetime.timedelta`

Scale delta time last sent.

psntp: `int`

Packet sequence number this packet.

psnlr: `int`

Packet sequence number last received.

deltatlr: `datetime.timedelta`

Delta time last received.

deltatls: `datetime.timedelta`

Delta time last sent.

IPv6-Opts Quick Start Option

For IPv6-Opts Quick Start option as described in [RFC 4782](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.qs.type	Option Type
0	0	ipv6_opts.qs.type.value	Option Number
0	0	ipv6_opts.qs.type.action	Action (00)
0	2	ipv6_opts.qs.type.change	Change Flag (1)
1	8	ipv6_opts.qs.length	Length of Option Data
2	16	ipv6_opts.qs.func	Function (0/8)
2	20	ipv6_opts.qs.rate	Rate Request / Report (in Kbps)
3	24	ipv6_opts.qs.ttl	QS TTL / <code>None</code>
4	32	ipv6_opts.qs.nounce	QS Nounce
7	62		Reserved

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_QS
```

Bases `DataType_Option`

Structure of IPv6-Opts Quick Start option [RFC 8250].

func: `pcapkit.const.ipv6.qs_function.QSFunction`
Function.

rate: `float`
Rate request and/or report (in *Kbps*).

ttl: `Optional[int]`
QS TTL.

nounce: `int`
QS nounce.

IPv6-Opts RPL Option

For IPv6-Opts RPL option as described in RFC 6553, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ipv6_opts.rpl.type</code>	Option Type
0	0	<code>ipv6_opts.rpl.type.value</code>	Option Number
0	0	<code>ipv6_opts.rpl.type.action</code>	Action (01)
0	2	<code>ipv6_opts.rpl.type.change</code>	Change Flag (1)
1	8	<code>ipv6_opts.rpl.length</code>	Length of Option Data
2	16	<code>ipv6_opts.rpl.flags</code>	RPL Option Flags
2	16	<code>ipv6_opts.rpl.flags.down</code>	Down Flag
2	17	<code>ipv6_opts.rpl.flags.rank_error</code>	Rank-Error Flag
2	18	<code>ipv6_opts.rpl.flags.fwd_error</code>	Forwarding-Error Flag
3	24	<code>ipv6_opts.rpl.id</code>	RPL Instance ID
4	32	<code>ipv6_opts.rpl.rank</code>	SenderRank
6	48	<code>ipv6_opts.rpl.data</code>	Sub-TLVs

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_RPL
```

Bases `DataType_Option`

Structure of IPv6-Opts RPL option [RFC 6553].

flags: `DataType_RPL_Flags`
RPL option flags.

id: `int`
RPL instance ID.

rank: `int`
Sender rank.

data: `Optional[bytes]`
Sub-TLVs (if `ipv6_opts.rpl.length` is **GREATER THAN** 4).

```
class pcapkit.protocols.internet.ipv6_opts.DataType_RPL_Flags
```

Bases `TypedDict`

RPL option flags.

down: `bool`
Down flag.

rank_error: `bool`

Rank-Error flag.

fwd_error: `bool`

Forwarding-Error flag.

IPv6-Opts MPL Option

For IPv6-Opts MPL option as described in [RFC 7731](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ipv6_opts.mpl.type</code>	Option Type
0	0	<code>ipv6_opts.mpl.type.value</code>	Option Number
0	0	<code>ipv6_opts.mpl.type.action</code>	Action (01)
0	2	<code>ipv6_opts.mpl.type.change</code>	Change Flag (1)
1	8	<code>ipv6_opts.mpl.length</code>	Length of Option Data
2	16	<code>ipv6_opts.mpl.seed_len</code>	Seed-ID Length
2	18	<code>ipv6_opts.mpl.flags</code>	MPL Option Flags
2	18	<code>ipv6_opts.mpl.max</code>	Maximum SEQ Flag
2	19	<code>ipv6_opts.mpl.verification</code>	Verification Flag
2	20		Reserved
3	24	<code>ipv6_opts.mpl.seq</code>	Sequence
4	32	<code>ipv6_opts.mpl.seed_id</code>	Seed-ID

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_MPL
```

Bases `DataType_Option`

Structure of IPv6-Opts MPL option [[RFC 7731](#)].

seed_len: `pcapkit.const.ipv6.seed_id.SeedID`

Seed-ID length.

flags: `DataType_MPL_Flags`

MPL option flags.

seq: `int`

Sequence.

seed_id: `Optional[int]`

Seed-ID.

```
class pcapkit.protocols.internet.ipv6_opts.DataType_MPL_Flags
```

Bases `TypedDict`

MPL option flags.

max: `bool`

Maximum sequence flag.

verification: `bool`

Verification flag.

IPv6-Opts ILNP Nounce Option

For IPv6-Opts ILNP Nounce option as described in [RFC 6744](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.ilnp.type	Option Type
0	0	ipv6_opts.ilnp.type.value	Option Number
0	0	ipv6_opts.ilnp.type.action	Action (10)
0	2	ipv6_opts.ilnp.type.change	Change Flag (0)
1	8	ipv6_opts.ilnp.length	Length of Option Data
2	16	ipv6_opts.ilnp.value	Nonce Value

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_ILNP
```

```
    Bases: DataType_Option
```

```
    Structure of IPv6-Opts ILNP Nounce option [RFC 6744].
```

```
    value: bytes
           Nonce value.
```

IPv6-Opts Line-Identification Option

For IPv6-Opts Line-Identification option as described in [RFC 6788](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.lio.type	Option Type
0	0	ipv6_opts.lio.type.value	Option Number
0	0	ipv6_opts.lio.type.action	Action (10)
0	2	ipv6_opts.lio.type.change	Change Flag (0)
1	8	ipv6_opts.lio.length	Length of Option Data
2	16	ipv6_opts.lio.lid_len	Line ID Length
3	24	ipv6_opts.lio.lid	Line ID

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_LIO
```

```
    Bases: DataType_Option
```

```
    Structure of IPv6-Opts Line-Identification option [RFC 6788].
```

```
    lid_len: int
            Line ID length.
```

```
    lid: bytes
         Line ID.
```

IPv6-Opts Jumbo Payload Option

For IPv6-Opts Jumbo Payload option as described in [RFC 2675](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ipv6_opts.jumbo.type</code>	Option Type
0	0	<code>ipv6_opts.jumbo.type.value</code>	Option Number
0	0	<code>ipv6_opts.jumbo.type.action</code>	Action (11)
0	2	<code>ipv6_opts.jumbo.type.change</code>	Change Flag (0)
1	8	<code>ipv6_opts.jumbo.length</code>	Length of Option Data
2	16	<code>ipv6_opts.jumbo.payload_len</code>	Jumbo Payload Length

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_Jumbo
```

```
    Bases: DataType_Option
```

Structure of IPv6-Opts Jumbo Payload option [[RFC 2675](#)].

```
    payload_len: int
        Jumbo payload length.
```

IPv6-Opts Home Address Option

For IPv6-Opts Home Address option as described in [RFC 6275](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ipv6_opts.home.type</code>	Option Type
0	0	<code>ipv6_opts.home.type.value</code>	Option Number
0	0	<code>ipv6_opts.home.type.action</code>	Action (11)
0	2	<code>ipv6_opts.home.type.change</code>	Change Flag (0)
1	8	<code>ipv6_opts.home.length</code>	Length of Option Data
2	16	<code>ipv6_opts.home.ip</code>	Home Address

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_Home
```

```
    Bases: DataType_Option
```

Structure of IPv6-Opts Home Address option [[RFC 6275](#)].

```
    ip: ipaddress.IPv6Address
        Home address.
```

IPv6-Opts IP_DFF Option

For IPv6-Opts IP_DFF option as described in [RFC 6971](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	ipv6_opts.ip_dff.type	Option Type
0	0	ipv6_opts.ip_dff.type.value	Option Number
0	0	ipv6_opts.ip_dff.type.action	Action (11)
0	2	ipv6_opts.ip_dff.type.change	Change Flag (1)
1	8	ipv6_opts.ip_dff.length	Length of Option Data
2	16	ipv6_opts.ip_dff.version	Version
2	18	ipv6_opts.ip_dff.flags	Flags
2	18	ipv6_opts.ip_dff.flags.dup	DUP Flag
2	19	ipv6_opts.ip_dff.flags.ret	RET Flag
2	20		Reserved
3	24	ipv6_opts.ip_dff.seq	Sequence Number

```
class pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_IP_DFF
```

```
    Bases: DataType_Option
```

```
    Structure of IPv6-Opts IP_DFF option [RFC 6971].
```

```
    version: int
```

```
        Version.
```

```
    flags: DataType_IP_DFF_Flags
```

```
        Flags.
```

```
    seq: int
```

```
        Sequence number.
```

```
class pcapkit.protocols.internet.ipv6_opts.DataType_IP_DFF_Flags
```

```
    Bases: TypedDict
```

```
    Flags.
```

```
    dup: bool
```

```
        DUP flag.
```

```
    ret: bool
```

```
        RET flag.
```

IPv6-Route - Routing Header for IPv6

`pcapkit.protocols.internet.ipv6_route` contains *IPv6_Route* only, which implements extractor for Routing Header for IPv6 (IPv6-Route)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	route.next	Next Header
1	8	route.length	Header Extensive Length
2	16	route.type	Routing Type
3	24	route.seg_left	Segments Left
4	32	route.data	Type-Specific Data

```
class pcapkit.protocols.internet.ipv6_route.IPv6_Route (file=None, length=None,
                                                         **kwargs)
```

```
    Bases: pcapkit.protocols.internet.internet.Internet
```

⁰ https://en.wikipedia.org/wiki/IPv6_packet#Routing

This class implements Routing Header for IPv6.

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in [IANA](#).

Return type `pcapkit.const.reg.trans_type.TransType`

__length_hint__()

Return an estimated length for the object.

Return type `Literal[4]`

__post_init__(file, length=None, *, extension=False, **kwargs)

Post initialisation hook.

Parameters

- **file** (`io.BytesIO`) – Source packet stream.
- **length** (`Optional[int]`) – Length of packet data.

Keyword Arguments

- **extension** (`bool`) – If the protocol is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to `make()`.

__read_data_type_2(length)

Read IPv6-Route Type 2 data.

Structure of IPv6-Route Type 2 data [[RFC 6275](#)]:



Parameters **length** (`int`) – route data length

Returns parsed route data

Return type `DataType_IPv6_Route_2`

Raises `ProtocolError` – If length is NOT 20.

__read_data_type_none(length)

Read IPv6-Route unknown type data.

Structure of IPv6-Route unknown type data [[RFC 8200](#)][[RFC 5095](#)]:

```

+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
| Next Header | Hdr Ext Len | Routing Type | Segments Left |
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
|
|
|
|
|
|
|
|
|
|
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+

```

Parameters `length (int)` – route data length

Returns parsed route data

Return type `DataType_IPv6_Route_None`

`_read_data_type_rpl (length)`

Read IPv6-Route RPL Source data.

Structure of IPv6-Route RPL Source data [[RFC 6554](#)]:

```

0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
| Next Header | Hdr Ext Len | Routing Type | Segments Left |
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
| CmprI | CmprE | Pad | Reserved |
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
|
|
|
|
|
|
|
|
|
|
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+

```

Parameters `length (int)` – route data length

Returns parsed route data

Return type `DataType_IPv6_Route_RPL`

Raises `ProtocolError` – If length is NOT 20.

`_read_data_type_src (length)`

Read IPv6-Route Source Route data.

Structure of IPv6-Route Source Route data [[RFC 5095](#)]:


```

+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
| Next Header | Hdr Ext Len | Routing Type=0 | Segments Left |
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+
|
|
|
|
|
|
|
|
|
|
+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+

```

(continues on next page)

(continued from previous page)



Parameters `length` (*int*) – route data length

Returns parsed route data

Return type *DataType_IPv6_Route_Source*

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.


Returns Constructed packet data.

Return type *bytes*

read (*length=None, *, extension=False, **kwargs*)

Read Routing Header for IPv6.

Structure of IPv6-Route header [RFC 8200][RFC 5095]:



Parameters `length` (*Optional[int]*) – Length of packet data.

Keyword Arguments

- **extension** (*bool*) – If the packet is used as an IPv6 extension header.

- ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_IPv6_Route*

property alias

Acronym of corresponding protocol.

Return type Literal['IPv6-Route']

property length

Header length of current protocol.

Return type *int*

property name

Name of current protocol.

Return type Literal['Routeing Header for IPv6']

property payload

Payload of current instance.

Raises *UnsupportedCall* – if the protocol is used as an IPv6 extension header

Return type *pcapkit.protocols.protocol.Protocol*

property protocol

Name of next layer protocol.

Return type *pcapkit.const.reg.transype.TransType*

`pcapkit.protocols.internet.ipv6_route._ROUTE_PROC: Dict[int, str]`
IPv6 routing processors.

Code	Processor	Note
0	<code>_read_data_type_src()</code>	[RFC 5095] DEPRECATED
2	<code>_read_data_type_2()</code>	[RFC 6275]
3	<code>_read_data_type_rpl()</code>	[RFC 6554]

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

class `pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route`

Structure of IPv6-Route header [RFC 8200][RFC 5095].

next: *pcapkit.const.reg.transype.TransType*

Next header.

length: *int*

Header extensive length.

type: *pcapkit.const.ipv6.routing.Routing*

Routing type.

seg_left: *int*

Segments left.

packet: `bytes`
Raw packet data.

IPv6-Route Unknown Type

For IPv6-Route unknown type data as described in [RFC 8200](#) and [RFC 5095](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>route.next</code>	Next Header
1	8	<code>route.length</code>	Header Extensive Length
2	16	<code>route.type</code>	Routing Type
3	24	<code>route.seg_left</code>	Segments Left
4	32	<code>route.data</code>	Type-Specific Data

class `pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_None`

Bases TypedDict

Structure of IPv6-Route unknown type data [[RFC 8200](#)][[RFC 5095](#)].

data: `bytes`
Type-specific data.

IPv6-Route Source Route

For IPv6-Route Source Route data as described in [RFC 5095](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>route.next</code>	Next Header
1	8	<code>route.length</code>	Header Extensive Length
2	16	<code>route.type</code>	Routing Type
3	24	<code>route.seg_left</code>	Segments Left
4	32		Reserved
8	64	<code>route.ip</code>	Address

class `pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_Source`

Bases TypedDict

Structure of IPv6-Route Source Route data [[RFC 5095](#)].

ip: `Tuple[ipaddress.IPv6Address]`
Array of IPv6 addresses.

IPv6-Route Type 2

For IPv6-Route Type 2 data as described in [RFC 6275](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>route.next</code>	Next Header
1	8	<code>route.length</code>	Header Extensive Length
2	16	<code>route.type</code>	Routing Type
3	24	<code>route.seg_left</code>	Segments Left
4	32		Reserved
8	64	<code>route.ip</code>	Home Address

```
class pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_2
```

```
    Bases TypedDict
```

```
    Structure of IPv6-Route Type 2 data [RFC 6275].
```

```
    ip: ipaddress.IPv6Address
```

```
        Home IPv6 addresses.
```

IPv6-Route RPL Source

For IPv6-Route RPL Source data as described in [RFC 6554](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>route.next</code>	Next Header
1	8	<code>route.length</code>	Header Extensive Length
2	16	<code>route.type</code>	Routing Type
3	24	<code>route.seg_left</code>	Segments Left
4	32	<code>route.cmpr_i</code>	CmprI
4	36	<code>route.cmpr_e</code>	CmprE
5	40	<code>route.pad</code>	Pad Size
5	44		Reserved
8	64	<code>route.ip</code>	Addresses

```
class pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_RPL
```

```
    Bases TypedDict
```

```
    Structure of IPv6-Route RPL Source data [RFC 6554].
```

```
    cmpr_i: int
```

```
        CmprI.
```

```
    cmpr_e: int
```

```
        CmprE.
```

```
    pad: int
```

```
        Pad size.
```

```
    ip: Tuple[Union[ipaddress.IPv4Address, ipaddress.IPv6Address]]
```

```
        Array of IPv4 and/or IPv6 addresses.
```

IPv6 - Internet Protocol version 6

`pcapkit.protocols.internet.ipv6` contains *IPv6* only, which implements extractor for Internet Protocol version 6 (IPv6)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ip.version</code>	Version (6)
0	4	<code>ip.class</code>	Traffic Class
1	12	<code>ip.label</code>	Flow Label
4	32	<code>ip.payload</code>	Payload Length (header excludes)
6	48	<code>ip.next</code>	Next Header
7	56	<code>ip.limit</code>	Hop Limit
8	64	<code>ip.src</code>	Source Address
24	192	<code>ip.dst</code>	Destination Address

class `pcapkit.protocols.internet.ipv6.IPv6` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.internet.ip.IP`

This class implements Internet Protocol version 6.

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in IANA.

Return type `pcapkit.const.reg.transype.TransType`

`__length_hint__()`

Return an estimated length for the object.

Return type `Literal[40]`

`__decode_next_layer(ipv6, proto=None, length=None)`

Decode next layer extractor.

Parameters

- **ipv6** (`DataType_IPv6`) – info buffer
- **proto** (`str`) – next layer protocol name
- **length** (`int`) – valid (*not padding*) length

Returns current protocol with next layer extracted

Return type `DataType_IPv6`

`__read_ip_addr()`

Read IP address.

Returns Parsed IP address.

Return type `ipaddress.IPv6Address`

`__read_ip_hextet()`

Read first four hextets of IPv6.

Returns Parsed hextets data, including version number, traffic class and flow label.

Return type `Tuple[int, int, int]`

⁰ https://en.wikipedia.org/wiki/IPv6_packet

classmethod `id()`

Index ID of the protocol.

Returns Index ID of the protocol.

Return type `Literal['IPv6']`

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.


Returns Constructed packet data.

Return type `bytes`

read (*length=None, **kwargs*)

Read Internet Protocol version 6 (IPv6).

Structure of IPv6 header [[RFC 2460](#)]:



Parameters **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type `DataType_IPv6`

property `length`

Header length of corresponding protocol.

Return type `int`

property `name`

Name of corresponding protocol.

Return type `Literal['Internet Protocol version 6']`

property protocol

Name of next layer protocol.

Return type `pcapkit.const.reg.transtype.TransType`**Data Structure**

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

class `pcapkit.protocols.internet.ipv6.DataType_IPv6`**Bases** TypedDict

Structure of IPv6 header [RFC 2460].

version: `Literal[6]`

Version.

class: `int`

Traffic class.

label: `int`

Flow label.

payload: `int`

Payload length.

next: `pcapkit.const.reg.transtype.TransType`

Next header.

limit: `int`

Hop limit.

src: `ipaddress.IPv6Address`

Source address.

dst: `ipaddress.IPv6Address`

Destination address.

packet: `bytes`

Raw packet data.

IPX - Internetwork Packet Exchange

`pcapkit.protocols.internet.ipx` contains *IPX* only, which implements extractor for Internetwork Packet Exchange (IPX)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ipx.cksum</code>	Checksum
2	16	<code>ipx.len</code>	Packet Length (header includes)
4	32	<code>ipx.count</code>	Transport Control (hop count)
5	40	<code>ipx.type</code>	Packet Type
6	48	<code>ipx.dst</code>	Destination Address
18	144	<code>ipx.src</code>	Source Address

⁰ https://en.wikipedia.org/wiki/Internetwork_Packet_Exchange

class pcapkit.protocols.internet.ipx.**IPX** (*file=None, length=None, **kwargs*)

Bases: *pcapkit.protocols.internet.internet.Internet*

This class implements Internetwork Packet Exchange.

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in IANA.

Return type *pcapkit.const.reg.transtype.TransType*

`__length_hint__()`

Return an estimated length for the object.

Return type Literal[30]

`__read_ipx_address()`

Read IPX address field.

Returns Parsed IPX address field.

Return type *DataType_IPX_Address*

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type bytes

read (*length=None, **kwargs*)

Read Internetwork Packet Exchange.

Args: length (Optional[int]): Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_IPX*

property `dst`

Destination IPX address.

Return type str

property `length`

Header length of corresponding protocol.

Return type Literal[30]

property `name`

Name of corresponding protocol.

Return type Literal['Internetwork Packet Exchange']

property `protocol`

Name of next layer protocol.

Return type *pcapkit.const.reg.transtype.TransType*

property `src`

Source IPX address.

Return type `str`

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

```
class pcapkit.protocols.internet.ipx.DataType_IPX
```

Bases TypedDict

Structure of IPX header [RFC 1132].

chksum: `bytes`

Checksum.

len: `int`

Packet length (header includes).

count: `int`

Transport control (hop count).

type: `pcapkit.const.ipx.packet.Packet`

Packet type.

dst: `DataType_IPX_Address`

Destination address.

src: `DataType_IPX_Address`

Source address.

For IPX address field, its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>ipx.addr.network</code>	Network Number
4	32	<code>ipx.addr.node</code>	Node Number
10	80	<code>ipx.addr.socket</code>	Socket Number

```
class pcapkit.protocols.internet.ipx.DataType_IPX_Address
```

Bases TypedDict

Structure of IPX address.

network: `str`

Network number (: separated).

node: `str`

Node number (– separated).

socket: `pcapkit.const.ipx.socket.Socket`

Socket number.

addr: `str`

Full address (: separated).

MH - Mobility Header

`pcapkit.protocols.internet.mh` contains *MH* only, which implements extractor for Mobility Header (MH)⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>mh.next</code>	Next Header
1	8	<code>mh.length</code>	Header Length
2	16	<code>mh.type</code>	Mobility Header Type
3	24		Reserved
4	32	<code>mh.chksum</code>	Checksum
6	48	<code>mh.data</code>	Message Data

class `pcapkit.protocols.internet.mh.MH` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.internet.internet.Internet`

This class implements Mobility Header.

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in *IANA*.

Return type `pcapkit.const.reg.transtype.TransType`

`__length_hint__()`

Return an estimated length for the object.

Return type `Literal[6]`

`__post_init__(file, length=None, *, extension=False, **kwargs)`

Post initialisation hook.

Parameters

- **file** (`io.BytesIO`) – Source packet stream.
- **length** (`Optional[int]`) – Length of packet data.

Keyword Arguments

- **extension** (`bool`) – If the protocol is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to `make()`.

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Constructed packet data.


Return type `bytes`

read (*length=None, *, extension=False, **kwargs*)

Read Mobility Header.

Structure of MH header [**RFC 6275**]:

⁰ https://en.wikipedia.org/wiki/Mobile_IP#Changes_in_IPv6_for_Mobile_IPv6



Parameters `length` (*Optional*[*int*]) – Length of packet data.

Keyword Arguments

- **extension** (*bool*) – If the packet is used as an IPv6 extension header.
- ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_MH*

```
property length
```

Header length of current protocol.

Return type `int`

```
property name
```

Name of current protocol.

Return type Literal['Mobility Header']

property payload

Payload of current instance.

Raises *UnsupportedCall* – if the protocol is used as an IPv6 extension header

Return type *pcapkit.protocols.protocol.Protocol*

property protocol

Name of next layer protocol.

Return type *pcapkit.const.reg.transtype.TransType*

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

```
class pcapkit.protocols.internet.mh.DataType_MH
```

Bases TypedDict

```
next: pcapkit.const.reg.transtype.TransType
```

Next header.

```
length:  int
```

Header length.

type: `pcapkit.const.mh.packet.Packet`
Mobility header type.

```
chksum:  bytes
Checksum.
```

```
data: bytes
    Message data.
```

Base Protocol

`pcapkit.protocols.internet.internet` contains *Internet*, which is a base class for internet layer protocols, eg. *AH*, *IPsec*, *IPv4*, *IPv6*, *IPX*, and etc.

[illegible]

Bases: `pcapkit.protocols.protocol.Protocol`

Abstract base class for internet layer protocol family.

```
__layer__ = 'Internet'
    Layer of protocol.
```

__proto__: DefaultDict[int, Tuple[str, str]]
Protocol index mapping for decoding next layer, c.f. `self._decode_next_layer` & `self._import_next_layer`. The values should be a tuple representing the module name and class name.

Code	Module	Class
0	<i>pcapkit.protocols.internet.hopopt</i>	<i>HOPOPT</i>
4	<i>pcapkit.protocols.internet.ipv4</i>	<i>IPv4</i>
6	<i>pcapkit.protocols.transport.tcp</i>	<i>TCP</i>
17	<i>pcapkit.protocols.transport.udp</i>	<i>UDP</i>
41	<i>pcapkit.protocols.internet.ipv6</i>	<i>IPv6</i>
43	<i>pcapkit.protocols.internet.ipv6_route</i>	<i>IPv6_Route</i>
44	<i>pcapkit.protocols.internet.ipv6_frag</i>	<i>IPv6_Frag</i>
51	<i>pcapkit.protocols.internet.ah</i>	<i>AH</i>
60	<i>pcapkit.protocols.internet.ipv6_opts</i>	<i>IPv6_Opts</i>
111	<i>pcapkit.protocols.internet.ipx</i>	<i>IPX</i>
135	<i>pcapkit.protocols.internet.mh</i>	<i>MH</i>
139	<i>pcapkit.protocols.internet.hip</i>	<i>HIP</i>

`_decode_next_layer` (*dict_*, *proto=None*, *length=None*, ***, *version=4*, *ipv6_exthdr=None*)
Decode next layer extractor.

Parameters

- **dict** (*dict*) – info buffer
- **proto** (*int*) – next layer protocol index
- **length** (*int*) – valid (*non-padding*) length

Keyword Arguments

- **version** (*Literal*[4, 6]) – IP version
- **ipv6_exthdr** (`pcapkit.corekit.protochain.ProtoChain`) – protocol chain of IPv6 extension headers

Returns current protocol with next layer extracted

Return type `dict`

`_import_next_layer` (*proto*, *length=None*, *, *version=4*, *extension=False*)

Import next layer extractor.

This method currently supports following protocols as registered in *TransType*:

proto	Class
0	<i>HOPOPT</i>
4	<i>IPv4</i>
6	<i>TCP</i>
17	<i>UDP</i>
41	<i>IPv6</i>
43	<i>IPv6_Route</i>
44	<i>IPv6_Frag</i>
51	<i>AH</i>
60	<i>IPv6_Opts</i>
111	<i>IPX</i>
135	<i>MH</i>
139	<i>HIP</i>

Parameters

- **`proto`** (*int*) – next layer protocol index
- **`length`** (*int*) – valid (*non-padding*) length

Keyword Arguments

- **`version`** (*Literal[4, 6]*) – IP protocol version
- **`extension`** (*bool*) – if is extension header

Returns instance of next layer

Return type *pcapkit.protocols.protocol.Protocol*

`_read_protos` (*size*)

Read next layer protocol type.

Parameters **`size`** (*int*) – buffer size

Returns next layer's protocol enumeration

Return type *pcapkit.const.reg.transtype.TransType*

property layer

Protocol layer.

Return type *Literal['Internet']*

1.3.4 Transport Layer Protocols

`pcapkit.protocols.transport` is collection of all protocols in transport layer, with detailed implementation and methods.

UDP - User Datagram Protocol

`pcapkit.protocols.transport.udp` contains `UDP` only, which implements extractor for User Datagram Protocol (UDP)⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>udp.srcport</code>	Source Port
2	16	<code>udp.dstport</code>	Destination Port
4	32	<code>udp.len</code>	Length (header includes)
6	48	<code>udp.checksum</code>	Checksum

class `pcapkit.protocols.transport.udp.UDP` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.transport.transport.Transport`

This class implements User Datagram Protocol.

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in IANA.

Return type `pcapkit.const.reg.transtype.TransType`

`__length_hint__()`

Return an estimated length for the object.

Return type `Literal[8]`

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.


Returns Constructed packet data.

Return type `bytes`

read (*length=None, **kwargs*)

Read User Datagram Protocol (UDP).

Structure of UDP header [RFC 768]:



⁰ https://en.wikipedia.org/wiki/User_Datagram_Protocol

Parameters `length` (*Optional[int]*) – Length of packet data.

Keyword Arguments `**kwargs` – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_UDP*

property `dst`

Destination port.

Return type `int`

property `length`

Header length of current protocol.

Return type `Literal[8]`

property `name`

Name of current protocol.

Return type `Literal['User Datagram Protocol']`

property `src`

Source port.

Return type `int`

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

```
class pcapkit.protocols.transport.udp.DataType_UDP
```

Bases `TypedDict`

Structure of UDP header [[RFC 768](#)].

srcport: `int`

Source port.

dstport: `int`

Destination port.

len: `int`

Length.

checksum: `bytes`

Checksum.

TCP - Transmission Control Protocol

`pcapkit.protocols.transport.tcp` contains *TCP* only, which implements extractor for Transmission Control Protocol (TCP)*⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>tcp.srcport</code>	Source Port
2	16	<code>tcp.dstport</code>	Destination Port
4	32	<code>tcp.seq</code>	Sequence Number
8	64	<code>tcp.ack</code>	Acknowledgement Number (if ACK set)
12	96	<code>tcp.hdr_len</code>	Data Offset
12	100		Reserved (must be \x00)
12	103	<code>tcp.flags.ns</code>	ECN Concealment Protection (NS)
13	104	<code>tcp.flags.cwr</code>	Congestion Window Reduced (CWR)
13	105	<code>tcp.flags.ece</code>	ECN-Echo (ECE)
13	106	<code>tcp.flags.urg</code>	Urgent (URG)
13	107	<code>tcp.flags.ack</code>	Acknowledgement (ACK)
13	108	<code>tcp.flags.psh</code>	Push Function (PSH)
13	109	<code>tcp.flags.rst</code>	Reset Connection (RST)
13	110	<code>tcp.flags.syn</code>	Synchronize Sequence Numbers (SYN)
13	111	<code>tcp.flags.fin</code>	Last Packet from Sender (FIN)
14	112	<code>tcp.window_size</code>	Size of Receive Window
16	128	<code>tcp.checksum</code>	Checksum
18	144	<code>tcp.urgent_pointer</code>	Urgent Pointer (if URG set)
20	160	<code>tcp.opt</code>	TCP Options (if data offset > 5)

class `pcapkit.protocols.transport.tcp.TCP` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.transport.transport.Transport`

This class implements Transmission Control Protocol.

_syn: `bool`

SYN flag.

_ack: `bool`

ACK flag.

classmethod `__index__()`

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol in *IANA*.

Return type `pcapkit.const.reg.transtype.TransType`

__length_hint__()

Return an estimated length for the object.


Return type `Literal[20]`

_read_join_ack (*bits, size, kind*)

Read Join Connection option for Third ACK.

Structure of MP_JOIN-ACK [*RFC 6824*]:

⁰ https://en.wikipedia.org/wiki/Transmission_Control_Protocol



Parameters

- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)


Returns extracted Join Connection (MP_JOIN-ACK) option for Third ACK

Return type *DataType_TCP_Opt_MP_JOIN_ACK*

_read_join_syn (*bits, size, kind*)

Read Join Connection option for Initial SYN.

Structure of MP_JOIN-SYN [RFC 6824]:



Parameters

- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)


Returns extracted Join Connection (MP_JOIN-SYN) option for Initial SYN

Return type *DataType_TCP_Opt_MP_JOIN_SYN*

_read_join_synack (*bits, size, kind*)


Read Join Connection option for Responding SYN/ACK.

Structure of MP_JOIN-SYN/ACK [RFC 6824]:



(continues on next page)

(continued from previous page)

**Parameters**

- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)

Returns extracted Join Connection (MP_JOIN-SYN/ACK) option for Responding SYN/ACK**Return type** *DataType_TCP_Opt_MP_JOIN_SYNACK***_read_mode_acopt** (*size, kind*)

Read Alternate Checksum Request option.

Structure of TCP CHKSUM-REQ [RFC 1146][RFC 6247]:

**Parameters**

- **size** (*int*) – length of option
- **kind** (*Literal[14]*) – option kind value (Alt-Chksum Request)

Returns extracted Alternate Checksum Request (CHKSUM-REQ) option**Return type** *DataType_TCP_Opt_ACOPT***_read_mode_donone** (*size, kind*)

Read options request no process.


Parameters

- **size** (*int*) – length of option
- **kind** (*int*) – option kind value

Returns Extracted option with no operation.**Return type** *DataType_TCP_Opt_DONONE***_read_mode_mptcp** (*size, kind*)


Read Multipath TCP option.

Structure of MP-TCP [RFC 6824]:



(continues on next page)

(continued from previous page)


**Parameters**

- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)

Returns extracted Multipath TCP (MP-TCP) option**Return type** *DataType_TCP_Opt_MPTCP***`_read_mode_pocsp`** (*size, kind*)

Read Partial Order Connection Service Profile option.

Structure of TCP POC-SP Option [RFC 1693][RFC 6247]:


**Parameters**

- **size** (*int*) – length of option
- **kind** (*Literal[10]*) – option kind value (POC-Serv Profile)

Returns extracted Partial Order Connection Service Profile (POC-SP) option**Return type** *DataType_TCP_Opt_POCS***`_read_mode_qsopt`** (*size, kind*)

Read Quick-Start Response option.

Structure of TCP QSOpt [RFC 4782]:

**Parameters**


- **size** (*int*) – length of option
- **kind** (*Literal[27]*) – option kind value (Quick-Start Response)

Returns extracted Quick-Start Response (QS) option**Return type** *DataType_TCP_Opt_QSOPT*

`_read_mode_tcpao` (*size*, *kind*)

Read Authentication option.

Structure of TCP AOpt [RFC 5925]:



Parameters

- **size** (*int*) – length of option
- **kind** (*Literal[29]*) – option kind value (TCP Authentication Option)


Returns extracted Authentication (AO) option

Return type *DataType_TCP_Opt_TCPAO*

`_read_mode_tsopt` (*size*, *kind*)

Read Timestamps option.

Structure of TCP TSopt [RFC 7323]:



Parameters

- **size** (*int*) – length of option
- **kind** (*Literal[8]*) – option kind value (Timestamps)

Returns extracted Timestamps (TS) option

Return type *DataType_TCP_Opt_TS*

`_read_mode_unpack` (*size*, *kind*)

Read options request unpack process.

Parameters

- **size** (*int*) – length of option
- **kind** (*int*) – option kind value

Returns Extracted option which unpacked.

Return type *DataType_TCP_Opt_UNPACK*

`_read_mode_utopt` (*size*, *kind*)

Read User Timeout option.

Structure of TCP TIMEOUT [RFC 5482]:

0	1	2	3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1			
Kind = 28	Length = 4	U	User Timeout

Parameters

- **size** (*int*) – length of option
- **kind** (*Literal[28]*) – option kind value (User Timeout Option)

Returns extracted User Timeout (TIMEOUT) option

Return type *DataType_TCP_Opt_UTOPT*

_read_mptcp_add (*bits, size, kind*)

Read Add Address option.

Structure of ADD_ADDR [RFC 6824]:

1	2	3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1		
Kind	Length	Subtype IPVer Address ID
Address (IPv4 - 4 octets / IPv6 - 16 octets)		
Port (2 octets, optional)		

Parameters

- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)

Returns extracted Add Address (ADD_ADDR) option

Return type *DataType_TCP_Opt_ADD_ADDR*

Raises *ProtocolError* – If the option is malformed.

_read_mptcp_capable (*bits, size, kind*)

Read Multipath Capable option.

Structure of MP_CAPABLE [RFC 6824]:

1	2	3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1		
Kind	Length	Subtype Version A B C D E F G H
Option Sender's Key (64 bits)		
Option Receiver's Key (64 bits)		

(continues on next page)

(continued from previous page)

```

|                                     (if option Length == 20)                                     |
|                                                                                             |
+-----+


```

Parameters

- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)

Returns extracted Multipath Capable (MP_CAPABLE) option**Return type** *DataType_TCP_Opt_MP_CAPABLE***`_read_mptcp_dss`** (*bits, size, kind*)


Read Data Sequence Signal (Data ACK and Data Sequence Mapping) option.

Structure of DSS [**RFC 6824**]:**Parameters**


- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)

Returns extracted Data Sequence Signal (DSS) option**Return type** *DataType_TCP_Opt_DSS***`_read_mptcp_fail`** (*bits, size, kind*)

Read Fallback option.

Structure of MP_FAIL [**RFC 6824**]:

(continues on next page)



Parameters

- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal*[30]) – option kind value (Multipath TCP)


Returns extracted Fallback (MP_FAIL) option

Return type *DataType_TCP_Opt_MP_FAIL*

```
_read_mptcp_fastclose (bits, size, kind)
```

Read Fast Close option.

Structure of MP_FASTCLOSE [RFC 6824]:



Parameters

- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal*[30]) – option kind value (Multipath TCP)

Returns extracted Fast Close (MP_FASTCLOSE) option

Return type *DataType_TCP_Opt_MP_FAIL*

```
_read_mptcp_join (bits, size, kind)
```

Read Join Connection option.

Parameters


- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal*[30]) – option kind value (Multipath TCP)

Returns extracted Join Connection (MP_JOIN) option

Return type *DataType_TCP_Opt_MP_JOIN*

`_read_mptcp_prio` (*bits*, *size*, *kind*)
Read Change Subflow Priority option.

Structure of MP_PRIO [RFC 6824]:



Parameters


- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)

Returns extracted Change Subflow Priority (MP_PRIO) option

Return type *DataType_TCP_Opt_REMOVE_ADDR*

`_read_mptcp_remove` (*bits*, *size*, *kind*)
Read Remove Address option.

Structure of REMOVE_ADDR [RFC 6824]:



Parameters

- **bits** (*str*) – 4-bit data (after subtype)
- **size** (*int*) – length of option
- **kind** (*Literal[30]*) – option kind value (Multipath TCP)

Returns extracted Remove Address (REMOVE_ADDR) option

Return type *DataType_TCP_Opt_REMOVE_ADDR*

`_read_tcp_options` (*size*)
Read TCP option list.

Parameters **size** (*int*) – length of option list

Returns Tuple of TCP option list and extracted TCP options.

Return type Tuple[Tuple[*pcapkit.const.tcp.option.Option*], *DataType_TCP_Opt*]

`make` (***kwargs*)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.


Returns Constructed packet data.

Return type *bytes*

read (*length=None*, ***kwargs*)

Read Transmission Control Protocol (TCP).

Structure of TCP header [RFC 793]:



Parameters *length* (*Optional[int]*) – Length of packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_TCP*

property *dst*

Destination port.

Return type *int*

property *length*

Header length of current protocol.

Return type *int*

property *name*

Name of current protocol.

Return type *Literal[‘Transmission Control Protocol’]*

property *src*

Source port.

Return type *int*

pcapkit.protocols.transport.tcp.TCP_OPT: *DataType_TCP_OPT*

TCP option *dict* parsing mapping.

kind	length	type	process	comment	name
0					[RFC 793] End of Option List
1					[RFC 793] No-Operation
2	4	H	1		[RFC 793] Maximum Segment Size
3	3	B	1		[RFC 7323] Window Scale
4	2	?		True	[RFC 2018] SACK Permitted
5	?	P	0	2+8*N	[RFC 2018] SACK
6	6	P	0		[RFC 1072][RFC 6247] Echo
7	6	P	0		[RFC 1072][RFC 6247] Echo Reply
8	10	II	2		[RFC 7323] Timestamps
9	2	?		True	[RFC 1693][RFC 6247] POC Permitted
10	3	??P	3		[RFC 1693][RFC 6247] POC-Serv Profile
11	6	P	0		[RFC 1693][RFC 6247] Connection Count
12	6	P	0		[RFC 1693][RFC 6247] CC.NEW
13	6	P	0		[RFC 1693][RFC 6247] CC.ECHO
14	3	B	4		[RFC 1146][RFC 6247] Alt-Chksum Request
15	?	P	0		[RFC 1146][RFC 6247] Alt-Chksum Data
19	18	P	0		[RFC 2385] MD5 Signature Option
27	8	P	5		[RFC 4782] Quick-Start Response
28	4	P	6		[RFC 5482] User Timeout Option
29	?	P	7		[RFC 5925] TCP Authentication Option
30	?	P	8		[RFC 6824] Multipath TCP
34	?	P	0		[RFC 7413] Fast Open

See also:

`pcapkit.protocols.transport.tcp.DataType_TCP_OPT`

`pcapkit.protocols.transport.tcp.process_opt: Dict[int, Callable[[pcapkit.protocols.transp`
Process method for TCP options.

Code	Method	Description
0	<code>_read_mode_donone()</code>	do nothing
1	<code>_read_mode_unpack()</code>	unpack according to size
2	<code>_read_mode_tsopt()</code>	timestamps
3	<code>_read_mode_pocsp()</code>	POC service profile
4	<code>_read_mode_acopt()</code>	alternate checksum request
5	<code>_read_mode_qsopt()</code>	Quick-Start response
6	<code>_read_mode_utopt()</code>	user timeout option
7	<code>_read_mode_tcpao()</code>	TCP authentication option
8	<code>_read_mode_mptcp()</code>	multipath TCP

`pcapkit.protocols.transport.tcp.mptcp_opt: Dict[int, Callable[[pcapkit.protocols.transp`
Process method for multipath TCP options [RFC 6824].

Code	Method	Description
0	<code>_read_mptcp_capable()</code>	MP_CAPABLE
1	<code>_read_mptcp_join()</code>	MP_JOIN
2	<code>_read_mptcp_dss()</code>	DSS
3	<code>_read_mptcp_add()</code>	ADD_ADDR
4	<code>_read_mptcp_remove()</code>	REMOVE_ADDR
5	<code>_read_mptcp_prio()</code>	MP_PRIO
6	<code>_read_mptcp_fail()</code>	MP_FAIL
7	<code>_read_mptcp_fastclose()</code>	MP_FASTCLOSE

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the `pcapkit` module.

```
class pcapkit.protocols.transport.tcp.DataType_TCP
```

Bases TypedDict

Structure of TCP header [RFC 793].

srcport: `int`

Source port.

dstport: `int`

Description port.

seq: `int`

Sequence number.

ack: `int`

Acknowledgement number.

hdr_len: `int`

Data offset.

flags: `DataType_TCP_Flags`

Flags.

window_size: `int`

Size of receive window.

checksum: `bytes`

Checksum.

urgent_pointer: `int`

Urgent pointer.

opt: `Tuple[pcapkit.const.tcp.option.Option]`

Array of TCP options.

packet: `bytes`

Raw packet data.

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Flags
```

Bases TypedDict

Flags.

ns: `bool`
ECN concealment protection.

cwr: `bool`
Congestion window reduced.

ece: `bool`
ECN-Echo.

urg: `bool`
Urgent.

ack: `bool`
Acknowledgement.

psh: `bool`
Push function.

rst: `bool`
Reset connection.

syn: `bool`
Synchronize sequence numbers.

fin: `bool`
Last packet from sender.

class pcapkit.protocols.transport.tcp.DataType_TCP_Opt

Bases TypedDict

Structure of TCP options.

kind: `int`
Option kind value.

length: `int`
Length of option.

class pcapkit.protocols.transport.tcp.DataType_TCP_OPT

Bases TypedDict

TCP option `dict` parsing mapping.

flag: `bool`
If the length of option is **GREATER THAN** 1.

desc: `str`
Description string, also attribute name.

func: `Optional[Callable[[int], int]]`
Function, length of data bytes.

proc: `Optional[int]`
Process method that data bytes need (when *flag* is `True`).

See also:

pcapkit.protocols.transport.tcp.process_opt

TCP Miscellaneous Options

No Process Options

For TCP options require no process, its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.opt.kind	Kind
1	8	tcp.opt.length	Length
2	16	tcp.opt.data	Kind-specific Data

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DONONE
```

```
    Bases DataType_TCP_Opt
```

Structure of TCP options.

```
    data: bytes
```

Kind-specific data.

Unpack Process Options

For TCP options require unpack process, its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.opt.kind	Kind
1	8	tcp.opt.length	Length
2	16	tcp.opt.data	Kind-specific Data

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_UNPACK
```

```
    Bases DataType_TCP_Opt
```

Structure of TCP options.

```
    data: bytes
```

Kind-specific data.

Timestamps Option

For TCP Timestamps (TS) option as described in [RFC 7323](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.ts.kind	Kind (8)
1	8	tcp.ts.length	Length (10)
2	16	tcp.ts.val	Timestamp Value
6	48	tcp.ts.ecr	Timestamps Echo Reply

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_TS
```

```
    Bases DataType_TCP_Opt
```

Structure of TCP TSopt [[RFC 7323](#)].

```
val: int
    Timestamp value.

ecr: int
    Timestamps echo reply.
```

Partial Order Connection Service Profile Option

For TCP Partial Order Connection Service Profile (POC-SP) option as described in [RFC 1693](#) and [RFC 6247](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.pocsp.kind	Kind (10)
1	8	tcp.pocsp.length	Length (3)
2	16	tcp.pocsp.start	Start Flag
2	17	tcp.pocsp.end	End Flag
2	18	tcp.pocsp.filler	Filler

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_POCSPT
    Bases: DataType_TCP_Opt
    Structure of TCP POC-SP Option [RFC 1693][RFC 6247].

    start: bool
        Start flag.

    end: bool
        End flag.

    filler: bytes
        Filler.
```

Alternate Checksum Request Option

For TCP Alternate Checksum Request (CHKSUM-REQ) option as described in [RFC 1146](#) and [RFC 6247](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.chksumreq.kind	Kind (14)
1	8	tcp.chksumreq.length	Length (3)
2	16	tcp.chksumreq.ac	Checksum Algorithm

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ACOPT
    Bases: DataType_TCP_Opt
    Structure of TCP CHKSUM-REQ [RFC 1146][RFC 6247].

    ac: pcapkit.const.tcp.checksum.Checksum
        Checksum algorithm.
```

Quick-Start Response Option

For TCP Quick-Start Response (QS) option as described in [RFC 4782](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.qs.kind	Kind (27)
1	8	tcp.qs.length	Length (8)
2	16		Reserved (must be \x00)
2	20	tcp.qs.req_rate	Request Rate
3	24	tcp.qs.ttl_diff	TTL Difference
4	32	tcp.qs.nounce	QS Nounce
7	62		Reserved (must be \x00)

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_QSOPT
```

```
    Bases: DataType_TCP_Opt
```

```
    Structure of TCP QSOpt [RFC 4782].
```

```
    req_rate: int
```

```
        Request rate.
```

```
    ttl_diff: int
```

```
        TTL difference.
```

```
    nounce: int
```

```
        QS nounce.
```

User Timeout Option

For TCP User Timeout (TIMEOUT) option as described in [RFC 5482](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.timeout.kind	Kind (28)
1	8	tcp.timeout.length	Length (4)
2	16	tcp.timeout.granularity	Granularity
2	17	tcp.timeout.timeout	User Timeout

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_UTOPT
```

```
    Bases: DataType_TCP_Opt
```

```
    Structure of TCP TIMEOUT [RFC 5482].
```

```
    granularity: Literal['minutes', 'seconds']
```

```
        Granularity.
```

```
    timeout: datetime.timedelta
```

```
        User timeout.
```

Authentication Option

For Authentication (AO) option as described in [RFC 5925](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.ao.kind	Kind (29)
1	8	tcp.ao.length	Length
2	16	tcp.ao.key_id	KeyID
3	24	tcp.ao.r_next_key_id	RNextKeyID
4	32	tcp.ao.mac	Message Authentication Code

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_TCPAO
```

```
    Bases: DataType_TCP_Opt
```

```
    Structure of TCP AOpt [RFC 5925].
```

```
    key_id: int
            KeyID.
```

```
    r_next_key_id: int
                  RNextKeyID.
```

```
    mac: bytes
          Message authentication code.
```

Multipath TCP Options

For Multipath TCP (MP-TCP) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length
2	16	tcp.mp.subtype	Subtype
2	20	tcp.mp.data	Subtype-specific Data

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MPTCP
```

```
    Bases: DataType_TCP_Opt
```

```
    Structure of MP-TCP [RFC 6824].
```

```
    subtype: pcapkit.const.tcp.mp_tcp_option.MPTCPOption
             Subtype.
```

```
    data: Optional[bytes]
           Subtype-specific data.
```

Multipath Capable Option

For Multipath Capable (MP_CAPABLE) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length (12/20)
2	16	tcp.mp.subtype	Subtype (0)
2	20	tcp.mp.capable.version	Version
3	24	tcp.mp.capable.flags.req	Checksum Require Flag (A)
3	25	tcp.mp.capable.flags.ext	Extensibility Flag (B)
3	26	tcp.mp.capable.flags.res	Unassigned (C - G)
3	31	tcp.mp.capable.flags.hsa	HMAC-SHA1 Flag (H)
4	32	tcp.mp.capable.skey	Option Sender's Key
12	96	tcp.mp.capable.rkey	Option Receiver's Key (only if option length is 20)

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABLE
    Bases: DataType_TCP_Opt_MPTCP
    Structure of MP_CAPABLE [RFC 6824].
    capable: DataType_TCP_Opt_MP_CAPABLE_Data
        Subtype-specific data.

class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABLE_Data
    Bases: TypedDict
    Structure of MP_CAPABLE [RFC 6824].
    version: int
        Version.
    flags: DataType_TCP_Opt_MP_CAPABLE_Flags
        Flags.
    skey: int
        Option sender's key.
    rkey: Optional[int]
        Option receiver's key.

class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABLE_Flags
    Bases: TypedDict
    Flags.
    req: bool
        Checksum require flag.
    ext: bool
        Extensibility flag.
    res: Tuple[bool, bool, bool, bool, bool]
        Unassigned flags.
    hsa: bool
        HMAC-SHA1 flag.
```

Join Connection Option

For Join Connection (MP_JOIN) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length
2	16	tcp.mp.subtype	Subtype (1)
2	20	tcp.mp.data	Handshake-specific Data

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN
```

```
    Bases: DataType_TCP_Opt_MPTCP
```

```
    Structure of MP_JOIN [RFC 6824].
```

```
    connection: Optional[Literal['SYN/ACK', 'SYN', 'ACK']]
        Join connection type.
```

```
    join: DataType_TCP_Opt_MP_JOIN_Data
        Subtype-specific data.
```

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_Data
```

```
    Bases: TypedDict
```

```
    Structure of MP_JOIN [RFC 6824].
```

```
    data: Optional[bytes]
        Unknown type data.
```

MP_JOIN-SYN

For Join Connection (MP_JOIN-SYN) option for Initial SYN as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length (12)
2	16	tcp.mp.subtype	Subtype (1 SYN)
2	20		Reserved (must be \x00)
2	23	tcp.mp.join.syn.backup	Backup Path (B)
3	24	tcp.mp.join.syn.addr_id	Address ID
4	32	tcp.mp.join.syn.token	Receiver's Token
8	64	tcp.mp.join.syn.rand_num	Sender's Random Number

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYN
```

```
    Bases: DataType_TCP_Opt_MP_JOIN_Data
```

```
    Structure of MP_JOIN-SYN [RFC 6824].
```

```
    syn: DataType_TCP_Opt_MP_JOIN_SYN_Data
        Subtype-specific data.
```

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYN_Data
```

```
    Bases: TypedDict
```


Structure of MP_JOIN-SYN [RFC 6824].

```

backup:  bool
    Backup path.

addr_id:  int
    Address ID.

token:  int
    Receiver's token.

rand_num:  int
    Sender's random number.

```

MP_JOIN-SYN/ACK

For Join Connection (MP_JOIN-SYN/ACK) option for Responding SYN/ACK as described in RFC 6824, its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length (16)
2	16	tcp.mp.subtype	Subtype (1 SYN/ACK)
2	20		Reserved (must be \x00)
2	23	tcp.mp.join.synack.backup	Backup Path (B)
3	24	tcp.mp.join.synack.addr_id	Address ID
4	32	tcp.mp.join.synack.hmac	Sender's Truncated HMAC
12	96	tcp.mp.join.synack.rand_num	Sender's Random Number

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYNACK
```

```
    Bases: DataType_TCP_Opt_MP_JOIN_Data
```

Structure of MP_JOIN-SYN/ACK [RFC 6824].

```

syn:  DataType_TCP_Opt_MP_JOIN_SYNACK_Data
    Subtype-specific data.

```

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYNACK_Data
```

```
    Bases: TypedDict
```

Structure of MP_JOIN-SYN/ACK [RFC 6824].

```

backup:  bool
    Backup path.

addr_id:  int
    Address ID.

hmac:  bytes
    Sender's truncated HMAC.

rand_num:  int
    Sender's random number.

```

MP_JOIN-ACK

For Join Connection (MP_JOIN-ACK) option for Third ACK as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length (16)
2	16	tcp.mp.subtype	Subtype (1 ACK)
2	20		Reserved (must be \x00)
4	32	tcp.mp.join.ack.hmac	Sender's HMAC

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_ACK
```

```
    Bases: DataType_TCP_Opt_MP_JOIN_Data
```

```
    Structure of MP_JOIN-ACK [RFC 6824].
```

```
    syn:   DataType_TCP_Opt_MP_JOIN_ACK_Data
           Subtype-specific data.
```

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_ACK_Data
```

```
    Bases: TypedDict
```

```
    Structure of MP_JOIN-ACK [RFC 6824].
```

```
    hmac:  bytes
           Sender's HMAC.
```

Data Sequence Signal Option

For Data Sequence Signal (DSS) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length
2	16	tcp.mp.subtype	Subtype (2)
2	20		Reserved (must be \x00)
3	27	tcp.mp.dss.flags.fin	DATA_FIN (F)
3	28	tcp.mp.dss.flags.dsn_len	DSN Length (m)
3	29	tcp.mp.dss.flags. data_pre	DSN, SSN, Data-Level Length, CHKSUM Present (M)
3	30	tcp.mp.dss.flags.ack_len	ACK Length (a)
3	31	tcp.mp.dss.flags.ack_pre	Data ACK Present (A)
4	32	tcp.mp.dss.ack	Data ACK (4 / 8 octets)
8/12	64/96	tcp.mp.dss.dsn	DSN (4 / 8 octets)
12/20	48/160	tcp.mp.dss.ssn	Subflow Sequence Number
16/24	128/192	tcp.mp.dss.dl_len	Data-Level Length
18/26	144/208	tcp.mp.dss.checksum	Checksum

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS
```

```
    Bases: DataType_TCP_Opt_MPTCP
```

```
    Structure of DSS [RFC 6824].
```

dss: `DataType_TCP_Opt_DSS_Data`
Subtype-specific data.

class `pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Data`

Bases TypedDict

Structure of DSS [[RFC 6824](#)].

flags: `DataType_TCP_Opt_DSS_Flags`
Flags.

ack: `Optional[int]`
Data ACK.

dsn: `Optional[int]`
DSN.

ssn: `Optional[int]`
Subflow sequence number.

dl_len: `int`
Data-level length.

checksum: `bytes`
Checksum.

class `pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Flags`

Bases TypedDict

Flags.

fin: `bool`
DATA_FIN.

dsn_len: `int`
DSN length.

data_pre: `int`
DSN, SSN, data-level length, checksum present.

ack_len: `int`
ACK length.

ack_pre: `bool`
ACK present.

Add Address Option

For Add Address (ADD_ADDR) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>tcp.mp.kind</code>	Kind (30)
1	8	<code>tcp.mp.length</code>	Length
2	16	<code>tcp.mp.subtype</code>	Subtype (3)
2	20	<code>tcp.mp.add_addr.ip_ver</code>	IP Version
3	24	<code>tcp.mp.add_addr.addr_id</code>	Address ID
4	32	<code>tcp.mp.add_addr.addr</code>	IP Address (4 / 16)
8/20	64/160	<code>tcp.mp.add_addr.port</code>	Port (optional)

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ADD_ADDR
    Bases DataType_TCP_Opt_MPTCP
    Structure of ADD_ADDR [RFC 6824].
    add_addr: DataType_TCP_Opt_ADD_ADDR_Data
        Subtype-specific data.

class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ADD_ADDR_Data
    Bases TypedDict
    Structure of ADD_ADDR [RFC 6824].
    ip_ver: Literal[4, 6]
        IP version.
    addr_id: int
        Address ID.
    addr: Union[ipaddress.IPv4Address, ipaddress.IPv6Address]
        IP address.
    port: Optional[int]
        Port.
```

Remove Address Option

For Remove Address (REMOVE_ADDR) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length
2	16	tcp.mp.subtype	Subtype (4)
2	20		Reserved (must be \x00)
3	24	tcp.mp.remove_addr.addr_id	Address ID (optional list)

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_REMOVE_ADDR
    Bases DataType_TCP_Opt_MPTCP
    Structure of REMOVE_ADDR [RFC 6824].
    remove_addr: DataType_TCP_Opt_REMOVE_ADDR_Data
        Subtype-specific data.

class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_REMOVE_ADDR_Data
    Bases TypedDict
    Structure of REMOVE_ADDR [RFC 6824].
    addr_id: Tuple[int]
        Array of address IDs.
```

Change Subflow Priority Option

For Change Subflow Priority (MP_PRIO) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length
2	16	tcp.mp.subtype	Subtype (4)
2	23	tcp.mp.prio.backup	Backup Path (B)
3	24	tcp.mp.prio.addr_id	Address ID (optional)

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_PRIO
```

```
    Bases: DataType_TCP_Opt_MPTCP
```

```
    Structure of MP_PRIO [RFC 6824].
```

```
    prio:  DataType_TCP_Opt_MP_PRIO_Data
```

```
        Subtype-specific data.
```

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_PRIO_Data
```

```
    Bases: TypedDict
```

```
    Structure of MP_PRIO [RFC 6824].
```

```
    backup:  bool
```

```
        Backup path.
```

```
    addr_id:  Optional[int]
```

```
        Address ID.
```

Fallback Option

For Fallback (MP_FAIL) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length
2	16	tcp.mp.subtype	Subtype (4)
2	23		Reserved (must be \x00)
4	32	tcp.mp.fail.dsn	Data Sequence Number

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_FAIL
```

```
    Bases: DataType_TCP_Opt_MPTCP
```

```
    Structure of MP_FAIL [RFC 6824].
```

```
    fail:  DataType_TCP_Opt_MP_FAIL_Data
```

```
        Subtype-specific data.
```

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_FAIL_Data
```

```
    Bases: TypedDict
```

```
    Structure of MP_FAIL [RFC 6824].
```

dsn: `int`

Data sequence number.

Fast Close Option

For Fast Close (MP_FASTCLOSE) options as described in [RFC 6824](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	tcp.mp.kind	Kind (30)
1	8	tcp.mp.length	Length
2	16	tcp.mp.subtype	Subtype (4)
2	23		Reserved (must be \x00)
4	32	tcp.mp.fastclose.rkey	Option Receiver's Key

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_FASTCLOSE
```

Bases `DataType_TCP_Opt_MPTCP`

Structure of MP_FASTCLOSE [\[RFC 6824\]](#).

fastclose: `DataType_TCP_Opt_MP_FASTCLOSE_Data`

Subtype-specific data.

```
class pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_FASTCLOSE_Data
```

Bases `TypedDict`

Structure of MP_FASTCLOSE [\[RFC 6824\]](#).

rkey: `int`

Option receiver's key.

Base Protocol

`pcapkit.protocols.transport.transport` contains `Transport`, which is a base class for transport layer protocols, eg. TCP and UDP.

```
class pcapkit.protocols.transport.transport.Transport (file=None, length=None,
**kwargs)
```

Bases: `pcapkit.protocols.protocol.Protocol`

Abstract base class for transport layer protocol family.

__layer__ = `'Transport'`

Layer of protocol.

__import_next_layer (`proto`, `length=None`)

Import next layer extractor.

Parameters

- **proto** (`str`) – next layer protocol name
- **length** (`int`) – valid (*non-padding*) length

Returns instance of next layer

Return type `pcapkit.protocols.protocol.Protocol`

property layer

Protocol layer.

Return type Literal['Transport']

1.3.5 Application Layer Protocols

`pcapkit.protocols.application` is collection of all protocols in application layer, with detailed implementation and methods.

FTP - File Transfer Protocol

`pcapkit.protocols.application.ftp` contains *FTP* only, which implements extractor for File Transfer Protocol (FTP)⁰.

class `pcapkit.protocols.application.ftp.FTP` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.application.application.Application`

This class implements File Transfer Protocol.

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type `bytes`

read (*length=None, **kwargs*)

Read File Transfer Protocol (FTP).

Parameters *length* (*Optional[int]*) – Length of packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type Union[*DataType_FTP_Request*, *DataType_FTP_Response*]

Raises *ProtocolError* – If the packet is malformed.

property length

Header length of current protocol.

Raises *UnsupportedCall* – This protocol doesn't support *length*.

property name

Name of current protocol.

Return type Literal['File Transfer Protocol']

⁰ https://en.wikipedia.org/wiki/File_Transfer_Protocol

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

class pcapkit.protocols.application.ftp.DataType_FTP_Request

Bases TypedDict

Structure of FTP request packet [RFC 959].

type: Literal['request']

Packet type.

command: pcapkit.corekit.infoclass.Info

FTP command.

arg: Optional[str]

FTP command arguments.

raw: bytes

Raw packet data.

class pcapkit.protocols.application.ftp.DataType_FTP_Response

Bases TypedDict

Structure of FTP response packet [RFC 959].

type: Literal['response']

Packet type.

code: pcapkit.const.ftp.return_code.ReturnCode

FTP response code.

arg: Optional[str]

FTP response arguments (messages).

mf: bool

More fragmented messages flag.

raw: bytes

Raw packet data.

HTTP - Hypertext Transfer Protocol

pcapkit.protocols.application.http contains *HTTP* only, which is a base class for Hypertext Transfer Protocol (HTTP)⁰ family, eg. HTTP/1.* and HTTP/2.

class pcapkit.protocols.application.http.HTTP (*file=None, length=None, **kwargs*)

Bases: *pcapkit.protocols.application.application.Application*

This class implements all protocols in HTTP family.

- Hypertext Transfer Protocol (HTTP/1.1) [RFC 7230]
- Hypertext Transfer Protocol version 2 (HTTP/2) [RFC 7540]

classmethod id()

Index ID of the protocol.

⁰ https://en.wikipedia.org/wiki/Hypertext_Transfer_Protocol

Returns Index ID of the protocol.

Return type Tuple[Literal['HTTPv1'], Literal['HTTPv2']]

property length

Header length of current protocol.

Raises *UnsupportedCall* – This protocol doesn't support *length*.

property name

Name of current protocol.

Return type Literal['Hypertext Transfer Protocol']

HTTP/1.* - Hypertext Transfer Protocol

pcapkit.protocols.application.httpv1 contains *HTTPv1* only, which implements extractor for Hypertext Transfer Protocol (HTTP/1.*)⁰, whose structure is described as below:

```
METHOD URL HTTP/VERSION\r\n ::= REQUEST LINE
<key> : <value>\r\n          ::= REQUEST HEADER
..... (Ellipsis)           ::= REQUEST HEADER
\r\n                         ::= REQUEST SEPARATOR
<body>                       ::= REQUEST BODY (optional)

HTTP/VERSION CODE DESP \r\n ::= RESPONSE LINE
<key> : <value>\r\n          ::= RESPONSE HEADER
..... (Ellipsis)           ::= RESPONSE HEADER
\r\n                         ::= RESPONSE SEPARATOR
<body>                       ::= RESPONSE BODY (optional)
```

class *pcapkit.protocols.application.httpv1.HTTPv1* (*file=None*, *length=None*,
***kwargs*)

Bases: *pcapkit.protocols.application.http.HTTP*

This class implements Hypertext Transfer Protocol (HTTP/1.*).

__read_http_body (*body*)

Read HTTP/1.* body.

Parameters *body* (*bytes*) – HTTP body data.

Returns Raw HTTP body.

Return type *str*

__read_http_header (*header*)

Read HTTP/1.* header.

Structure of HTTP/1.* header [RFC 7230]:

```
start-line      ::= request-line / status-line
request-line    ::= method SP request-target SP HTTP-version CRLF
status-line     ::= HTTP-version SP status-code SP reason-phrase CRLF
header-field    ::= field-name ":" OWS field-value OWS
```

Parameters *header* (*bytes*) – HTTP header data.

Returns Parsed packet data.

⁰ https://en.wikipedia.org/wiki/Hypertext_Transfer_Protocol

Return type Union[*DataType_HTTP_Request_Header*, *DataType_HTTP_Response_Header*]

Raises *ProtocolError* – If the packet is malformed.

classmethod `id()`

Index ID of the protocol.

Returns Index ID of the protocol.

Return type Literal['HTTPv1']

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type bytes

read (*length=None*, ***kwargs*)

Read Hypertext Transfer Protocol (HTTP/1.*).

Structure of HTTP/1.* packet [RFC 7230]:

HTTP-message	::=	start-line
		*(header-field CRLF)
		CRLF
		[message-body]

Parameters `length` (*Optional[int]*) – Length of packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_HTTP*

Raises *ProtocolError* – If the packet is malformed.

_receipt = None

Type of HTTP receipt.

Type Literal['request', 'response']

property alias

Acronym of current protocol.

Return type Literal['HTTP/0.9', 'HTTP/1.0', 'HTTP/1.1']

```
pcapkit.protocols.application.httpv1.HTTP_METHODS = ['GET', 'HEAD', 'POST', 'PUT', 'DELETE', 'TRACE']
Supported HTTP method.
```

```
pcapkit.protocols.application.httpv1._RE_METHOD = re.compile(b'GET|HEAD|POST|PUT|DELETE|TRACE')
Regular expression to match HTTP methods.
```

```
pcapkit.protocols.application.httpv1._RE_STATUS = re.compile(b'\\d{3}')
Regular expression to match HTTP status code.
```

```
pcapkit.protocols.application.httpv1._RE_VERSION = re.compile(b'HTTP/(?P<version>\\d\\.\\d\\.\\d)')
Regular expression to match HTTP version string.
```

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

```
class pcapkit.protocols.application.httpv1.DataType_HTTP
    Bases TypedDict
    Structure of HTTP/1.* packet [RFC 7230].
    receipt: Literal['request', 'response']
        HTTP packet receipt.
    header: Union[DataType_HTTP_Request_Header, DataType_HTTP_Response_Header]
        Parsed HTTP header data.
    body: bytes
        HTTP body data.
    raw: DataType_HTTP_Raw
        Raw HTTP packet data.

class pcapkit.protocols.application.httpv1.DataType_HTTP_Raw
    Bases TypedDict
    Raw HTTP packet data.
    header: bytes
        Raw HTTP header data.
    body: bytes
        Raw HTTP body data.
    packet: bytes
        Raw HTTP packet data.

class pcapkit.protocols.application.httpv1.DataType_HTTP_Request_Header
    Bases TypedDict
    HTTP request header.
    request: DataType_HTTP_Request_Header_Meta
        Request metadata.

class pcapkit.protocols.application.httpv1.DataType_HTTP_Response_Header
    Bases TypedDict
    HTTP response header.
    response: DataType_HTTP_Response_Header_Meta
        Response metadata.

class pcapkit.protocols.application.httpv1.DataType_HTTP_Request_Header_Meta
    Bases TypedDict
    Request metadata.
    method: str
        HTTP request method.
```

target: `str`
HTTP request target URI.

version: `Literal['0.9', '1.0', '1.1']`
HTTP version string.

class `pcapkit.protocols.application.httpv1.DataType_HTTP_Response_Header_Meta`

Bases `TypedDict`

Response metadata.

version: `Literal['0.9', '1.0', '1.1']`
HTTP version string.

status: `int`
HTTP response status code.

phrase: `str`
HTTP response status reason.

HTTP/2 - Hypertext Transfer Protocol

`pcapkit.protocols.application.httpv2` contains `HTTPv2` only, which implements extractor for Hypertext Transfer Protocol (HTTP/2)⁰, whose structure is described as below:

Octets	Bits	Name	Description
0	0	<code>http.length</code>	Length
3	24	<code>http.type</code>	Type
4	32	<code>http.flags</code>	Flags
5	40		Reserved
5	41	<code>http.sid</code>	Stream Identifier
9	72	<code>http.payload</code>	Frame Payload

class `pcapkit.protocols.application.httpv2.HTTPv2` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.application.http.HTTP`


This class implements Hypertext Transfer Protocol (HTTP/2).

__length_hint__()
Total length of corresponding protocol.

Return type `Literal[9]`

_read_http_continuation (*size, kind, flag*)
Read HTTP/2 CONTINUATION frames.

Structure of HTTP/2 CONTINUATION frame [RFC 7540]:



(continues on next page)

⁰ <https://en.wikipedia.org/wiki/HTTP/2>

(continued from previous page)

	Header Block Fragment (*)	...
+	-----	+

Parameters

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.

Return type *DataType_HTTPv2_CONTINUATION*

Raises *ProtocolError* – If the packet is malformed.

_read_http_data (*size, kind, flag*)

Read HTTP/2 DATA frames.

Structure of HTTP/2 DATA frame [RFC 7540]:

+	-----	+
	Length (24)	
+	-----	+
	Type (8)	
+	-----	+
R	Stream Identifier (31)	
+	-----	+
	Pad Length? (8)	
+	-----	+
	Data (*)	...
+	-----	+
	Padding (*)	...
+	-----	+

Parameters

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.

Return type *DataType_HTTPv2_DATA*

Raises *ProtocolError* – If the packet is malformed.

_read_http_goaway (*size, kind, flag*)

Read HTTP/2 GOAWAY frames.

Structure of HTTP/2 GOAWAY frame [RFC 7540]:

+	-----	+
	Length (24)	
+	-----	+
	Type (8)	
+	-----	+
	Flags (8)	
+	-----	+

(continues on next page)

(continued from previous page)

R	Stream Identifier (31)	
+-----+-----+-----+		
R	Last-Stream-ID (31)	
+-----+-----+-----+		
	Error Code (32)	
+-----+-----+-----+		
	Additional Debug Data (*)	
+-----+-----+-----+		

Parameters

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.

Return type *DataType_HTTPv2_GOAWAY*

Raises *ProtocolError* – If the packet is malformed.

_read_http_headers (*size, kind, flag*)

Read HTTP/2 HEADERS frames.

Structure of HTTP/2 HEADERS frame [RFC 7540]:

```

+-----+
|                               |
|           Length (24)       |
+-----+-----+-----+
|  Type (8)  |  Flags (8)  |
+-----+-----+-----+
|R|           Stream Identifier (31)           |
+-----+-----+-----+
|Pad Length? (8)|
+-----+-----+-----+
|E|           Stream Dependency? (31)           |
+-----+-----+-----+
|  Weight? (8)  |
+-----+-----+-----+
|           Header Block Fragment (*)           ...
+-----+-----+-----+
|           Padding (*)           ...
+-----+-----+-----+

```

Parameters

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.

Return type *DataType_HTTPv2_HEADERS*

Raises *ProtocolError* – If the packet is malformed.

`_read_http_none` (*size, kind, flag*)

Read HTTP packet with unassigned type.

Parameters

- **`size`** (*int*) – length of packet data
- **`kind`** (*int*) – packet type
- **`flag`** (*str*) – packet flags (8 bits)

Returns Parsed packet data.


Return type *DataType_HTTPv2_Unassigned*

Raises *ProtocolError* – If the packet is malformed.

`_read_http_ping` (*size, kind, flag*)

Read HTTP/2 PING frames.

Structure of HTTP/2 PING frame [RFC 7540]:



Parameters

- **`size`** (*int*) – length of packet data
- **`kind`** (*int*) – packet type
- **`flag`** (*str*) – packet flags (8 bits)

Returns Parsed packet data.


Return type *DataType_HTTPv2_PING*

Raises *ProtocolError* – If the packet is malformed.

`_read_http_priority` (*size, kind, flag*)

Read HTTP/2 PRIORITY frames.

Structure of HTTP/2 PRIORITY frame [RFC 7540]:



(continues on next page)

(continued from previous page)

```

|   Weight (8)   |
+-+-----+

```


Parameters

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.**Return type** *DataType_HTTPv2_PRIORITY***Raises** *ProtocolError* – If the packet is malformed.**`_read_http_push_promise`** (*size, kind, flag*)

Read HTTP/2 PUSH_PROMISE frames.

Structure of HTTP/2 PUSH_PROMISE frame [RFC 7540]:


**Parameters**

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.**Return type** *DataType_HTTPv2_PUSH_PROMISE***Raises** *ProtocolError* – If the packet is malformed.**`_read_http_rst_stream`** (*size, kind, flag*)

Read HTTP/2 RST_STREAM frames.

Structure of HTTP/2 RST_STREAM frame [RFC 7540]:



(continues on next page)

(continued from previous page)

	Type (8)		Flags (8)	
+--+	-----+	+	-----+	+
R	Stream Identifier (31)			
+	-----+			+
	Error Code (32)			
+	-----+			+

Parameters

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.

Return type *DataType_HTTPv2_RST_STREAM*

Raises *ProtocolError* – If the packet is malformed.

_read_http_settings (*size, kind, flag*)

Read HTTP/2 SETTINGS frames.

Structure of HTTP/2 SETTINGS frame [RFC 7540]:

+	-----+	+
	Length (24)	
+	-----+	+
	Type (8)	
+	-----+	+
R	Stream Identifier (31)	
+	-----+	
	Identifier (16)	
+	-----+	+
	Value (32)	
+	-----+	+
	

Parameters

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.


Return type *DataType_HTTPv2_SETTINGS*

Raises *ProtocolError* – If the packet is malformed.

_read_http_window_update (*size, kind, flag*)

Read HTTP/2 WINDOW_UPDATE frames.

Structure of HTTP/2 WINDOW_UPDATE frame [RFC 7540]:

**Parameters**

- **size** (*int*) – length of packet data
- **kind** (*int*) – packet type
- **flag** (*str*) – packet flags (8 bits)

Returns Parsed packet data.

Return type *DataType_HTTPv2_WINDOW_UPDATE*

Raises *ProtocolError* – If the packet is malformed.

classmethod *id()*

Index ID of the protocol.

Returns Index ID of the protocol.

Return type Literal['HTTPv2']

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.


Returns Constructed packet data.

Return type *bytes*

read (*length=None, **kwargs*)

Read Hypertext Transfer Protocol (HTTP/2).

Structure of HTTP/2 packet [RFC 7540]:



Parameters *length* (*Optional[int]*) – Length of packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type *DataType_HTTPv2*

Raises *ProtocolError* – If the packet is malformed.

property alias

Acronym of current protocol.

Return type Literal['HTTP/2']

`pcapkit.protocols.application.httpv2._HTTP_FUNC: Dict[int, Callable[[pcapkit.protocols.app`
Process method for HTTP/2 packets.

Code	Method	Description
N/A	<code>_read_http_none()</code>	Unsigned
0x00	<code>_read_http_data()</code>	DATA
0x01	<code>_read_http_headers()</code>	HEADERS
0x02	<code>_read_http_priority()</code>	PRIORITY
0x03	<code>_read_http_rst_stream()</code>	RST_STREAM
0x04	<code>_read_http_settings()</code>	SETTINGS
0x05	<code>_read_http_push_promise()</code>	PUSH_PROMISE
0x06	<code>_read_http_ping()</code>	PING
0x07	<code>_read_http_goaway()</code>	GOAWAY
0x08	<code>_read_http_window_update()</code>	WINDOW_UPDATE
0x09	<code>_read_http_continuation()</code>	CONTINUATION

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

class `pcapkit.protocols.application.httpv2.DataType_HTTPv2`

Bases TypedDict

Structure of HTTP/2 packet [RFC 7540].

length: `int`

Length.

type: `pcapkit.const.http.frame.Frame`

Type.

sid: `int`

Stream identifier.

packet: `bytes`

Raw packet data.

class `pcapkit.protocols.application.httpv2.DataType_HTTPv2_Frame`

Bases TypedDict

HTTP/2 packet data.

HTTP/2 Unassigned Frame

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_Unassigned
    Bases: DataType_HTTPv2_Frame

    flags: Literal[None]
        HTTP/2 packet flags.

    payload: Optional[types]
        Raw packet payload.
```

HTTP/2 DATA Frame

For HTTP/2 DATA frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (0)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	72	http.pad_len	Pad Length (Optional)
10	80	http.data	Data
?	?		Padding (Optional)

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_DATA
    Bases: DataType_HTTPv2_Frame

    Structure of HTTP/2 DATA frame [RFC 7540].

    flags: DataType_HTTPv2_DATA_Flags
        HTTP/2 packet flags.

    data: bytes
        HTTP/2 transferred data.

class pcapkit.protocols.application.httpv2.DataType_HTTPv2_DATA_Flags
    Bases: TypedDict

    HTTP/2 DATA frame packet flags.

    END_STREAM: bool
        Bit 0

    PADDED: bool
        Bit 3
```

HTTP/2 HEADERS Frame

For HTTP/2 HEADERS frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (1)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	72	http.pad_len	Pad Length (Optional)
10	80	http.exclusive	Exclusive Flag
10	81	http.deps	Stream Dependency (Optional)
14	112	http.weight	Weight (Optional)
15	120	http.frag	Header Block Fragment
?	?		Padding (Optional)

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEADERS
```

```
    Bases: DataType_HTTPv2_Frame
```

```
    Structure of HTTP/2 HEADERS frame [RFC 7540].
```

```
    flags:   DataType_HTTPv2_HEADERS_Flags
```

```
            HTTP/2 packet flags.
```

```
    frag:   Optional[bytes]
```

```
            Header block fragment.
```

```
    pad_len: int
```

```
            Pad length.
```

```
    exclusive: bool
```

```
            Exclusive flag.
```

```
    deps:   int
```

```
            Stream dependency.
```

```
    weight: int
```

```
            Weight.
```

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEADERS_Flags
```

```
    Bases: TypedDict
```

```
    HTTP/2 HEADERS frame packet flags.
```

```
    END_STREAM: bool
```

```
            Bit 0
```

```
    END_HEADERS: bool
```

```
            Bit 2
```

```
    PADDED: bool
```

```
            Bit 3
```

```
    PRIORITY: bool
```

```
            Bit 5
```

HTTP/2 PRIORITY Frame

For HTTP/2 PRIORITY frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (2)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	72	http.exclusive	Exclusive Flag
9	73	http.deps	Stream Dependency
13	104	http.weight	Weight

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_PRIORITY
```

```
    Bases: DataType_HTTPv2_Frame
```

```
    Structure of HTTP/2 PRIORITY frame [RFC 7540].
```

```
    flags: Literal[None]
```

```
        HTTP/2 packet flags.
```

```
    exclusive: bool
```

```
        Exclusive flag.
```

```
    deps: int
```

```
        Stream dependency.
```

```
    weight: int
```

```
        Weight.
```

HTTP/2 RST_STREAM Frame

For HTTP/2 RST_STREAM frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (3)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	72	http.error	Error Code

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_RST_STREAM
```

```
    Bases: DataType_HTTPv2_Frame
```

```
    Structure of HTTP/2 PRIORITY frame [RFC 7540].
```

```
    flags: Literal[None]
```

```
        HTTP/2 packet flags.
```

```
    error: pcapkit.const.http.error\_code.ErrorCode
```

```
        Error code.
```

HTTP/2 SETTINGS Frame

For HTTP/2 SETTINGS frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (4)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	72	http.settings	Settings
9	72	http.settings.id	Identifier
10	80	http.settings.value	Value

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_SETTINGS
```

```
    Bases: DataType_HTTPv2_Frame
```

```
    Structure of HTTP/2 SETTINGS frame [RFC 7540].
```

```
    flags:   DataType_HTTPv2_SETTINGS_Flags
```

```
            HTTP/2 packet flags.
```

```
    settings: Tuple[pcapkit.const.http.setting.Setting]
```

```
            Array of HTTP/2 settings.
```

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_SETTINGS_Flags
```

```
    Bases: TypedDict
```

```
    HTTP/2 packet flags.
```

```
    ACK: bool
```

```
        Bit 0
```

HTTP/2 PUSH_PROMISE Frame

For HTTP/2 PUSH_PROMISE frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (5)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	72	http.pad_len	Pad Length (Optional)
10	80		Reserved
10	81	http.pid	Promised Stream ID
14	112	http.frag	Header Block Fragment
?	?		Padding (Optional)

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_PUSH_PROMISE
```

```
    Bases: DataType_HTTPv2_Frame
```

```
    Structure of HTTP/2 PUSH_PROMISE frame [RFC 7540].
```

flags: `DataType_HTTPv2_PUSH_PROMISE_Flags`
HTTP/2 packet flags.

pid: `int`
Promised stream ID.

frag: `Optional[bytes]`
Header block fragment.

pad_len: `int`
Pad length.

class `pcapkit.protocols.application.httpv2.DataType_HTTPv2_PUSH_PROMISE_Flags`

Bases `TypedDict`

HTTP/2 packet flags.

END_HEADERS: `bool`

Bit 2

PADDED: `bool`

Bit 3

HTTP/2 PING Frame

For HTTP/2 PING frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	<code>http.length</code>	Length
3	24	<code>http.type</code>	Type (6)
4	32	<code>http.flags</code>	Flags
5	40		Reserved
5	41	<code>http.sid</code>	Stream Identifier
9	72	<code>http.data</code>	Opaque Data

class `pcapkit.protocols.application.httpv2.DataType_HTTPv2_PING`

Bases `DataType_HTTPv2_Frame`

Structure of HTTP/2 PING frame [[RFC 7540](#)].

flags: `DataType_HTTPv2_PING_Flags`
HTTP/2 packet flags.

data: `bytes`
Opaque data.

class `pcapkit.protocols.application.httpv2.DataType_HTTPv2_PING_Flags`

Bases `TypedDict`

HTTP/2 packet flags.

ACK: `bool`

Bit 0

HTTP/2 GOAWAY Frame

For HTTP/2 GOAWAY frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (7)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	72		Reserved
9	73	http.last_sid	Last Stream ID
13	104	http.error	Error Code
17	136	http.data	Additional Debug Data (Optional)

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_GOAWAY
```

```
    Bases: DataType_HTTPv2_Frame
```

```
    Structure of HTTP/2 GOAWAY frame [RFC 7540].
```

```
    flags: Literal[None]
           HTTP/2 packet flags.
```

```
    last_sid: int
             Last stream ID.
```

```
    error: pcapkit.const.http.error_code.ErrorCode
           Error code.
```

```
    data: Optional[None]
          Additional debug data.
```

HTTP/2 WINDOW_UPDATE Frame

For HTTP/2 WINDOW_UPDATE frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (8)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	72		Reserved
9	73	http.window	Window Size Increment

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_WINDOW_UPDATE
```

```
    Bases: DataType_HTTPv2_Frame
```

```
    Structure of HTTP/2 WINDOW_UPDATE frame [RFC 7540].
```

```
    flags: Literal[None]
           HTTP/2 packet flags.
```

window: `int`
Window size increment.

HTTP/2 CONTINUATION Frame

For HTTP/2 CONTINUATION frame as described in [RFC 7540](#), its structure is described as below:

Octets	Bits	Name	Description
0	0	http.length	Length
3	24	http.type	Type (9)
4	32	http.flags	Flags
5	40		Reserved
5	41	http.sid	Stream Identifier
9	73	http.frag	Header Block Fragment

```
class pcapkit.protocols.application.httpv2.DataType_HTTPv2_CONTINUATION
    Bases: DataType_HTTPv2_Frame
    Structure of HTTP/2 CONTINUATION frame [RFC 7540].
    flags: DataType_HTTPv2_CONTINUATION_Flags
        HTTP/2 packet flags.
    frag: bytes
        Header block fragment.

class pcapkit.protocols.application.httpv2.DataType_HTTPv2_CONTINUATION_Flags
    Bases: TypedDict
    HTTP/2 packet flags.
    END_HEADERS: bool
    Bit 2
```

Base Protocol

`pcapkit.protocols.application.application` contains only `Application`, which is a base class for application layer protocols, eg. HTTP/1.*, HTTP/2 and etc.

```
class pcapkit.protocols.application.application.Application(file=None,
                                                            length=None,
                                                            **kwargs)
    Bases: pcapkit.protocols.protocol.Protocol
    Abstract base class for transport layer protocol family.
    __layer__ = 'Application'
        Layer of protocol.
    classmethod __index__()
        Numeral registry index of the protocol.
        Raises IntError – This protocol doesn't support __index__().
    __post_init__(file=None, length=None, **kwargs)
        Post initialisation hook.
```

Parameters

- **file** (*Optional*[*io.BytesIO*]) – Source packet stream.
- **length** (*Optional*[*int*]) – Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to `make()`.

`__decode_next_layer` (*dict*_, *proto=None*, *length=None*)

Decode next layer protocol.

Raises *UnsupportedCall* – This protocol doesn't support `__decode_next_layer()`.

`__import_next_layer` (*proto*, *length=None*)

Import next layer extractor.

Raises *UnsupportedCall* – This protocol doesn't support `__import_next_layer()`.

property layer

Protocol layer.

Return type `Literal['Application']`

1.3.6 Miscellaneous Protocols

Raw Packet Data

`pcapkit.protocols.raw` contains *Raw* only, which implements extractor for unknown protocol, and constructs a *Protocol* like object.

class `pcapkit.protocols.raw.Raw` (*file=None*, *length=None*, ****kwargs**)

Bases: `pcapkit.protocols.protocol.Protocol`

This class implements universal unknown protocol.

classmethod `__index__` ()

Numeral registry index of the protocol.

Raises *UnsupportedCall* – This protocol has no registry entry.

`__post_init__` (*file*, *length=None*, ***, *error=None*, ****kwargs**)

Post initialisation hook.

Parameters

- **file** (*io.BytesIO*) – Source packet stream.
- **length** (*Optional*[*int*]) – Length of packet data.

Keyword Arguments

- **error** (*Optional*[*str*]) – Parsing errors if any (for parsing).
- ****kwargs** – Arbitrary keyword arguments.

Would `pcapkit` encounter malformed packets, the original parsing error message will be provided as in `error`.

See also:

For construction argument, please refer to `make()`.

make (***kwargs*)

Make raw packet data.

Keyword Arguments

- **packet** (*bytes*) – Raw packet data.
- ****kwargs** – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type *bytes*

read (*length=None, *, error=None, **kwargs*)

Read raw packet data.

Parameters **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments

- **error** (*Optional[str]*) – Parsing errors if any.
- ****kwargs** – Arbitrary keyword arguments.

Returns The parsed packet data.

Return type *DataType_Raw*

property length

Header length of current protocol.

Raises *UnsupportedCall* – This protocol doesn't support *length*.

property name

Name of current protocol.

Return type *Literal['Unknown']*

property protocol

Name of next layer protocol.

Raises *UnsupportedCall* – This protocol doesn't support *protocol*.

Data Structure

Important: Following classes are only for *documentation* purpose. They do **NOT** exist in the *pcapkit* module.

class pcapkit.protocols.raw.**DataType_Raw**

Bases TypedDict

Raw packet data.

packet: *bytes*

raw packet data

error: *Optional[str]*

optional error message

No-Payload Packet

`pcapkit.protocols.null` contains `NoPayload` only, which implements a `Protocol` like object whose payload is recursively `NoPayload` itself.

class `pcapkit.protocols.null.NoPayload` (*file=None, length=None, **kwargs*)

Bases: `pcapkit.protocols.protocol.Protocol`

This class implements no-payload protocol.

classmethod `__index__` ()

Numeral registry index of the protocol.

Raises `UnsupportedCall` – This protocol has no registry entry.

`__post_init__` (*file=None, length=None, **kwargs*)

Post initialisation hook.

Parameters

- **file** (*Optional[io.BytesIO]*) – Source packet stream.
- **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

`__decode_next_layer` (**args, **kwargs*)

Decode next layer protocol.

Parameters ***args** – arbitrary positional arguments

Keyword Arguments ****kwargs** – arbitrary keyword arguments

Raises `UnsupportedCall` – This protocol doesn't support `__decode_next_layer()`.

`__import_next_layer` (**args, **kwargs*)

Import next layer extractor.

Parameters ***args** – arbitrary positional arguments

Keyword Arguments ****kwargs** – arbitrary keyword arguments

Raises `UnsupportedCall` – This protocol doesn't support `__import_next_layer()`.

make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type `bytes`

read (*length=None, **kwargs*)

Read (parse) packet data.

Parameters **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type `dict`

property `length`

Header length of current protocol.

Raises `UnsupportedCall` – This protocol doesn't support `length`.

property name

Name of current protocol.

Return type `Literal['Null']`

property protocol

Name of next layer protocol.

Raises `UnsupportedCall` – This protocol doesn't support `protocol`.

1.3.7 Base Protocol

class `pcapkit.protocols.protocol.Protocol` (*file=None, length=None, **kwargs*)

Bases: `object`

Abstract base class for all protocol family.

__layer__ = `None`

Layer of protocol. Can be one of Link, Internet, Transport and Application.

Type `Literal['Link', 'Internet', 'Transport', 'Application']`

__proto__ = `{}`

Protocol index mapping for decoding next layer, c.f. `self.__decode_next_layer` & `self.__import_next_layer`. The values should be a tuple representing the module name and class name.

Type `DefaultDict[int, Tuple[str, str]]`

__bytes__ ()

Returns source data stream in `bytes`.

__contains__ (*name*)

Returns if *name* is in `self._info`.

Parameters *name* (*Any*) – name to search

Returns if name exists

Return type `bool`

classmethod **__eq__** (*other*)

Returns if *other* is of the same protocol as the current object.

Parameters *other* (`Union[Protocol, Type[Protocol]]`) – Comparison against the object.

Returns If *other* is of the same protocol as the current object.

Return type `bool`

__getitem__ (*key*)

Subscription (`getitem`) support.

- If *key* is a `:obj`slice`` object, `ProtocolUnbound` will be raised.
- If *key* is a `Protocol` object, the method will fetch its indexes (`id()`).
- Later, search the packet's chain of protocols with the calculated *key*.
- If no matches, then raises `ProtocolNotFound`.

Parameters *key* (`Union[str, Protocol, Type[Protocol]]`) – Indexing key.

Returns The sub-packet from the current packet of indexed protocol.

Return type *pcapkit.protocols.protocol.Protocol*

Raises

- **ProtocolUnbound** – If key is a *slice* object.
- **ProtocolNotFound** – If key is not in the current packet.

__hash__()

Return the hash value for *self._data*.

abstract classmethod __index__()

Numeral registry index of the protocol.

Returns Numeral registry index of the protocol.

Return type *enum.IntEnum*

__init__(*file=None, length=None, **kwargs*)

Initialisation.

Parameters

- **file** (*Optional[io.BytesIO]*) – Source packet stream.
- **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments

- **_error** (*bool*) – If the object is initiated after parsing errors (*self._onerror*).
- **_layer** (*str*) – Parse packet until *_layer* (*self._onerror*).
- **_protocol** (*str*) – Parse packet until *_protocol* (*self._onerror*).
- ****kwargs** – Arbitrary keyword arguments.

__iter__()

Iterate through *self._data*.

__length_hint__()

Return an estimated length for the object.

__post_init__(*file=None, length=None, **kwargs*)

Post initialisation hook.

Parameters

- **file** (*Optional[io.BytesIO]*) – Source packet stream.
- **length** (*Optional[int]*) – Length of packet data.

Keyword Arguments ****kwargs** – Arbitrary keyword arguments.

See also:

For construction argument, please refer to *make()*.

__repr__()

Returns representation of parsed protocol data.

Example

```
>>> protocol
<Frame Info(..., ethernet=Info(...), protocols='Ethernet:IPv6:Raw')>
```

`_check_term_threshold()`

Check if reached termination threshold.

Returns if reached termination threshold

Return type `bool`

`_decode_next_layer(dict_, proto=None, length=None)`

Decode next layer protocol.

Parameters

- **`dict`** (*dict*) – info buffer
- **`proto`** (*int*) – next layer protocol index
- **`length`** (*int*) – valid (*non-padding*) length

Returns current protocol with next layer extracted

Return type `dict`

`_import_next_layer(proto, length=None)`

Import next layer extractor.

Parameters

- **`proto`** (*int*) – next layer protocol index
- **`length`** (*int*) – valid (*non-padding*) length

Returns instance of next layer

Return type `pcapkit.protocols.protocol.Protocol`

`classmethod _make_index(name, default=None, *, namespace=None, reversed=False, pack=False, size=4, signed=False, lilendian=False)`

Return first index of name from a `dict` or enumeration.

Parameters

- **`name`** (`Union[str, int, enum.IntEnum]`) – item to be indexed
- **`default`** (*int*) – default value

Keyword Arguments

- **`namespace`** (`Union[dict, enum.EnumMeta]`) – namespace for item
- **`reversed`** (*bool*) – if namespace is `str -> int` pairs
- **`pack`** (*bool*) – if need `struct.pack()` to pack the result
- **`size`** (*int*) – buffer size
- **`signed`** (*bool*) – signed flag
- **`lilendian`** (*bool*) – little-endian flag

Returns Index of name from a dict or enumeration. If `packet` is `True`, returns `bytes`; otherwise, returns `int`.

Return type `Union[int, bytes]`

Raises `ProtocolNotImplemented` – If name is **NOT** in namespace and default is `None`.

`classmethod _make_pack(integer, *, size=1, signed=False, lilendian=False)`

Pack integers to bytes.

Parameters `integer` (*int*) –

Keyword Arguments

- **size** (*int*) – buffer size
- **signed** (*bool*) – signed flag
- **lilendian** (*bool*) – little-endian flag

Returns Packed data upon success.

Return type `bytes`

Raises `StructError` – If failed to pack the integer.

`_read_binary` (*size=1*)

Read bytes and convert into binaries.

Parameters **size** (*int*) – buffer size

Returns binary bits (0/1)

Return type `str`

`_read_fileng` (**args, **kwargs*)

Read file buffer (`self._file`).

This method wraps the `file.read()` call.

Parameters ***args** – arbitrary positional arguments

Keyword Arguments ****kwargs** – arbitrary keyword arguments

Returns Data read from file buffer.

Return type `bytes`

`_read_packet` (**args, **kw*)

Read raw packet data.

Parameters **length** (*int*) – length of the packet

Keyword Arguments

- **header** (*Optional[int]*) – length of the packet header
- **payload** (*Optional[int]*) – length of the packet payload
- **discard** (*bool*) – flag if discard header data

Returns

- If header omits, returns the whole packet data in `bytes`.
- If discard is set as True, returns the packet body (in `bytes`) only.
- Otherwise, returns the header and payload data as a `dict`:

```
class Packet (TypedDict):
    """Header and payload data."""

    #: packet header
    header: bytes
    #: packet payload
    payload: bytes
```

`_read_protos` (*size*)

Read next layer protocol type.

Parameters **size** (*int*) – buffer size

Returns

- If *succeed*, returns the name of next layer protocol (*str*).
- If *fail*, returns `None`.

`_read_unpack` (*size=1*, *, *signed=False*, *lilendian=False*, *quiet=False*)

Read bytes and unpack for integers.

Parameters **size** (*int*) – buffer size

Keyword Arguments

- **signed** (*bool*) – signed flag
- **lilendian** (*bool*) – little-endian flag
- **quiet** (*bool*) – quiet (no exception) flag

Returns unpacked data upon success

Return type `Optional[int]`

Raises `StructError` – If `unpack(struct.pack())` failed, and `struct.error` raised.

`static decode` (*byte*, *, *encoding=None*, *errors='strict'*)

Decode *bytes* into *str*.

Should decoding failed using *encoding*, the method will try again decoding the *bytes* as `'unicode_escape'`.

Parameters **byte** (*bytes*) – Source bytestring.

Keyword Arguments

- **encoding** (`Optional[str]`) – The encoding with which to decode the *bytes*. If not provided, *pcapkit* will first try detecting its encoding using *chardet*. The fallback encoding would is **UTF-8**.
- **errors** (*str*) – The error handling scheme to use for the handling of decoding errors. The default is `'strict'` meaning that decoding errors raise a `UnicodeDecodeError`. Other possible values are `'ignore'` and `'replace'` as well as any other name registered with `codecs.register_error()` that can handle `UnicodeDecodeError`.

Returns Decoede string.

Return type *str*

See also:

`bytes.decode()`

`classmethod id` ()

Index ID of the protocol.

By default, it returns the name of the protocol.

Returns Index ID of the protocol.

Return type `Union[str, Tuple[str]]`

See also:

`pcapkit.protocols.protocol.Protocol.__getitem__()`

abstract make (***kwargs*)

Make (construct) packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Constructed packet data.

Return type `bytes`

abstract read (*length=None, **kwargs*)

Read (parse) packet data.

Parameters *length* (*Optional[int]*) – Length of packet data.

Keyword Arguments ***kwargs* – Arbitrary keyword arguments.

Returns Parsed packet data.

Return type `dict`

static unquote (*url, *, encoding='utf-8', errors='replace'*)

Unquote URLs into readable format.

Should decoding failed, the method will try again replacing '%' with '\x' then decoding the url as 'unicode_escape'.

Parameters *url* (*str*) – URL string.

Keyword Arguments

- **encoding** (*str*) – The encoding with which to decode the `bytes`.
- **errors** (*str*) – The error handling scheme to use for the handling of decoding errors. The default is 'strict' meaning that decoding errors raise a `UnicodeDecodeError`. Other possible values are 'ignore' and 'replace' as well as any other name registered with `codecs.register_error()` that can handle `UnicodeDecodeError`.

Returns Unquoted string.

Return type `str`

See also:

`urllib.parse.unquote()`

_exlayer

Parse packet until such layer.

Type `str`

_exproto

Parse packet until such protocol.

Type `str`

_onerror

If the object is initiated after parsing errors.

Type `bool`

_seekset

Initial offset of `self._file`

Type `int`

`_sigterm`

If terminate parsing next layer of protocol.

Type `bool`

`property alias`

Acronym of current protocol.

Return type `str`

`property data`

Binary packet data of current instance.

Return type `bytes`

`property info`

Info dict of current instance.

Return type `pcapkit.corekit.infoclass.Info`

`abstract property length`

Header length of current protocol.

Return type `int`

`abstract property name`

Name of current protocol.

Return type `str`

`property payload`

Payload of current instance.

Return type `pcapkit.protocols.protocol.Protocol`

`property protochain`

Protocol chain of current instance.

Return type `pcapkit.corekit.protochain.ProtoChain`

`property protocol`

Name of next layer protocol (if any).

Return type `Optional[str]`

1.4 Reassembly Packets & Datagrams

`pcapkit.reassembly` bases on algorithms described in [RFC 815](#), implements datagram reassembly of IP and TCP packets.

1.4.1 Fragmented Packets Reassembly

`pcapkit.reassembly.reassembly` contains class:~`pcapkit.reassembly.reassembly.Reassembly` only, which is an abstract base class for all reassembly classes, bases on algorithms described in [RFC 815](#), implements datagram reassembly of IP and TCP packets.

class `pcapkit.reassembly.reassembly.Reassembly` (*, *strict=True*)

Bases: `object`

Base class for reassembly procedure.

__call__ (*packet*)

Call packet reassembly.

Parameters *packet* (*dict*) – packet dict to be reassembled (detailed format described in corresponding protocol)

__init__ (*, *strict=True*)

Initialise packet reassembly.

Keyword Arguments *strict* (*bool*) – if return all datagrams (including those not implemented) when submit

fetch ()

Fetch datagram.

Returns Tuple of reassembled datagrams.

Return type Tuple[dict]

Fetch reassembled datagrams from `__dtgram` and returns a *tuple* of such datagrams.

If `__newflg` set as `True`, the method will call `submit()` to (*force*) obtain newly reassembled payload. Otherwise, the already calculated `__dtgram` will be returned.

index (*pkt_num*)

Return datagram index.

Parameters *pkt_num* (*int*) – index of packet

Returns reassembled datagram index which was from No. *pkt_num* packet; if not found, returns `None`

Return type Optional[int]

abstract reassembly (*info*)

Reassembly procedure.

Parameters *info* (`pcapkit.corekit.infoclass.Info`) – info dict of packets to be reassembled

run (*packets*)

Run automatically.

Parameters *packets* (*List[dict]*) – list of packet dicts to be reassembled

abstract submit (*buf*, ***kwargs*)

Submit reassembled payload.

Parameters *buf* (*dict*) – buffer dict of reassembled packets

__buffer

dict buffer field

_dtgram
list reassembled datagram

_newflg
if new packets reassembled flag
Type `bool`

_strflg
strict mode flag
Type `bool`

property count
Total number of reassembled packets.
Return type `int`

property datagram
Reassembled datagram.
Return type `tuple`

abstract property name
Protocol of current packet.
Return type `str`

abstract property protocol
Protocol of current reassembly object.
Return type `str`

1.4.2 IP Datagram Reassembly

`pcapkit.reassembly.ip` contains `IP_Reassembly` only, which reconstructs fragmented IP packets back to origin. The following algorithm implement is based on IP reassembly procedure introduced in [RFC 791](#), using RCVBT (fragment receivedbit table). Though another algorithm is explained in [RFC 815](#), replacing RCVBT, however, this implement still used the elder one.

Notation

FO	Fragment Offset
IHL	Internet Header Length
MF	More Fragments Flag
TTL	Time To Live
NFB	Number of Fragment Blocks
TL	Total Length
TDL	Total Data Length
BUFID	Buffer Identifier
RCVBT	Fragment Received Bit Table
TLB	Timer Lower Bound

Algorithm

```

DO {
  BUFID <- source|destination|protocol|identification;

  IF (FO = 0 AND MF = 0) {
    IF (buffer with BUFID is allocated) {
      flush all reassembly for this BUFID;
      Submit datagram to next step;
      DONE.
    }
  }

  IF (no buffer with BUFID is allocated) {
    allocate reassembly resources with BUFID;
    TIMER <- TLB;
    TDL <- 0;
    put data from fragment into data buffer with BUFID
      [from octet FO*8 to octet (TL-(IHL*4))+FO*8];
    set RCVBT bits [from FO to FO+((TL-(IHL*4)+7)/8)];
  }

  IF (MF = 0) {
    TDL <- TL-(IHL*4)+(FO*8)
  }

  IF (FO = 0) {
    put header in header buffer
  }

  IF (TDL # 0 AND all RCVBT bits [from 0 to (TDL+7)/8] are set) {
    TL <- TDL+(IHL*4)
    Submit datagram to next step;
    free all reassembly resources for this BUFID;
    DONE.
  }

  TIMER <- MAX(TIMER,TTL);
} give up until (next fragment or timer expires);

timer expires: {
  flush all reassembly with this BUFID;
  DONE.
}

```

Implementation

class pcapkit.reassembly.ip.**IP_Reassembly**(*,strict=True)

Bases: `pcapkit.reassembly.reassembly.Reassembly`

Reassembly for IP payload.

reassembly(info)

Reassembly procedure.

Parameters info (`pcapkit.corekit.infoclass.Info`) – info dict of packets to be reassembled

submit (*buf*, *, *checked=False*)
Submit reassembled payload.

Parameters **buf** (*dict*) – buffer dict of reassembled packets

Keyword Arguments **bufid** (*tuple*) – buffer identifier

Returns reassembled packets

Return type *list*

1.4.3 IPv4 Datagram Reassembly

`pcapkit.reassembly.ipv4` contains `IPv4_Reassembly` only, which reconstructs fragmented IPv4 packets back to origin. Please refer to *IP Datagram Reassembly* for more information.

Data Structure

ipv4.packet Data structure for **IPv4 datagram reassembly** (`reassembly()`) is as following:

ipv4.datagram Data structure for **reassembled IPv4 datagram** (element from `datagram tuple`) is as following:

ipv4.buffer Data structure for internal buffering when performing reassembly algorithms (`_buffer`) is as following:

```
(dict) buffer --> memory buffer for reassembly
|--> (tuple) BUFID : (dict)
|   |--> ipv4.src      |
|   |--> ipc6.dst      |
|   |--> ipv4.label    |
|   |--> ipv4_frag.next|
|
|   |--> 'TDL' : (int) total data length
|   |--> RCVBT : (bytearray) fragment received bit table
|               |--> (bytes) b'\x00' -> not received
|               |--> (bytes) b'\x01' -> received
|               |--> (bytes) ...
|   |--> 'index' : (list) list of reassembled packets
|                   |--> (int) packet range number
|   |--> 'header' : (bytearray) header buffer
|   |--> 'datagram' : (bytearray) data buffer, holes set_
->to b'\x00'
|--> (tuple) BUFID ...
```

Implementation

class `pcapkit.reassembly.ipv4.IPv4_Reassembly` (*, *strict=True*)
Bases: `pcapkit.reassembly.ip.IP_Reassembly`

Reassembly for IPv4 payload.

Example

```
>>> from pcapkit.reassembly import IPv4_Reassembly
# Initialise instance:
>>> ipv4_reassembly = IPv4_Reassembly()
# Call reassembly:
>>> ipv4_reassembly(packet_dict)
```

(continues on next page)

(continued from previous page)

```
# Fetch result:
>>> result = ipv4_reassembly.datagram
```

property name

Protocol of current packet.

Return type Literal['Internet Protocol version 4']**property protocol**

Protocol of current reassembly object.

Return type Literal['IPv4']

1.4.4 IPv6 Datagram Reassembly

`pcapkit.reassembly.ipv6` contains *IPv6_Reassembly* only, which reconstructs fragmented IPv6 packets back to origin. Please refer to *IP Datagram Reassembly* for more information.

Data Structure

ipv6.packet Data structure for IPv6 datagram reassembly (*reassembly()*) is as following:

```
packet_dict = dict(
    bufid = tuple(
        ipv6.src,          # source IP address
        ipv6.dst,          # destination IP address
        ipv6.label,        # label
        ipv6_frag.next,    # next header field in IPv6 Fragment Header
    ),
    num = frame.number,    # original packet range number
    fo = ipv6_frag.offset, # fragment offset
    ihl = ipv6.hdr_len,    # header length, only headers before IPv6-Frag
    mf = ipv6_frag.mf,     # more fragment flag
    tl = ipv6.len,         # total length, header includes
    header = ipv6.header,  # raw bytearray type header before IPv6-Frag
    payload = ipv6.payload, # raw bytearray type payload after IPv6-Frag
)
```

ipv6.datagram Data structure for reassembled IPv6 datagram (element from *datagram tuple*) is as following:

```
(tuple) datagram
|--> (dict) data
|   |--> 'NotImplemented' : (bool) True --> implemented
|   |--> 'index' : (tuple) packet numbers
|       |--> (int) original packet range number
|   |--> 'packet' : (Optional[bytes]) reassembled IPv6 packet
|--> (dict) data
|   |--> 'NotImplemented' : (bool) False --> not implemented
|   |--> 'index' : (tuple) packet numbers
|       |--> (int) original packet range number
|   |--> 'header' : (Optional[bytes]) IPv6 header
|   |--> 'payload' : (Optional[tuple]) partially reassembled IPv6 payload
|       |--> (Optional[bytes]) IPv4 payload fragment
|--> (dict) data ...
```

ipv6.buffer Data structure for internal buffering when performing reassembly algorithms (*_buffer*) is as following:

```
(dict) buffer --> memory buffer for reassembly
|--> (tuple) BUFID : (dict)
|
|   |--> ipv6.src      |
|   |--> ipv6.dst      |
|   |--> ipv6.label    |
|   |--> ipv6_frag.next |
|
|                               |--> 'TDL' : (int) total data length
|                               |--> RCVBT : (bytearray) fragment received bit table
|                               |
|                               |   |--> (bytes) b'\x00' -> not received
|                               |   |--> (bytes) b'\x01' -> received
|                               |   |--> (bytes) ...
|
|                               |--> 'index' : (list) list of reassembled packets
|                               |
|                               |   |--> (int) packet range number
|
|                               |--> 'header' : (bytearray) header buffer
|
|                               |--> 'datagram' : (bytearray) data buffer, holes set_
|
|   ↳to b'\x00'
|   |--> (tuple) BUFID ...
```

Implementation

class pcapkit.reassembly.ipv6.IPv6_Reassembly(*, strict=True)

Bases: *pcapkit.reassembly.ip.IP_Reassembly*

Reassembly for IPv6 payload.

Example

```
>>> from pcapkit.reassembly import IPv6_Reassembly
# Initialise instance:
>>> ipv6_reassembly = IPv6_Reassembly()
# Call reassembly:
>>> ipv6_reassembly(packet_dict)
# Fetch result:
>>> result = ipv6_reassembly.datagram
```

property name

Protocol of current packet.

Return type Literal['Internet Protocol version 6']

property protocol

Protocol of current reassembly object.

Return type Literal['IPv6']

1.4.5 TCP Datagram Reassembly

`pcapkit.reassembly.tcp` contains `TCP_Reassembly` only, which reconstructs fragmented TCP packets back to origin. The algorithm for TCP reassembly is described as below.

Notation

DSN	Data Sequence Number
ACK	TCP Acknowledgement
SYN	TCP Synchronisation Flag
FIN	TCP Finish Flag
RST	TCP Reset Connection Flag
BUFID	Buffer Identifier
HDL	Hole Descriptor List
ISN	Initial Sequence Number
src	source IP
dst	destination IP
srcport	source TCP port
dstport	destination TCP port

Algorithm

```

DO {
  BUFID <- src|dst|srcport|dstport|ACK;
  IF (SYN is true) {
    IF (buffer with BUFID is allocated) {
      flush all reassembly for this BUFID;
      submit datagram to next step;
    }
  }

  IF (no buffer with BUFID is allocated) {
    allocate reassembly resources with BUFID;
    ISN <- DSN;
    put data from fragment into data buffer with BUFID
      [from octet fragment.first to octet fragment.last];
    update HDL;
  }

  IF (FIN is true or RST is true) {
    submit datagram to next step;
    free all reassembly resources for this BUFID;
    BREAK.
  }
} give up until (next fragment);

update HDL: {
  DO {
    select the next hole descriptor from HDL;

    IF (fragment.first >= hole.first) CONTINUE.
    IF (fragment.last <= hole.first) CONTINUE.
  }
}

```

(continues on next page)

(continued from previous page)

```

delete the current entry from HDL;

IF (fragment.first >= hole.first) {
    create new entry "new_hole" in HDL;
    new_hole.first <- hole.first;
    new_hole.last <- fragment.first - 1;
    BREAK.
}

IF (fragment.last <= hole.last) {
    create new entry "new_hole" in HDL;
    new_hole.first <- fragment.last + 1;
    new_hole.last <- hole.last;
    BREAK.
}
} give up until (no entry from HDL)
}

```

The following algorithm implement is based on **IP Datagram Reassembly Algorithm** introduced in **RFC 815**. It described an algorithm dealing with RCVBT (fragment received bit table) appeared in **RFC 791**. And here is the process:

1. Select the next hole descriptor from the hole descriptor list. If there are no more entries, go to step eight.
2. If `fragment.first` is greater than `hole.last`, go to step one.
3. If `fragment.last` is less than `hole.first`, go to step one.
4. Delete the current entry from the hole descriptor list.
5. If `fragment.first` is greater than `hole.first`, then create a new hole descriptor `new_hole` with `new_hole.first` equal to `hole.first`, and `new_hole.last` equal to `fragment.first` minus one (-1).
6. If `fragment.last` is less than `hole.last` and `fragment.more_fragments` is true, then create a new hole descriptor `new_hole`, with `new_hole.first` equal to `fragment.last` plus one (+1) and `new_hole.last` equal to `hole.last`.
7. Go to step one.
8. If the hole descriptor list is now empty, the datagram is now complete. Pass it on to the higher level protocol processor for further handling. Otherwise, return.

Data Structure

tcp.packet Data structure for **TCP datagram reassembly** (`reassembly()`) is as following:

```

packet_dict = Info(
    bufid = tuple(
        ip.src,           # source IP address
        ip.dst,           # destination IP address
        tcp.srcport,      # source port
        tcp.dstport,      # destination port
    ),
    num = frame.number,   # original packet range number
    syn = tcp.flags.syn,  # synchronise flag
    fin = tcp.flags.fin,  # finish flag
    rst = tcp.flags.rst,  # reset connection flag

```

(continues on next page)

(continued from previous page)

```

len = tcp.raw_len,          # payload length, header excludes
first = tcp.seq,            # this sequence number
last = tcp.seq + tcp.raw_len, # next (wanted) sequence number
payload = tcp.raw,         # raw bytearray type payload
)

```

tcp.datagram Data structure for **reassembled TCP datagram** (element from *datagram tuple*) is as following:

```

(tuple) datagram
|--> (Info) data
|   |--> 'NotImplemented' : (bool) True --> implemented
|   |--> 'id' : (Info) original packet identifier
|       |--> 'src' --> (tuple)
|           |--> (str) ip.src
|           |--> (int) tcp.srcport
|       |--> 'dst' --> (tuple)
|           |--> (str) ip.dst
|           |--> (int) tcp.dstport
|       |--> 'ack' --> (int) original packet ACK number
|   |--> 'index' : (tuple) packet numbers
|       |--> (int) original packet range number
|   |--> 'payload' : (Optional[bytes]) reassembled application layer data
|   |--> 'packets' : (Tuple[Analysis]) analysed payload
|--> (Info) data
|   |--> 'NotImplemented' : (bool) False --> not implemented
|   |--> 'id' : (Info) original packet identifier
|       |--> 'src' --> (tuple)
|           |--> (str) ip.src
|           |--> (int) tcp.srcport
|       |--> 'dst' --> (tuple)
|           |--> (str) ip.dst
|           |--> (int) tcp.dstport
|       |--> 'ack' --> (int) original packet ACK number
|   |--> 'ack' : (int) original packet ACK number
|   |--> 'index' : (tuple) packet numbers
|       |--> (int) original packet range number
|   |--> 'payload' : (Optional[tuple]) partially reassembled payload
|       |--> (Optional[bytes]) payload fragment
|   |--> 'packets' : (Tuple[Analysis]) analysed payloads
|--> (Info) data ...

```

tcp.buffer Data structure for internal buffering when performing reassembly algorithms (*_buffer*) is as following:

```

(dict) buffer --> memory buffer for reassembly
|--> (tuple) BUFID : (dict)
|   |--> ip.src
|   |--> ip.dst
|   |--> tcp.srcport
|   |--> tcp.dstport
|   |--> 'hdl' : (list) hole descriptor list
|       |--> (Info) hole --> hole descriptor
|           |--> "first" --> (int) start of hole
|           |--> "last" --> (int) stop of hole
|       |--> (int) ACK : (dict)
|           |--> 'ind' : (list) list of
|--> reassembled packets
|   |--> (int) packet range
--> number

```

(continues on next page)

(continued from previous page)

```
|                                |--> 'isn' : (int) ISN of payload_
↪buffer                          |                                |
|                                |--> 'len' : (int) length of payload_
↪buffer                          |                                |
|                                |--> 'raw' : (bytearray) reassembled_
↪payload, holes set to b'\x00'  |                                |
|                                |--> (int) ACK ...
|                                |--> ...
|--> (tuple) BUFID ...
```

Implementation

class pcapkit.reassembly.tcp.TCP_Reassembly(*, strict=True)

Bases: `pcapkit.reassembly.reassembly.Reassembly`

Reassembly for TCP payload.

Example

```
>>> from pcapkit.reassembly import TCP_Reassembly
# Initialise instance:
>>> tcp_reassembly = TCP_Reassembly()
# Call reassembly:
>>> tcp_reassembly(packet_dict)
# Fetch result:
>>> result = tcp_reassembly.datagram
```

reassembly (*info*)

Reassembly procedure.

Parameters **info** (`pcapkit.corekit.infoclass.Info`) – *info* dict of packets to be reassembled

submit (*buf*, *, *bufid*)

Submit reassembled payload.

Parameters **buf** (*dict*) – *buffer* dict of reassembled packets

Keyword Arguments **bufid** (*tuple*) – buffer identifier

Returns reassembled *packets*

Return type List[dict]

property name

Protocol of current packet.

Return type Literal['Transmission Control Protocol']

property protocol

Protocol of current reassembly object.

Return type Literal['TCP']

1.5 Core Utilities

`pcapkit.corekit` is the collection of core utilities for `pcapkit` implementation, including `dict` like class `Info`, tuple like class `VersionInfo`, and protocol collection class `ProtoChain`.

1.5.1 Info Class

`pcapkit.corekit.infoclass` contains `dict` like class `Info` only, which is originally designed to work alike `dataclasses.dataclass()` as introduced in [PEP 557](#).

class `pcapkit.corekit.infoclass.Info` (`dict_=None, **kwargs`)

Bases: `collections.abc.Mapping`

Turn dictionaries into `object` like instances.

Notes

- `Info` objects inherit from `dict` type
 - `Info` objects are *iterable*, and support all functions as `dict`
 - `Info` objects are **one-time-modeling**, thus cannot set or delete attributes after initialisation
-

static `__new__` (`cls, dict_=None, **kwargs`)

Create a new instance.

Parameters `dict` (`Dict[str, Any]`) – Source `dict` data.

Keyword Arguments `**kwargs` – Arbitrary keyword arguments.

Notes

Keys with the same names as the builtin methods will be renamed with 2 suffix implicitly and internally.

info2dict ()

Convert `Info` into `dict`.

Returns Converted `dict`.

Return type `Dict[str, Any]`

1.5.2 Protocol Chain

`pcapkit.corekit.protochain` contains special protocol collection class `ProtoChain`.

class `pcapkit.corekit.protochain.ProtoChain` (`proto=None, alias=None, *, basis=None`)

Bases: `collections.abc.Container`

Protocols chain.

__alias__: `pcapkit.corekit.protochain._AliasList`

Protocol aliases chain.

__proto__: `pcapkit.corekit.protochain._ProtoList`

Protocol classes chain.

__contains__ (*name*)

Returns if *name* is in the chain.

Parameters **name** (*Union[str, pcapkit.protocols.protocol.Protocol, Type[pcapkit.protocols.protocol, Protocol]]*) – *name* to search

Returns if *name* is in the chain

Return type `bool`

__init__ (*proto=None, alias=None, *, basis=None*)

Initialisation.

Parameters

- **proto** (*Optional[pcapkit.protocols.protocol.Protocol]*) – New protocol class on the top stack.
- **alias** (*Optional[str]*) – New protocol alias on the top stack.

Keyword Arguments **basis** (*pcapkit.corekit.protochain.ProtoChain*) – Original protocol chain as base stacks.

__repr__ ()

Returns representation of protocol chain data.

Example

```
>>> protochain
ProtoChain(<class 'pcapkit.protocols.link.ethernet.Ethernet'>, ...)
```

__str__ ()

Returns formatted hex representation of source data stream.

Example

```
>>> protochain
ProtoChain(<class 'pcapkit.protocols.link.ethernet.Ethernet'>, ...)
>>> print(protochain)
Ethernet:IPv6:Raw
```

count (*value*)

Number of occurrences of *value*.

Parameters **value** – (*Union[str, pcapkit.protocols.protocol.Protocol, Type[pcapkit.protocols.protocol, Protocol]]*): *value* to search

Returns Number of occurrences of *value*.

Return type `int`

See also:

This method calls `self.__alias__.count` for the actual processing.

index (*value, start=None, stop=None*)

First index of *value*.

Parameters

- **value** (`Union[str, pcapkit.protocols.protocol.Protocol, Type[pcapkit.protocols.protocol, Protocol]]`) – value to search
- **start** (`int`) – start offset
- **stop** (`int`) – stop offset

Returns First index of value.

Return type `int`

Raises `IntError` – If the value is not present.

See also:

This method calls `self.__alias__.index` for the actual processing.

property alias

Protocol aliases chain.

Return type `pcapkit.corekit.protocol._AliasList`

property chain

Protocol chain string.

Return type `str`

property proto

Protocol classes chain.

Return type `pcapkit.corekit.protocol._ProtoList`

tuple

Protocol names.

Return type `Tuple[str]`

class `pcapkit.corekit.protochain._AliasList` (`data=None, *, base=None`)

Bases: `collections.abc.Sequence`

List of protocol aliases for ProtoChain

__data__: `List[str]`

Protocol aliases chain data.

__contains__ (`x`)

Returns if `x` is in the chain.

Parameters `x` (`Union[str, pcapkit.protocols.protocol.Protocol, Type[pcapkit.protocols.protocol, Protocol]]`) – name to search

Returns if `x` is in the chain

Return type `bool`

__getitem__ (`index`)

Subscription (`getitem`) support.

Parameters `index` (`int`) – Indexing key.

Returns Protocol alias at such index.

Return type `str`

__init__ (`data=None, *, base=None`)

Initialisation.

Parameters `data` (`Optional[str]`) – New protocol alias on top stack.

Keyword Arguments **base** `(Union[pcapkit.corekit.protochain._AliasLists, List[str]])` – Original protocol alias chain as base stacks.

__iter__ `()`
Iterate through the protocol chain.

Return type `Iterator[str]`

__len__ `()`
Length of the protocol chain.

Return type `int`

__reversed__ `()`
Reverse the protocol alias chain.

Return type `List[str]`

count `(value)`
Number of occurrences of `value`.

Parameters **value** `– (Union[str, pcapkit.protocols.protocol.Protocol, Type[pcapkit.protocols.protocol, Protocol]])`: value to search

Returns Number of occurrences of `value`.

Return type `int`

index `(value, start=0, stop=None)`
First index of `value`.

Parameters

- **value** `(Union[str, pcapkit.protocols.protocol.Protocol, Type[pcapkit.protocols.protocol, Protocol]])` – value to search
- **start** `(int)` – start offset
- **stop** `(int)` – stop offset

Returns First index of `value`.

Return type `int`

Raises `IntError` – If the value is not present.

property data
Protocol alias data.

Return type `List[str]`

class `pcapkit.corekit.protochain._ProtoList (data=None, *, base=None)`
Bases: `collections.abc.Collection`
List of protocol classes for `ProtoChain`.

__data__: `List[pcapkit.protocols.protocol.Protocol]`
Protocol classes chain data.

__contains__ `(x)`
Returns if `x` is in the chain.

Parameters **x** `(Union[str, pcapkit.protocols.protocol.Protocol, Type[pcapkit.protocols.protocol, Protocol]])` – name to search

Returns if `x` is in the chain

Return type `bool`

__init__ (*data=None, *, base=None*)
Initialisation.

Parameters **data** (*Optional* [`pcapkit.protocols.protocol.Protocol`]) – New protocol class on the top stack.

Keyword Arguments **base** (*Union* [`pcapkit.corekit.protochain._ProtoList`, *List* [`pcapkit.protocols.protocol.Protocol`]]) – Original protocol class chain as base stacks.

__iter__ ()
Iterate through the protocol chain.

Return type `Iterator` [`pcapkit.protocols.protocol.Protocol`]

__len__ ()
Length of the protocol chain.

Return type `int`

property data
Protocol data.

Return type `List` [`pcapkit.protocols.protocol.Protocol`]

1.5.3 Version Info

`pcapkit.corekit.version` contains `tuple` like class `VersionInfo`, which is originally designed alike `sys.version_info`.

class `pcapkit.corekit.version.VersionInfo` (*major, minor*)
Bases: `tuple`

`VersionInfo` is alike `sys.version_info`.

__asdict ()
Return a new dict which maps field names to their values.

classmethod **__make** (*iterable*)
Make a new `VersionInfo` object from a sequence or iterable

__replace (***kws*)
Return a new `VersionInfo` object replacing specified fields with new values

_field_defaults = {}

_fields = ('major', 'minor')

_fields_defaults = {}

major
Alias for field number 0

minor
Alias for field number 1

1.6 Dump Utilities

`pcapkit.dumpkit` is the collection of dumpers for `pcapkit` implementation, which is alike those described in `dictdumper`.

1.6.1 PCAP Dumper

```
class pcapkit.dumpkit.PCAP (fname, **kwargs)
    Bases: dictdumper.dumper.Dumper
    PCAP file dumper.

    __call__ (value, name=None)
        Dump a new frame.

        Parameters
            • value (Info [DataType_Frame]) – content to be dumped
            • name (Optional [str]) – name of current content block

        Returns the dumper class itself (to support chain calling)
        Return type PCAP

    __init__ (fname, *, protocol, byteorder='little', nanosecond=False, **kwargs)
        Initialise dumper.

        Parameters fname (str) – output file name

        Keyword Arguments
            • protocol (Union [pcapkit.const.reg.linktype.LinkType, enum. IntEnum, str, int]) – data link type
            • byteorder (Literal ['little', 'big']) – header byte order
            • nanosecond (bool) – nanosecond-resolution file flag
            • **kwargs – arbitrary keyword arguments

    __append_value (value, file, name)
        Call this function to write contents.

        Parameters
            • value (Info [DataType_Frame]) – content to be dumped
            • file (io.BufferedReader) – output file
            • name (str) – name of current content block

    __dump_header (*, protocol, byteorder='little', nanosecond=False, **kwargs)
        Initially dump file heads and tails.

        Keyword Arguments
            • protocol (Union [pcapkit.const.reg.linktype.LinkType, enum. IntEnum, str, int]) – data link type
            • byteorder (Literal ['little', 'big']) – header byte order
            • nanosecond (bool) – nanosecond-resolution file flag
            • **kwargs – arbitrary keyword arguments
```

_fnum
Frame counter.
Type `int`

_link
Data link type.
Type `Union[pcapkit.const.reg.linktype.LinkType, enum.IntEnum, str, int]`

_nsec
Nanosecond-resolution file flag.
Type `bool`

property kind
File format of current dumper.
Return type `Literal['pcap']`

1.6.2 Undefined Dumper

class `pcapkit.dumpkit.NotImplementedIO` (*fname*, ****kwargs**)
Bases: `dictdumper.dumper.Dumper`
Unspecified output format.

__call__ (*value*, *name=None*)
Dump a new frame.

Parameters

- **value** (`Dict[str, Any]`) – content to be dumped
- **name** (`Optional[str]`) – name of current content block

Returns the dumper class itself (to support chain calling)

Return type `PCAP`

_append_value (*value*, *file*, *name*)
Call this function to write contents.

Parameters

- **value** (`Dict[str, Any]`) – content to be dumped
- **file** (`io.TextIOWrapper`) – output file
- **name** (`str`) – name of current content block

_dump_header (****kwargs**)
Initially dump file heads and tails.

Keyword Arguments ****kwargs** – arbitrary keyword arguments

property kind
File format of current dumper.
Return type `Literal[NotImplemented]`

1.7 Compatibility Tools

`pcapkit.toolkit` provides several utility functions for compatibility of multiple engine support.

1.7.1 Default (PyPCAPKit) Tools

`pcapkit.toolkit.default` contains all you need for `pcapkit` handy usage. All functions returns with a flag to indicate if usable for its caller.

`pcapkit.toolkit.default.ipv4_reassembly(frame)`

Make data for IPv4 reassembly.

Parameters `frame` (`pcapkit.protocols.pcap.frame.Frame`) – PCAP frame.

Returns

A tuple of data for IPv4 reassembly.

- If the `frame` can be used for IPv4 reassembly. A frame can be reassembled if it contains IPv4 layer (`pcapkit.protocols.internet.ipv4.IPv4`) and the **DF** (`IPv4.flags.df`) flag is `False`.
- If the `frame` can be reassembled, then the `dict` mapping of data for IPv4 reassembly (c.f. `ipv4.packet`) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`

See also:

`IPv4Reassembly`

`pcapkit.toolkit.default.ipv6_reassembly(frame)`

Make data for IPv6 reassembly.

Parameters `frame` (`pcapkit.protocols.pcap.frame.Frame`) – PCAP frame.

Returns

A tuple of data for IPv6 reassembly.

- If the `frame` can be used for IPv6 reassembly. A frame can be reassembled if it contains IPv6 layer (`pcapkit.protocols.internet.ipv6.IPv6`) and IPv6 Fragment header (**RFC 2460#section-4.5**, `pcapkit.protocols.internet.ipv6_frag.IPv6_Frag`).
- If the `frame` can be reassembled, then the `dict` mapping of data for IPv6 reassembly (`ipv6.packet`) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`

See also:

`IPv6Reassembly`

`pcapkit.toolkit.default.tcp_reassembly(frame)`

Make data for TCP reassembly.

Parameters `frame` (`pcapkit.protocols.pcap.frame.Frame`) – PCAP frame.

Returns

A tuple of data for TCP reassembly.

- If the `frame` can be used for TCP reassembly. A frame can be reassembled if it contains TCP layer (`pcapkit.protocols.transport.tcp.TCP`).
- If the `frame` can be reassembled, then the `dict` mapping of data for TCP reassembly (`tcp.packet`) will be returned; otherwise, returns `None`.

Return type Tuple[bool, Dict[str, Any]]

See also:

TCPReassembly

`pcapkit.toolkit.default.tcp_traceflow(frame, *, data_link)`

Trace packet flow for TCP.

Parameters `frame` (`pcapkit.protocols.pcap.frame.Frame`) – PCAP frame.

Keyword Arguments `data_link` (`str`) – Data link layer protocol (from global header).

Returns

A tuple of data for TCP reassembly.

- If the `packet` can be used for TCP flow tracing. A frame can be reassembled if it contains TCP layer (`pcapkit.protocols.transport.tcp.TCP`).
- If the `frame` can be reassembled, then the `dict` mapping of data for TCP flow tracing (`trace.packet`) will be returned; otherwise, returns `None`.

Return type Tuple[bool, Dict[str, Any]]

See also:

`TraceFlow`

1.7.2 DPKT Tools

`pcapkit.toolkit.dpkt` contains all you need for `pcapkit` handy usage with `DPKT` engine. All reforming functions returns with a flag to indicate if usable for its caller.

`pcapkit.toolkit.dpkt.ipv4_reassembly(packet, *, count=NotImplemented)`

Make data for IPv4 reassembly.

Parameters `packet` (`dpkt.dpkt.Packet`) – DPKT packet.

Keyword Arguments `count` (`int`) – Packet index. If not provided, default to `NotImplemented`.

Returns

A tuple of data for IPv4 reassembly.

- If the `packet` can be used for IPv4 reassembly. A packet can be reassembled if it contains IPv4 layer (`dpkt.ip.IP`) and the **DF** (`dpkt.ip.IP.df`) flag is `False`.
- If the `packet` can be reassembled, then the `dict` mapping of data for IPv4 reassembly (`ipv4.packet`) will be returned; otherwise, returns `None`.

Return type Tuple[bool, Dict[str, Any]]

See also:

IPv4Reassembly

`pcapkit.toolkit.dpkt.ipv6_hdr_len(ipv6)`

Calculate length of headers before IPv6 Fragment header.

Parameters `ipv6` (`dpkt.ip6.IP6`) – DPKT IPv6 packet.

Returns Length of headers before IPv6 Fragment header `dpkt.ip6.IP6FragmentHeader` ([RFC 2460#section-4.5](#)).

Return type `int`

As specified in [RFC 2460#section-4.1](#), such headers (before the IPv6 Fragment Header) includes Hop-by-Hop Options header `dpkt.ip6.IP6HopOptsHeader` ([RFC 2460#section-4.3](#)), Destination Options header `dpkt.ip6.IP6DstOptHeader` ([RFC 2460#section-4.6](#)) and Routing header `dpkt.ip6.IP6RoutingHeader` ([RFC 2460#section-4.4](#)).

`pcapkit.toolkit.dpkt.ipv6_reassembly` (`packet`, `*`, `count=NotImplemented`)

Make data for IPv6 reassembly.

Parameters `packet` (`dpkt.dpkt.Packet`) – DPKT packet.

Keyword Arguments `count` (`int`) – Packet index. If not provided, default to `NotImplemented`.

Returns

A tuple of data for IPv6 reassembly.

- If the packet can be used for IPv6 reassembly. A packet can be reassembled if it contains IPv6 layer (`dpkt.ip6.IP6`) and IPv6 Fragment header ([RFC 2460#section-4.5](#), `dpkt.ip6.IP6FragmentHeader`).
- If the packet can be reassembled, then the `dict` mapping of data for IPv6 reassembly (`ipv6.packet`) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`

See also:

`IPv6Reassembly`

`pcapkit.toolkit.dpkt.packet2chain` (`packet`)

Fetch DPKT packet protocol chain.

Parameters `packet` (`dpkt.dpkt.Packet`) – DPKT packet.

Returns Colon (:) seperated list of protocol chain.

Return type `str`

`pcapkit.toolkit.dpkt.packet2dict` (`packet`, `timestamp`, `*`, `data_link`)

Convert DPKT packet into `dict`.

Parameters `packet` (`c`) – Scapy packet.

Returns A `dict` mapping of packet data.

Return type `Dict[str, Any]`

`pcapkit.toolkit.dpkt.tcp_reassembly` (`packet`, `*`, `count=NotImplemented`)

Make data for TCP reassembly.

Parameters `packet` (`dpkt.dpkt.Packet`) – DPKT packet.

Keyword Arguments `count` (`int`) – Packet index. If not provided, default to `NotImplemented`.

Returns

A tuple of data for TCP reassembly.

- If the `packet` can be used for TCP reassembly. A packet can be reassembled if it contains TCP layer (`dpkt.tcp.TCP`).
- If the `packet` can be reassembled, then the `dict` mapping of data for TCP reassembly (`tcp.packet`) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`

See also:

`TCPReassembly`

`pcapkit.toolkit.dpkt.tcp_traceflow(packet, timestamp, *, data_link, count=NotImplemented)`
Trace packet flow for TCP.

Parameters

- **packet** (`dpkt.dpkt.Packet`) – DPKT packet.
- **timestamp** (`float`) – Timestamp of the packet.

Keyword Arguments

- **data_link** (`str`) – Data link layer protocol (from global header).
- **count** (`int`) – Packet index. If not provided, default to `NotImplemented`.

Returns

A tuple of data for TCP reassembly.

- If the `packet` can be used for TCP flow tracing. A packet can be reassembled if it contains TCP layer (`dpkt.tcp.TCP`).
- If the `packet` can be reassembled, then the `dict` mapping of data for TCP flow tracing (`trace.packet`) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`

See also:

`TraceFlow`

1.7.3 PyShark Tools

`pcapkit.toolkit.pyshark` contains all you need for `pcapkit` handy usage with `PyShark` engine. All reforming functions returns with a flag to indicate if usable for its caller.

`pcapkit.toolkit.pyshark.packet2dict(packet)`
Convert PyShark packet into `dict`.

Parameters **packet** (`pyshark.packet.packet.Packet`) – Scapy packet.

Returns A `dict` mapping of packet data.

Return type `Dict[str, Any]`

`pcapkit.toolkit.pyshark.tcp_traceflow(packet)`
Trace packet flow for TCP.

Parameters **packet** (`pyshark.packet.packet.Packet`) – Scapy packet.

Returns

A tuple of data for TCP reassembly.

- If the `packet` can be used for TCP flow tracing. A packet can be reassembled if it contains TCP layer.
- If the `packet` can be reassembled, then the `dict` mapping of data for TCP flow tracing (*trace.packet*) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`

See also:

TraceFlow

1.7.4 Scapy Tools

`pcapkit.toolkit.scapy` contains all you need for `pcapkit` handy usage with `Scapy` engine. All reforming functions returns with a flag to indicate if usable for its caller.

`pcapkit.toolkit.scapy.ipv4_reassembly(packet, *, count=NotImplemented)`
Make data for IPv4 reassembly.

Parameters `packet` (`scapy.packet.Packet`) – Scapy packet.

Keyword Arguments `count` (`int`) – Packet index. If not provided, default to `NotImplemented`.

Returns

A tuple of data for IPv4 reassembly.

- If the `packet` can be used for IPv4 reassembly. A packet can be reassembled if it contains IPv4 layer (`scapy.layers.inet.IP`) and the **DF** (`scapy.layers.inet.IP.flags.DF`) flag is `False`.
- If the `packet` can be reassembled, then the `dict` mapping of data for IPv4 reassembly (*ipv4.packet*) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`

See also:

IPv4Reassembly

`pcapkit.toolkit.scapy.ipv6_reassembly(packet, *, count=NotImplemented)`
Make data for IPv6 reassembly.

Parameters `packet` (`scapy.packet.Packet`) – Scapy packet.

Keyword Arguments `count` (`int`) – Packet index. If not provided, default to `NotImplemented`.

Returns

A tuple of data for IPv6 reassembly.

- If the `packet` can be used for IPv6 reassembly. A packet can be reassembled if it contains IPv6 layer (`scapy.layers.inet6.IPv6`) and IPv6 Fragment header (**RFC 2460#section-4.5**, `scapy.layers.inet6.IPv6ExtHdrFragment`).
- If the `packet` can be reassembled, then the `dict` mapping of data for IPv6 reassembly (*ipv6.packet*) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`

Raises `ModuleNotFound` – If `Scapy` is not installed.

See also:

IPv6Reassembly

`pcapkit.toolkit.scapy.packet2chain(packet)`

Fetch Scapy packet protocol chain.

Parameters `packet` (`scapy.packet.Packet`) – Scapy packet.**Returns** Colon (:) seperated list of protocol chain.**Return type** `str`**Raises** `ModuleNotFound` – If `Scapy` is not installed.`pcapkit.toolkit.scapy.packet2dict(packet)`Convert Scapy packet into `dict`.**Parameters** `packet` (`scapy.packet.Packet`) – Scapy packet.**Returns** A `dict` mapping of packet data.**Return type** `Dict[str, Any]`**Raises** `ModuleNotFound` – If `Scapy` is not installed.`pcapkit.toolkit.scapy.tcp_reassembly(packet, *, count=NotImplemented)`

Store data for TCP reassembly.

Parameters `packet` (`scapy.packet.Packet`) – Scapy packet.**Keyword Arguments** `count` (`int`) – Packet index. If not provided, default to `NotImplemented`.**Returns**

A tuple of data for TCP reassembly.

- If the `packet` can be used for TCP reassembly. A packet can be reassembled if it contains TCP layer (`scapy.layers.inet.TCP`).
- If the `packet` can be reassembled, then the `dict` mapping of data for TCP reassembly (`tcp.packet`) will be returned; otherwise, returns `None`.

Return type `Tuple[bool, Dict[str, Any]]`**See also:**

TCPReassembly

`pcapkit.toolkit.scapy.tcp_traceflow(packet, *, count=NotImplemented)`

Trace packet flow for TCP.

Parameters `packet` (`scapy.packet.Packet`) – Scapy packet.**Keyword Arguments** `count` (`int`) – Packet index. If not provided, default to `NotImplemented`.**Returns**

A tuple of data for TCP reassembly.

- If the `packet` can be used for TCP flow tracing. A packet can be reassembled if it contains TCP layer (`scapy.layers.inet.TCP`).
- If the `packet` can be reassembled, then the `dict` mapping of data for TCP flow tracing (`trace.packet`) will be returned; otherwise, returns `None`.

Return type Tuple[bool, Dict[str, Any]]

See also:

`TraceFlow`

1.8 Utility Functions & Classes

`pcapkit.utilities` contains several useful functions and classes which are foundations of `pcapkit`, including decorator function `seekset()` and `beholder()`, and several user-refined exceptions and validations.

1.8.1 Decorator Functions

`pcapkit.utilities.decorators` contains several useful decorators, including `seekset()` and `beholder()`.

@`pcapkit.utilities.decorators.seekset`

Read file from start then set back to original.

Important: This decorator function is designed for decorating *class methods*.

The decorator will keep the current offset of `self._file`, then call the decorated function. Afterwards, it will rewind the offset of `self._file` to the original and returns the return value from the decorated function.

Note: The decorated function should have following signature:

```
func(self, *args, **kw)
```

See also:

`pcapkit.protocols.protocol.Protocol._read_packet()`

@`pcapkit.utilities.decorators.seekset_ng`

Read file from start then set back to original.

Important: This decorator function is designed for decorating *plain functions*.

The decorator will rewind the offset of `file` to `seekset`, then call the decorated function and returns its return value.

Note: The decorated function should have following signature:

```
func(file, *args, seekset=os.SEEK_SET, **kw)
```

See also:

`pcapkit.foundation.analysis`

`@pcapkit.utilities.decorators.beholder`
Behold extraction procedure.

Important: This decorator function is designed for decorating *class methods*.

This decorate first keep the current offset of `self._file`, then try to call the decorated function. Should any exception raised, it will re-parse the `self._file` as *Raw* protocol.

Note: The decorated function should have following signature:

```
func(self, proto, length, *args, **kwargs)
```

See also:

`pcapkit.protocols.protocol.Protocol._decode_next_layer()`

`@pcapkit.utilities.decorators.beholder_ng`
Behold analysis procedure.

Important: This decorator function is designed for decorating *plain functions*.

This decorate first keep the current offset of `file`, then try to call the decorated function. Should any exception raised, it will re-parse the `file` as *Raw* protocol.

Note: The decorated function should have following signature:

```
func(file, length, *args, **kwargs)
```

See also:

`pcapkit.protocols.transport.transport.Transport._import_next_layer()`

Important: `pcapkit.utilities.decorators.seekset()` and `pcapkit.utilities.decorators.beholder()` are designed for decorating *class methods*.

1.8.2 User Defined Exceptions

pcapkit.exceptions refined built-in exceptions. Make it possible to show only user error stack information⁰, when exception raised on user's operation.

exception pcapkit.utilities.exceptions.**BaseError** (*args, quiet=False, **kwargs)
Bases: `Exception`

Base error class of all kinds.

Important:

- Turn off system-default traceback function by set `sys.tracebacklimit` to 0.
- But bugs appear in Python 3.6, so we have to set `sys.tracebacklimit` to None.

Note: This note is deprecated since Python fixed the problem above.

-
- In Python 2.7, `trace.print_stack(limit)()` dose not support negative limit.
-

See also:

`pcapkit.utilities.exceptions.stacklevel()`

`__init__` (*args, quiet=False, **kwargs)
Initialize self. See help(type(self)) for accurate signature.

exception pcapkit.utilities.exceptions.**BoolError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`

The argument(s) must be `bool` type.

exception pcapkit.utilities.exceptions.**BytearrayError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`

The argument(s) must be `bytearray` type.

exception pcapkit.utilities.exceptions.**BytesError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`

The argument(s) must be `bytes` type.

exception pcapkit.utilities.exceptions.**CallableError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`

The argument(s) must be `callable`.

exception pcapkit.utilities.exceptions.**ComparisonError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`

Rich comparison not supported between instances.

exception pcapkit.utilities.exceptions.**ComplexError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`

The function is not defined for complex instance.

⁰ See `tbtrim` project for a modern Pythonic implementation.

exception pcapkit.utilities.exceptions.**DictError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
 The argument(s) must be `dict` type.

exception pcapkit.utilities.exceptions.**DigitError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
 The argument(s) must be (a) number(s).

exception pcapkit.utilities.exceptions.**EndianError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `ValueError`
 Invalid endian (byte order).

exception pcapkit.utilities.exceptions.**EnumError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
 The argument(s) must be *enumeration protocol* type.

exception pcapkit.utilities.exceptions.**FileError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `OSError`
 [Errno 5] Wrong file format.

exception pcapkit.utilities.exceptions.**FileExists** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `FileExistsError`
 [Errno 17] File already exists.

exception pcapkit.utilities.exceptions.**FileNotFound** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `FileNotFoundError`
 [Errno 2] File not found.

exception pcapkit.utilities.exceptions.**FormatError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `AttributeError`
 Unknown format(s).

exception pcapkit.utilities.exceptions.**FragmentError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `KeyError`
 Invalid fragment dict.

exception pcapkit.utilities.exceptions.**IOObjError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
 The argument(s) must be *file-like object*.

exception pcapkit.utilities.exceptions.**IPError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
 The argument(s) must be *IP address*.

exception pcapkit.utilities.exceptions.**IndexNotFound** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `ValueError`
 Protocol not in ProtoChain.

exception pcapkit.utilities.exceptions.**InfoError** (*args, quiet=False, **kwargs)
 Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
 The argument(s) must be *Info* instance.

exception pcapkit.utilities.exceptions.**IntError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
The argument(s) must be integral.

exception pcapkit.utilities.exceptions.**IterableError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
The argument(s) must be *iterable*.

exception pcapkit.utilities.exceptions.**ListError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
The argument(s) must be `list` type.

exception pcapkit.utilities.exceptions.**ModuleNotFound** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `ModuleNotFoundError`
Module not found.

exception pcapkit.utilities.exceptions.**PacketError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `KeyError`
Invalid packet dict.

exception pcapkit.utilities.exceptions.**ProtocolError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `ValueError`
Invalid protocol format.

exception pcapkit.utilities.exceptions.**ProtocolNotFound** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `IndexError`
Protocol not found in ProtoChain.

exception pcapkit.utilities.exceptions.**ProtocolNotImplemented** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `NotImplementedError`
Protocol not implemented.

exception pcapkit.utilities.exceptions.**ProtocolUnbound** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
Protocol slice unbound.

exception pcapkit.utilities.exceptions.**RealError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
The function is not defined for real number.

exception pcapkit.utilities.exceptions.**StringError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`
The argument(s) must be `str` type.

exception pcapkit.utilities.exceptions.**StructError** (*args, quiet=False, **kwargs)
Bases: `pcapkit.utilities.exceptions.BaseError`, `struct.error`
Unpack failed.

exception pcapkit.utilities.exceptions.**TupleError** (*args, quiet=False, **kwargs)

Bases: `pcapkit.utilities.exceptions.BaseError`, `TypeError`

The argument(s) must be `tuple` type.

exception pcapkit.utilities.exceptions.**UnsupportedCall** (*args, quiet=False, **kwargs)

Bases: `pcapkit.utilities.exceptions.BaseError`, `AttributeError`

Unsupported function or property call.

exception pcapkit.utilities.exceptions.**VendorNotImplemented** (*args, quiet=False, **kwargs)

Bases: `pcapkit.utilities.exceptions.BaseError`, `NotImplementedError`

Vendor not implemented.

exception pcapkit.utilities.exceptions.**VersionError** (*args, quiet=False, **kwargs)

Bases: `pcapkit.utilities.exceptions.BaseError`, `ValueError`

Unknown IP version.

pcapkit.utilities.exceptions.**stacklevel** ()

Fetch current stack level.

The function will walk through the straceback stack (`traceback.extract_stack()`), and fetch the stack level where the path contains `/pcapkit/`. So that it won't display any disturbing internal traceback information when raising errors.

Returns Stack level until internal stacks, i.e. contains `/pcapkit/`.

Return type `int`

pcapkit.utilities.exceptions.**DEVMODE** = **False**

Development mode (DEVMODE) flag.

1.8.3 Validation Utilities

`pcapkit.utilities.validations` contains functions to validate arguments for functions and classes. It was first used in `PyNTLib` as validators.

pcapkit.utilities.validations.**_ip_frag_check** (*args, stacklevel=3)

Check if arguments are valid IP fragments (*IPv4* and/or *IPv6* packet).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

See also:

- `pcapkit.toolkit.default.ipv4_reassembly()`
- `pcapkit.toolkit.default.ipv6_reassembly()`

pcapkit.utilities.validations.**_tcp_frag_check** (*args, stacklevel=3)

Check if arguments are valid TCP fragments (*TCP packet*).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

See also:

`pcapkit.toolkit.default.tcp_reassembly()`

`pcapkit.utilities.validations.bool_check(*args, stacklevel=2)`

Check if arguments are bool type.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *BoolError* – If any of the arguments is **NOT** bool type.

`pcapkit.utilities.validations bytearray_check(*args, stacklevel=2)`

Check if arguments are bytearray type.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *BytearrayError* – If any of the arguments is **NOT** bytearray type.

`pcapkit.utilities.validations.bytes_check(*args, stacklevel=2)`

Check if arguments are bytes type.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *BytesError* – If any of the arguments is **NOT** bytes type.

`pcapkit.utilities.validations.complex_check(*args, stacklevel=2)`

Check if arguments are *complex numbers* (complex).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *ComplexError* – If any of the arguments is **NOT** *complex number* (complex).

`pcapkit.utilities.validations.dict_check(*args, stacklevel=2)`

Check if arguments are dict type.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *DictError* – If any of the arguments is **NOT** dict type.

`pcapkit.utilities.validations.enum_check(*args, stacklevel=2)`

Check if arguments are of *enumeration protocol* type (enum.EnumMeta and/or aenum.EnumMeta).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *EnumError* – If any of the arguments is **NOT** *enumeration protocol* type (`enum.EnumMeta` and/or `aenum.EnumMeta`).

`pcapkit.utilities.validations.frag_check(*args, protocol, stacklevel=3)`

Check if arguments are valid fragments.

Parameters

- ***args** – Arguments to check.
- **protocol** (*str*) – Originated fragmentation protocol (IPv4, IPv6 or TCP).
- **stacklevel** (*int*) – Stack level to fetch originated function name.
- If the protocol is IPv4, the fragment should be as an IPv4 *fragmentation*.
- If the protocol is IPv6, the fragment should be as an IPv6 *fragmentation*.
- If the protocol is TCP, the fragment should be as an TCP *fragmentation*.

Raises *FragmentError* – If any of the arguments is **NOT** valid fragment.

See also:

- `pcapkit.utilities.validations._ip_frag_check()`
- `pcapkit.utilities.validations._tcp_frag_check()`

`pcapkit.utilities.validations.info_check(*args, stacklevel=2)`

Check if arguments are *Info* instances.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *InfoError* – If any of the arguments is **NOT** *Info* instance.

`pcapkit.utilities.validations.int_check(*args, stacklevel=2)`

Check if arguments are *integrals* (*int*).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *IntError* – If any of the arguments is **NOT** *integral* (*int*).

`pcapkit.utilities.validations.io_check(*args, stacklevel=2)`

Check if arguments are *file-like object* (`io.IOBase`).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *IOObjError* – If any of the arguments is **NOT** *file-like object* (`io.IOBase`).

`pcapkit.utilities.validations.ip_check(*args, stacklevel=2)`

Check if arguments are *IP addresses* (`ipaddress.IPv4Address` and/or `ipaddress.IPv6Address`).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *IPError* – If any of the arguments is **NOT** *IP address* (`ipaddress.IPv4Address` and/or `ipaddress.IPv6Address`).

`pcapkit.utilities.validations.list_check(*args, stacklevel=2)`

Check if arguments are *list* type.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *ListError* – If any of the arguments is **NOT** *list* type.

`pcapkit.utilities.validations.number_check(*args, stacklevel=2)`

Check if arguments are *numbers*.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *DigitError* – If any of the arguments is **NOT** *number* (*int*, *float* and/or *complex*).

`pcapkit.utilities.validations.pkt_check(*args, stacklevel=3)`

Check if arguments are valid packets (*TCP packet*).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *PacketError* – If any of the arguments is **NOT** valid packet.

See also:

`pcapkit.toolkit.default.tcp_traceflow()`

`pcapkit.utilities.validations.real_check(*args, stacklevel=2)`

Check if arguments are *real numbers* (*int* and/or *float*).

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *RealError* – If any of the arguments is **NOT** *real number* (*int* and/or *float*).

`pcapkit.utilities.validations.str_check(*args, stacklevel=2)`

Check if arguments are *str* type.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *StringError* – If any of the arguments is **NOT** *str* type.

`pcapkit.utilities.validations.tuple_check(*args, stacklevel=2)`

Check if arguments are *tuple* type.

Parameters

- ***args** – Arguments to check.
- **stacklevel** (*int*) – Stack level to fetch originated function name.

Raises *TupleError* – If any of the arguments is **NOT** *tuple* type.

1.8.4 User Defined Warnings

`pcapkit.warnings` refined built-in warnings.

exception `pcapkit.utilities.warnings.AttributeWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `RuntimeWarning`

Unsupported attribute.

exception `pcapkit.utilities.warnings.BaseWarning(*args, **kwargs)`

Bases: `UserWarning`

Base warning class of all kinds.

__init__ (**args, **kwargs*)

Initialize self. See `help(type(self))` for accurate signature.

exception `pcapkit.utilities.warnings.DPKTWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `ResourceWarning`

Warnings on DPKT usage.

exception `pcapkit.utilities.warnings.DevModeWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `RuntimeWarning`

Run in development mode.

exception `pcapkit.utilities.warnings.EngineWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `ImportWarning`

Unsupported extraction engine.

exception `pcapkit.utilities.warnings.FileWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `RuntimeWarning`

Warning on file(s).

exception `pcapkit.utilities.warnings.FormatWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `ImportWarning`

Warning on unknown format(s).

exception `pcapkit.utilities.warnings.InvalidVendorWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `ImportWarning`

Vendor CLI invalid updater.

exception `pcapkit.utilities.warnings.LayerWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `RuntimeWarning`

Unrecognised layer.

exception `pcapkit.utilities.warnings.ProtocolWarning(*args, **kwargs)`

Bases: `pcapkit.utilities.warnings.BaseWarning`, `RuntimeWarning`

Unrecognised protocol.

exception pcapkit.utilities.warnings.**PySharkWarning**(*args, **kwargs)
Bases: [pcapkit.utilities.warnings.BaseWarning](#), [ResourceWarning](#)

Warnings on PyShark usage.

exception pcapkit.utilities.warnings.**ScapyWarning**(*args, **kwargs)
Bases: [pcapkit.utilities.warnings.BaseWarning](#), [ResourceWarning](#)

Warnings on Scapy usage.

exception pcapkit.utilities.warnings.**VendorRequestWarning**(*args, **kwargs)
Bases: [pcapkit.utilities.warnings.BaseWarning](#), [RuntimeWarning](#)

Vendor request connection failed.

exception pcapkit.utilities.warnings.**VendorRuntimeWarning**(*args, **kwargs)
Bases: [pcapkit.utilities.warnings.BaseWarning](#), [RuntimeWarning](#)

Vendor failed during runtime.

1.9 Constant Enumerations

1.9.1 ARP Constant Enumerations

ARP Hardware Types^{*0}

*

class pcapkit.const.arp.hardware.**Hardware**(value=<object object>, names=None, module=None, type=None, start=1)

Bases: [aenum.IntEnum](#)

[Hardware] Hardware Types [[RFC 826](#)][[RFC 5494](#)]

classmethod **_missing_**(value)
Lookup function used when value is not found.

static **get**(key, default=-1)
Backport support for original codes.

AEthernet = 257
AEthernet [[Geoffroy Gramaize](#)]

ARCNET = 7
ARCNET [[RFC 1201](#)]

ARPSec = 30
ARPSec [[Jerome Etienne](#)]

Amateur_Radio_AX_25 = 3
Amateur Radio AX.25 [[Philip Koch](#)]

Asynchronous_Transmission_Mode_16 = 16
Asynchronous Transmission Mode (ATM) [[JXB2](#)]

Asynchronous_Transmission_Mode_19 = 19
Asynchronous Transmission Mode (ATM) [[RFC 2225](#)]

⁰ <https://www.iana.org/assignments/arp-parameters/arp-parameters.xhtml#arp-parameters-2>

Asynchronous_Transmission_Mode_21 = 21
Asynchronous Transmission Mode (ATM) [Mike Burrows]

Autonet_Short_Address = 10
Autonet Short Address [Mike Burrows]

Chaos = 5
Chaos [Gill Pratt]

EUI_64 = 27
EUI-64 [Kenji Fujisawa]

Ethernet = 1
Ethernet (10Mb) [Jon Postel]

Experimental_Ethernet = 2
Experimental Ethernet (3Mb) [Jon Postel]

Fibre_Channel = 18
Fibre Channel [[RFC 4338](#)]

Frame_Relay = 15
Frame Relay [Andy Malis]

HDLC = 17
HDLC [Jon Postel]

HFI = 37
HFI [Tseng-Hui Lin]

HIPARP = 28
HIPARP [Jean Michel Pittet]

HW_EXP1 = 36
HW_EXP1 [[RFC 5494](#)]

HW_EXP2 = 256
HW_EXP2 [[RFC 5494](#)]

Hyperchannel = 8
Hyperchannel [Jon Postel]

IEEE_1394_1995 = 24
IEEE 1394.1995 [Myron Hattig]

IEEE_802_Networks = 6
IEEE 802 Networks [Jon Postel]

IP_and_ARP_over_ISO_7816_3 = 29
IP and ARP over ISO 7816-3 [Scott Guthery]

IPsec_tunnel = 31
IPsec tunnel [[RFC 3456](#)]

InfiniBand = 32
InfiniBand (TM) [[RFC 4391](#)]

Lanstar = 9
Lanstar [Tom Unger]

LocalNet = 12
LocalNet (IBM PCNet or SYTEK LocalNET) [Joseph Murdock]

```
LocalTalk = 11
    LocalTalk [Joyce K Reynolds]

MAPOS = 25
    MAPOS [Mitsuru Maruyama][RFC 2176]

MIL_STD_188_220 = 22
    MIL-STD-188-220 [Herb Jensen]

Metricom = 23
    Metricom [Jonathan Stone]

Proteon_ProNET_Token_Ring = 4
    Proteon ProNET Token Ring [Avri Doria]

Pure_IP = 35
    Pure IP [Inaky Perez-Gonzalez]

Reserved_0 = 0
    Reserved [RFC 5494]

Reserved_65535 = 65535
    Reserved [RFC 5494]

SMDS = 14
    SMDS [George Clapp]

Serial_Line = 20
    Serial Line [Jon Postel]

TIA_102_Project_25_Common_Air_Interface = 33
    TIA-102 Project 25 Common Air Interface (CAI) [Jeff Anderson, Telecommunications Industry of America (TIA) TR-8.5 Formulating Group, <cja015@motorola.com>, June 2004]

Twinaxial = 26
    Twinaxial [Marion Pitts]

Ultra_link = 13
    Ultra link [Rajiv Dhingra]

Wiegand_Interface = 34
    Wiegand Interface [Scott Guthery 2]
```

Operation Codes†⁰

†

```
class pcapkit.const.arp.operation.Operation (value=<object object>, names=None, module=None, type=None, start=1)
    Bases: aenum.IntEnum
    [Operation] Operation Codes [RFC 826][RFC 5494]
    classmethod _missing_ (value)
        Lookup function used when value is not found.
    static get (key, default=-1)
        Backport support for original codes.
    ARP_NAK = 10
    ARP_NAK [RFC 1577]
```

⁰ <https://www.iana.org/assignments/arp-parameters/arp-parameters.xhtml#arp-parameters-1>


```
DRARP_Error = 7
    DRARP-Error [RFC 1931]

DRARP_Reply = 6
    DRARP-Reply [RFC 1931]

DRARP_Request = 5
    DRARP-Request [RFC 1931]

InARP_Reply = 9
    InARP-Reply [RFC 2390]

InARP_Request = 8
    InARP-Request [RFC 2390]

MAPOS_UNARP = 23
    MAPOS-UNARP [Mitsuru Maruyama][RFC 2176]

MARS_GroupList_Reply = 21
    MARS-GroupList-Reply [Grenville Armitage]

MARS_GroupList_Request = 20
    MARS-GroupList-Request [Grenville Armitage]

MARS_Join = 14
    MARS-Join [Grenville Armitage]

MARS_Leave = 15
    MARS-Leave [Grenville Armitage]

MARS_MServ = 13
    MARS-MServ [Grenville Armitage]

MARS_Multi = 12
    MARS-Multi [Grenville Armitage]

MARS_NAK = 16
    MARS-NAK [Grenville Armitage]

MARS_Redirect_Map = 22
    MARS-Redirect-Map [Grenville Armitage]

MARS_Request = 11
    MARS-Request [Grenville Armitage]

MARS_SJoin = 18
    MARS-SJoin [Grenville Armitage]

MARS_SLeave = 19
    MARS-SLeave [Grenville Armitage]

MARS_Unserv = 17
    MARS-Unserv [Grenville Armitage]

OP_EXP1 = 24
    OP_EXP1 [RFC 5494]

OP_EXP2 = 25
    OP_EXP2 [RFC 5494]

REPLY = 2
    REPLY [RFC 826][RFC 5227]
```

```
REQUEST = 1
    REQUEST [RFC 826][RFC 5227]

Reserved_0 = 0
    Reserved [RFC 5494]

Reserved_65535 = 65535
    Reserved [RFC 5494]

reply_Reverse = 4
    reply Reverse [RFC 903]

request_Reverse = 3
    request Reverse [RFC 903]
```

1.9.2 FTP Constant Enumerations

FTP Commands^{*0}

*

```
class pcapkit.const.ftp.command.defaultInfo(dict_=None, **kwargs)
    Bases: pcapkit.corekit.infoclass.Info
    Extended Info with default values.
    __getitem__(key)
        Missing keys as specified in RFC 3659.
```

```
pcapkit.const.ftp.command.Command = Info(ABOR=Info(...), ACCT=Info(...), ADAT=Info(...), AL
FTP Command
```

FTP Return Codes^{†0}

†

```
class pcapkit.const.ftp.return_code.ReturnCode(value=<object object>, names=None,
                                                module=None, type=None, start=1)
```

Bases: aenum.IntEnum

[ReturnCode] FTP Server Return Code

```
classmethod _missing_(value)
    Lookup function used when value is not found.
```

```
static get(key, default=-1)
    Backport support for original codes.
```

CODE_110 = 110

Restart marker replay. In this case, the text is exact and not left to the particular implementation; it must read: MARK yyyy = mmmm where yyyy is User-process data stream marker, and mmmm server's equivalent marker (note the spaces between markers and "=").

CODE_120 = 120

Service ready in nnn minutes.

CODE_125 = 125

Data connection already open; transfer starting.

⁰ <https://www.iana.org/assignments/ftp-commands-extensions/ftp-commands-extensions.xhtml#ftp-commands-extensions-2>

⁰ https://en.wikipedia.org/wiki/List_of_FTP_server_return_codes

CODE_150 = 150
File status okay; about to open data connection.

CODE_202 = 202
Command not implemented, superfluous at this site.

CODE_211 = 211
System status, or system help reply.

CODE_212 = 212
Directory status.

CODE_213 = 213
File status.

CODE_214 = 214
Help message. Explains how to use the server or the meaning of a particular non-standard command. This reply is useful only to the human user.

CODE_215 = 215
NAME system type. Where NAME is an official system name from the registry kept by IANA.

CODE_220 = 220
Service ready for new user.

CODE_221 = 221
Service closing control connection.

CODE_225 = 225
Data connection open; no transfer in progress.

CODE_226 = 226
Closing data connection. Requested file action successful (for example, file transfer or file abort).

CODE_227 = 227
Entering Passive Mode (h1,h2,h3,h4,p1,p2).

CODE_228 = 228
Entering Long Passive Mode (long address, port).

CODE_229 = 229
Entering Extended Passive Mode (|||port|).

CODE_230 = 230
User logged in, proceed. Logged out if appropriate.

CODE_231 = 231
User logged out; service terminated.

CODE_232 = 232
Logout command noted, will complete when transfer done.

CODE_234 = 234
Specifies that the server accepts the authentication mechanism specified by the client, and the exchange of security data is complete. A higher level nonstandard code created by Microsoft.

CODE_250 = 250
Requested file action okay, completed.

CODE_257 = 257
"PATHNAME" created.

CODE_331 = 331
User name okay, need password.

CODE_332 = 332
Need account for login.

CODE_350 = 350
Requested file action pending further information

CODE_421 = 421
Service not available, closing control connection. This may be a reply to any command if the service knows it must shut down.

CODE_425 = 425
Can't open data connection.

CODE_426 = 426
Connection closed; transfer aborted.

CODE_430 = 430
Invalid username or password

CODE_434 = 434
Requested host unavailable.

CODE_450 = 450
Requested file action not taken.

CODE_451 = 451
Requested action aborted. Local error in processing.

CODE_452 = 452
Requested action not taken. Insufficient storage space in system. File unavailable (e. g. , file busy).

CODE_501 = 501
Syntax error in parameters or arguments.

CODE_502 = 502
Command not implemented.

CODE_503 = 503
Bad sequence of commands.

CODE_504 = 504
Command not implemented for that parameter.

CODE_530 = 530
Not logged in.

CODE_532 = 532
Need account for storing files.

CODE_534 = 534
Could Not Connect to Server - Policy Requires SSL

CODE_550 = 550
Requested action not taken. File unavailable (e. g. , file not found, no access).

CODE_551 = 551
Requested action aborted. Page type unknown.

CODE_552 = 552
Requested file action aborted. Exceeded storage allocation (for current directory or dataset).

CODE_553 = 553
Requested action not taken. File name not allowed.

CODE_631 = 631
Integrity protected reply.

CODE_632 = 632
Confidentiality and integrity protected reply.

CODE_633 = 633
Confidentiality protected reply.

`pcapkit.const.ftp.return_code.INFO` = {'0': 'Syntax', '1': 'Information', '2': 'Connection'}
Grouping information.

`pcapkit.const.ftp.return_code.KIND` = {'1': 'Positive Preliminary', '2': 'Positive Complete'}
Response kind; whether the response is good, bad or incomplete.

1.9.3 HIP Constant Enumerations

HIP Certificate Types^{*0}

*

class `pcapkit.const.hip.certificate.Certificate` (*value=<object object>, names=None, module=None, type=None, start=1*)

Bases: `aenum.IntEnum`

[Certificate] HIP Certificate Types

classmethod `_missing_` (*value*)
Lookup function used when value is not found.

static get (*key, default=-1*)
Backport support for original codes.

Distinguished_Name_of_X_509_v3 = 7
Distinguished Name of X.509 v3 [[RFC 8002](#)]

Hash_and_URL_of_X_509_v3 = 3
Hash and URL of X.509 v3 [[RFC 8002](#)]

LDAP_URL_of_X_509_v3 = 5
LDAP URL of X.509 v3 [[RFC 8002](#)]

Obsoleted_2 = 2
Obsoleted [[RFC 8002](#)]

Obsoleted_4 = 4
Obsoleted [[RFC 8002](#)]

Obsoleted_6 = 6
Obsoleted [[RFC 8002](#)]

Obsoleted_8 = 8
Obsoleted [[RFC 8002](#)]

Reserved = 0
Reserved [[RFC 8002](#)]

X_509_v3 = 1
X.509 v3 [[RFC 8002](#)]

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#certificate-types>

HIP Cipher IDs†⁰

†

```
class pcapkit.const.hip.cipher.Cipher (value=<object object>, names=None, module=None,  
                                         type=None, start=1)
```

Bases: aenum.IntEnum

[Cipher] Cipher IDs

```
classmethod _missing_ (value)  
    Lookup function used when value is not found.
```

```
static get (key, default=- 1)  
    Backport support for original codes.
```

```
AES_128_CBC = 2  
    AES-128-CBC [RFC 7401]
```

```
AES_256_CBC = 4  
    AES-256-CBC [RFC 7401]
```

```
NULL_ENCRYPT = 1  
    NULL-ENCRYPT [RFC 7401]
```

```
RESERVED_0 = 0  
    RESERVED [RFC 7401]
```

```
RESERVED_3 = 3  
    RESERVED [RFC 7401]
```

DI-Types‡⁰

‡

```
class pcapkit.const.hip.di.DITypes (value=<object object>, names=None, module=None,  
                                     type=None, start=1)
```

Bases: aenum.IntEnum

[DITypes] DI-Types

```
classmethod _missing_ (value)  
    Lookup function used when value is not found.
```

```
static get (key, default=- 1)  
    Backport support for original codes.
```

```
FQDN = 1  
    FQDN [RFC 7401]
```

```
NAI = 2  
    NAI [RFC 7401]
```

```
none_included = 0  
    none included [RFC 7401]
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-cipher-id>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-7>

ECDSA Curve Label⁰

```
class pcapkit.const.hip.ecdsa_curve.ECDSACurve (value=<object object>, names=None,
                                                module=None, type=None, start=1)

    Bases: aenum.IntEnum

    [ECDSACurve] ECDSA Curve Label

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    NIST_P_256 = 1
        NIST P-256 [RFC 7401]

    NIST_P_384 = 2
        NIST P-384 [RFC 7401]

    RESERVED = 0
        RESERVED [RFC 7401]
```

ECDSA_LOW Curve Label⁰

¶

```
class pcapkit.const.hip.ecdsa_low_curve.ECDSALowCurve (value=<object object>,
                                                         names=None, module=None,
                                                         type=None, start=1)

    Bases: aenum.IntEnum

    [ECDSALowCurve] ECDSA_LOW Curve Label

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    RESERVED = 0
        RESERVED [RFC 7401]

    SECP160R1 = 1
        SECP160R1 [RFC 7401]
```

ESP Transform Suite IDs³⁵

```
class pcapkit.const.hip.esp_transform_suite.ESPTransformSuite (value=<object
                                                                object>,
                                                                names=None,
                                                                module=None,
                                                                type=None,
                                                                start=1)

    Bases: aenum.IntEnum

    [ESPTransformSuite] ESP Transform Suite IDs
```

¹⁵⁹ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#ecdsa-curve-label>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#ecdsa-low-curve-label>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#esp-transform-suite-ids>

classmethod `_missing_` (*value*)
Lookup function used when value is not found.

static `get` (*key*, *default=-1*)
Backport support for original codes.

AES_128_CBC_with_HMAC_SHA1 = 1
AES-128-CBC with HMAC-SHA1 [RFC 3602][RFC 2404]

AES_128_CBC_with_HMAC_SHA_256 = 8
AES-128-CBC with HMAC-SHA-256 [RFC 3602][RFC 4868]

AES_256_CBC_with_HMAC_SHA_256 = 9
AES-256-CBC with HMAC-SHA-256 [RFC 3602][RFC 4868]

AES_CCM_16 = 11
AES-CCM-16 [RFC 4309]

AES_CCM_8 = 10
AES-CCM-8 [RFC 4309]

AES_CMAC_96 = 14
AES-CMAC-96 [RFC 4493][RFC 4494]

AES_GCM_with_a_16_octet_ICV = 13
AES-GCM with a 16 octet ICV [RFC 4106]

AES_GCM_with_an_8_octet_ICV = 12
AES-GCM with an 8 octet ICV [RFC 4106]

AES_GMAC = 15
AES-GMAC [RFC 4543]

DEPRECATED_2 = 2
DEPRECATED [RFC 7402]

DEPRECATED_3 = 3
DEPRECATED [RFC 7402]

DEPRECATED_4 = 4
DEPRECATED [RFC 7402]

DEPRECATED_5 = 5
DEPRECATED [RFC 7402]

DEPRECATED_6 = 6
DEPRECATED [RFC 7402]

NULL_with_HMAC_SHA_256 = 7
NULL with HMAC-SHA-256 [RFC 2410][RFC 4868]

RESERVED = 0
RESERVED [RFC 7402]

Group IDs⁰

```
class pcapkit.const.hip.group.Group (value=<object object>, names=None, module=None,
                                     type=None, start=1)
```

Bases: aenum.IntEnum

[Group] Group IDs

```
classmethod _missing_ (value)
```

Lookup function used when value is not found.

```
static get (key, default=- 1)
```

Backport support for original codes.

```
Group_1536_bit_MODP_group = 3
```

1536-bit MODP group [RFC 7401]

```
Group_2048_bit_MODP_group = 11
```

2048-bit MODP group [RFC 7401]

```
Group_3072_bit_MODP_group = 4
```

3072-bit MODP group [RFC 7401]

```
Group_384_bit_group = 1
```

384-bit group [RFC 5201] DEPRECATED

```
Group_6144_bit_MODP_group = 5
```

6144-bit MODP group [RFC 5201] DEPRECATED

```
Group_8192_bit_MODP_group = 6
```

8192-bit MODP group [RFC 5201] DEPRECATED

```
NIST_P_256 = 7
```

NIST P-256 [RFC 7401]

```
NIST_P_384 = 8
```

NIST P-384 [RFC 7401]

```
NIST_P_521 = 9
```

NIST P-521 [RFC 7401]

```
OAKLEY_well_known_group_1 = 2
```

OAKLEY well known group 1 [RFC 5201] DEPRECATED

```
Reserved = 0
```

Reserved [RFC 7401]

```
SECP160R1 = 10
```

SECP160R1 [RFC 7401]

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-5>

HI Algorithm⁰

```
class pcapkit.const.hip.hi_algorithm.HIAlgorithm (value=<object object>,
                                                names=None, module=None,
                                                type=None, start=1)

Bases: aenum.IntEnum

[HIAlgorithm] HI Algorithm

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

DSA = 3
    DSA [RFC 7401]

ECDSA = 7
    ECDSA [RFC 7401]

ECDSA_LOW = 9
    ECDSA_LOW [RFC 7401]

NULL_ENCRYPT = 1
    NULL-ENCRYPT [RFC 2410]

RESERVED = 0
    RESERVED [RFC 7401]

RSA = 5
    RSA [RFC 7401]

Unassigned_2 = 2
    Unassigned

Unassigned_4 = 4
    Unassigned

Unassigned_6 = 6
    Unassigned

Unassigned_8 = 8
    Unassigned
```

HIT Suite ID⁰

```
class pcapkit.const.hip.hit_suite.HITSuite (value=<object object>, names=None, mod-
                                           ule=None, type=None, start=1)

Bases: aenum.IntEnum

[HITSuite] HIT Suite ID

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hi-algorithm>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hit-suite-id>

```

ECDSA_LOW_SHA_1 = 3
    ECDSA_LOW/SHA-1 [RFC 7401]

ECDSA_SHA_384 = 2
    ECDSA/SHA-384 [RFC 7401]

RESERVED = 0
    RESERVED [RFC 7401]

RSA_DSA_SHA_256 = 1
    RSA,DSA/SHA-256 [RFC 7401]

```

HIP NAT Traversal Modes⁰

```

class pcapkit.const.hip.nat_traversal.NATTraversal (value=<object      object>,
                                                    names=None,      module=None,
                                                    type=None, start=1)

Bases: aenum.IntEnum

[NATTraversal] HIP NAT Traversal Modes

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

ICE_STUN_UDP = 2
    ICE-STUN-UDP [RFC 5770]

Reserved = 0
    Reserved [RFC 5770]

UDP_ENCAPSULATION = 1
    UDP-ENCAPSULATION [RFC 5770]

```

Notify Message Types^{**0}

**

```

class pcapkit.const.hip.notify_message.NotifyMessage (value=<object      object>,
                                                       names=None,  module=None,
                                                       type=None, start=1)

Bases: aenum.IntEnum

[NotifyMessage] Notify Message Types

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

AUTHENTICATION_FAILED = 24
    AUTHENTICATION_FAILED [RFC 7401]

BLOCKED_BY_POLICY = 42
    BLOCKED_BY_POLICY [RFC 7401]

```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#nat-traversal>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-9>

```
CHECKSUM_FAILED = 26
    CHECKSUM_FAILED [RFC 7401]

CONNECTIVITY_CHECKS_FAILED = 61
    CONNECTIVITY_CHECKS_FAILED [RFC 5770]

CREDENTIALS_REQUIRED = 48
    CREDENTIALS_REQUIRED [RFC 8002]

ENCRYPTION_FAILED = 32
    ENCRYPTION_FAILED [RFC 7401]

HIP_MAC_FAILED = 28
    HIP_MAC_FAILED [RFC 7401]

I2_ACKNOWLEDGEMENT = 16384
    I2_ACKNOWLEDGEMENT [RFC 7401]

INVALID_CERTIFICATE = 50
    INVALID_CERTIFICATE [RFC 8002]

INVALID_DH_CHOSEN = 15
    INVALID_DH_CHOSEN [RFC 7401]

INVALID_ESP_TRANSFORM_CHOSEN = 19
    INVALID_ESP_TRANSFORM_CHOSEN [RFC 7402]

INVALID_HIP_CIPHER_CHOSEN = 17
    INVALID_HIP_CIPHER_CHOSEN [RFC 7401]

INVALID_HIT = 40
    INVALID_HIT [RFC 7401]

INVALID_SYNTAX = 7
    INVALID_SYNTAX [RFC 7401]

LOCATOR_TYPE_UNSUPPORTED = 46
    LOCATOR_TYPE_UNSUPPORTED [RFC 8046]

MESSAGE_NOT_RELAYED = 62
    MESSAGE_NOT_RELAYED [RFC 5770]

NO_DH_PROPOSAL_CHOSEN = 14
    NO_DH_PROPOSAL_CHOSEN [RFC 7401]

NO_ESP_PROPOSAL_CHOSEN = 18
    NO_ESP_PROPOSAL_CHOSEN [RFC 7402]

NO_HIP_PROPOSAL_CHOSEN = 16
    NO_HIP_PROPOSAL_CHOSEN [RFC 7401]

NO_VALID_HIP_TRANSPORT_MODE = 100
    NO_VALID_HIP_TRANSPORT_MODE [RFC 6261]

NO_VALID_NAT_TRAVERSAL_MODE_PARAMETER = 60
    NO_VALID_NAT_TRAVERSAL_MODE_PARAMETER [RFC 5770]

OVERLAY_TTL_EXCEEDED = 70
    OVERLAY_TTL_EXCEEDED [RFC 6079]

REG_REQUIRED = 51
    REG_REQUIRED [RFC 8003]
```

```

RESPONDER_BUSY_PLEASE_RETRY = 44
    RESPONDER_BUSY_PLEASE_RETRY [RFC 7401]

Reserved = 0
    Reserved [RFC 7401]

UNKNOWN_NEXT_HOP = 90
    UNKNOWN_NEXT_HOP [RFC 6028]

UNSUPPORTED_CRITICAL_PARAMETER_TYPE = 1
    UNSUPPORTED_CRITICAL_PARAMETER_TYPE [RFC 7401]

UNSUPPORTED_HIT_SUITE = 20
    UNSUPPORTED_HIT_SUITE [RFC 7401]

Unassigned_25 = 25
    Unassigned

Unassigned_27 = 27
    Unassigned

Unassigned_41 = 41
    Unassigned

Unassigned_43 = 43
    Unassigned

Unassigned_45 = 45
    Unassigned

Unassigned_47 = 47
    Unassigned

Unassigned_49 = 49
    Unassigned

```

Packet Types††⁰

††

```

class pcapkit.const.hip.packet.Packet (value=<object object>, names=None, module=None,
                                         type=None, start=1)

```

Bases: aenum.IntEnum

[Packet] HIP Packet Types

```

classmethod _missing_ (value)
    Lookup function used when value is not found.

```

```

static get (key, default=-1)
    Backport support for original codes.

```

```

CLOSE = 18
    CLOSE [RFC 7401] the HIP Association Closing Packet

```

```

CLOSE_ACK = 19
    CLOSE_ACK [RFC 7401] the HIP Closing Acknowledgment Packet

```

```

HDRR = 20
    HDRR [RFC 6537] HIP Distributed Hash Table Resource Record

```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-1>

```
HIP_DATA = 32
    HIP_DATA [RFC 6078]

I1 = 1
    I1 [RFC 7401] the HIP Initiator Packet

I2 = 3
    I2 [RFC 7401] the Second HIP Initiator Packet

NOTIFY = 17
    NOTIFY [RFC 7401] the HIP Notify Packet

R1 = 2
    R1 [RFC 7401] the HIP Responder Packet

R2 = 4
    R2 [RFC 7401] the Second HIP Responder Packet

Reserved = 0
    Reserved [RFC 7401]

UPDATE = 16
    UPDATE [RFC 7401] the HIP Update Packet
```

Parameter Types⁰

¶¶

```
class pcapkit.const.hip.parameter.Parameter (value=<object object>, names=None, module=None, type=None, start=1)
```

Bases: `aenum.IntEnum`

[Parameter] HIP Parameter Types

```
classmethod _missing_ (value)
    Lookup function used when value is not found.
```

```
static get (key, default=-1)
    Backport support for original codes.
```

```
ACK = 449
    ACK [RFC 7401]
```

```
ACK_DATA = 4545
    ACK_DATA [RFC 6078]
```

```
CERT = 768
    CERT [RFC 7401][RFC 8002]
```

```
DH_GROUP_LIST = 511
    DH_GROUP_LIST [RFC 7401]
```

```
DIFFIE_HELLMAN = 513
    DIFFIE_HELLMAN [RFC 7401]
```

```
ECHO_REQUEST_SIGNED = 897
    ECHO_REQUEST_SIGNED [RFC 7401]
```

```
ECHO_REQUEST_UNSIGNED = 63661
    ECHO_REQUEST_UNSIGNED [RFC 7401]
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-4>

```
ECHO_RESPONSE_SIGNED = 961
    ECHO_RESPONSE_SIGNED [RFC 7401]

ECHO_RESPONSE_UNSIGNED = 63425
    ECHO_RESPONSE_UNSIGNED [RFC 7401]

ENCRYPTED = 641
    ENCRYPTED [RFC 7401]

ESP_INFO = 65
    ESP_INFO [RFC 7402] 12

ESP_TRANSFORM = 4095
    ESP_TRANSFORM [RFC 7402]

FROM = 65498
    FROM [RFC 8004] 16

HIP_CIPHER = 579
    HIP_CIPHER [RFC 7401]

HIP_MAC = 61505
    HIP_MAC [RFC 7401]

HIP_MAC_2 = 61569
    HIP_MAC_2 [RFC 7401]

HIP_SIGNATURE = 61697
    HIP_SIGNATURE [RFC 7401]

HIP_SIGNATURE_2 = 61633
    HIP_SIGNATURE_2 [RFC 7401]

HIP_TRANSFORM = 577
    HIP_TRANSFORM [RFC 5201] (v1 only)

HIP_TRANSPORT_MODE = 7680
    HIP_TRANSPORT_MODE [RFC 6261]

HIT_SUITE_LIST = 715
    HIT_SUITE_LIST [RFC 7401]

HOST_ID = 705
    HOST_ID [RFC 7401]

LOCATOR_SET = 193
    LOCATOR_SET [RFC 8046]

NAT_TRAVERSAL_MODE = 608
    NAT_TRAVERSAL_MODE [RFC 5770]

NOTIFICATION = 832
    NOTIFICATION [RFC 7401]

OVERLAY_ID = 4592
    OVERLAY_ID [RFC 6079]

OVERLAY_TTL = 64011
    OVERLAY_TTL [RFC 6079] 4

PAYLOAD_MIC = 4577
    PAYLOAD_MIC [RFC 6078]
```

```
PUZZLE = 257
    PUZZLE [RFC 7401] 12

R1_COUNTER = 129
    R1_COUNTER [RFC 7401] 12

R1_Counter = 128
    R1_Counter [RFC 5201] 12 (v1 only)

REG_FAILED = 936
    REG_FAILED [RFC 8003]

REG_FROM = 950
    REG_FROM [RFC 5770] 20

REG_INFO = 930
    REG_INFO [RFC 8003]

REG_REQUEST = 932
    REG_REQUEST [RFC 8003]

REG_RESPONSE = 934
    REG_RESPONSE [RFC 8003]

RELAY_FROM = 63998
    RELAY_FROM [RFC 5770] 20

RELAY_HMAC = 65520
    RELAY_HMAC [RFC 5770]

RELAY_TO = 64002
    RELAY_TO [RFC 5770] 20

ROUTE_DST = 4601
    ROUTE_DST [RFC 6028]

ROUTE_VIA = 64017
    ROUTE_VIA [RFC 6028]

RVS_HMAC = 65500
    RVS_HMAC [RFC 8004]

SEQ = 385
    SEQ [RFC 7401] 4

SEQ_DATA = 4481
    SEQ_DATA [RFC 6078] 4

SOLUTION = 321
    SOLUTION [RFC 7401] 20

TRANSACTION_ID = 4580
    TRANSACTION_ID [RFC 6078]

TRANSACTION_PACING = 610
    TRANSACTION_PACING [RFC 5770] 4

TRANSPORT_FORMAT_LIST = 2049
    TRANSPORT_FORMAT_LIST [RFC 7401]

Unassigned_512 = 512
    Unassigned
```



```

Unassigned_578 = 578
    Unassigned

Unassigned_609 = 609
    Unassigned

Unassigned_65499 = 65499
    Unassigned

Unassigned_65501 = 65501
    Unassigned

Unassigned_931 = 931
    Unassigned

Unassigned_933 = 933
    Unassigned

Unassigned_935 = 935
    Unassigned

VIA_RVS = 65502
    VIA_RVS [RFC 8004]

```

Registration Types§§⁰

§

```

class pcapkit.const.hip.registration.Registration (value=<object object>,
                                                    names=None,      module=None,
                                                    type=None, start=1)

    Bases: aenum.IntEnum

    [Registration] Registration Types

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    RELAY_UDP_HIP = 2
        RELAY_UDP_HIP [RFC 5770]

    RENDEZVOUS = 1
        RENDEZVOUS [RFC 8004]

    Unassigned = 0
        Unassigned

```

¹⁵⁹ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-11>

Registration Failure Types⁰

¶¶

```
class pcapkit.const.hip.registration_failure.RegistrationFailure (value=<object
                                                                    object>,
                                                                    names=None,
                                                                    mod-
                                                                    ule=None,
                                                                    type=None,
                                                                    start=1)
```

Bases: aenum.IntEnum

[RegistrationFailure] Registration Failure Types

```
classmethod _missing_ (value)
    Lookup function used when value is not found.
```

```
static get (key, default=- 1)
    Backport support for original codes.
```

```
Bad_certificate = 4
    Bad certificate [RFC 8003]
```

```
Certificate_expired = 6
    Certificate expired [RFC 8003]
```

```
Certificate_other = 7
    Certificate other [RFC 8003]
```

```
Insufficient_resources = 2
    Insufficient resources [RFC 8003]
```

```
Invalid_certificate = 3
    Invalid certificate [RFC 8003]
```

```
Registration_requires_additional_credentials = 0
    Registration requires additional credentials [RFC 8003]
```

```
Registration_type_unavailable = 1
    Registration type unavailable [RFC 8003]
```

```
Unknown_CA = 8
    Unknown CA [RFC 8003]
```

```
Unsupported_certificate = 5
    Unsupported certificate [RFC 8003]
```

Suite IDs³⁵

```
class pcapkit.const.hip.suite.Suite (value=<object object>, names=None, module=None,
                                                                    type=None, start=1)
```

Bases: aenum.IntEnum

[Suite] Suite IDs

```
classmethod _missing_ (value)
    Lookup function used when value is not found.
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-13>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-6>

```

static get (key, default=- 1)
    Backport support for original codes.

AES_CBC_with_HMAC_SHA1 = 1
    AES-CBC with HMAC-SHA1 [RFC 5201]

BLOWFISH_CBC_with_HMAC_SHA1 = 4
    BLOWFISH-CBC with HMAC-SHA1 [RFC 5201]

NULL_ENCRYPT_with_HMAC_MD5 = 6
    NULL-ENCRYPT with HMAC-MD5 [RFC 5201]

NULL_ENCRYPT_with_HMAC_SHA1 = 5
    NULL-ENCRYPT with HMAC-SHA1 [RFC 5201]

Reserved = 0
    Reserved [RFC 5201]

Suite_3DES_CBC_with_HMAC_MD5 = 3
    3DES-CBC with HMAC-MD5 [RFC 5201]

Suite_3DES_CBC_with_HMAC_SHA1 = 2
    3DES-CBC with HMAC-SHA1 [RFC 5201]

```

HIP Transport Modes⁰

```

class pcapkit.const.hip.transport.Transport (value=<object object>, names=None, mod-
                                              ule=None, type=None, start=1)

    Bases: aenum.IntEnum

    [Transport] HIP Transport Modes

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    DEFAULT = 1
        DEFAULT [RFC 6261]

    ESP = 2
        ESP [RFC 6261]

    ESP_TCP = 3
        ESP-TCP [RFC 6261]

    RESERVED = 0
        RESERVED [RFC 6261]

```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#transport-modes>

1.9.4 HTTP Constant Enumerations

HTTP/2 Error Code^{*0}

*

```
class pcapkit.const.http.error_code.ErrorCode(value=<object object>, names=None,  
                                              module=None, type=None, start=1)
```

Bases: aenum.IntEnum

[ErrorCode] HTTP/2 Error Code

classmethod **_missing_**(value)

Lookup function used when value is not found.

static get(key, default=-1)

Backport support for original codes.

CANCEL = 8

desc

COMPRESSION_ERROR = 9

desc

CONNECT_ERROR = 10

desc

ENHANCE_YOUR_CALM = 11

desc

FLOW_CONTROL_ERROR = 3

desc

FRAME_SIZE_ERROR = 6

desc

HTTP_1_1_REQUIRED = 13

desc

INADEQUATE_SECURITY = 12

desc

INTERNAL_ERROR = 2

desc

NO_ERROR = 0

desc

PROTOCOL_ERROR = 1

desc

REFUSED_STREAM = 7

desc

SETTINGS_TIMEOUT = 4

desc

STREAM_CLOSED = 5

desc

⁰ <https://www.iana.org/assignments/http2-parameters/http2-parameters.xhtml#error-code>

HTTP/2 Frame Type†⁰

†

```

class pcapkit.const.http.frame.Frame (value=<object object>, names=None, module=None,
                                         type=None, start=1)
    Bases: aenum.IntEnum
    [Frame] HTTP/2 Frame Type

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    ALTSVC = 10
        ALTSVC [:rfc:`7838, Section 4`]

    CONTINUATION = 9
        CONTINUATION [:rfc:`7540, Section 6.10`]

    DATA = 0
        DATA [:rfc:`7540, Section 6.1`]

    GOAWAY = 7
        GOAWAY [:rfc:`7540, Section 6.8`]

    HEADERS = 1
        HEADERS [:rfc:`7540, Section 6.2`]

    ORIGIN = 12
        ORIGIN [RFC 8336]

    PING = 6
        PING [:rfc:`7540, Section 6.7`]

    PRIORITY = 2
        PRIORITY [:rfc:`7540, Section 6.3`]

    PUSH_PROMISE = 5
        PUSH_PROMISE [:rfc:`7540, Section 6.6`]

    RST_STREAM = 3
        RST_STREAM [:rfc:`7540, Section 6.4`]

    SETTINGS = 4
        SETTINGS [:rfc:`7540, Section 6.5`]

    Unassigned = 11
        Unassigned

    WINDOW_UPDATE = 8
        WINDOW_UPDATE [:rfc:`7540, Section 6.9`]

```

⁰ <https://www.iana.org/assignments/http2-parameters/http2-parameters.xhtml#frame-type>

HTTP/2 Settings⁰

⌘

```
class pcapkit.const.http.setting.Setting (value=<object object>, names=None, module=None, type=None, start=1)
    Bases: aenum.IntEnum
    [Setting] HTTP/2 Settings
    classmethod _missing_ (value)
        Lookup function used when value is not found.
    static get (key, default=- 1)
        Backport support for original codes.
    ENABLE_PUSH = 2
        ENABLE_PUSH [:rfc:`7540, Section 6.5.2`] 1
    HEADER_TABLE_SIZE = 1
        HEADER_TABLE_SIZE [:rfc:`7540, Section 6.5.2`] 4096
    INITIAL_WINDOW_SIZE = 4
        INITIAL_WINDOW_SIZE [:rfc:`7540, Section 6.5.2`] 65535
    MAX_CONCURRENT_STREAMS = 3
        MAX_CONCURRENT_STREAMS [:rfc:`7540, Section 6.5.2`] infinite
    MAX_FRAME_SIZE = 5
        MAX_FRAME_SIZE [:rfc:`7540, Section 6.5.2`] 16384
    MAX_HEADER_LIST_SIZE = 6
        MAX_HEADER_LIST_SIZE [:rfc:`7540, Section 6.5.2`] infinite
    Reserved = 0
        Reserved [RFC 7540]
    SETTINGS_ENABLE_CONNECT_PROTOCOL = 8
        SETTINGS_ENABLE_CONNECT_PROTOCOL [RFC 8441] 0
    TLS_RENEG_PERMITTED = 16
        TLS_RENEG_PERMITTED [MS-HTTP2E][Gabriel Montenegro] 0x00
    Unassigned = 7
        Unassigned
```

1.9.5 IPv4 Constant Enumerations

Classification Level Encodings

```
class pcapkit.const.ipv4.classification_level.ClassificationLevel (value=<object object>,
                                                                    names=None,
                                                                    module=None,
                                                                    type=None,
                                                                    start=1)
    Bases: aenum.IntEnum
```

⁰ <https://www.iana.org/assignments/http2-parameters/http2-parameters.xhtml#settings>

[ClassificationLevel] Classification Level Encodings

```

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=-1)
    Backport support for original codes.

Confidential = 150
Reserved_1 = 241
Reserved_2 = 204
Reserved_3 = 102
Reserved_4 = 1
Secret = 90
Top_Secret = 61
Unclassified = 171

```

Option Classes

```

class pcapkit.const.ipv4.option_class.OptionClass (value=<object object>,
                                                    names=None, module=None,
                                                    type=None, start=1)

    Bases: aenum.IntEnum

    [OptionClass] Option Classes

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=-1)
        Backport support for original codes.

    control = 0
    debugging_and_measurement = 2
    reserved_for_future_use_1 = 1
    reserved_for_future_use_3 = 3

```

IP Option Numbers^{*0}

*

```

class pcapkit.const.ipv4.option_number.OptionNumber (value=<object object>,
                                                         names=None, module=None,
                                                         type=None, start=1)

    Bases: aenum.IntEnum

    [OptionNumber] IP Option Numbers

    classmethod _missing_ (value)
        Lookup function used when value is not found.

```

⁰ <https://www.iana.org/assignments/ip-parameters/ip-parameters.xhtml#ip-parameters-1>

static get (*key, default=- 1*)
Backport support for original codes.

ADDEXT = 147
ADDEXT - Address Extension [Ullmann IPv7][[RFC 6814](#)]

CIPSO = 134
CIPSO - Commercial Security [draft-ietf-cipso-ipsecurity-01]

DPS = 151
DPS - Dynamic Packet State [Andy Malis][[RFC 6814](#)]

EIP = 145
EIP - Extended Internet Protocol [[RFC 1385](#)][[RFC 6814](#)]

ENCODE = 15
ENCODE [VerSteeg][[RFC 6814](#)]

EOOL = 0
EOOL - End of Options List [[RFC 791](#)][Jon Postel]

EXP_158 = 158
EXP - RFC3692-style Experiment [[RFC 4727](#)]

EXP_222 = 222
EXP - RFC3692-style Experiment [[RFC 4727](#)]

EXP_30 = 30
EXP - RFC3692-style Experiment [[RFC 4727](#)]

EXP_94 = 94
EXP - RFC3692-style Experiment [[RFC 4727](#)]

E_SEC = 133
E-SEC - Extended Security [[RFC 1108](#)]

FINN = 205
FINN - Experimental Flow Control [Greg Finn]

IMITD = 144
IMITD - IMI Traffic Descriptor [Lee]

LSR = 131
LSR - Loose Source Route [[RFC 791](#)][Jon Postel]

MTUP = 11
MTUP - MTU Probe [[RFC 1063](#)][[RFC 1191](#)]

MTUR = 12
MTUR - MTU Reply [[RFC 1063](#)][[RFC 1191](#)]

NOP = 1
NOP - No Operation [[RFC 791](#)][Jon Postel]

QS = 25
QS - Quick-Start [[RFC 4782](#)]

RR = 7
RR - Record Route [[RFC 791](#)][Jon Postel]

RTRALT = 148
RTRALT - Router Alert [[RFC 2113](#)]

SDB = 149
 SDB - Selective Directed Broadcast [Charles Bud Graff][[RFC 6814](#)]
SEC = 130
 SEC - Security [[RFC 1108](#)]
SID = 136
 SID - Stream ID [[RFC 791](#)][Jon Postel][[RFC 6814](#)]
SSR = 137
 SSR - Strict Source Route [[RFC 791](#)][Jon Postel]
TR = 82
 TR - Traceroute [[RFC 1393](#)][[RFC 6814](#)]
TS = 68
 TS - Time Stamp [[RFC 791](#)][Jon Postel]
UMP = 152
 UMP - Upstream Multicast Pkt. [Dino Farinacci][[RFC 6814](#)]
Unassigned_150 = 150
 Unassigned (Released 18 October 2005)
VISA = 142
 VISA - Experimental Access Control [Deborah Estrin][[RFC 6814](#)]
ZSU = 10
 ZSU - Experimental Measurement [ZSu]

Protection Authority Bit Assignments

```

class pcapkit.const.ipv4.protection_authority.ProtectionAuthority (value=<object
                                object>,
                                names=None,
                                mod-
                                ule=None,
                                type=None,
                                start=1)

Bases: aenum.IntEnum

[ProtectionAuthority] Protection Authority Bit Assignments

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

DOE = 4

Field_Termination_Indicator = 7

GENSER = 0

NSA = 3

SCI = 2

SIOP_ESI = 1

Unassigned_5 = 5
  
```

Unassigned_6 = 6

QS Functions

```
class pcapkit.const.ipv4.qs_function.QSFunction (value=<object object>, names=None,
                                                module=None, type=None, start=1)

Bases: aenum.IntEnum

[QSFunction] QS Functions

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

Quick_Start_Request = 0

Report_of_Approved_Rate = 8
```

IPv4 Router Alert Option Values†⁰

†

```
class pcapkit.const.ipv4.router_alert.RouterAlert (value=<object object>,
                                                    names=None,      module=None,
                                                    type=None, start=1)

Bases: aenum.IntEnum

[RouterAlert] IPv4 Router Alert Option Values

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

Aggregated_Reservation_Nesting_Level_0 = 1
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_1 = 2
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_10 = 11
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_11 = 12
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_12 = 13
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_13 = 14
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_14 = 15
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_15 = 16
    Aggregated Reservation Nesting Level [RFC 3175]
```

⁰ <https://www.iana.org/assignments/ip-parameters/ip-parameters.xhtml#ipv4-router-alert-option-values>

Aggregated_Reservation_Nesting_Level_16 = 17
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_17 = 18
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_18 = 19
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_19 = 20
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_2 = 3
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_20 = 21
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_21 = 22
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_22 = 23
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_23 = 24
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_24 = 25
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_25 = 26
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_26 = 27
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_27 = 28
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_28 = 29
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_29 = 30
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_3 = 4
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_30 = 31
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_31 = 32
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_4 = 5
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_5 = 6
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_6 = 7
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_7 = 8
Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_8 = 9
Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_9 = 10
Aggregated Reservation Nesting Level [RFC 3175]

NSIS_NATFW_NSLP = 65
NSIS NATFW NSLP [RFC 5973]

QoS_NSLP_Aggregation_Level_0 = 33
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_1 = 34
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_10 = 43
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_11 = 44
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_12 = 45
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_13 = 46
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_14 = 47
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_15 = 48
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_16 = 49
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_17 = 50
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_18 = 51
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_19 = 52
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_2 = 35
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_20 = 53
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_21 = 54
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_22 = 55
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_23 = 56
QoS NSLP Aggregation Levels 0-31 [RFC 5974]

```

QoS_NSLP_Aggregation_Level_24 = 57
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_25 = 58
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_26 = 59
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_27 = 60
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_28 = 61
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_29 = 62
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_3 = 36
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_30 = 63
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_31 = 64
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_4 = 37
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_5 = 38
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_6 = 39
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_7 = 40
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_8 = 41
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

QoS_NSLP_Aggregation_Level_9 = 42
    QoS NSLP Aggregation Levels 0-31 [RFC 5974]

Reserved = 65535
    Reserved [RFC 5350]

```

ToS (DS Field) Delay

```

class pcapkit.const.ipv4.tos_del.ToSDelay (value=<object object>, names=None, mod-
                                         ile=None, type=None, start=1)

    Bases: aenum.IntEnum

    [ToSDelay] ToS (DS Field) Delay

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    LOW = 1

```

NORMAL = 0

ToS ECN Field

```
class pcapkit.const.ipv4.tos_ecn.ToSECN(value=<object object>, names=None, module=None, type=None, start=1)

Bases: aenum.IntEnum

[ToSECN] ToS ECN Field

classmethod _missing_(value)
    Lookup function used when value is not found.

static get(key, default=-1)
    Backport support for original codes.

CE = 3

ECT_0b01 = 1

ECT_0b10 = 2

Not_ECT = 0
```

ToS (DS Field) Precedence

```
class pcapkit.const.ipv4.tos_pre.ToSPrecedence(value=<object object>, names=None, module=None, type=None, start=1)

Bases: aenum.IntEnum

[ToSPrecedence] ToS (DS Field) Precedence

classmethod _missing_(value)
    Lookup function used when value is not found.

static get(key, default=-1)
    Backport support for original codes.

CRITIC_ECP = 5

Flash = 3

Flash_Override = 4

Immediate = 2

Internetnetwork_Control = 6

Network_Control = 7

Priority = 1

Routine = 0
```

ToS (DS Field) Reliability

```

class pcapkit.const.ipv4.tos_rel.ToSReliability (value=<object object>, names=None,
                                                module=None, type=None, start=1)

    Bases: aenum.IntEnum

    [ToSReliability] ToS (DS Field) Reliability

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    HIGH = 1

    NORMAL = 0

```

ToS (DS Field) Throughput

```

class pcapkit.const.ipv4.tos_thr.ToSThroughput (value=<object object>, names=None,
                                                module=None, type=None, start=1)

    Bases: aenum.IntEnum

    [ToSThroughput] ToS (DS Field) Throughput

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    HIGH = 1

    NORMAL = 0

```

1.9.6 IPv6 Constant Enumerations

IPv6 Extension Header Types^{*0}

*

```

class pcapkit.const.ipv6.extension_header.ExtensionHeader (value=<object object>,
                                                            names=None, module=None,
                                                            type=None, start=1)

    Bases: aenum.IntEnum

    [ExtensionHeader] IPv6 Extension Header Types

    static get (key, default=- 1)
        Backport support for original codes.

    AH = 51
        AH [RFC 4302] Authentication Header

    ESP = 50
        ESP [RFC 4303] Encap Security Payload

```

⁰ <https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters.xhtml#extension-header>

HIP = 139
HIP [RFC 7401] Host Identity Protocol

HOPOPT = 0
HOPOPT [RFC 8200] IPv6 Hop-by-Hop Option

IPv6_Frag = 44
IPv6-Frag [Steve Deering] Fragment Header for IPv6

IPv6_Opts = 60
IPv6-Opts [RFC 8200] Destination Options for IPv6

IPv6_Route = 43
IPv6-Route [Steve Deering] Routing Header for IPv6

Mobility_Header = 135
Mobility Header [RFC 6275]

Shim6 = 140
Shim6 [RFC 5533] Shim6 Protocol

Use_for_experimentation_and_testing_253 = 253
Use for experimentation and testing [RFC 3692]

Use_for_experimentation_and_testing_254 = 254
Use for experimentation and testing [RFC 3692]

Destination Options and Hop-by-Hop Options†⁰

†

```
class pcapkit.const.ipv6.option.Option (value=<object object>, names=None, module=None, type=None, start=1)

Bases: aenum.IntEnum

[Option] Destination Options and Hop-by-Hop Options

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

CALIPSO = 7
    CALIPSO [RFC 5570]

DEPRECATED = 138
    DEPRECATED [CHARLES LYNN]

Deprecated = 77
    Deprecated [RFC 7731]

HOME = 201
    HOME [RFC 6275]

ILNP = 139
    ILNP [RFC 6744]

IOAM_TEMPORARY_registered_2020_04_16_expires_2021_04_16_0x11 = 17
    IOAM TEMPORARY - registered 2020-04-16, expires 2021-04-16 [draft-ietf-ippm-ioam-ipv6-options]
```

⁰ <https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters.xhtml#ipv6-parameters-2>

IOAM_TEMPORARY_registered_2020_04_16_expires_2021_04_16_0x31 = 49
 IOAM TEMPORARY - registered 2020-04-16, expires 2021-04-16 [draft-ietf-ippm-ioam-ipv6-options]

IP_DFF = 238
 IP_DFF [RFC 6971]

JUMBO = 194
 JUMBO [RFC 2675]

LIO = 140
 LIO [RFC 6788]

MPL = 109
 MPL [RFC 7731]

PAD = 0
 PAD [IPV6]

PADN = 1
 PADN [IPV6]

PDM = 15
 PDM [RFC 8250]

Path_MTU_Record_Option_TEMPORARY_registered_2019_09_03_expires_2020_09_03 = 48
 Path MTU Record Option TEMPORARY - registered 2019-09-03, expires 2020-09-03 [draft-ietf-6man-mtu-option]

QS = 38
 QS [RFC 4782][RFC Errata 2034]

RA = 5
 RA [RFC 2711]

RFC3692_style_Experiment_0x1E = 30
 RFC3692-style Experiment [RFC 4727]

RFC3692_style_Experiment_0x3E = 62
 RFC3692-style Experiment [RFC 4727]

RFC3692_style_Experiment_0x5E = 94
 RFC3692-style Experiment [RFC 4727]

RFC3692_style_Experiment_0x7E = 126
 RFC3692-style Experiment [RFC 4727]

RFC3692_style_Experiment_0x9E = 158
 RFC3692-style Experiment [RFC 4727]

RFC3692_style_Experiment_0xBE = 190
 RFC3692-style Experiment [RFC 4727]

RFC3692_style_Experiment_0xDE = 222
 RFC3692-style Experiment [RFC 4727]

RFC3692_style_Experiment_0xFE = 254
 RFC3692-style Experiment [RFC 4727]

RPL_0x63 = 99
 RPL [RFC 6553][RFC-ietf-roll-useofrplinfo-31]

RPL_Option_0x23 = 35
 RPL Option [RFC-ietf-roll-useofrplinfo-31]

```
SMF_DPD = 8
    SMF_DPD [RFC 6621]

TUN = 4
    TUN [RFC 2473]
```

IPv6 QS Functions

```
class pcapkit.const.ipv6.qs_function.QSFunction (value=<object object>, names=None,
                                                module=None, type=None, start=1)

Bases: aenum.IntEnum

[QSFunction] QS Functions

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

Quick_Start_Request = 0

Report_of_Approved_Rate = 8
```

IPv6 Router Alert Option Values†⁰

‡

```
class pcapkit.const.ipv6.router_alert.RouterAlert (value=<object object>,
                                                    names=None, module=None,
                                                    type=None, start=1)

Bases: aenum.IntEnum

[RouterAlert] IPv6 Router Alert Option Values

classmethod _missing_ (value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

Aggregated_Reservation_Nesting_Level_0 = 4
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_1 = 5
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_10 = 14
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_11 = 15
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_12 = 16
    Aggregated Reservation Nesting Level [RFC 3175]

Aggregated_Reservation_Nesting_Level_13 = 17
    Aggregated Reservation Nesting Level [RFC 3175]
```

⁰ <https://www.iana.org/assignments/ipv6-routeralert-values/ipv6-routeralert-values.xhtml#ipv6-routeralert-values-1>

Aggregated_Reservation_Nesting_Level_14 = 18
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_15 = 19
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_16 = 20
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_17 = 21
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_18 = 22
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_19 = 23
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_2 = 6
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_20 = 24
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_21 = 25
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_22 = 26
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_23 = 27
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_24 = 28
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_25 = 29
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_26 = 30
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_27 = 31
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_28 = 32
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_29 = 33
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_3 = 7
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_30 = 34
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_31 = 35
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_4 = 8
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_5 = 9
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_6 = 10
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_7 = 11
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_8 = 12
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Aggregated_Reservation_Nesting_Level_9 = 13
Aggregated Reservation Nesting Level [\[RFC 3175\]](#)

Datagram_contains_RSVP_message = 1
Datagram contains RSVP message [\[RFC 2711\]](#)

Datagram_contains_a_Multicast_Listener_Discovery_message = 0
Datagram contains a Multicast Listener Discovery message [\[RFC 2710\]](#)

Datagram_contains_an_Active_Networks_message = 2
Datagram contains an Active Networks message [\[RFC 2711\]](#)

MPLS_OAM = 69
MPLS OAM [\[RFC 7506\]](#)

NSIS_NATFW_NSLP = 68
NSIS NATFW NSLP [\[RFC 5973\]](#)

QoS_NSLP_Aggregation_Level_0 = 36
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_1 = 37
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_10 = 46
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_11 = 47
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_12 = 48
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_13 = 49
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_14 = 50
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_15 = 51
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_16 = 52
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_17 = 53
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_18 = 54
QoS NSLP Aggregation Levels 0-31 [\[RFC 5974\]](#)

QoS_NSLP_Aggregation_Level_19 = 55
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_2 = 38
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_20 = 56
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_21 = 57
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_22 = 58
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_23 = 59
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_24 = 60
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_25 = 61
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_26 = 62
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_27 = 63
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_28 = 64
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_29 = 65
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_3 = 39
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_30 = 66
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_31 = 67
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_4 = 40
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_5 = 41
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_6 = 42
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_7 = 43
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_8 = 44
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

QoS_NSLP_Aggregation_Level_9 = 45
QoS NSLP Aggregation Levels 0-31 [[RFC 5974](#)]

Reserved_3 = 3
Reserved [RFC 5350]

Reserved_65535 = 65535
Reserved [The Internet Assigned Numbers Authority]

Routing Types⁰

```
class pcapkit.const.ipv6.routing.Routing(value=<object object>, names=None, module=None, type=None, start=1)

Bases: aenum.IntEnum

[Routing] IPv6 Routing Types

classmethod _missing_(value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

Nimrod = 1
    Nimrod DEPRECATED 2009-05-06

RFC3692_style_Experiment_1 = 253
    RFC3692-style Experiment 1 [RFC 4727]

RFC3692_style_Experiment_2 = 254
    RFC3692-style Experiment 2 [RFC 4727]

RPL_Source_Route_Header = 3
    RPL Source Route Header [RFC 6554]

Reserved = 255
    Reserved

Segment_Routing_Header = 4
    Segment Routing Header [RFC 8754] SRH

Source_Route = 0
    Source Route [IPV6][RFC 5095] DEPRECATED

Type_2_Routing_Header = 2
    Type 2 Routing Header [RFC 6275]
```

Seed-ID Types

```
class pcapkit.const.ipv6.seed_id.SeedID(value=<object object>, names=None, module=None, type=None, start=1)

Bases: aenum.IntEnum

[SeedID] Seed-ID Types

classmethod _missing_(value)
    Lookup function used when value is not found.

static get (key, default=- 1)
    Backport support for original codes.

IPV6_SOURCE_ADDRESS = 0
```

¹⁵⁹ <https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters.xhtml#ipv6-parameters-3>

```
SEEDID_128_BIT_UNSIGNED_INTEGER = 3
SEEDID_16_BIT_UNSIGNED_INTEGER = 1
SEEDID_64_BIT_UNSIGNED_INTEGER = 2
```

TaggerId Types⁰

¶

```
class pcapkit.const.ipv6.tagger_id.TaggerID (value=<object object>, names=None, module=None, type=None, start=1)
```

Bases: aenum.IntEnum

[TaggerID] TaggerID Types

classmethod **_missing_** (value)

Lookup function used when value is not found.

static **get** (key, default=- 1)

Backport support for original codes.

DEFAULT = 1

DEFAULT [RFC 6621]

IPv4 = 2

IPv4 [RFC 6621]

IPv6 = 3

IPv6 [RFC 6621]

NULL = 0

NULL [RFC 6621]

1.9.7 IPX Constant Enumerations

IPX Packet Types^{*0}

*

```
class pcapkit.const.ipx.packet.Packet (value=<object object>, names=None, module=None, type=None, start=1)
```

Bases: aenum.IntEnum

[Packet] IPX Packet Types

classmethod **_missing_** (value)

Lookup function used when value is not found.

static **get** (key, default=- 1)

Backport support for original codes.

Echo_Packet = 2

Echo Packet

Error_Packet = 3

Error Packet

⁰ <https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters.xhtml#taggerId-types>

⁰ https://en.wikipedia.org/wiki/Internetwork_Packet_Exchange#IPX_packet_structure

NCP = 17
NCP - NetWare Core Protocol

PEP = 4
PEP - Packet Exchange Protocol, used for SAP (Service Advertising Protocol)

RIP = 1
RIP - Routing Information Protocol ([[RFC 1582](#)], [[RFC 2091](#)])

SPX = 5
SPX - Sequenced Packet Exchange

Unknown = 0
Unknown

IPX Socket Types[†]

†

class pcapkit.const.ipx.socket.**Socket** (*value=<object object>, names=None, module=None, type=None, start=1*)

Bases: aenum.IntEnum

[Socket] Socket Types

classmethod **_missing_** (*value*)
Lookup function used when value is not found.

static **get** (*key, default=-1*)
Backport support for original codes.

Diagnostic_Packet = 1110
Diagnostic Packet

Echo_Protocol_Packet = 2
Echo Protocol Packet

Error_Handling_Packet = 3
Error Handling Packet

IPX = 32864
IPX

IPXF = 37011
IPXF - IPX Fragmentation Protocol

NetBIOS = 1109
NetBIOS

NetWare_Core_Protocol = 1105
NetWare Core Protocol - NCP – used by Novell NetWare servers

Routing_Information_Packet = 1
Routing Information Packet

Routing_Information_Protocol = 1107
Routing Information Protocol - RIP

Serialization_Packet = 1111
Serialization Packet - used for NCP as well

⁰ https://en.wikipedia.org/wiki/Internetwork_Packet_Exchange#Socket_number


```

Service_Advertising_Protocol = 1106
    Service Advertising Protocol - SAP

TCP_over_IPXF = 37009
    TCP over IPXF

UDP_over_IPXF = 37010
    UDP over IPXF

Used_by_Novell_NetWare_Client = 16387
    Used by Novell NetWare Client

```

1.9.8 MH Constant Enumerations

Mobility Header Types^{*0}

*

```

class pcapkit.const.mh.packet.Packet (value=<object object>, names=None, module=None,
                                         type=None, start=1)
    Bases: aenum.IntEnum

    [Packet] Mobility Header Types - for the MH Type field in the Mobility Header

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    Binding_Acknowledgement = 6
        Binding Acknowledgement [RFC 6275]

    Binding_Error = 7
        Binding Error [RFC 6275]

    Binding_Refresh_Request = 0
        Binding Refresh Request [RFC 6275]

    Binding_Revocation_Message = 16
        Binding Revocation Message [RFC 5846]

    Binding_Update = 5
        Binding Update [RFC 6275]

    Care_of_Test = 4
        Care-of Test [RFC 6275]

    Care_of_Test_Init = 2
        Care-of Test Init [RFC 6275]

    Experimental_Mobility_Header = 11
        Experimental Mobility Header [RFC 5096]

    Fast_Binding_Acknowledgment = 9
        Fast Binding Acknowledgment [RFC 5568]

    Fast_Binding_Update = 8
        Fast Binding Update [RFC 5568]

```

⁰ <https://www.iana.org/assignments/mobility-parameters/mobility-parameters.xhtml#mobility-parameters-1>

Fast_Neighbor_Advertisement = 10
Fast Neighbor Advertisement [RFC 5568] (Deprecated)

Flow_Binding_Message = 21
Flow Binding Message [RFC 7109]

Handover_Acknowledge_Message = 15
Handover Acknowledge Message [RFC 5568]

Handover_Initiate_Message = 14
Handover Initiate Message [RFC 5568]

Heartbeat_Message = 13
Heartbeat Message [RFC 5847]

Home_Agent_Switch_Message = 12
Home Agent Switch Message [RFC 5142]

Home_Test = 3
Home Test [RFC 6275]

Home_Test_Init = 1
Home Test Init [RFC 6275]

Localized_Routing_Acknowledgment = 18
Localized Routing Acknowledgment [RFC 6705]

Localized_Routing_Initiation = 17
Localized Routing Initiation [RFC 6705]

Subscription_Query = 22
Subscription Query [RFC 7161]

Subscription_Response = 23
Subscription Response [RFC 7161]

Update_Notification = 19
Update Notification [RFC 7077]

Update_Notification_Acknowledgement = 20
Update Notification Acknowledgement [RFC 7077]

1.9.9 OSPF Constant Enumerations

Authentication Codes^{*0}

*

```
class pcapkit.const.ospf.authentication.Authentication (value=<object object>,
                                                         names=None,      mod-
                                                         ule=None,      type=None,
                                                         start=1)

Bases: aenum.IntEnum

[Authentication] Authentication Types

classmethod _missing_ (value)
    Lookup function used when value is not found.
```

⁰ <https://www.iana.org/assignments/ospf-authentication-codes/ospf-authentication-codes.xhtml#authentication-codes>

```

static get (key, default=- 1)
    Backport support for original codes.

Cryptographic_Authentication_with_Extended_Sequence_Numbers = 3
    Cryptographic Authentication with Extended Sequence Numbers [RFC 7474]

Cryptographic_authentication = 2
    Cryptographic authentication [RFC 2328][RFC 5709]

No_Authentication = 0
    No Authentication [RFC 1583]

Simple_Password_Authentication = 1
    Simple Password Authentication [RFC 1583]

```

OSPF Packet Type†⁰

†

```

class pcapkit.const.ospf.packet.Packet (value=<object object>, names=None, module=None, type=None, start=1)

    Bases: aenum.IntEnum

    [Packet] OSPF Packet Types

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=- 1)
        Backport support for original codes.

    Database_Description = 2
        Database Description [RFC 2328]

    Hello = 1
        Hello [RFC 2328]

    Link_State_Ack = 5
        Link State Ack [RFC 2328]

    Link_State_Request = 3
        Link State Request [RFC 2328]

    Link_State_Update = 4
        Link State Update [RFC 2328]

    Reserved = 0
        Reserved

```

⁰ <https://www.iana.org/assignments/ospfv2-parameters/ospfv2-parameters.xhtml#ospfv2-parameters-3>

1.9.10 Protocol Type Registry Constant Enumerations

LINK-LAYER HEADER TYPES^{*0}

*

```
class pcapkit.const.reg.linktype.LinkType (value=<object object>, names=None, module=None, type=None, start=1)
```

Bases: aenum.IntEnum

[LinkType] Link-Layer Header Type Values

```
classmethod _missing_ (value)  
    Lookup function used when value is not found.
```

```
static get (key, default=-1)  
    Backport support for original codes.
```

```
APPLE_IP_OVER_IEEE1394 = 138  
    DLT_APPLE_IP_OVER_IEEE1394
```

```
ARCNET_BSD = 7  
    DLT_ARCNET
```

```
ARCNET_LINUX = 129  
    DLT_ARCNET_LINUX
```

```
ATM_RFC1483 = 100  
    DLT_ATM_RFC1483
```

```
ATSC_ALP = 289  
    DLT_ATSC_ALP
```

```
AX25 = 3  
    DLT_AX25
```

```
AX25_KISS = 202  
    DLT_AX25_KISS
```

```
BACNET_MS_TP = 165  
    DLT_BACNET_MS_TP
```

```
BLUETOOTH_BREDR_BB = 255  
    DLT_BLUETOOTH_BREDR_BB
```

```
BLUETOOTH_HCI_H4 = 187  
    DLT_BLUETOOTH_HCI_H4
```

```
BLUETOOTH_HCI_H4_WITH_PHDR = 201  
    DLT_BLUETOOTH_HCI_H4_WITH_PHDR
```

```
BLUETOOTH_LE_LL = 251  
    DLT_BLUETOOTH_LE_LL
```

```
BLUETOOTH_LE_LL_WITH_PHDR = 256  
    DLT_BLUETOOTH_LE_LL_WITH_PHDR
```

```
BLUETOOTH_LINUX_MONITOR = 254  
    DLT_BLUETOOTH_LINUX_MONITOR
```

```
CAN_SOCKETCAN = 227  
    DLT_CAN_SOCKETCAN
```

⁰ <http://www.tcpdump.org/linktypes.html>

```
C_HDLC = 104
    DLT_C_HDLC

C_HDLC_WITH_DIR = 205
    DLT_C_HDLC_WITH_DIR

DBUS = 231
    DLT_DBUS

DISPLAYPORT_AUX = 275
    DLT_DISPLAYPORT_AUX

DOCSIS = 143
    DLT_DOCSIS

DOCSIS31_XRA31 = 273
    DLT_DOCSIS31_XRA31

DSA_TAG_BRCM = 281
    DLT_DSA_TAG_BRCM

DSA_TAG_BRCM_PREPEND = 282
    DLT_DSA_TAG_BRCM_PREPEND

DSA_TAG_DSA = 284
    DLT_DSA_TAG_DSA

DSA_TAG_EDSA = 285
    DLT_DSA_TAG_EDSA

DVB_CI = 235
    DLT_DVB_CI

EBHSCR = 279
    DLT_EBHSCR

ELEE = 286
    DLT_ELEE

EPON = 259
    DLT_EPON

ERF = 197
    DLT_ERF

ETHERNET = 1
    DLT_EN10MB

ETHERNET_MPACKET = 274
    DLT_ETHERNET_MPACKET

FC_2 = 224
    DLT_FC_2

FC_2_WITH_FRAME_DELIMS = 225
    DLT_FC_2_WITH_FRAME_DELIMS

FDDI = 10
    DLT_FDDI

FRELAY = 107
    DLT_FRELAY
```

```
FRELAY_WITH_DIR = 206
    DLT_FRELAY_WITH_DIR

GPF_F = 171
    DLT_GPF_F

GPF_T = 170
    DLT_GPF_T

GPRS_LLC = 169
    DLT_GPRS_LLC

IEEE802_11 = 105
    DLT_IEEE802_11

IEEE802_11_AVS = 163
    DLT_IEEE802_11_RADIO_AVS

IEEE802_11_PRISM = 119
    DLT_PRISM_HEADER

IEEE802_11_RADIOTAP = 127
    DLT_IEEE802_11_RADIO

IEEE802_15_4_NOFCS = 230
    DLT_IEEE802_15_4_NOFCS

IEEE802_15_4_NONASK_PHY = 215
    DLT_IEEE802_15_4_NONASK_PHY

IEEE802_15_4_TAP = 283
    DLT_IEEE802_15_4_TAP

IEEE802_15_4_WITHFCS = 195
    DLT_IEEE802_15_4_WITHFCS

IEEE802_5 = 6
    DLT_IEEE802

INFINIBAND = 247
    DLT_INFINIBAND

IPMB_LINUX = 209
    DLT_IPMB_LINUX

IPMI_HPM_2 = 260
    DLT_IPMI_HPM_2

IPNET = 226
    DLT_IPNET

IPOIB = 242
    DLT_IPOIB

IPV4 = 228
    DLT_IPV4

IPV6 = 229
    DLT_IPV6

IP_OVER_FC = 122
    DLT_IP_OVER_FC
```

```
ISO_14443 = 264
    DLT_ISO_14443

LAPB_WITH_DIR = 207
    DLT_LAPB_WITH_DIR

LAPD = 203
    DLT_LAPD

LINUX_IRDA = 144
    DLT_LINUX_IRDA

LINUX_LAPD = 177
    DLT_LINUX_LAPD

LINUX_SLL = 113
    DLT_LINUX_SLL

LINUX_SLL2 = 276
    DLT_LINUX_SLL2

LOOP = 108
    DLT_LOOP

LORATAP = 270
    DLT_LORATAP

LTALK = 114
    DLT_LTALK

MFR = 182
    DLT_MFR

MPEG_2_TS = 243
    DLT_MPEG_2_TS

MTP2 = 140
    DLT_MTP2

MTP2_WITH_PHDR = 139
    DLT_MTP2_WITH_PHDR

MTP3 = 141
    DLT_MTP3

MUX27010 = 236
    DLT_MUX27010

NETANALYZER = 240
    DLT_NETANALYZER

NETANALYZER_TRANSPARENT = 241
    DLT_NETANALYZER_TRANSPARENT

NETLINK = 253
    DLT_NETLINK

NFC_LLCP = 245
    DLT_NFC_LLCP

NFLOG = 239
    DLT_NFLOG
```

```
NG40 = 244
    DLT_NG40

NORDIC_BLE = 272
    DLT_NORDIC_BLE

NULL = 0
    DLT_NULL

OPENVIZSLA = 278
    DLT_OPENVIZSLA

PFLOG = 117
    DLT_PFLOG

PKTAP = 258
    DLT_PKTAP

PPI = 192
    DLT_PPI

PPP = 9
    DLT_PPP

PPP_ETHER = 51
    DLT_PPP_ETHER

PPP_HDLC = 50
    DLT_PPP_SERIAL

PPP_PPPD = 166
    DLT_PPP_PPPD

PPP_WITH_DIR = 204
    DLT_PPP_WITH_DIR

PROFIBUS_DL = 257
    DLT_PROFIBUS_DL

RAW = 101
    DLT_RAW

RDS = 265
    DLT_RDS

RTAC_SERIAL = 250
    DLT_RTAC_SERIAL

SCCP = 142
    DLT_SCCP

SCTP = 248
    DLT_SCTP

SDLC = 268
    DLT_SDLC

SITA = 196
    DLT_SITA

SLIP = 8
    DLT_SLIP
```



```
STANAG_5066_D_PDU = 237
    DLT_STANAG_5066_D_PDU

SUNATM = 123
    DLT_SUNATM

USBPCAP = 249
    DLT_USBPCAP

USB_2_0 = 288
    DLT_USB_2_0

USB_DARWIN = 266
    DLT_USB_DARWIN

USB_LINUX = 189
    DLT_USB_LINUX

USB_LINUX_MMAPPED = 220
    DLT_USB_LINUX_MMAPPED

USER_0 = 147
    DLT_USER_0

USER_1 = 148
    DLT_USER_1

USER_10 = 157
    DLT_USER_10

USER_11 = 158
    DLT_USER_11

USER_12 = 159
    DLT_USER_12

USER_13 = 160
    DLT_USER_13

USER_14 = 161
    DLT_USER_14

USER_15 = 162
    DLT_USER_15

USER_2 = 149
    DLT_USER_2

USER_3 = 150
    DLT_USER_3

USER_4 = 151
    DLT_USER_4

USER_5 = 152
    DLT_USER_5

USER_6 = 153
    DLT_USER_6

USER_7 = 154
    DLT_USER_7
```

```
USER_8 = 155
    DLT_USER_8

USER_9 = 156
    DLT_USER_9

VPP_DISPATCH = 280
    DLT_VPP_DISPATCH

VSOCK = 271
    DLT_VSOCK

WATTSTOPPER_DLM = 263
    DLT_WATTSTOPPER_DLM

ZWAVE_R1_R2 = 261
    DLT_ZWAVE_R1_R2

ZWAVE_R3 = 262
    DLT_ZWAVE_R3

Z_WAVE_SERIAL = 287
    DLT_Z_WAVE_SERIAL
```

ETHER TYPES†⁰

†

```
class pcapkit.const.reg.ethertype.EtherType (value=<object object>, names=None, module=None, type=None, start=1)
    Bases: aenum.IntEnum
    [EtherType] Ethertype IEEE 802 Numbers

    classmethod _missing_ (value)
        Lookup function used when value is not found.

    static get (key, default=-1)
        Backport support for original codes.

    ARAI_Bunkichi = 33188
        ARAI Bunkichi [Neil Sembower]

    ATOMIC = 34527
        ATOMIC [Joe Touch]

    AT_T_0x8008 = 32776
        AT&T [Neil Sembower]

    AT_T_0x8046 = 32838
        AT&T [Neil Sembower]

    AT_T_0x8047 = 32839
        AT&T [Neil Sembower]

    AT_T_0x8069 = 32873
        AT&T [Neil Sembower]

    Address_Resolution_Protocol = 2054
        Address Resolution Protocol (ARP) [RFC 7042]
```

⁰ <https://www.iana.org/assignments/ieee-802-numbers/ieee-802-numbers.xhtml#ieee-802-numbers-1>

Aeonic_Systems = 32822
Aeonic Systems [Neil Sembower]

Alpha_Micro = 33098
Alpha Micro [Neil Sembower]

Apollo_Computer = 33015
Apollo Computer [Neil Sembower]

Apollo_Domain = 32793
Apollo Domain [Neil Sembower]

AppleTalk_AARP = 33011
AppleTalk AARP (Kinetics) [Neil Sembower]

Appletalk = 32923
Appletalk [Neil Sembower]

Applitek_Corporation = 32967
Applitek Corporation [Neil Sembower]

Autophon = 32874
Autophon [Neil Sembower]

BBN_Simnet = 21000
BBN Simnet [Neil Sembower]

BBN_VITAL_LanBridge_cache = 65280
BBN VITAL-LanBridge cache [Neil Sembower]

BIIN_0x814D = 33101
BIIN [Neil Sembower]

BIIN_0x814E = 33102
BIIN [Neil Sembower]

Banyan_Systems_0x80C4 = 32964
Banyan Systems [Neil Sembower]

Banyan_Systems_0x80C5 = 32965
Banyan Systems [Neil Sembower]

Banyan_VINES = 2989
Banyan VINES [Neil Sembower]

Berkeley_Trailer_nego = 4096
Berkeley Trailer nego [Neil Sembower]

Cabletron = 28724
Cabletron [Neil Sembower]

Chaosnet = 2052
Chaosnet [Neil Sembower]

ComDesign = 32876
ComDesign [Neil Sembower]

Computgraphic_Corp = 32877
Computgraphic Corp. [Neil Sembower]

Counterpoint_Computers = 32866
Counterpoint Computers [Neil Sembower]

Cronus_Direct = 32772
Cronus Direct [[RFC 824](#)][Daniel Tappan]

Cronus_VLN = 32771
Cronus VLN [[RFC 824](#)][Daniel Tappan]

Customer_VLAN_Tag_Type = 33024
Customer VLAN Tag Type (C-Tag, formerly called the Q-Tag) (initially Wellfleet) [[RFC 7042](#)]

DEC_Customer_Protocol = 24582
DEC Customer Protocol [Neil Sembower]

DEC_DECNET_Phase_IV_Route = 24579
DEC DECNET Phase IV Route [Neil Sembower]

DEC_Diagnostic_Protocol = 24581
DEC Diagnostic Protocol [Neil Sembower]

DEC_Ethernet_Encryption = 32829
DEC Ethernet Encryption [Neil Sembower]

DEC_LANBridge = 32824
DEC LANBridge [Neil Sembower]

DEC_LAN_Traffic_Monitor = 32831
DEC LAN Traffic Monitor [Neil Sembower]

DEC_LAT = 24580
DEC LAT [Neil Sembower]

DEC_LAVC_SCA = 24583
DEC LAVC, SCA [Neil Sembower]

DEC_MOP_Dump_Load = 24577
DEC MOP Dump/Load [Neil Sembower]

DEC_MOP_Remote_Console = 24578
DEC MOP Remote Console [Neil Sembower]

DEC_Unassigned_0x6000 = 24576
DEC Unassigned (Exp.) [Neil Sembower]

DEC_Unassigned_0x803E = 32830
DEC Unassigned [Neil Sembower]

DLOG_0x0660 = 1632
DLOG [Neil Sembower]

DLOG_0x0661 = 1633
DLOG [Neil Sembower]

Dansk_Data_Elektronik = 32891
Dansk Data Elektronik [Neil Sembower]

Delta_Controls = 34526
Delta Controls [Neil Sembower]

ECMA_Internet = 2051
ECMA Internet [Neil Sembower]

EtherType_3Com_TCP_IP_Sys = 36866
3Com(Bridge) TCP-IP Sys [Neil Sembower]

```

EtherType_3Com_XNS_Sys_Mgmt = 36865
    3Com(Bridge) XNS Sys Mgmt [Neil Sembower]

EtherType_3Com_loop_detect = 36867
    3Com(Bridge) loop detect [Neil Sembower]

Evans_Sutherland = 32861
    Evans & Sutherland [Neil Sembower]

Excelan = 32784
    Excelan [Neil Sembower]

ExperData = 32841
    ExperData [Neil Sembower]

Frame_Relay_ARP = 2056
    Frame Relay ARP [RFC 1701]

General_Dynamics = 32872
    General Dynamics [Neil Sembower]

General_Switch_Management_Protocol = 34828
    General Switch Management Protocol (GSMP) [RFC 7042]

GeoNetworking_as_defined_in_ETSI_EN_302_636_4_1 = 35143
    GeoNetworking as defined in ETSI EN 302 636-4-1 [IEEE]

HIPPI_FP_encapsulation = 33152
    HIPPI-FP encapsulation [Neil Sembower]

HP_Probe = 32773
    HP Probe [Neil Sembower]

Hayes_Microcomputers = 33072
    Hayes Microcomputers [Neil Sembower]

IBM_SNA_Service_on_Ether = 32981
    IBM SNA Service on Ether [Neil Sembower]

IEEE_Std_802_11_Fast_Roaming_Remote_Request = 35085
    IEEE Std 802.11 - Fast Roaming Remote Request (802.11r) [IEEE]

IEEE_Std_802_11_Pre_Authentication = 35015
    IEEE Std 802.11 - Pre-Authentication (802.11i) [IEEE]

IEEE_Std_802_1AB_Link_Layer_Discovery_Protocol = 35020
    IEEE Std 802.1AB - Link Layer Discovery Protocol (LLDP) [IEEE]

IEEE_Std_802_1AE_Media_Access_Control_Security = 35045
    IEEE Std 802.1AE - Media Access Control Security [IEEE]

IEEE_Std_802_1Q_Multiple_Multicast_Registration_Protocol = 35062
    IEEE Std 802.1Q - Multiple Multicast Registration Protocol (MMRP) [IEEE]

IEEE_Std_802_1Q_Multiple_VLAN_Registration_Protocol = 35061
    IEEE Std 802.1Q - Multiple VLAN Registration Protocol (MVRP) [IEEE]

IEEE_Std_802_1Q_Service_VLAN_tag_identifier = 34984
    IEEE Std 802.1Q - Service VLAN tag identifier (S-Tag) [IEEE]

IEEE_Std_802_1Qbe_Multiple_I_SID_Registration_Protocol = 35113
    IEEE Std 802.1Qbe - Multiple I-SID Registration Protocol [IEEE]

```

IEEE_Std_802_1Qbg_ECP_Protocol = 35136
IEEE Std 802.1Qbg - ECP Protocol (also used in 802.1BR) [IEEE]

IEEE_Std_802_1X_Port_based_network_access_control = 34958
IEEE Std 802.1X - Port-based network access control [IEEE]

IEEE_Std_802_21_Media_Independent_Handover_Protocol = 35095
IEEE Std 802.21 - Media Independent Handover Protocol [IEEE]

IEEE_Std_802_3_Ethernet_Passive_Optical_Network = 34824
IEEE Std 802.3 - Ethernet Passive Optical Network (EPON) [EPON][[RFC 7042](#)]

IEEE_Std_802_Local_Experimental_Ethertype_0x88B5 = 34997
IEEE Std 802 - Local Experimental Ethertype [IEEE]

IEEE_Std_802_Local_Experimental_Ethertype_0x88B6 = 34998
IEEE Std 802 - Local Experimental Ethertype [IEEE]

IEEE_Std_802_OUI_Extended_Ethertype = 34999
IEEE Std 802 - OUI Extended Ethertype [IEEE]

IP_Autonomous_Systems = 34668
IP Autonomous Systems [[RFC 1701](#)]

Internet_Protocol_version_4 = 2048
Internet Protocol version 4 (IPv4) [[RFC 7042](#)]

Internet_Protocol_version_6 = 34525
Internet Protocol version 6 (IPv6) [[RFC 7042](#)]

L2_IS_IS = 8948
L2-IS-IS [[RFC 6325](#)]

Little_Machines = 32864
Little Machines [Neil Sembower]

LoWPAN_encapsulation = 41197
LoWPAN encapsulation [[RFC 7973](#)]

Logicraft = 33096
Logicraft [Neil Sembower]

Loopback = 36864
Loopback [Neil Sembower]

MPLS = 34887
MPLS [[RFC 5332](#)]

MPLS_with_upstream_assigned_label = 34888
MPLS with upstream-assigned label [[RFC 5332](#)]

Matra = 32890
Matra [Neil Sembower]

Merit_Internodal = 32892
Merit Internodal [Hans Werner Braun]

Motorola_Computer = 33165
Motorola Computer [Neil Sembower]

Multi_Topology = 39458
Multi-Topology [[RFC 8377](#)]

Multicast_Channel_Allocation_Protocol = 34913
Multicast Channel Allocation Protocol (MCAP) [[RFC 7042](#)]

NBS_Internet = 2050
NBS Internet [Neil Sembower]

NSH = 35151
NSH (Network Service Header) [[RFC 8300](#)]

Nestar = 32774
Nestar [Neil Sembower]

Network_Computing_Devices = 33097
Network Computing Devices [Neil Sembower]

Nixdorf = 1024
Nixdorf [Neil Sembower]

Nixdorf_Computers = 32931
Nixdorf Computers [Neil Sembower]

PCS_Basic_Block_Protocol = 16962
PCS Basic Block Protocol [Neil Sembower]

PPP_over_Ethernet_Discovery_Stage = 34915
PPP over Ethernet (PPPoE) Discovery Stage [[RFC 2516](#)]

PPP_over_Ethernet_Session_Stage = 34916
PPP over Ethernet (PPPoE) Session Stage [[RFC 2516](#)]

PUP_Addr_Trans_0x0201 = 513
PUP Addr Trans (see 0A01) [Neil Sembower]

PUP_Addr_Trans_0x0A01 = 2561
PUP Addr Trans [Neil Sembower]

Pacer_Software = 32966
Pacer Software [Neil Sembower]

Planning_Research_Corp = 32836
Planning Research Corp. [Neil Sembower]

Point_to_Point_Protocol = 34827
Point-to-Point Protocol (PPP) [[RFC 7042](#)]

Proteon = 28720
Proteon [Neil Sembower]

Provider_Backbone_Bridging_Instance_tag = 35047
Provider Backbone Bridging Instance tag [IEEE Std 802.1Q-2014]

Rational_Corp = 33104
Rational Corp [Neil Sembower]

Raw_Frame_Relay = 25945
Raw Frame Relay [[RFC 1701](#)]

Reserved = 65535
Reserved [[RFC 1701](#)]

Reserved_for_HIPPI_6400_0x8182 = 33154
Reserved for HIPPI-6400 [Neil Sembower]

Reserved_for_HIPPI_6400_0x8183 = 33155
Reserved for HIPPI-6400 [Neil Sembower]

Retix = 33010
Retix [Neil Sembower]

Reverse_Address_Resolution_Protocol = 32821
Reverse Address Resolution Protocol (RARP) [[RFC 903](#)][Joseph Murdock]

SECTRA = 34523
SECTRA [Neil Sembower]

SGI_Time_Warner_prop = 33150
SGI/Time Warner prop. [Neil Sembower]

SGI_bounce_server = 32790
SGI bounce server [Andrew Cherenson]

SGI_diagnostics = 32787
SGI diagnostics [Andrew Cherenson]

SGI_network_games = 32788
SGI network games [Andrew Cherenson]

SGI_reserved = 32789
SGI reserved [Andrew Cherenson]

SNMP = 33100
SNMP [Joyce K Reynolds]

STP_HIPPI_ST = 33153
STP, HIPPI-ST [Neil Sembower]

Secure_Data = 34669
Secure Data [[RFC 1701](#)]

Spider_Systems_Ltd = 32927
Spider Systems Ltd. [Neil Sembower]

Stanford_V_Kernel_exp = 32859
Stanford V Kernel exp. [Neil Sembower]

Stanford_V_Kernel_prod = 32860
Stanford V Kernel prod. [Neil Sembower]

Symbolics_Private = 2076
Symbolics Private [David Plummer]

TCP_IP_Compression = 34667
TCP/IP Compression [[RFC 1144](#)][[RFC 1701](#)]

TRILL = 8947
TRILL [[RFC 6325](#)]

TRILL_Fine_Grained_Labeling = 35131
TRILL Fine Grained Labeling (FGL) [[RFC 7172](#)]

TRILL_RBridg_Channel = 35142
TRILL RBridg Channel [[RFC 7178](#)]

Technically_Elite_Concept = 33103
Technically Elite Concept [Neil Sembower]

The_Ethertype_will_be_used_to_identify_a_Channel_in_which_control_messages_are_encapsu

The Ethertype will be used to identify a “Channel” in which control messages are encapsulated as payload of GRE packets. When a GRE packet tagged with the Ethertype is received, the payload will be handed to the network processor for processing. [RFC 8157]

Tigan_Inc = 32815

Tigan, Inc. [Neil Sembower]

Trans_Ether_Bridging = 25944

Trans Ether Bridging [RFC 1701]

Tymshare = 32814

Tymshare [Neil Sembower]

Ungermann_Bass_dia_loop = 28674

Ungermann-Bass dia/loop [Neil Sembower]

Ungermann_Bass_download = 28672

Ungermann-Bass download [Neil Sembower]

Ungermann_Bass_net_debugr = 2304

Ungermann-Bass net debugr [Neil Sembower]

Univ_of_Mass_Amherst_0x8065 = 32869

Univ. of Mass. @ Amherst [Neil Sembower]

Univ_of_Mass_Amherst_0x8066 = 32870

Univ. of Mass. @ Amherst [Neil Sembower]

VG_Laboratory_Systems = 33073

VG Laboratory Systems [Neil Sembower]

VINES_Echo = 2991

VINES Echo [RFC 1701]

VINES_Loopback = 2990

VINES Loopback [RFC 1701]

Valid_Systems = 5632

Valid Systems [Neil Sembower]

Varian_Associates = 32989

Varian Associates [Neil Sembower]

Veeco_Integrated_Auto = 32871

Veeco Integrated Auto. [Neil Sembower]

Vitalink_TransLAN_III = 32896

Vitalink TransLAN III [Neil Sembower]

Wellfleet_Communications = 33023

Wellfleet Communications [Neil Sembower]

XEROX_NS_IDP = 1536

Data Link Layer and Physical Layer Specification”, AA-K759B-TK, Digital Equipment Corporation, Maynard, MA. Also as: “The Ethernet - A Local Area Network”, Version 1.0, Digital Equipment Corporation, Intel Corporation, Xerox Corporation, September 1980. And: “The Ethernet, A Local Area Network: Data Link Layer and Physical Layer Specifications”, Digital, Intel and Xerox, November 1982. And: XEROX, “The Ethernet, A Local Area Network: Data Link Layer and Physical Layer Specification”, X3T51/80-50, Xerox Corporation, Stamford, CT., October 1980.][Neil Sembower]

Type XEROX NS IDP [“The Ethernet, A Local Area Network

XEROX_PUP = 512

XEROX PUP (see 0A00) [Boggs, D., J. Shoch, E. Taft, and R. Metcalfe, “PUP: An Internetwork Architecture”, XEROX Palo Alto Research Center, CSL-79-10, July 1979; also in IEEE Transactions on Communication, Volume COM-28, Number 4, April 1980.][Neil Sembower]

XNS_Compatibility = 2055

XNS Compatibility [Neil Sembower]

XTP = 33149

XTP [Neil Sembower]

X_25_Level_3 = 2053

X.25 Level 3 [Neil Sembower]

X_75_Internet = 2049

X.75 Internet [Neil Sembower]

Xerox_IEEE802_3_PUP = 2560

Xerox IEEE802.3 PUP [Neil Sembower]

Assigned Internet Protocol Numbers†⁰

‡

```
class pcapkit.const.reg.transtype.TransType (value=<object object>, names=None, module=None, type=None, start=1)
```

Bases: aenum.IntEnum

[TransType] Transport Layer Protocol Numbers

classmethod **_missing_** (value)

Lookup function used when value is not found.

static **get** (key, default=-1)

Backport support for original codes.

AH = 51

[RFC 4302] Authentication Header

ARGUS = 13

[Robert W Scheifler] ARGUS (deprecated))

ARIS = 104

[Nancy Feldman] ARIS

AX_25 = 93

[Brian Kantor] AX.25 Frames

A_N = 107

[Bob Braden] Active Networks

BBN_RCC_MON = 10

[Steve Chipman] BBN RCC Monitoring

BNA = 49

[Gary Salamon] BNA

BR_SAT_MON = 76

[Steven Blumenthal] Backroom SATNET Monitoring

⁰ <https://www.iana.org/assignments/protocol-numbers/protocol-numbers.xhtml#protocol-numbers-1>

CBT = 7
[Tony Ballardie] CBT

CFTP = 62
[Forsdick, H., “CFTP”, Network Message, Bolt Beranek and Newman, January 1982.][Harry Forsdick]
CFTP

CHAOS = 16
[J Noel Chiappa] Chaos

CPHB = 73
[David Mittnacht] Computer Protocol Heart Beat

CPNX = 72
[David Mittnacht] Computer Protocol Network Executive

CRTP = 126
[Robert Sautter] Combat Radio Transport Protocol

CRUDP = 127
[Robert Sautter] Combat Radio User Datagram

Compaq_Peer = 110
[Victor Volpe] Compaq Peer Protocol

DCCP = 33
[RFC 4340] Datagram Congestion Control Protocol

DCN_MEAS = 19
[David Mills] DCN Measurement Subsystems

DDP = 37
[Wesley Craig] Datagram Delivery Protocol

DDX = 116
[John Worley] D-II Data Exchange (DDX)

DGP = 86
[M/A-COM Government Systems, “Dissimilar Gateway Protocol Specification, Draft Version”, Contract no. CS901145, November 16, 1987.][Mike Little] Dissimilar Gateway Protocol

DSR = 48
[RFC 4728] Dynamic Source Routing Protocol

EGP = 8
[RFC 888][David Mills] Exterior Gateway Protocol

EIGRP = 88
[RFC 7868] EIGRP

EMCON = 14
[<mystery contact>] EMCON

ENCAP = 98
[RFC 1241][Robert Woodburn] Encapsulation Header

ESP = 50
[RFC 4303] Encap Security Payload

ETHERIP = 97
[RFC 3378] Ethernet-within-IP Encapsulation

Ethernet = 143
[draft-ietf-spring-srv6-network-programming] Ethernet (TEMPORARY - registered 2020-01-31, expires 2021-01-31)

FC = 133
[Murali Rajagopal][[RFC 6172](#)] Fibre Channel

FIRE = 125
[Criag Partridge]

GGP = 3
[[RFC 823](#)] Gateway-to-Gateway

GMTP = 100
[RXB5] GMTP

GRE = 47
[[RFC 2784](#)][Tony Li] Generic Routing Encapsulation

HIP = 139
[[RFC 7401](#)] Host Identity Protocol

HMP = 20
[[RFC 869](#)][Bob Hinden] Host Monitoring

HOPOPT = 0
[[RFC 8200](#)] IPv6 Hop-by-Hop Option

IATP = 117
[John Murphy] Interactive Agent Transfer Protocol

ICMP = 1
[[RFC 792](#)] Internet Control Message

IDPR = 35
[Martha Steenstrup] Inter-Domain Policy Routing Protocol

IDPR_CMTP = 38
[Martha Steenstrup] IDPR Control Message Transport Proto

IDRP = 45
[Sue Hares] Inter-Domain Routing Protocol

IFMP = 101
[Bob Hinden][November 1995, 1997.] Ipsilon Flow Management Protocol

IGMP = 2
[[RFC 1112](#)] Internet Group Management

IGP = 9
[Internet Assigned Numbers Authority] any private interior gateway (used by Cisco for their IGRP)

IL = 40
[Dave Presotto] IL Transport Protocol

IPCV = 71
[Steven Blumenthal] Internet Packet Core Utility

IPComp = 108
[[RFC 2393](#)] IP Payload Compression Protocol

IPIP = 94
[John Ioannidis] IP-within-IP Encapsulation Protocol

IPLT = 129
[Hollbach]

IPPC = 67
[Steven Blumenthal] Internet Pluribus Packet Core

IPTM = 84
[Jim Stevens] Internet Protocol Traffic Manager

IPX_in_IP = 111
[CJ Lee] IPX in IP

IPv4 = 4
[RFC 2003] IPv4 encapsulation

IPv6 = 41
[RFC 2473] IPv6 encapsulation

IPv6_Frag = 44
[Steve Deering] Fragment Header for IPv6

IPv6_ICMP = 58
[RFC 8200] ICMP for IPv6

IPv6_NoNxt = 59
[RFC 8200] No Next Header for IPv6

IPv6_Opts = 60
[RFC 8200] Destination Options for IPv6

IPv6_Route = 43
[Steve Deering] Routing Header for IPv6

IRTP = 28
[RFC 938][Trudy Miller] Internet Reliable Transaction

ISIS_over_IPv4 = 124
[Tony Przygienda]

ISO_IP = 80
[Marshall T Rose] ISO Internet Protocol

ISO_TP4 = 29
[RFC 905][<mystery contact>] ISO Transport Protocol Class 4

I_NLSP = 52
[K Robert Glenn] Integrated Net Layer Security TUBA

KRYPTOLAN = 65
[Paul Liu] Kryptolan

L2TP = 115
[RFC 3931][Bernard Aboba] Layer Two Tunneling Protocol

LARP = 91
[Brian Horn] Locus Address Resolution Protocol

LEAF_1 = 25
[Barry Boehm] Leaf-1

LEAF_2 = 26
[Barry Boehm] Leaf-2

MERIT_INP = 32
[Hans Werner Braun] MERIT Internodal Protocol

MFE_NSP = 31
[Shuttleworth, B., “A Documentary of MFENet, a National Computer Network”, UCRL-52317, Lawrence Livermore Labs, Livermore, California, June 1977.][Barry Howard] MFE Network Services Protocol

MICP = 95
[John Ioannidis] Mobile Internetworking Control Pro. (deprecated))

MOBILE = 55
[Charlie Perkins] IP Mobility

MPLS_in_IP = 137
[\[RFC 4023\]](#)

MTP = 92
[Susie Armstrong] Multicast Transport Protocol

MUX = 18
[Cohen, D. and J. Postel, “Multiplexing Protocol”, IEN 90, USC/Information Sciences Institute, May 1979.][Jon Postel] Multiplexing

Mobility_Header = 135
[\[RFC 6275\]](#)

NARP = 54
[\[RFC 1735\]](#) NBMA Address Resolution Protocol

NETBLT = 30
[\[RFC 969\]](#)[David Clark] Bulk Data Transfer Protocol

NSFNET_IGP = 85
[Hans Werner Braun] NSFNET-IGP

NVP_II = 11
[\[RFC 741\]](#)[Steve Casner] Network Voice Protocol

OSPF_IGP = 89
[\[RFC 1583\]](#)[\[RFC 2328\]](#)[\[RFC 5340\]](#)[John Moy] OSPF_IGP

PGM = 113
[Tony Speakman] PGM Reliable Transport Protocol

PIM = 103
[\[RFC 7761\]](#)[Dino Farinacci] Protocol Independent Multicast

PIPE = 131
[Bernhard Petri] Private IP Encapsulation within IP

PNNI = 102
[Ross Callon] PNNI over IP

PRM = 21
[Zaw Sing Su] Packet Radio Measurement

PTP = 123
[Michael Welzl] Performance Transparency Protocol

PUP = 12
An Internetwork Architecture”, XEROX Palo Alto Research Center, CSL-79-10, July 1979; also in IEEE Transactions on Communication, Volume COM-28, Number 4, April 1980.][XEROX] PUP

Type [Boggs, D., J. Shoch, E. Taft, and R. Metcalfe, “PUP

PVP = 75
[Steve Casner] Packet Video Protocol

QNX = 106
[Michael Hunter] QNX

RDP = 27
[RFC 908][Bob Hinden] Reliable Data Protocol

ROHC = 142
[RFC 5858] Robust Header Compression

RSVP = 46
[RFC 2205][RFC 3209][Bob Braden] Reservation Protocol

RSVP_E2E_IGNORE = 134
[RFC 3175]

RVD = 66
[Michael Greenwald] MIT Remote Virtual Disk Protocol

Reserved = 255
[Internet Assigned Numbers Authority]

SAT_EXPAK = 64
[Steven Blumenthal] SATNET and Backroom EXPAK

SAT_MON = 69
[Steven Blumenthal] SATNET Monitoring

SCC_SP = 96
[Howard Hart] Semaphore Communications Sec. Pro.

SCPS = 105
[Robert Durst] SCPS

SCTP = 132
[Randall R Stewart] Stream Control Transmission Protocol

SDRP = 42
[Deborah Estrin] Source Demand Routing Protocol

SECURE_VMTP = 82
[Dave Cheriton] SECURE-VMTP

SKIP = 57
[Tom Markson] SKIP

SM = 122
[Jon Crowcroft][draft-perlman-simple-multicast] Simple Multicast Protocol (deprecated))

SMP = 121
[Leif Ekblad] Simple Message Protocol

SNP = 109
[Manickam R Sridhar] Sitara Networks Protocol

SPS = 130
[Bill McIntosh] Secure Packet Shield

SRP = 119
[Mark Hamilton] SpectraLink Radio Protocol

SSCOPMCE = 128
[Kurt Waber]

ST = 5
[RFC 1190][RFC 1819] Stream

STP = 118
[Jean Michel Pittet] Schedule Transfer Protocol

SUN_ND = 77
[William Melohn] SUN ND PROTOCOL-Temporary

SWIPE = 53
[John Ioannidis] IP with Encryption (deprecated))

Shim6 = 140
[RFC 5533] Shim6 Protocol

Sprite_RPC = 90
[Welch, B., “The Sprite Remote Procedure Call System”, Technical Report, UCB/Computer Science Dept., 86/302, University of California at Berkeley, June 1986.][Bruce Willins] Sprite RPC Protocol

TCF = 87
[Guillermo A Loyola] TCF

TCP = 6
[RFC 793] Transmission Control

TLSP = 56
[Christer Oberg] Transport Layer Security Protocol using Kryptonet key management

TP = 39
[Dirk Fromhein] TP++ Transport Protocol

TRUNK_1 = 23
[Barry Boehm] Trunk-1

TRUNK_2 = 24
[Barry Boehm] Trunk-2

TTP = 84
[Jim Stevens] Transaction Transport Protocol

TransType_3PC = 34
[Stuart A Friedberg] Third Party Connect Protocol

UDP = 17
[RFC 768][Jon Postel] User Datagram

UDPLite = 136
[RFC 3828]

UTI = 120
[Peter Lothberg] UTI

Use_for_experimentation_and_testing_253 = 253
[RFC 3692] Use for experimentation and testing

Use_for_experimentation_and_testing_254 = 254
[RFC 3692] Use for experimentation and testing

VINES = 83
[Brian Horn] VINES

VISA = 70
[Gene Tsudik] VISA Protocol

VMTP = 81
[Dave Cheriton] VMTP

VRP = 112
[RFC 5798] Virtual Router Redundancy Protocol

WB_EXPAK = 79
[Steven Blumenthal] WIDEBAND EXPAK

WB_MON = 78
[Steven Blumenthal] WIDEBAND Monitoring

WESP = 141
[RFC 5840] Wrapped Encapsulating Security Payload

WSN = 74
[Victor Dafoulas] Wang Span Network

XNET = 15
[Haverty, J., "XNET Formats for Internet Protocol Version 4", IEN 158, October 1980.][Jack Haverty] Cross Net Debugger

XNS_IDP = 22
Data Link Layer and Physical Layer Specification", AA-K759B-TK, Digital Equipment Corporation, Maynard, MA. Also as: "The Ethernet - A Local Area Network", Version 1.0, Digital Equipment Corporation, Intel Corporation, Xerox Corporation, September 1980. And: "The Ethernet, A Local Area Network: Data Link Layer and Physical Layer Specifications", Digital, Intel and Xerox, November 1982. And: XEROX, "The Ethernet, A Local Area Network: Data Link Layer and Physical Layer Specification", X3T51/80-50, Xerox Corporation, Stamford, CT., October 1980.][XEROX] XEROX NS IDP

Type ["The Ethernet, A Local Area Network"]

XTP = 36
[Greg Chesson] XTP

any_0_hop_protocol = 114
[Internet Assigned Numbers Authority] any 0-hop protocol

any_distributed_file_system = 68
[Internet Assigned Numbers Authority] any distributed file system

any_host_internal_protocol = 61
[Internet Assigned Numbers Authority] any host internal protocol

any_local_network = 63
[Internet Assigned Numbers Authority] any local network

any_private_encryption_scheme = 99
[Internet Assigned Numbers Authority] any private encryption scheme

manet = 138
[RFC 5498] MANET Protocols

1.9.11 TCP Constant Enumerations

TCP Checksum^{*0}

*

```
class pcapkit.const.tcp.checksum.Checksum(value=<object object>, names=None, module=None, type=None, start=1)

    Bases: aenum.IntEnum

    [Checksum] TCP Checksum [RFC 1146]

    classmethod _missing_(value)
        Lookup function used when value is not found.

    static get(key, default=- 1)
        Backport support for original codes.

    Checksum_16_bit_Fletcher_s_algorithm = 2

    Checksum_8_bit_Fletcher_s_algorithm = 1

    Redundant_Checksum_Avoidance = 3

    TCP_checksum = 0
```

TCP Option Kind Numbers^{†0}

†

```
class pcapkit.const.tcp.option.Option(value=<object object>, names=None, module=None, type=None, start=1)

    Bases: aenum.IntEnum

    [Option] TCP Option Kind Numbers

    classmethod _missing_(value)
        Lookup function used when value is not found.

    static get(key, default=- 1)
        Backport support for original codes.

    AO = 29
        TCP Authentication Option (TCP-AO) [RFC 5925]

    Bubba = 17
        Bubba [Stev Knowles]

    CC = 11
        CC (obsolete) [RFC 1644][RFC 6247]

    CCECHO = 13
        CC.ECHO (obsolete) [RFC 1644][RFC 6247]

    CCNEW = 12
        CC.NEW (obsolete) [RFC 1644][RFC 6247]

    CHKREQ = 14
        TCP Alternate Checksum Request (obsolete) [RFC 1146][RFC 6247]
```

⁰ <https://www.iana.org/assignments/tcp-parameters/tcp-parameters.xhtml#tcp-parameters-2>

⁰ <https://www.iana.org/assignments/tcp-parameters/tcp-parameters.xhtml#tcp-parameters-1>

CHKSUM = 15
TCP Alternate Checksum Data (obsolete) [RFC 1146][RFC 6247]

Corruption_experienced = 23
Corruption experienced [Keith Scott]

ECHO = 6
Echo (obsoleted by option 8) [RFC 1072][RFC 6247]

ECHORE = 7
Echo Reply (obsoleted by option 8) [RFC 1072][RFC 6247]

EOOL = 0
End of Option List [RFC 793]

Encryption_Negotiation = 69
Encryption Negotiation (TCP-ENO) [RFC 8547]

FASTOPEN = 34
TCP Fast Open Cookie [RFC 7413]

MP = 30
Multipath TCP (MPTCP) [RFC 8684]

MSS = 2
Maximum Segment Size [RFC 793]

NOP = 1
No-Operation [RFC 793]

POC = 9
Partial Order Connection Permitted (obsolete) [RFC 1693][RFC 6247]

POCSP = 10
Partial Order Service Profile (obsolete) [RFC 1693][RFC 6247]

QS = 27
Quick-Start Response [RFC 4782]

RFC3692_style_Experiment_1 = 253
RFC3692-style Experiment 1 (also improperly used for shipping products) [*] [RFC 4727]

RFC3692_style_Experiment_2 = 254
RFC3692-style Experiment 2 (also improperly used for shipping products) [*] [RFC 4727]

Record_Boundaries = 22
Record Boundaries [Keith Scott]

Reserved_31 = 31
Reserved (known unauthorized use without proper IANA assignment) [**]

Reserved_32 = 32
Reserved (known unauthorized use without proper IANA assignment) [**]

Reserved_33 = 33
Reserved (known unauthorized use without proper IANA assignment) [**]

Reserved_70 = 70
Reserved (known unauthorized use without proper IANA assignment) [**]

Reserved_76 = 76
Reserved (known unauthorized use without proper IANA assignment) [**]

Reserved_77 = 77
Reserved (known unauthorized use without proper IANA assignment) [**]

Reserved_78 = 78
Reserved (known unauthorized use without proper IANA assignment) [**]

SACK = 5
SACK [RFC 2018]

SACKPMT = 4
SACK Permitted [RFC 2018]

SCPS_Capabilities = 20
SCPS Capabilities [Keith Scott]

SIG = 19
MD5 Signature Option (obsoleted by option 29) [RFC 2385]

SNAP = 24
SNAP [Vladimir Sukonnik]

Selective_Negative_Acknowledgements = 21
Selective Negative Acknowledgements [Keith Scott]

Skeeter = 16
Skeeter [Stev Knowles]

TCP_Compression_Filter = 26
TCP Compression Filter [Steve Bellovin]

TIMEOUT = 28
User Timeout Option (also, other known unauthorized use) [***][1] [RFC 5482]

TS = 8
Timestamps [RFC 7323]

Trailer_Checksum_Option = 18
Trailer Checksum Option [Subbu Subramaniam][Monroe Bridges]

Unassigned = 25
Unassigned (released 2000-12-18)

WS = 3
Window Scale [RFC 7323]

1.9.12 VLAN Constant Enumerations

Priority Levels^{*0}

*

```
class pcapkit.const.vlan.priority_level.PriorityLevel (value=<object object>,
                                                         names=None, module=None,
                                                         type=None, start=1)
```

Bases: aenum.IntEnum

[PriorityLevel] Priority levels defined in IEEE 802.1p.

classmethod _missing_ (value)

Lookup function used when value is not found.

⁰ https://en.wikipedia.org/wiki/IEEE_P802.1p#Priority_levels

```

static get (key, default=- 1)
    Backport support for original codes.

BE = 0
    1 - Best effort (default)

BK = 1
    0 - Background (lowest)

CA = 3
    3 - Critical applications

EE = 2
    2 - Excellent effort

IC = 6
    6 - Internetwork control

NC = 7
    7 - Network control (highest)

VI = 4
    4 - Video, < 100 ms latency and jitter

VO = 5
    5 - Voice, < 10 ms latency and jitter

```

1.10 Web Crawlers for Constant Enumerations

1.10.1 ARP Vendor Crawlers

ARP Hardware Types^{*0}

*

```

class pcapkit.vendor.arp.hardware.Hardware
    Bases: pcapkit.vendor.default.Vendor

    Hardware Types [RFC 826][RFC 5494]

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/arp-parameters/arp-parameters-2.csv'
        Link to registry.

```

⁰ <https://www.iana.org/assignments/arp-parameters/arp-parameters.xhtml#arp-parameters-2>

Operation Codes†⁰

†

```
class pcapkit.vendor.arp.operation.Operation
    Bases: pcapkit.vendor.default.Vendor

    Operation Codes [RFC 826][RFC 5494]

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/arp-parameters/arp-parameters-1.csv'
        Link to registry.
```

1.10.2 FTP Vendor Crawlers

FTP Commands*⁰

*

```
class pcapkit.vendor.ftp.command.Command
    Bases: pcapkit.vendor.default.Vendor

    FTP Command

    context (data)
        Generate constant context.

        Parameters data (List[str]) – CSV data.

        Returns Constant context.

        Return type str

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    LINK = 'https://www.iana.org/assignments/ftp-commands-extensions/ftp-commands-extensions-2.csv'
        Link to registry.

pcapkit.vendor.ftp.command.LINE (NAME, DOCS, INFO, MISS)
    Constant template of enumerate registry from IANA CSV.

pcapkit.vendor.ftp.command.make (cmmd, feat, desc, kind, conf, rfcs, cmmt)
    Command entry template.

pcapkit.vendor.ftp.command.CONF = {'h': 'historic', 'm': 'mandatory to implement', 'o': 'optional', 'r': 'recommended'}
    Conformance requirements.

pcapkit.vendor.ftp.command.KIND = {'a': 'access control', 'p': 'parameter setting', 's': 'service specific'}
    Command type.
```

⁰ <https://www.iana.org/assignments/arp-parameters/arp-parameters.xhtml#arp-parameters-1>

⁰ <https://www.iana.org/assignments/ftp-commands-extensions/ftp-commands-extensions.xhtml#ftp-commands-extensions-2>

FTP Return Codes†⁰

†

```

class pcapkit.vendor.ftp.return_code.ReturnCode
    Bases: pcapkit.vendor.default.Vendor

    FTP Server Return Code

    context (soup)
        Generate constant context.

        Parameters soup (bs4.BeautifulSoup) – Parsed HTML source.

        Returns Constant context.

        Return type str

    count (soup)
        Count field records.

    process (soup)
        Process registry data.

        Parameters soup (bs4.BeautifulSoup) – Parsed HTML source.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    request (text)
        Fetch registry data.

        Parameters text (str) – Context from LINK.

        Returns Parsed HTML source.

        Return type bs4.BeautifulSoup

    FLAG = 'isinstance(value, int) and 100 <= value <= 659'
        Value limit checker.

    LINK = 'https://en.wikipedia.org/wiki/List_of_FTP_server_return_codes'
        Link to registry.

pcapkit.vendor.ftp.return_code.LINE (NAME, DOCS, FLAG, ENUM)

```

1.10.3 HIP Vendor Crawler

HIP Certificate Types*⁰

*

```

class pcapkit.vendor.hip.certificate.Certificate
    Bases: pcapkit.vendor.default.Vendor

    HIP Certificate Types

    FLAG = 'isinstance(value, int) and 0 <= value <= 255'
        Value limit checker.

```

⁰ https://en.wikipedia.org/wiki/List_of_FTP_server_return_codes

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#certificate-types>

```
LINK = 'https://www.iana.org/assignments/hip-parameters/certificate-types.csv'  
Link to registry.
```

HIP Cipher IDs†⁰

†

```
class pcapkit.vendor.hip.cipher.Cipher  
    Bases: pcapkit.vendor.default.Vendor  
  
    Cipher IDs  
  
    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'  
        Value limit checker.  
  
    LINK = 'https://www.iana.org/assignments/hip-parameters/hip-cipher-id.csv'  
        Link to registry.
```

DI-Types‡⁰

‡

```
class pcapkit.vendor.hip.di.DITypes  
    Bases: pcapkit.vendor.default.Vendor  
  
    DI-Types  
  
    FLAG = 'isinstance(value, int) and 0 <= value <= 15'  
        Value limit checker.  
  
    LINK = 'https://www.iana.org/assignments/hip-parameters/hip-parameters-7.csv'  
        Link to registry.
```

ECDSA Curve Label§⁰

```
class pcapkit.vendor.hip.ecdsa_curve.ECDSACurve  
    Bases: pcapkit.vendor.default.Vendor  
  
    ECDSA Curve Label  
  
    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'  
        Value limit checker.  
  
    LINK = 'https://www.iana.org/assignments/hip-parameters/ecdsa-curve-label.csv'  
        Link to registry.
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-cipher-id>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-7>

¹⁵⁹ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#ecdsa-curve-label>

ECDSA_LOW Curve Label⁰

¶

```
class pcapkit.vendor.hip.ecdsa_low_curve.ECDSALowCurve
    Bases: pcapkit.vendor.default.Vendor

    ECDSA_LOW Curve Label

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/ecdsa-low-curve-label.csv'
        Link to registry.
```

ESP Transform Suite IDs³⁵

```
class pcapkit.vendor.hip.esp_transform_suite.ESPTransformSuite
    Bases: pcapkit.vendor.default.Vendor

    ESP Transform Suite IDs

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/esp-transform-suite-ids.csv'
        Link to registry.
```

Group IDs⁰

```
class pcapkit.vendor.hip.group.Group
    Bases: pcapkit.vendor.default.Vendor

    Group IDs

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    FLAG = 'isinstance(value, int) and 0 <= value <= 255'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/hip-parameters-5.csv'
        Link to registry.
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#ecdsa-low-curve-label>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#esp-transform-suite-ids>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-5>

HI Algorithm⁰

```
class pcapkit.vendor.hip.hi_algorithm.HIAlgorithm
    Bases: pcapkit.vendor.default.Vendor

    HI Algorithm

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/hi-algorithm.csv'
        Link to registry.
```

HIT Suite ID⁰

```
class pcapkit.vendor.hip.hit_suite.HITSuite
    Bases: pcapkit.vendor.default.Vendor

    HIT Suite ID

    FLAG = 'isinstance(value, int) and 0 <= value <= 15'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/hit-suite-id.csv'
        Link to registry.
```

HIP NAT Traversal Modes⁰

```
class pcapkit.vendor.hip.nat_traversal.NATTraversal
    Bases: pcapkit.vendor.default.Vendor

    HIP NAT Traversal Modes

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/nat-traversal.csv'
        Link to registry.
```

Notify Message Types^{**0}

**

```
class pcapkit.vendor.hip.notify_message.NotifyMessage
    Bases: pcapkit.vendor.default.Vendor

    Notify Message Types

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/hip-parameters-9.csv'
        Link to registry.
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hi-algorithm>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hit-suite-id>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#nat-traversal>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-9>

Packet Types††⁰

††

```
class pcapkit.vendor.hip.packet.Packet
    Bases: pcapkit.vendor.default.Vendor

    HIP Packet Types

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    FLAG = 'isinstance(value, int) and 0 <= value <= 127'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/hip-parameters-1.csv'
        Link to registry.
```

Parameter Types‡‡⁰

‡‡

```
class pcapkit.vendor.hip.parameter.Parameter
    Bases: pcapkit.vendor.default.Vendor

    HIP Parameter Types

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/hip-parameters-4.csv'
        Link to registry.
```

Registration Types§§⁰

§

```
class pcapkit.vendor.hip.registration.Registration
    Bases: pcapkit.vendor.default.Vendor

    Registration Types

    FLAG = 'isinstance(value, int) and 0 <= value <= 255'
        Value limit checker.
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-1>⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-4>¹⁵⁹ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-11>

LINK = '<https://www.iana.org/assignments/hip-parameters/hip-parameters-11.csv>'
Link to registry.

Registration Failure Types⁰

⁰

```
class pcapkit.vendor.hip.registration_failure.RegistrationFailure
    Bases: pcapkit.vendor.default.Vendor
    Registration Failure Types

    FLAG = 'isinstance(value, int) and 0 <= value <= 255'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/hip-parameters-13.csv'
        Link to registry.
```

Suite IDs³⁵

```
class pcapkit.vendor.hip.suite.Suite
    Bases: pcapkit.vendor.default.Vendor
    Suite IDs

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/hip-parameters-6.csv'
        Link to registry.
```

HIP Transport Modes⁰

```
class pcapkit.vendor.hip.transport.Transport
    Bases: pcapkit.vendor.default.Vendor
    HIP Transport Modes

    FLAG = 'isinstance(value, int) and 0 <= value <= 3'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/hip-parameters/transport-modes.csv'
        Link to registry.
```

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-13>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#hip-parameters-6>

⁰ <https://www.iana.org/assignments/hip-parameters/hip-parameters.xhtml#transport-modes>

1.10.4 HTTP Vendor Crawler

HTTP/2 Error Code^{*0}

*

```
class pcapkit.vendor.http.error_code.ErrorCode
    Bases: pcapkit.vendor.default.Vendor

    HTTP/2 Error Code

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    FLAG = 'isinstance(value, int) and 0x00000000 <= value <= 0xFFFFFFFF'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/http2-parameters/error-code.csv'
        Link to registry.

pcapkit.vendor.http.error_code.hexlify (code)
    Convert code to hex form.
```

HTTP/2 Frame Type^{†0}

†

```
class pcapkit.vendor.http.frame.Frame
    Bases: pcapkit.vendor.default.Vendor

    HTTP/2 Frame Type

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    FLAG = 'isinstance(value, int) and 0x00 <= value <= 0xFF'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/http2-parameters/frame-type.csv'
        Link to registry.

pcapkit.vendor.http.frame.hexlify (code)
    Convert code to hex form.
```

⁰ <https://www.iana.org/assignments/http2-parameters/http2-parameters.xhtml#error-code>

⁰ <https://www.iana.org/assignments/http2-parameters/http2-parameters.xhtml#frame-type>

HTTP/2 Settings⁰

⌘

```
class pcapkit.vendor.http.setting.Setting
    Bases: pcapkit.vendor.default.Vendor
    HTTP/2 Settings

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.
        Returns Enumeration fields. List[str]: Missing fields.
        Return type List[str]

    FLAG = 'isinstance(value, int) and 0x0000 <= value <= 0xFFFF'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/http2-parameters/settings.csv'
        Link to registry.

pcapkit.vendor.http.setting.hexlify(code)
    Convert code to hex form.
```

1.10.5 IPv4 Vendor Crawler

Classification Level Encodings

```
class pcapkit.vendor.ipv4.classification_level.ClassificationLevel
    Bases: pcapkit.vendor.default.Vendor
    Classification Level Encodings

    count (data)
        Count field records.

        Parameters data (Dict[int, str]) – Registry data.
        Returns Field recordings.
        Return type Counter

    process (data)
        Process registry data.

        Parameters data (Dict[int, str]) – Registry data.
        Returns Enumeration fields. List[str]: Missing fields.
        Return type List[str]

    request ()
        Fetch registry data.

        Returns Registry data (DATA).
        Return type Dict[int, str]
```

⁰ <https://www.iana.org/assignments/http2-parameters/http2-parameters.xhtml#settings>

FLAG = 'isinstance(value, int) and 0b00000000 <= value <= 0b11111111'
Value limit checker.

pcapkit.vendor.ipv4.classification_level.**binary**(code)
Convert code to binary form.

pcapkit.vendor.ipv4.classification_level.**DATA** = {1: 'Reserved [4]', 61: 'Top Secret', 90:
Encoding registry.

Option Classes

class pcapkit.vendor.ipv4.option_class.**OptionClass**
Bases: *pcapkit.vendor.default.Vendor*

Option Classes

count(data)
Count field records.

Parameters data (Dict[int, str]) – Registry data.

Returns Field recordings.

Return type Counter

process(data)
Process registry data.

Parameters data (Dict[int, str]) – Registry data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

request()
Fetch registry data.

Returns Registry data (DATA).

Return type Dict[int, str]

FLAG = 'isinstance(value, int) and 0 <= value <= 3'
Value limit checker.s

pcapkit.vendor.ipv4.option_class.**binary**(code)
Convert code to binary form.

pcapkit.vendor.ipv4.option_class.**DATA** = {0: 'control', 1: 'reserved for future use', 2:
Option class registry.

IP Option Numbers^{*0}

*

class pcapkit.vendor.ipv4.option_number.**OptionNumber**
Bases: *pcapkit.vendor.default.Vendor*

IP Option Numbers

count(data)
Count field records.

⁰ <https://www.iana.org/assignments/ip-parameters/ip-parameters.xhtml#ip-parameters-1>

Parameters `data` (`List[str]`) – CSV data.

Returns Field recordings.

Return type Counter

process (`data`)

Process CSV data.

Parameters `data` (`List[str]`) – CSV data.

Returns Enumeration fields. `List[str]`: Missing fields.

Return type `List[str]`

FLAG = `'isinstance(value, int) and 0 <= value <= 255'`

Value limit checker.

LINK = `'https://www.iana.org/assignments/ip-parameters/ip-parameters-1.csv'`

Link to registry.

Protection Authority Bit Assignments

class `pcapkit.vendor.ipv4.protection_authority.ProtectionAuthority`

Bases: `pcapkit.vendor.default.Vendor`

Protection Authority Bit Assignments

count (`data`)

Count field records.

Parameters `data` (`Dict[int, str]`) – Registry data.

Returns Field recordings.

Return type Counter

process (`data`)

Process registry data.

Parameters `data` (`Dict[int, str]`) – Registry data.

Returns Enumeration fields. `List[str]`: Missing fields.

Return type `List[str]`

request ()

Fetch registry data.

Returns Registry data (`DATA`).

Return type `Dict[int, str]`

FLAG = `'isinstance(value, int) and 0 <= value <= 7'`

Value limit checker.

`pcapkit.vendor.ipv4.protection_authority.DATA` = {0: 'GENSER', 1: 'SIOP-ESI', 2: 'SCI', 3: 'SIOP-ESI', 4: 'SIOP-ESI', 5: 'SIOP-ESI', 6: 'SIOP-ESI', 7: 'SIOP-ESI'}

Protection authority registry.

QS Functions

class pcapkit.vendor.ipv4.qs_function.QSFunction

Bases: *pcapkit.vendor.default.Vendor*

QS Functions

count (*data*)

Count field records.

Parameters *data* (*Dict[int, str]*) – Registry data.

Returns Field recordings.

Return type Counter

process (*data*)

Process registry data.

Parameters *data* (*Dict[int, str]*) – Registry data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

request ()

Fetch registry data.

Returns Registry data (*DATA*).

Return type Dict[int, str]

FLAG = 'isinstance(value, int) and 0 <= value <= 8'

Value limit checker.

pcapkit.vendor.ipv4.qs_function.DATA = {0: 'Quick-Start Request', 8: 'Report of Approved
QS function registry.

IPv4 Router Alert Option Values†⁰

†

class pcapkit.vendor.ipv4.router_alert.RouterAlert

Bases: *pcapkit.vendor.default.Vendor*

IPv4 Router Alert Option Values

process (*data*)

Process CSV data.

Parameters *data* (*List[str]*) – CSV data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

FLAG = 'isinstance(value, int) and 0 <= value <= 65535'

Value limit checker.

LINK = 'https://www.iana.org/assignments/ip-parameters/ipv4-router-alert-option-values'

Link to registry.

⁰ <https://www.iana.org/assignments/ip-parameters/ip-parameters.xhtml#ipv4-router-alert-option-values>

ToS (DS Field) Delay

```
class pcapkit.vendor.ipv4.tos_del.ToSDelay
    Bases: pcapkit.vendor.default.Vendor

    ToS (DS Field) Delay

    count (data)
        Count field records.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Field recordings.

        Return type Counter

    process (data)
        Process registry data.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    request ()
        Fetch registry data.

        Returns Registry data (DATA).

        Return type Dict[int, str]

    FLAG = 'isinstance(value, int) and 0 <= value <= 1'
        Value limit checker.

pcapkit.vendor.ipv4.tos_del.DATA = {0: 'Normal', 1: 'Low'}
    ToS registry.
```

ToS ECN Field

```
class pcapkit.vendor.ipv4.tos_ecn.ToSECN
    Bases: pcapkit.vendor.default.Vendor

    ToS ECN Field

    count (data)
        Count field records.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Field recordings.

        Return type Counter

    process (data)
        Process registry data.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    rename (name, code)
        Rename duplicated fields.
```

Parameters

- **name** (*str*) – Field name.
- **code** (*int*) – Field code.

Returns Revised field name.

Return type *str*

request ()

Fetch registry data.

Returns Registry data (*DATA*).

Return type Dict[int, str]

FLAG = 'isinstance(value, int) and 0b00 <= value <= 0b11'

Value limit checker.

```
pcapkit.vendor.ipv4.tos_ecn.DATA = {0: 'Not-ECT', 1: 'ECT(1)', 2: 'ECT(0)', 3: 'CE'}
ToS registry.
```

ToS (DS Field) Precedence

class pcapkit.vendor.ipv4.tos_pre.ToSPrecedence

Bases: *pcapkit.vendor.default.Vendor*

ToS (DS Field) Precedence

count (*data*)

Count field records.

Parameters *data* (Dict[int, str]) – Registry data.

Returns Field recordings.

Return type Counter

process (*data*)

Process registry data.

Parameters *data* (Dict[int, str]) – Registry data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

request ()

Fetch registry data.

Returns Registry data (*DATA*).

Return type Dict[int, str]

FLAG = 'isinstance(value, int) and 0b000 <= value <= 0b111'

Value limit checker.

```
pcapkit.vendor.ipv4.tos_pre.DATA = {0: 'Routine', 1: 'Priority', 2: 'Immediate', 3: 'F'}
ToS registry.
```

ToS (DS Field) Reliability

```
class pcapkit.vendor.ipv4.tos_rel.ToSReliability
    Bases: pcapkit.vendor.default.Vendor

    ToS (DS Field) Reliability

    count (data)
        Count field records.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Field recordings.

        Return type Counter

    process (data)
        Process registry data.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    request ()
        Fetch registry data.

        Returns Registry data (DATA).

        Return type Dict[int, str]

    FLAG = 'isinstance(value, int) and 0 <= value <= 1'
        Value limit checker.

pcapkit.vendor.ipv4.tos_rel.DATA = {0: 'Normal', 1: 'High'}
    ToS registry.
```

ToS (DS Field) Throughput

```
class pcapkit.vendor.ipv4.tos_thr.ToSThroughput
    Bases: pcapkit.vendor.default.Vendor

    ToS (DS Field) Throughput

    count (data)
        Count field records.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Field recordings.

        Return type Counter

    process (data)
        Process registry data.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    request ()
        Fetch registry data.
```

Returns Registry data (*DATA*).

Return type Dict[int, str]

FLAG = 'isinstance(value, int) and 0 <= value <= 1'

pcapkit.vendor.ipv4.tos_thr.DATA = {0: 'Normal', 1: 'High'}
ToS registry.

1.10.6 IPv6 Vendor Crawler

IPv6 Extension Header Types^{*0}

*

class pcapkit.vendor.ipv6.extension_header.**ExtensionHeader**
Bases: *pcapkit.vendor.default.Vendor*

IPv6 Extension Header Types

context (*data*)

Generate constant context.

Parameters *data* (*List[str]*) – CSV data.

Returns Constant context.

Return type str

count (*data*)

Count field records.

Parameters *data* (*List[str]*) – CSV data.

Returns Field recordings.

Return type Counter

process (*data*)

Process CSV data.

Parameters *data* (*List[str]*) – CSV data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

LINK = 'https://www.iana.org/assignments/protocol-numbers/protocol-numbers-1.csv'

Link to registry.

pcapkit.vendor.ipv6.extension_header.**LINE** (*NAME, DOCS, ENUM*)

⁰ <https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters.xhtml#extension-header>

Destination Options and Hop-by-Hop Options†⁰

†

```
class pcapkit.vendor.ipv6.option.Option
    Bases: pcapkit.vendor.default.Vendor

    Destination Options and Hop-by-Hop Options

    count (data)
        Count field records.

        Parameters data (List[str]) – CSV data.

        Returns Field recordings.

        Return type Counter

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    FLAG = 'isinstance(value, int) and 0x00 <= value <= 0xFF'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters-2.csv'
        Link to registry.

pcapkit.vendor.ipv6.option.DATA = {0: ('pad', 'Pad1'), 1: ('padn', 'PadN'), 4: ('tun',
    IPv6 option registry.
```

IPv6 QS Functions

```
class pcapkit.vendor.ipv6.qs_function.QSFunction
    Bases: pcapkit.vendor.default.Vendor

    QS Functions

    count (data)
        Count field records.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Field recordings.

        Return type Counter

    process (data)
        Process registry data.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    request ()
        Fetch registry data.
```

⁰ <https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters.xhtml#ipv6-parameters-2>

Returns Registry data (*DATA*).

Return type Dict[int, str]

FLAG = 'isinstance(value, int) and 0 <= value <= 8'

Value limit checker.

```
pcapkit.vendor.ipv6.qs_function.DATA = {0: 'Quick-Start Request', 8: 'Report of Approved
    QS function registry.
```

IPv6 Router Alert Option Values⁰

⚡

```
class pcapkit.vendor.ipv6.router_alert.RouterAlert
    Bases: pcapkit.vendor.default.Vendor
```

IPv6 Router Alert Option Values

process (*data*)

Process CSV data.

Parameters *data* (*List[str]*) – CSV data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

FLAG = 'isinstance(value, int) and 0 <= value <= 65535'

Value limit checker.

LINK = 'https://www.iana.org/assignments/ipv6-routeralert-values/ipv6-routeralert-values'

Link to registry.

Routing Types⁰

```
class pcapkit.vendor.ipv6.routing.Routing
    Bases: pcapkit.vendor.default.Vendor
```

IPv6 Routing Types

process (*data*)

Process CSV data.

Parameters *data* (*List[str]*) – CSV data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

FLAG = 'isinstance(value, int) and 0 <= value <= 255'

Value limit checker.

LINK = 'https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters-3.csv'

Link to registry.

⁰ <https://www.iana.org/assignments/ipv6-routeralert-values/ipv6-routeralert-values.xhtml#ipv6-routeralert-values-1>

¹⁵⁹ <https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters.xhtml#ipv6-parameters-3>

Seed-ID Types

```
class pcapkit.vendor.ipv6.seed_id.SeedID
    Bases: pcapkit.vendor.default.Vendor

    Seed-ID Types

    count (data)
        Count field records.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Field recordings.

        Return type Counter

    process (data)
        Process registry data.

        Parameters data (Dict[int, str]) – Registry data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    request ()
        Fetch registry data.

        Returns Registry data (DATA).

        Return type Dict[int, str]

    FLAG = 'isinstance(value, int) and 0b00 <= value <= 0b11'
        Value limit checker.

pcapkit.vendor.ipv6.seed_id.DATA = {0: 'IPv6 Source Address', 1: '16-Bit Unsigned Integer'}
Seed-ID type registry [RFC 7731].
```

TaggerId Types⁰

¶

```
class pcapkit.vendor.ipv6.tagger_id.TaggerID
    Bases: pcapkit.vendor.default.Vendor

    TaggerID Types

    process (data)
        Process CSV data.

        Parameters data (List[str]) – CSV data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    FLAG = 'isinstance(value, int) and 0 <= value <= 7'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/ipv6-parameters/taggerId-types.csv'
        Link to registry.
```

⁰ <https://www.iana.org/assignments/ipv6-parameters/ipv6-parameters.xhtml#taggerId-types>

1.10.7 IPX Vendor Crawler

IPX Packet Types^{*0}

*

```
class pcapkit.vendor.ipx.packet.Packet
    Bases: pcapkit.vendor.default.Vendor
    IPX Packet Types

    count (data)
        Count field records.

    process (soup)
        Process HTML source.

        Parameters data (bs4.BeautifulSoup) – Parsed HTML source.
        Returns Enumeration fields. List[str]: Missing fields.
        Return type List[str]

    request (text)
        Fetch HTML source.

        Parameters text (str) – Context from LINK.
        Returns Parsed HTML source.
        Return type bs4.BeautifulSoup

    FLAG = 'isinstance(value, int) and 0 <= value <= 255'
        Value limit checker.

    LINK = 'https://en.wikipedia.org/wiki/Internetwork_Packet_Exchange#IPX_packet_structur'
        Link to registry.
```

IPX Socket Types^{†0}

†

```
class pcapkit.vendor.ipx.socket.Socket
    Bases: pcapkit.vendor.default.Vendor
    Socket Types

    count (data)
        Count field records.

    process (soup)
        Process HTML source.

        Parameters data (bs4.BeautifulSoup) – Parsed HTML source.
        Returns Enumeration fields. List[str]: Missing fields.
        Return type List[str]

    request (text)
        Fetch HTML source.
```

⁰ https://en.wikipedia.org/wiki/Internetwork_Packet_Exchange#IPX_packet_structure

⁰ https://en.wikipedia.org/wiki/Internetwork_Packet_Exchange#Socket_number

Parameters `text` (*str*) – Context from LINK.

Returns Parsed HTML source.

Return type `bs4.BeautifulSoup`

FLAG = `'isinstance(value, int) and 0x0000 <= value <= 0xFFFF'`
Value limit checker.

LINK = `'https://en.wikipedia.org/wiki/Internetwork_Packet_Exchange#Socket_number'`
Link to registry.

1.10.8 MH Vendor Crawler

Mobility Header Types^{*0}

*

class `pcapkit.vendor.mh.packet.Packet`
Bases: `pcapkit.vendor.default.Vendor`

Mobility Header Types - for the MH Type field in the Mobility Header

process (*data*)
Process CSV data.

Parameters `data` (*List[str]*) – CSV data.

Returns Enumeration fields. *List[str]*: Missing fields.

Return type *List[str]*

FLAG = `'isinstance(value, int) and 0 <= value <= 255'`
Value limit checker.

LINK = `'https://www.iana.org/assignments/mobility-parameters/mobility-parameters-1.csv'`
Link to registry.

1.10.9 OSPF Vendor Crawler

Authentication Codes^{*0}

*

class `pcapkit.vendor.ospf.authentication.Authentication`
Bases: `pcapkit.vendor.default.Vendor`

Authentication Types

FLAG = `'isinstance(value, int) and 0 <= value <= 65535'`
Value limit checker.

LINK = `'https://www.iana.org/assignments/ospf-authentication-codes/authentication-codes'`
Link to registry.

⁰ <https://www.iana.org/assignments/mobility-parameters/mobility-parameters.xhtml#mobility-parameters-1>

⁰ <https://www.iana.org/assignments/ospf-authentication-codes/ospf-authentication-codes.xhtml#authentication-codes>

OSPF Packet Type†⁰

†

```
class pcapkit.vendor.ospf.packet.Packet
    Bases: pcapkit.vendor.default.Vendor

    OSPF Packet Types

    FLAG = 'isinstance(value, int) and 0 <= value <= 65535'
        Value limit checker.

    LINK = 'https://www.iana.org/assignments/ospfv2-parameters/ospfv2-parameters-3.csv'
        Link to registry.
```

1.10.10 Protocol Type Registry Vendor Crawlers

LINK-LAYER HEADER TYPES*⁰

*

```
class pcapkit.vendor.reg.linktype.LinkType
    Bases: pcapkit.vendor.default.Vendor

    Link-Layer Header Type Values

    count (data)
        Count field records.

    process (data)
        Process registry data.

        Parameters data (List[str]) – Registry data.

        Returns Enumeration fields. List[str]: Missing fields.

        Return type List[str]

    request (text)
        Fetch registry table.

        Parameters text (str) – Context from LINK.

        Returns Rows (tr) from registry table (table).

        Return type List[str]

    FLAG = 'isinstance(value, int) and 0x00000000 <= value <= 0xFFFFFFFF'
        Value limit checker.

    LINK = 'http://www.tcpdump.org/linktypes.html'
        Link to registry.
```

⁰ <https://www.iana.org/assignments/ospfv2-parameters/ospfv2-parameters.xhtml#ospfv2-parameters-3>

⁰ <http://www.tcpdump.org/linktypes.html>

ETHER TYPES†⁰

†

class pcapkit.vendor.reg.ethertype.**EtherType**Bases: *pcapkit.vendor.default.Vendor*

Ethertype IEEE 802 Numbers

count (*data*)

Count field records.

Parameters *data* (*List[str]*) – CSV data.**Returns** Field recordings.**Return type** Counter**process** (*data*)

Process CSV data.

Parameters *data* (*List[str]*) – CSV data.**Returns** Enumeration fields. List[str]: Missing fields.**Return type** List[str]**rename** (*name*, *code*)

Rename duplicated fields.

Parameters

- **name** (*str*) – Field name.
- **code** (*str*) – Field code (hex).

Keyword Arguments **original** (*str*) – Original field name (extracted from CSV records).**Returns** Revised field name.**Return type** str**FLAG** = 'isinstance(value, int) and 0x0000 <= value <= 0xFFFF'

Value limit checker.

LINK = 'https://www.iana.org/assignments/ieee-802-numbers/ieee-802-numbers-1.csv'

Link to registry.

Assigned Internet Protocol Numbers‡⁰

‡

class pcapkit.vendor.reg.transtype.**TransType**Bases: *pcapkit.vendor.default.Vendor*

Transport Layer Protocol Numbers

count (*data*)

Count field records.

Parameters *data* (*List[str]*) – CSV data.**Returns** Field recordings.

⁰ <https://www.iana.org/assignments/ieee-802-numbers/ieee-802-numbers.xhtml#ieee-802-numbers-1>⁰ <https://www.iana.org/assignments/protocol-numbers/protocol-numbers.xhtml#protocol-numbers-1>

```
process (data)
    Process CSV data.

    Parameters data (List[str]) – CSV data.

    Returns Enumeration fields. List[str]: Missing fields.

    Return type List[str]

FLAG = 'isinstance(value, int) and 0 <= value <= 255'
    Value limit checker.

LINK = 'https://www.iana.org/assignments/protocol-numbers/protocol-numbers-1.csv'
    Link to registry.
```

1.10.11 TCP Vendor Crawler

TCP Checksum*⁰

*

```
class pcapkit.vendor.tcp.checksum.Checksum
```

Bases: `pcapkit.vendor.default.Vendor`

TCP Checksum [RFC 1146]

count (*data*)

Count field records.

Parameters `data` (`Dict[int, str]`) – Registry data.

Returns Field recordings.

Return type Counter

```
process (data)
```

Process CSV data.

Parameters `data` (`Dict[int, str]`) – Registry data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

```
request ()
```

Fetch registry data.

Returns TCP checksum options, i.e. *DATA*.

Return type Dict[int, str]

```
FLAG = 'isinstance(value, int) and 0 <= value <= 255'
```

Value limit checker.

```
pcapkit.vendor.tcp.checksum.DATA = {0:  'TCP checksum', 1:  "8-bit Fletcher's algorithm", 2:  "16-bit Fletcher's algorithm", 3:  "CRC-32", 4:  "CRC-32C", 5:  "CRC-64", 6:  "CRC-64C", 7:  "CRC-64N", 8:  "CRC-64N-2", 9:  "CRC-64N-3", 10: "CRC-64N-4", 11: "CRC-64N-5", 12: "CRC-64N-6", 13: "CRC-64N-7", 14: "CRC-64N-8", 15: "CRC-64N-9", 16: "CRC-64N-10", 17: "CRC-64N-11", 18: "CRC-64N-12", 19: "CRC-64N-13", 20: "CRC-64N-14", 21: "CRC-64N-15", 22: "CRC-64N-16", 23: "CRC-64N-17", 24: "CRC-64N-18", 25: "CRC-64N-19", 26: "CRC-64N-20", 27: "CRC-64N-21", 28: "CRC-64N-22", 29: "CRC-64N-23", 30: "CRC-64N-24", 31: "CRC-64N-25", 32: "CRC-64N-26", 33: "CRC-64N-27", 34: "CRC-64N-28", 35: "CRC-64N-29", 36: "CRC-64N-30", 37: "CRC-64N-31", 38: "CRC-64N-32", 39: "CRC-64N-33", 40: "CRC-64N-34", 41: "CRC-64N-35", 42: "CRC-64N-36", 43: "CRC-64N-37", 44: "CRC-64N-38", 45: "CRC-64N-39", 46: "CRC-64N-40", 47: "CRC-64N-41", 48: "CRC-64N-42", 49: "CRC-64N-43", 50: "CRC-64N-44", 51: "CRC-64N-45", 52: "CRC-64N-46", 53: "CRC-64N-47", 54: "CRC-64N-48", 55: "CRC-64N-49", 56: "CRC-64N-50", 57: "CRC-64N-51", 58: "CRC-64N-52", 59: "CRC-64N-53", 60: "CRC-64N-54", 61: "CRC-64N-55", 62: "CRC-64N-56", 63: "CRC-64N-57", 64: "CRC-64N-58", 65: "CRC-64N-59", 66: "CRC-64N-60", 67: "CRC-64N-61", 68: "CRC-64N-62", 69: "CRC-64N-63", 70: "CRC-64N-64", 71: "CRC-64N-65", 72: "CRC-64N-66", 73: "CRC-64N-67", 74: "CRC-64N-68", 75: "CRC-64N-69", 76: "CRC-64N-70", 77: "CRC-64N-71", 78: "CRC-64N-72", 79: "CRC-64N-73", 80: "CRC-64N-74", 81: "CRC-64N-75", 82: "CRC-64N-76", 83: "CRC-64N-77", 84: "CRC-64N-78", 85: "CRC-64N-79", 86: "CRC-64N-80", 87: "CRC-64N-81", 88: "CRC-64N-82", 89: "CRC-64N-83", 90: "CRC-64N-84", 91: "CRC-64N-85", 92: "CRC-64N-86", 93: "CRC-64N-87", 94: "CRC-64N-88", 95: "CRC-64N-89", 96: "CRC-64N-90", 97: "CRC-64N-91", 98: "CRC-64N-92", 99: "CRC-64N-93", 100: "CRC-64N-94", 101: "CRC-64N-95", 102: "CRC-64N-96", 103: "CRC-64N-97", 104: "CRC-64N-98", 105: "CRC-64N-99", 106: "CRC-64N-100", 107: "CRC-64N-101", 108: "CRC-64N-102", 109: "CRC-64N-103", 110: "CRC-64N-104", 111: "CRC-64N-105", 112: "CRC-64N-106", 113: "CRC-64N-107", 114: "CRC-64N-108", 115: "CRC-64N-109", 116: "CRC-64N-110", 117: "CRC-64N-111", 118: "CRC-64N-112", 119: "CRC-64N-113", 120: "CRC-64N-114", 121: "CRC-64N-115", 122: "CRC-64N-116", 123: "CRC-64N-117", 124: "CRC-64N-118", 125: "CRC-64N-119", 126: "CRC-64N-120", 127: "CRC-64N-121", 128: "CRC-64N-122", 129: "CRC-64N-123", 130: "CRC-64N-124", 131: "CRC-64N-125", 132: "CRC-64N-126", 133: "CRC-64N-127", 134: "CRC-64N-128", 135: "CRC-64N-129", 136: "CRC-64N-130", 137: "CRC-64N-131", 138: "CRC-64N-132", 139: "CRC-64N-133", 140: "CRC-64N-134", 141: "CRC-64N-135", 142: "CRC-64N-136", 143: "CRC-64N-137", 144: "CRC-64N-138", 145: "CRC-64N-139", 146: "CRC-64N-140", 147: "CRC-64N-141", 148: "CRC-64N-142", 149: "CRC-64N-143", 150: "CRC-64N-144", 151: "CRC-64N-145", 152: "CRC-64N-146", 153: "CRC-64N-147", 154: "CRC-64N-148", 155: "CRC-64N-149", 156: "CRC-64N-150", 157: "CRC-64N-151", 158: "CRC-64N-152", 159: "CRC-64N-153", 160: "CRC-64N-154", 161: "CRC-64N-155", 162: "CRC-64N-156", 163: "CRC-64N-157", 164: "CRC-64N-158", 165: "CRC-64N-159", 166: "CRC-64N-160", 167: "CRC-64N-161", 168: "CRC-64N-162", 169: "CRC-64N-163", 170: "CRC-64N-164", 171: "CRC-64N-165", 172: "CRC-64N-166", 173: "CRC-64N-167", 174: "CRC-64N-168", 175: "CRC-64N-169", 176: "CRC-64N-170", 177: "CRC-64N-171", 178: "CRC-64N-172", 179: "CRC-64N-173", 180: "CRC-64N-174", 181: "CRC-64N-175", 182: "CRC-64N-176", 183: "CRC-64N-177", 184: "CRC-64N-178", 185: "CRC-64N-179", 186: "CRC-64N-180", 187: "CRC-64N-181", 188: "CRC-64N-182", 189: "CRC-64N-183", 190: "CRC-64N-184", 191: "CRC-64N-185", 192: "CRC-64N-186", 193: "CRC-64N-187", 194: "CRC-64N-188", 195: "CRC-64N-189", 196: "CRC-64N-190", 197: "CRC-64N-191", 198: "CRC-64N-192", 199: "CRC-64N-193", 200: "CRC-64N-194", 201: "CRC-64N-195", 202: "CRC-64N-196", 203: "CRC-64N-197", 204: "CRC-64N-198", 205: "CRC-64N-199", 206: "CRC-64N-200", 207: "CRC-64N-201", 208: "CRC-64N-202", 209: "CRC-64N-203", 210: "CRC-64N-204", 211: "CRC-64N-205", 212: "CRC-64N-206", 213: "CRC-64N-207", 214: "CRC-64N-208", 215: "CRC-64N-209", 216: "CRC-64N-210", 217: "CRC-64N-211", 218: "CRC-64N-212", 219: "CRC-64N-213", 220: "CRC-64N-214", 221: "CRC-64N-215", 222: "CRC-64N-216", 223: "CRC-64N-217", 224: "CRC-64N-218", 225: "CRC-64N-219", 226: "CRC-64N-220", 227: "CRC-64N-221", 228: "CRC-64N-222", 229: "CRC-64N-223", 230: "CRC-64N-224", 231: "CRC-64N-225", 232: "CRC-64N-226", 233: "CRC-64N-227", 234: "CRC-64N-228", 235: "CRC-64N-229", 236: "CRC-64N-230", 237: "CRC-64N-231", 238: "CRC-64N-232", 239: "CRC-64N-233", 240: "CRC-64N-234", 241: "CRC-64N-235", 242: "CRC-64N-236", 243: "CRC-64N-237", 244: "CRC-64N-238", 245: "CRC-64N-239", 246: "CRC-64N-240", 247: "CRC-64N-241", 248: "CRC-64N-242", 249: "CRC-64N-243", 250: "CRC-64N-244", 251: "CRC-64N-245", 252: "CRC-64N-246", 253: "CRC-64N-247", 254: "CRC-64N-248", 255: "CRC-64N-249", 256: "CRC-64N-250", 257: "CRC-64N-251", 258: "CRC-64N-252", 259: "CRC-64N-253", 260: "CRC-64N-254", 261: "CRC-64N-255", 262: "CRC-64N-256", 263: "CRC-64N-257", 264: "CRC-64N-258", 265: "CRC-64N-259", 266: "CRC-64N-260", 267: "CRC-64N-261", 268: "CRC-64N-262", 269: "CRC-64N-263", 270: "CRC
```

⁰ <https://www.iana.org/assignments/tcp-parameters/tcp-parameters.xhtml#tcp-parameters-2>

TCP Option Kind Numbers†⁰

†

class pcapkit.vendor.tcp.option.OptionBases: *pcapkit.vendor.default.Vendor*

TCP Option Kind Numbers

count (*data*)

Count field records.

Parameters *data* (*List[str]*) – CSV data.**Returns** Field recordings.**Return type** Counter**process** (*data*)

Process CSV data.

Parameters *data* (*List[str]*) – CSV data.**Returns** Enumeration fields. *List[str]*: Missing fields.**Return type** *List[str]***FLAG** = 'isinstance(value, int) and 0 <= value <= 255'

Value limit checker.

LINK = 'https://www.iana.org/assignments/tcp-parameters/tcp-parameters-1.csv'

Link to registry.

```
pcapkit.vendor.tcp.option.DATA = {0: (False, 'eool'), 1: (False, 'nop'), 2: (True, 'mss')
TCP option registry.
```

```
pcapkit.vendor.tcp.option.F = False
```

Boolean aliases.

```
pcapkit.vendor.tcp.option.T = True
```

Boolean aliases.

1.10.12 VLAN Vendor Crawler

Priority Levels*⁰

*

class pcapkit.vendor.vlan.priority_level.PriorityLevelBases: *pcapkit.vendor.default.Vendor*

Priority levels defined in IEEE 802.1p.

count (*soup*)

Count field records.

process (*soup*)

Process HTML data.

Parameters *data* (*bs4.BeautifulSoup*) – Parsed HTML source.

⁰ <https://www.iana.org/assignments/tcp-parameters/tcp-parameters.xhtml#tcp-parameters-1>⁰ https://en.wikipedia.org/wiki/IEEE_P802.1p#Priority_levels

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

request (*text*)

Fetch CSV file.

Parameters **text** (*str*) – Context from *LINK*.

Returns Parsed HTML source.

Return type bs4.BeautifulSoup

FLAG = 'isinstance(value, int) and 0b000 <= value <= 0b111'

Value limit checker.

LINK = 'https://en.wikipedia.org/wiki/IEEE_P802.1p#Priority_levels'

Link to registry.

1.10.13 Base Generator

class pcapkit.vendor.default.**Vendor**

Bases: *object*

Default vendor generator.

Inherit this class with *FLAG* & *LINK* attributes, etc. to implement a new vendor generator.

__init__ ()

Generate new constant files.

static **__new__** (*cls*)

Subclassing checkpoint.

Raises *VendorNotImplemented* – If *cls* is not a subclass of *Vendor*.

__request ()

Fetch CSV data from *LINK*.

This is the low-level call of *request* ().

If *LINK* is None, it will directly call the upper method *request* () with **NO** arguments.

The method will first try to *GET* the content of *LINK*. Should any exception raised, it will first try with proxy settings from *get_proxies* ().

Note: Since some *LINK* links are from Wikipedia, etc., they might not be available in certain areas, e.g. the amazing PRC :)

Would proxies failed again, it will prompt for user intervention, i.e. it will use *webbrowser.open* () to open the page in browser for you, and you can manually load that page and save the HTML source at the location it provides.

Returns CSV data.

Return type List[str]

Warns *VendorRequestWarning* – If connection failed with and/or without proxies.

See also:

request ()

context (*data*)

Generate constant context.

Parameters **data** (*List[str]*) – CSV data.

Returns Constant context.

Return type *str*

count (*data*)

Count field records.

Parameters **data** (*List[str]*) – CSV data.

Returns Field recordings.

Return type Counter

process (*data*)

Process CSV data.

Parameters **data** (*List[str]*) – CSV data.

Returns Enumeration fields. List[str]: Missing fields.

Return type List[str]

rename (*name, code, *, original=None*)

Rename duplicated fields.

Parameters

- **name** (*str*) – Field name.
- **code** (*int*) – Field code.

Keyword Arguments **original** (*str*) – Original field name (extracted from CSV records).

Returns Revised field name.

Return type *str*

Example

If *name* has multiple occurrences in the source registry, the field name will be sanitised as `${name}_${code}`.

Otherwise, the plain *name* will be returned.

request (*text=None*)

Fetch CSV file.

Parameters **text** (*str*) – Context from *LINK*.

Returns CSV data.

Return type List[str]

safe_name (*name*)

Convert enumeration name to `enum.Enum` friendly.

Parameters **name** (*str*) – original enumeration name

Returns Converted enumeration name.

Return type *str*

static wrap_comment (*text*)
Wraps long-length text to shorter lines of comments.

Parameters **text** (*str*) – Source text.

Returns Wrapped comments.

DOCS
Docstring of constant enumeration.

Type *str*

FLAG = None
Value limit checker.

Type *str*

LINK = None
Link to registry.

Type *str*

NAME
Name of constant enumeration.

Type *str*

`pcapkit.vendor.default.LINE` (*NAME, DOCS, FLAG, ENUM, MISS*)
Default constant template of enumerate registry from IANA CSV.

`pcapkit.vendor.default.get_proxies()`
Get proxy for blocked sites.

The function will read `PCAPKIT_HTTP_PROXY` and `PCAPKIT_HTTPS_PROXY`, if any, for the proxy settings of `requests`.

Returns Proxy settings for `requests`.

Return type Dict[*str*, *str*]

1.10.14 Command Line Tool

```
usage: pcapkit-vendor [-h] [-V] ...

update constant enumerations

positional arguments:
  target                update targets, supply none to update all

optional arguments:
  -h, --help            show this help message and exit
  -V, --version          show program's version number and exit
```

`pcapkit.vendor.__main__.get_parser()`
CLI argument parser.

Returns Argument parser.

Return type `argparse.ArgumentParser`

`pcapkit.vendor.__main__.main()`
Entrypoint.

Warns InvalidVendorWarning – If vendor target not found in `pcapkit.vendor` module.

`pcapkit.vendor.__main__.run (vendor)`
Script runner.

Parameters vendor (`Type[Vendor]`) – Subclass of `Vendor` from `pcapkit.vendor`.

Warns VendorRuntimeWarning – If failed to initiate the `vendor` class.

In `pcapkit`, all files can be described as following eight different components.

- Interface (`pcapkit.interface`)
user interface for the `pcapkit` library, which standardise and simplify the usage of this library
- Foundation (`pcapkit.foundation`)
synthesise file I/O and protocol analysis, coordinate information exchange in all network layers
- Reassembly (`pcapkit.reassembly`)
base on algorithms described in **RFC 815**, implement datagram reassembly of IP and TCP packets
- Protocols (`pcapkit.protocols`)
collection of all protocol family, with detailed implementation and methods
- Utilities (`pcapkit.utilities`)
collection of utility functions and classes
- CoreKit (`pcapkit.corekit`)
core utilities for `pcapkit` implementation
- ToolKit (`pcapkit.toolkit`)
utility tools for `pcapkit` implementation
- DumpKit (`pcapkit.dumpkit`)
dump utilities for `pcapkit` implementation

1.11 Library Index

`pcapkit` has defined various and numerous functions and classes, which have different features and purposes. To make a simple index for this library, `pcapkit.all` contains all things from `pcapkit`.

COMMAND LINE INTERFACE

`pcapkit.__main__` was originally the module file of `jspcap.py`, which is now deprecated and merged with `pcapkit`.

```
usage: pcapkit-cli [-h] [-V] [-o file-name] [-f format] [-j] [-p] [-t] [-a]
                  [-v] [-F] [-E PKG] [-P PROTOCOL] [-L LAYER]
                  input-file-name

PCAP file extractor and formatted dumper

positional arguments:
  input-file-name      The name of input pcap file. If ".pcap" omits, it will
                        be automatically appended.

optional arguments:
  -h, --help            show this help message and exit
  -V, --version          show program's version number and exit
  -o file-name, --output file-name
                        The name of input pcap file. If format extension
                        omits, it will be automatically appended.
  -f format, --format format
                        Print a extraction report in the specified output
                        format. Available are all formats supported by
                        dictdumper, e.g.: json, plist, and tree.
  -j, --json            Display extraction report as json. This will yield
                        "raw" output that may be used by external tools. This
                        option overrides all other options.
  -p, --plist           Display extraction report as macOS Property List
                        (plist). This will yield "raw" output that may be used
                        by external tools. This option overrides all other
                        options.
  -t, --tree            Display extraction report as tree view text. This will
                        yield "raw" output that may be used by external tools.
                        This option overrides all other options.
  -a, --auto-extension  If output file extension omits, append automatically.
  -v, --verbose          Show more information.
  -F, --files           Split each frame into different files.
  -E PKG, --engine PKG  Indicate extraction engine. Note that except default
                        or pcapkit engine, all other engines need support of
                        corresponding packages.
  -P PROTOCOL, --protocol PROTOCOL
                        Indicate extraction stops after which protocol.
  -L LAYER, --layer LAYER
                        Indicate extract frames until which layer.
```


ABOUT

PyPCAPKit is an independent open source library, using only *DictDumper* as its formatted output dumper.

Note: There is a project called *jspcap* works on *pcapkit*, which is a command line tool for PCAP extraction but now ***DEPRECATED***.

Unlike popular PCAP file extractors, such as *Scapy*, *dpkt*, *PyShark*, and etc, *pcapkit* uses **streaming** strategy to read input files. That is to read frame by frame, decrease occupation on memory, as well as enhance efficiency in some way.

3.1 Module Structure

In *pcapkit*, all files can be described as following eight parts.

- Interface (*pcapkit.interface*)
User interface for the *pcapkit* library, which standardise and simplify the usage of this library.
- Foundation (*pcapkit.foundation*)
Synthesise file I/O and protocol analysis, coordinate information exchange in all network layers.
- Reassembly (*pcapkit.reassembly*)
Based on algorithms described in **RFC 815**, implement datagram reassembly of IP and TCP packets.
- Protocols (*pcapkit.protocols*)
Collection of all protocol family, with detail implementation and methods, as well as constructors.
- CoreKit (*pcapkit.corekit*)
Core utilities for *pcapkit* implementation.
- TookKit (*pcapkit.toolkit*)
Compatibility tools for *pcapkit* implementation.
- DumpKit (*pcapkit.dumpkit*)
Dump utilities for *pcapkit* implementation.
- Utilities (*pcapkit.utilities*)
Collection of four utility functions and classes.

3.2 Engine Comparison

Besides, due to complexity of *pcapkit*, its extraction procedure takes around *0.0009* seconds per packet, which is not ideal enough. Thus *pcapkit* introduced alternative extraction engines to accelerate this procedure. By now *pcapkit* supports *Scapy*, *DPKT*, and *PyShark*. Plus, *pcapkit* supports two strategies of multiprocessing (*server* & *pipeline*). For more information, please refer to the documentation.

3.2.1 Test Environment

Operating System	macOS Mojave
Processor Name	Intel Core i7
Processor Speed	2.6 GHz
Total Number of Cores	6
Memory	16 GB

3.2.2 Test Results

Engine	Performance (seconds per packet)
dpkt	0.00017389218012491862
scapy	0.00036091208457946774
default	0.0009537641207377116
pipeline	0.0009694552421569824
server	0.018088217973709107
pyshark	0.04200994372367859

INSTALLATION

Note: *pypcapkit* supports Python versions **since 3.4**.

Simply run the following to install the current version from PyPI:

```
pip install pypcapkit
```

Or install the latest version from the gi repository:

```
git clone https://github.com/JarryShaw/PyPCAPKit.git
cd pypcapkit
pip install -e .
# and to update at any time
git pull
```

And since *pypcapkit* supports various extraction engines, and extensive plug-in functions, you may want to install the optional ones:

```
# for DPKT only
pip install pypcapkit[DPKT]
# for Scapy only
pip install pypcapkit[Scapy]
# for PyShark only
pip install pypcapkit[PyShark]
# and to install all the optional packages
pip install pypcapkit[all]
# or to do this explicitly
pip install pypcapkit dpkt scapy pyshark
```


SAMPLES

5.1 Usage Samples

As described above, `pcapkit` is quite easy to use, with simply three verbs as its main interface. Several scenarios are shown as below.

1. extract a PCAP file and dump the result to a specific file (with no reassembly)

```
import pcapkit
# dump to a PLIST file with no frame storage (property frame disabled)
plist = pcapkit.extract(fin='in.pcap', fout='out.plist', format='plist',
    ↳store=False)
# dump to a JSON file with no extension auto-complete
json = pcapkit.extract(fin='in.cap', fout='out.json', format='json',
    ↳extension=False)
# dump to a folder with each tree-view text file per frame
tree = pcapkit.extract(fin='in.pcap', fout='out', format='tree', files=True)
```

2. extract a PCAP file and fetch IP packet (both IPv4 and IPv6) from a frame (with no output file)

```
>>> import pcapkit
>>> extraction = pcapkit.extract(fin='in.pcap', nofile=True)
>>> frame0 = extraction.frame[0]
# check if IP in this frame, otherwise ProtocolNotFound will be raised
>>> flag = pcapkit.IP in frame0
>>> tcp = frame0[pcapkit.IP] if flag else None
```

3. extract a PCAP file and reassemble TCP payload (with no output file nor frame storage)

```
import pcapkit
# set strict to make sure full reassembly
extraction = pcapkit.extract(fin='in.pcap', store=False, nofile=True, tcp=True,
    ↳strict=True)
# print extracted packet if HTTP in reassembled payloads
for packet in extraction.reassembly.tcp:
    for reassembly in packet.packets:
        if pcapkit.HTTP in reassembly.protochain:
            print(reassembly.info)
```

5.2 CLI Samples

The CLI (command line interface) of *pcapkit* has two different access.

- through console scripts

Use command name `pcapkit` [...] directly (as shown in samples).

- through Python module

`python -m pcapkit` [...] works exactly the same as above.

Here are some usage samples:

1. export to a macOS Property List ([Xcode](#) has special support for this format)

```
$ pcapkit in --format plist --verbose
Loading file 'in.pcap'
- Frame 1: Ethernet:IPv6:ICMPv6
- Frame 2: Ethernet:IPv6:ICMPv6
- Frame 3: Ethernet:IPv4:TCP
- Frame 4: Ethernet:IPv4:TCP
- Frame 5: Ethernet:IPv4:TCP
- Frame 6: Ethernet:IPv4:UDP
Report file stored in 'out.plist'
```

2. export to a JSON file (with no format specified)

```
$ pcapkit in --output out.json --verbose
Loading file 'in.pcap'
- Frame 1: Ethernet:IPv6:ICMPv6
- Frame 2: Ethernet:IPv6:ICMPv6
- Frame 3: Ethernet:IPv4:TCP
- Frame 4: Ethernet:IPv4:TCP
- Frame 5: Ethernet:IPv4:TCP
- Frame 6: Ethernet:IPv4:UDP
Report file stored in 'out.json'
```

3. export to a text tree view file (without extension autocorrect)

```
$ pcapkit in --output out --format tree --verbose
Loading file 'in.pcap'
- Frame 1: Ethernet:IPv6:ICMPv6
- Frame 2: Ethernet:IPv6:ICMPv6
- Frame 3: Ethernet:IPv4:TCP
- Frame 4: Ethernet:IPv4:TCP
- Frame 5: Ethernet:IPv4:TCP
- Frame 6: Ethernet:IPv4:UDP
Report file stored in 'out'
```

INDICES AND TABLES

- `genindex`
- `modindex`
- `search`

PYTHON MODULE INDEX

p

- pcapkit, 3
- pcapkit.all, 366
- pcapkit.const, 266
 - arp, 266
 - arp.hardware, 266
 - arp.operation, 268
 - ftp, 270
 - command, 270
 - return_code, 270
 - hip, 273
 - certificate, 273
 - cipher, 274
 - di, 274
 - ecdsa_curve, 275
 - ecdsa_low_curve, 275
 - esp_transform_suite, 275
 - group, 277
 - hi_algorithm, 278
 - hit_suite, 278
 - nat_traversal, 279
 - notify_message, 279
 - packet, 281
 - parameter, 282
 - registration, 285
 - registration_failure, 286
 - suite, 286
 - transport, 287
 - http, 288
 - error_code, 288
 - frame, 289
 - setting, 290
 - ipv4, 290
 - classification_level, 290
 - option_class, 291
 - option_number, 291
 - protection_authority, 293
 - qs_function, 294
 - ipv4.router_alert, 294
 - ipv4.tos_del, 297
 - ipv4.tos_ecn, 298
 - ipv4.tos_pre, 298
 - ipv4.tos_rel, 299
 - ipv4.tos_thr, 299
 - ipv6, 299
 - extension_header, 299
 - option, 300
 - qs_function, 302
 - router_alert, 302
 - routing, 306
 - seed_id, 306
 - tagger_id, 307
 - ipx, 307
 - packet, 307
 - socket, 308
 - mh, 309
 - packet, 309
 - ospf, 310
 - authentication, 310
 - packet, 311
 - reg, 312
 - ethertype, 318
 - linktype, 312
 - transtype, 326
 - tcp, 334
 - checksum, 334
 - option, 334
 - vlan, 336
 - priority_level, 336
- corekit, 243
 - infoclass, 243
 - protochain, 243
 - version, 247
- dumpkit, 248
- foundation, 3
 - analysis, 3
 - extraction, 4
 - traceflow, 19
- interface, 21
- protocols, 23

pcapkit.protocols.application, 203
pcapkit.protocols.application.application, 222
pcapkit.protocols.application.ftp, 203
pcapkit.protocols.application.http, 204
pcapkit.protocols.application.httpv1, 205
pcapkit.protocols.application.httpv2, 208
pcapkit.protocols.internet, 45
pcapkit.protocols.internet.ah, 45
pcapkit.protocols.internet.hip, 48
pcapkit.protocols.internet.hopopt, 104
pcapkit.protocols.internet.internet, 174
pcapkit.protocols.internet.ip, 124
pcapkit.protocols.internet.ipsec, 124
pcapkit.protocols.internet.ipv4, 125
pcapkit.protocols.internet.ipv6, 167
pcapkit.protocols.internet.ipv6_frag, 138
pcapkit.protocols.internet.ipv6_opts, 140
pcapkit.protocols.internet.ipv6_route, 160
pcapkit.protocols.internet.ipx, 169
pcapkit.protocols.internet.mh, 172
pcapkit.protocols.link, 32
pcapkit.protocols.link.arp, 32
pcapkit.protocols.link.ethernet, 34
pcapkit.protocols.link.l2tp, 36
pcapkit.protocols.link.link, 44
pcapkit.protocols.link.ospf, 39
pcapkit.protocols.link.rarp, 42
pcapkit.protocols.link.vlan, 43
pcapkit.protocols.null, 225
pcapkit.protocols.pcap, 23
pcapkit.protocols.pcap.frame, 27
pcapkit.protocols.pcap.header, 24
pcapkit.protocols.raw, 223
pcapkit.protocols.transport, 176
pcapkit.protocols.transport.tcp, 178
pcapkit.protocols.transport.transport, 202
pcapkit.protocols.transport.udp, 176
pcapkit.reassembly, 232
pcapkit.reassembly.ip, 235
pcapkit.reassembly.ipv4, 236
pcapkit.reassembly.ipv6, 238
pcapkit.reassembly.reassembly, 233
pcapkit.reassembly.tcp, 242
pcapkit.toolkit, 250
pcapkit.toolkit.default, 250
pcapkit.toolkit.dpkt, 251
pcapkit.toolkit.pyshark, 253
pcapkit.toolkit.scapy, 254
pcapkit.utilities, 256
pcapkit.utilities.exceptions, 258
pcapkit.utilities.validations, 261
pcapkit.utilities.warnings, 265
pcapkit.vendor, 337
pcapkit.vendor.__main__, 365
pcapkit.vendor.arp, 337
pcapkit.vendor.arp.hardware, 337
pcapkit.vendor.arp.operation, 338
pcapkit.vendor.default, 363
pcapkit.vendor.ftp, 338
pcapkit.vendor.ftp.command, 338
pcapkit.vendor.ftp.return_code, 339
pcapkit.vendor.hip, 339
pcapkit.vendor.hip.certificate, 339
pcapkit.vendor.hip.cipher, 340
pcapkit.vendor.hip.di, 340
pcapkit.vendor.hip.ecdsa_curve, 340
pcapkit.vendor.hip.ecdsa_low_curve, 341
pcapkit.vendor.hip.esp_transform_suite, 341
pcapkit.vendor.hip.group, 341
pcapkit.vendor.hip.hi_algorithm, 342
pcapkit.vendor.hip.hit_suite, 342
pcapkit.vendor.hip.nat_traversal, 342
pcapkit.vendor.hip.notify_message, 342
pcapkit.vendor.hip.packet, 343
pcapkit.vendor.hip.parameter, 343
pcapkit.vendor.hip.registration, 343
pcapkit.vendor.hip.registration_failure, 344
pcapkit.vendor.hip.suite, 344
pcapkit.vendor.hip.transport, 344
pcapkit.vendor.http, 345
pcapkit.vendor.http.error_code, 345
pcapkit.vendor.http.frame, 345
pcapkit.vendor.http.setting, 346
pcapkit.vendor.ipv4, 346
pcapkit.vendor.ipv4.classification_level, 346
pcapkit.vendor.ipv4.option_class, 347
pcapkit.vendor.ipv4.option_number, 347
pcapkit.vendor.ipv4.protection_authority, 348
pcapkit.vendor.ipv4.qs_function, 349
pcapkit.vendor.ipv4.router_alert, 349
pcapkit.vendor.ipv4.tos_del, 350
pcapkit.vendor.ipv4.tos_ecn, 350
pcapkit.vendor.ipv4.tos_pre, 351
pcapkit.vendor.ipv4.tos_rel, 352
pcapkit.vendor.ipv4.tos_thr, 352
pcapkit.vendor.ipv6, 353

pcapkit.vendor.ipv6.extension_header,
353
pcapkit.vendor.ipv6.option, 354
pcapkit.vendor.ipv6.qs_function, 354
pcapkit.vendor.ipv6.router_alert, 355
pcapkit.vendor.ipv6.routing, 355
pcapkit.vendor.ipv6.seed_id, 356
pcapkit.vendor.ipv6.tagger_id, 356
pcapkit.vendor.ipx, 357
pcapkit.vendor.ipx.packet, 357
pcapkit.vendor.ipx.socket, 357
pcapkit.vendor.mh, 358
pcapkit.vendor.mh.packet, 358
pcapkit.vendor.ospf, 358
pcapkit.vendor.ospf.authentication, 358
pcapkit.vendor.ospf.packet, 359
pcapkit.vendor.reg, 359
pcapkit.vendor.reg.ethertype, 360
pcapkit.vendor.reg.linktype, 359
pcapkit.vendor.reg.transtype, 360
pcapkit.vendor.tcp, 361
pcapkit.vendor.tcp.checksum, 361
pcapkit.vendor.tcp.option, 362
pcapkit.vendor.vlan, 362
pcapkit.vendor.vlan.priority_level, 362

Symbols

- `_AliasList` (class in `pcapkit.corekit.protochain`), 245
- `_MAGIC_NUM` (in module `pcapkit.protocols.pcap.header`), 26
- `_ProtoList` (class in `pcapkit.corekit.protochain`), 246
- `_RE_METHOD` (in module `pcapkit.protocols.application.httpv1`), 206
- `_RE_STATUS` (in module `pcapkit.protocols.application.httpv1`), 206
- `_RE_VERSION` (in module `pcapkit.protocols.application.httpv1`), 206
- `__alias__` (`pcapkit.corekit.protochain.ProtoChain` attribute), 243
- `__bytes__`() (`pcapkit.protocols.protocol.Protocol` method), 226
- `__call__`() (`pcapkit.dumpkit.NotImplementedIO` method), 249
- `__call__`() (`pcapkit.dumpkit.PCAP` method), 248
- `__call__`() (`pcapkit.foundation.extraction.Extractor` method), 7
- `__call__`() (`pcapkit.foundation.traceflow.TraceFlow` method), 19
- `__call__`() (`pcapkit.reassembly.reassembly.Reassembly` method), 233
- `__contains__`() (`pcapkit.corekit.protochain.ProtoChain` method), 243
- `__contains__`() (`pcapkit.corekit.protochain._AliasList` method), 245
- `__contains__`() (`pcapkit.corekit.protochain._ProtoList` method), 246
- `__contains__`() (`pcapkit.protocols.pcap.frame.Frame` method), 28
- `__contains__`() (`pcapkit.protocols.protocol.Protocol` method), 226
- `__data__` (`pcapkit.corekit.protochain._AliasList` attribute), 245
- `__data__` (`pcapkit.corekit.protochain._ProtoList` attribute), 246
- `__enter__`() (`pcapkit.foundation.extraction.Extractor` method), 7
- `__eq__`() (`pcapkit.protocols.protocol.Protocol` class method), 226
- `__exit__`() (`pcapkit.foundation.extraction.Extractor` method), 8
- `__getitem__`() (`pcapkit.const.ftp.command.defaultInfo` method), 270
- `__getitem__`() (`pcapkit.corekit.protochain._AliasList` method), 245
- `__getitem__`() (`pcapkit.protocols.pcap.frame.Frame` method), 28
- `__getitem__`() (`pcapkit.protocols.protocol.Protocol` method), 226
- `__hash__`() (`pcapkit.protocols.protocol.Protocol` method), 227
- `__index__`() (`pcapkit.protocols.application.application.Application` class method), 222
- `__index__`() (`pcapkit.protocols.internet.ah.AH` class method), 46
- `__index__`() (`pcapkit.protocols.internet.hip.HIP` class method), 48
- `__index__`() (`pcapkit.protocols.internet.hopopt.HOPOPT` class method), 104
- `__index__`() (`pcapkit.protocols.internet.ipv4.Ipv4` class method), 125
- `__index__`() (`pcapkit.protocols.internet.ipv6.Ipv6` class method), 167
- `__index__`() (`pcapkit.protocols.internet.ipv6_frag.Ipv6_Frag` class method), 138
- `__index__`() (`pcapkit.protocols.internet.ipv6_opts.Ipv6_Opts` class method), 140
- `__index__`() (`pcapkit.protocols.internet.ipv6_route.Ipv6_Route` class method), 140

class method), 161
 __index__() (pcapkit.protocols.internet.ipx.IPX class method), 170
 __index__() (pcapkit.protocols.internet.mh.MH class method), 172
 __index__() (pcapkit.protocols.link.arp.ARP class method), 32
 __index__() (pcapkit.protocols.link.ethernet.Ethernet class method), 35
 __index__() (pcapkit.protocols.link.l2tp.L2TP class method), 36
 __index__() (pcapkit.protocols.link.ospf.OSPF class method), 39
 __index__() (pcapkit.protocols.link.rarp.RARP class method), 42
 __index__() (pcapkit.protocols.link.vlan.VLAN class method), 43
 __index__() (pcapkit.protocols.null.NoPayload class method), 225
 __index__() (pcapkit.protocols.pcap.frame.Frame class method), 28
 __index__() (pcapkit.protocols.pcap.header.Header class method), 24
 __index__() (pcapkit.protocols.protocol.Protocol class method), 227
 __index__() (pcapkit.protocols.raw.Raw class method), 223
 __index__() (pcapkit.protocols.transport.tcp.TCP class method), 178
 __index__() (pcapkit.protocols.transport.udp.UDP class method), 176
 __init__() (pcapkit.corekit.protochain.ProtoChain method), 244
 __init__() (pcapkit.corekit.protochain._AliasList method), 245
 __init__() (pcapkit.corekit.protochain._ProtoList method), 247
 __init__() (pcapkit.dumpkit.PCAP method), 248
 __init__() (pcapkit.foundation.extraction.Extractor method), 8
 __init__() (pcapkit.foundation.traceflow.TraceFlow method), 19
 __init__() (pcapkit.protocols.protocol.Protocol method), 227
 __init__() (pcapkit.reassembly.reassembly.Reassembly method), 233
 __init__() (pcapkit.utilities.exceptions.BaseError method), 258
 __init__() (pcapkit.utilities.warnings.BaseWarning method), 265
 __init__() (pcapkit.vendor.default.Vendor method), 363
 __iter__() (pcapkit.corekit.protochain._AliasList method), 246
 __iter__() (pcapkit.corekit.protochain._ProtoList method), 247
 __iter__() (pcapkit.foundation.extraction.Extractor method), 9
 __iter__() (pcapkit.protocols.protocol.Protocol method), 227
 __layer__() (pcapkit.protocols.application.application.Application attribute), 222
 __layer__() (pcapkit.protocols.internet.internet.Internet attribute), 174
 __layer__() (pcapkit.protocols.link.link.Link attribute), 44
 __layer__() (pcapkit.protocols.protocol.Protocol attribute), 226
 __layer__() (pcapkit.protocols.transport.transport.Transport attribute), 202
 __len__() (pcapkit.corekit.protochain._AliasList method), 246
 __len__() (pcapkit.corekit.protochain._ProtoList method), 247
 __len__() (pcapkit.protocols.pcap.header.Header method), 24
 __length_hint__() (pcapkit.protocols.application.http2.HTTPv2 method), 208
 __length_hint__() (pcapkit.protocols.internet.ah.AH method), 46
 __length_hint__() (pcapkit.protocols.internet.hip.HIP method), 48
 __length_hint__() (pcapkit.protocols.internet.hopopt.HOPOPT method), 104
 __length_hint__() (pcapkit.protocols.internet.ipv4.IPv4 method), 125
 __length_hint__() (pcapkit.protocols.internet.ipv6.IPv6 method), 167
 __length_hint__() (pcapkit.protocols.internet.ipv6_frag.IPv6_Frag method), 138
 __length_hint__() (pcapkit.protocols.internet.ipv6_opts.IPv6_Opts method), 141
 __length_hint__() (pcapkit.protocols.internet.ipv6_route.IPv6_Route method), 161
 __length_hint__() (pcapkit.protocols.internet.ipx.IPX method), 170
 __length_hint__() (pcapkit.protocols.internet.mh.MH method), 172
 __length_hint__() (pcapkit.protocols.link.arp.ARP method), 32

<code>__length_hint__()</code>	(<i>pcap-kit.protocols.link.ethernet.Ethernet</i> method), 35	<code>kit.protocols.pcap.frame.Frame</code> method), 28	<code>__post_init__()</code>	(<i>pcap-kit.protocols.pcap.header.Header</i> method), 24
<code>__length_hint__()</code>	(<i>pcap-kit.protocols.link.l2tp.L2TP</i> method), 36		<code>__post_init__()</code>	(<i>pcap-kit.protocols.protocol.Protocol</i> method), 227
<code>__length_hint__()</code>	(<i>pcap-kit.protocols.link.ospf.OSPF</i> method), 39		<code>__post_init__()</code>	(<i>pcapkit.protocols.raw.Raw</i> method), 223
<code>__length_hint__()</code>	(<i>pcap-kit.protocols.link.vlan.VLAN</i> method), 43		<code>__proto__</code>	(<i>pcapkit.corekit.protochain.ProtoChain</i> attribute), 243
<code>__length_hint__()</code>	(<i>pcap-kit.protocols.pcap.frame.Frame</i> method), 28		<code>__proto__</code>	(<i>pcapkit.protocols.internet.internet.Internet</i> attribute), 174
<code>__length_hint__()</code>	(<i>pcap-kit.protocols.pcap.header.Header</i> method), 24		<code>__proto__</code>	(<i>pcapkit.protocols.link.link.Link</i> attribute), 44
<code>__length_hint__()</code>	(<i>pcap-kit.protocols.protocol.Protocol</i> method), 227		<code>__proto__</code>	(<i>pcapkit.protocols.pcap.frame.Frame</i> attribute), 28
<code>__length_hint__()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 178		<code>__proto__</code>	(<i>pcapkit.protocols.protocol.Protocol</i> attribute), 226
<code>__length_hint__()</code>	(<i>pcap-kit.protocols.transport.udp.UDP</i> method), 176		<code>__repr__()</code>	(<i>pcapkit.corekit.protochain.ProtoChain</i> method), 244
<code>__new__()</code>	(<i>pcapkit.corekit.infoclass.Info</i> static method), 243		<code>__repr__()</code>	(<i>pcapkit.protocols.protocol.Protocol</i> method), 227
<code>__new__()</code>	(<i>pcapkit.vendor.default.Vendor</i> static method), 363		<code>__reversed__()</code>	(<i>pcap-kit.corekit.protochain._AliasList</i> method), 246
<code>__next__()</code>	(<i>pcapkit.foundation.extraction.Extractor</i> method), 9		<code>__str__()</code>	(<i>pcapkit.corekit.protochain.ProtoChain</i> method), 244
<code>__post_init__()</code>	(<i>pcap-kit.protocols.application.application.Application</i> method), 222		<code>_ack</code>	(<i>pcapkit.protocols.transport.tcp.TCP</i> attribute), 178
<code>__post_init__()</code>	(<i>pcapkit.protocols.internet.ah.AH</i> method), 46		<code>_acnm</code>	(<i>pcapkit.protocols.link.arp.ARP</i> attribute), 32
<code>__post_init__()</code>	(<i>pcap-kit.protocols.internet.hip.HIP</i> method), 48		<code>_acnm</code>	(<i>pcapkit.protocols.link.rarp.RARP</i> attribute), 42
<code>__post_init__()</code>	(<i>pcap-kit.protocols.internet.hopopt.HOPOPT</i> method), 104		<code>_aftermathmp()</code>	(<i>pcap-kit.foundation.extraction.Extractor</i> method), 9
<code>__post_init__()</code>	(<i>pcap-kit.protocols.internet.ipv6_frag.Ipv6_Frag</i> method), 139		<code>_analyse_ftp()</code>	(in module <i>pcap-kit.foundation.analysis</i>), 3
<code>__post_init__()</code>	(<i>pcap-kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 141		<code>_analyse_httpv1()</code>	(in module <i>pcap-kit.foundation.analysis</i>), 3
<code>__post_init__()</code>	(<i>pcap-kit.protocols.internet.ipv6_route.Ipv6_Route</i> method), 161		<code>_analyse_httpv2()</code>	(in module <i>pcap-kit.foundation.analysis</i>), 4
<code>__post_init__()</code>	(<i>pcap-kit.protocols.internet.mh.MH</i> method), 172		<code>_append_value()</code>	(<i>pcap-kit.dumpkit.NotImplementedIO</i> method), 249
<code>__post_init__()</code>	(<i>pcapkit.protocols.null.NoPayload</i> method), 225		<code>_append_value()</code>	(<i>pcapkit.dumpkit.PCAP</i> method), 248
<code>__post_init__()</code>	(<i>pcap-kit.protocols.pcap.frame.Frame</i> method), 28		<code>_asdict()</code>	(<i>pcapkit.corekit.version.VersionInfo</i> method), 247
			<code>_buffer</code>	(<i>pcapkit.foundation.traceflow.TraceFlow</i> attribute), 20
			<code>_buffer</code>	(<i>pcapkit.reassembly.reassembly.Reassembly</i> attribute), 233
			<code>_check_term_threshold()</code>	(<i>pcap-</i>

`kit.protocols.protocol.Protocol` method), 227
`_cleanup()` (`pcapkit.foundation.extraction.Extractor` method), 9
`_decode_next_layer()` (`pcapkit.protocols.application.application.Application` method), 223
`_decode_next_layer()` (`pcapkit.protocols.internet.internet.Internet` method), 174
`_decode_next_layer()` (`pcapkit.protocols.internet.ipv6.IPv6` method), 167
`_decode_next_layer()` (`pcapkit.protocols.null.NoPayload` method), 225
`_decode_next_layer()` (`pcapkit.protocols.pcap.frame.Frame` method), 29
`_decode_next_layer()` (`pcapkit.protocols.pcap.header.Header` method), 24
`_decode_next_layer()` (`pcapkit.protocols.protocol.Protocol` method), 228
`_default_read_frame()` (`pcapkit.foundation.extraction.Extractor` method), 9
`_dlink` (`pcapkit.foundation.extraction.Extractor` attribute), 6
`_dpkt_read_frame()` (`pcapkit.foundation.extraction.Extractor` method), 10
`_dtgram` (`pcapkit.reassembly.reassembly.Reassembly` attribute), 233
`_dump_header()` (`pcapkit.dumpkit.NotImplementedIO` method), 249
`_dump_header()` (`pcapkit.dumpkit.PCAP` method), 248
`_endian` (`pcapkit.foundation.traceflow.TraceFlow` attribute), 20
`_exeng` (`pcapkit.foundation.extraction.Extractor` attribute), 6
`_exlayer` (`pcapkit.protocols.protocol.Protocol` attribute), 231
`_exlyr` (`pcapkit.foundation.extraction.Extractor` attribute), 6
`_expkg` (`pcapkit.foundation.extraction.Extractor` attribute), 7
`_exproto` (`pcapkit.protocols.protocol.Protocol` attribute), 231
`_exptl` (`pcapkit.foundation.extraction.Extractor` attribute), 6
`_extmp` (`pcapkit.foundation.extraction.Extractor` attribute), 7
`_fdpext` (`pcapkit.foundation.traceflow.TraceFlow` attribute), 20
`_fext` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_field_defaults` (`pcapkit.corekit.version.VersionInfo` attribute), 247
`_fields` (`pcapkit.corekit.version.VersionInfo` attribute), 247
`_fields_defaults` (`pcapkit.corekit.version.VersionInfo` attribute), 247
`_flag_a` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_flag_d` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_flag_e` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_flag_f` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_flag_m` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_flag_q` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_flag_t` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_flag_v` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_fnum` (`pcapkit.dumpkit.PCAP` attribute), 248
`_foutio` (`pcapkit.foundation.traceflow.TraceFlow` attribute), 20
`_fproot` (`pcapkit.foundation.traceflow.TraceFlow` attribute), 20
`_frame` (`pcapkit.foundation.extraction.Extractor` attribute), 6
`_frnum` (`pcapkit.foundation.extraction.Extractor` attribute), 6
`_gbhdr` (`pcapkit.foundation.extraction.Extractor` attribute), 6
`_ifile` (`pcapkit.foundation.extraction.Extractor` attribute), 6
`_ifnm` (`pcapkit.foundation.extraction.Extractor` attribute), 5
`_import_next_layer()` (`pcapkit.protocols.application.application.Application` method), 223
`_import_next_layer()` (`pcapkit.protocols.internet.internet.Internet` method), 175
`_import_next_layer()` (`pcapkit.protocols.link.link.Link` method), 44
`_import_next_layer()` (`pcapkit.protocols.null.NoPayload` method), 225

<code>_import_next_layer()</code>	(<i>pcap-kit.protocols.pcap.frame.Frame</i> method), 29	<code>_missing_()</code>	(<i>pcap-kit.const.hip.hi_algorithm.HIAlgorithm</i> class method), 278
<code>_import_next_layer()</code>	(<i>pcap-kit.protocols.pcap.header.Header</i> method), 24	<code>_missing_()</code>	(<i>pcapkit.const.hip.hit_suite.HITSuite</i> class method), 278
<code>_import_next_layer()</code>	(<i>pcap-kit.protocols.protocol.Protocol</i> method), 228	<code>_missing_()</code>	(<i>pcap-kit.const.hip.nat_traversal.NATTraversal</i> class method), 279
<code>_import_next_layer()</code>	(<i>pcap-kit.protocols.transport.transport.Transport</i> method), 202	<code>_missing_()</code>	(<i>pcap-kit.const.hip.notify_message.NotifyMessage</i> class method), 279
<code>_ip_frag_check()</code>	(in module <i>pcap-kit.utilities.validations</i>), 261	<code>_missing_()</code>	(<i>pcapkit.const.hip.packet.Packet</i> class method), 281
<code>_ipv4</code>	(<i>pcapkit.foundation.extraction.Extractor</i> attribute), 6	<code>_missing_()</code>	(<i>pcapkit.const.hip.parameter.Parameter</i> class method), 282
<code>_ipv6</code>	(<i>pcapkit.foundation.extraction.Extractor</i> attribute), 6	<code>_missing_()</code>	(<i>pcap-kit.const.hip.registration.Registration</i> class method), 285
<code>_link</code>	(<i>pcapkit.dumpkit.PCAP</i> attribute), 249	<code>_missing_()</code>	(<i>pcap-kit.const.hip.registration_failure.RegistrationFailure</i> class method), 286
<code>_make()</code>	(<i>pcapkit.corekit.version.VersionInfo</i> class method), 247	<code>_missing_()</code>	(<i>pcapkit.const.hip.suite.Suite</i> class method), 286
<code>_make_index()</code>	(<i>pcapkit.protocols.protocol.Protocol</i> class method), 228	<code>_missing_()</code>	(<i>pcapkit.const.hip.transport.Transport</i> class method), 287
<code>_make_magic()</code>	(<i>pcap-kit.protocols.pcap.header.Header</i> method), 24	<code>_missing_()</code>	(<i>pcap-kit.const.http.error_code.ErrorCode</i> class method), 288
<code>_make_pack()</code>	(<i>pcapkit.protocols.protocol.Protocol</i> class method), 228	<code>_missing_()</code>	(<i>pcapkit.const.http.frame.Frame</i> class method), 289
<code>_make_timestamp()</code>	(<i>pcap-kit.protocols.pcap.frame.Frame</i> method), 29	<code>_missing_()</code>	(<i>pcapkit.const.http.setting.Setting</i> class method), 290
<code>_missing_()</code>	(<i>pcapkit.const.arp.hardware.Hardware</i> class method), 266	<code>_missing_()</code>	(<i>pcap-kit.const.ipv4.classification_level.ClassificationLevel</i> class method), 291
<code>_missing_()</code>	(<i>pcapkit.const.arp.operation.Operation</i> class method), 268	<code>_missing_()</code>	(<i>pcap-kit.const.ipv4.option_class.OptionClass</i> class method), 291
<code>_missing_()</code>	(<i>pcap-kit.const.ftp.return_code.ReturnCode</i> class method), 270	<code>_missing_()</code>	(<i>pcap-kit.const.ipv4.option_number.OptionNumber</i> class method), 291
<code>_missing_()</code>	(<i>pcapkit.const.hip.certificate.Certificate</i> class method), 273	<code>_missing_()</code>	(<i>pcap-kit.const.ipv4.protection_authority.ProtectionAuthority</i> class method), 293
<code>_missing_()</code>	(<i>pcapkit.const.hip.cipher.Cipher</i> class method), 274	<code>_missing_()</code>	(<i>pcap-kit.const.ipv4.qs_function.QSFunction</i> class method), 294
<code>_missing_()</code>	(<i>pcapkit.const.hip.di.DITypes</i> class method), 274	<code>_missing_()</code>	(<i>pcap-kit.const.ipv4.router_alert.RouterAlert</i> class method), 294
<code>_missing_()</code>	(<i>pcap-kit.const.hip.ecdsa_curve.ECDSACurve</i> class method), 275	<code>_missing_()</code>	(<i>pcapkit.const.ipv4.tos_del.ToSDelay</i> class method), 297
<code>_missing_()</code>	(<i>pcap-kit.const.hip.ecdsa_low_curve.ECDSALowCurve</i> class method), 275	<code>_missing_()</code>	(<i>pcapkit.const.ipv4.tos_ecn.ToSECN</i> class method), 297
<code>_missing_()</code>	(<i>pcap-kit.const.hip.esp_transform_suite.ESPTransformSuite</i> class method), 275		
<code>_missing_()</code>	(<i>pcapkit.const.hip.group.Group</i> class method), 275		

<i>class method</i>), 298		<i>_mpkit</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7
<i>_missing_()</i> (<i>pcapkit.const.ipv4.tos_pre.ToSPrecedence</i> class method), 298		<i>_mpmng</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7
<i>_missing_()</i> (<i>pcapkit.const.ipv4.tos_rel.ToSReliability</i> class method), 299		<i>_mpprc</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7
<i>_missing_()</i> (<i>pcapkit.const.ipv4.tos_thr.ToSThroughput</i> class method), 299		<i>_mprsm</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7
<i>_missing_()</i> (<i>pcapkit.const.ipv6.option.Option</i> class method), 300		<i>_mpsrv</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7
<i>_missing_()</i> (<i>pcapkit.const.ipv6.qs_function.QSFunction</i> class method), 302		<i>_name</i> (<i>pcapkit.protocols.link.arp.ARP</i> attribute), 32
<i>_missing_()</i> (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> class method), 302		<i>_name</i> (<i>pcapkit.protocols.link.rarp.RARP</i> attribute), 42
<i>_missing_()</i> (<i>pcapkit.const.ipv6.routing.Routing</i> class method), 306		<i>_newflg</i> (<i>pcapkit.foundation.traceflow.TraceFlow</i> attribute), 20
<i>_missing_()</i> (<i>pcapkit.const.ipv6.seed_id.SeedID</i> class method), 306		<i>_newflg</i> (<i>pcapkit.reassembly.reassembly.Reassembly</i> attribute), 234
<i>_missing_()</i> (<i>pcapkit.const.ipv6.tagger_id.TaggerID</i> class method), 307		<i>_nnsec</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7
<i>_missing_()</i> (<i>pcapkit.const.ipx.packet.Packet</i> class method), 307		<i>_nnsecd</i> (<i>pcapkit.foundation.traceflow.TraceFlow</i> attribute), 20
<i>_missing_()</i> (<i>pcapkit.const.ipx.socket.Socket</i> class method), 308		<i>_nsec</i> (<i>pcapkit.dumpkit.PCAP</i> attribute), 249
<i>_missing_()</i> (<i>pcapkit.const.mh.packet.Packet</i> class method), 309		<i>_ofile</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 6
<i>_missing_()</i> (<i>pcapkit.const.ospf.authentication.Authentication</i> class method), 310		<i>_ofnm</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 5
<i>_missing_()</i> (<i>pcapkit.const.ospf.packet.Packet</i> class method), 311		<i>_onerror</i> (<i>pcapkit.protocols.protocol.Protocol</i> attribute), 231
<i>_missing_()</i> (<i>pcapkit.const.reg.ethertype.EtherType</i> class method), 318		<i>_pipeline_read_frame()</i> (<i>pcapkit.foundation.extraction.Extractor</i> method), 10
<i>_missing_()</i> (<i>pcapkit.const.reg.linktype.LinkType</i> class method), 312		<i>_proto</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 6
<i>_missing_()</i> (<i>pcapkit.const.reg.transtype.TransType</i> class method), 326		<i>_pyshark_read_frame()</i> (<i>pcapkit.foundation.extraction.Extractor</i> method), 10
<i>_missing_()</i> (<i>pcapkit.const.tcp.checksum.Checksum</i> class method), 334		<i>_read_addr_resolve()</i> (<i>pcapkit.protocols.link.arp.ARP</i> method), 32
<i>_missing_()</i> (<i>pcapkit.const.tcp.option.Option</i> class method), 334		<i>_read_binary()</i> (<i>pcapkit.protocols.protocol.Protocol</i> method), 229
<i>_missing_()</i> (<i>pcapkit.const.vlan.priority_level.PriorityLevel</i> class method), 336		<i>_read_data_type_2()</i> (<i>pcapkit.protocols.internet.ipv6_route.IPv6_Route</i> method), 161
<i>_mpbuf</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7		<i>_read_data_type_none()</i> (<i>pcapkit.protocols.internet.ipv6_route.IPv6_Route</i> method), 161
<i>_mpfdp</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7		<i>_read_data_type_rpl()</i> (<i>pcapkit.protocols.internet.ipv6_route.IPv6_Route</i> method), 162
<i>_mpfrm</i> (<i>pcapkit.foundation.extraction.Extractor</i> attribute), 7		<i>_read_data_type_src()</i> (<i>pcapkit.protocols.internet.ipv6_route.IPv6_Route</i> method), 162
		<i>_read_encrypt_auth()</i> (<i>pcapkit.protocols.link.ospf.OSPF</i> method), 39

<code>_read_fileng()</code>	(<i>pcap-kit.protocols.protocol.Protocol</i> method), 229	<code>_read_ip_hextet()</code>	(<i>pcap-kit.protocols.internet.ipv6.IPv6</i> method), 167
<code>_read_frame()</code>	(<i>pcap-kit.foundation.extraction.Extractor</i> method), 11	<code>_read_ipv4_addr()</code>	(<i>pcap-kit.protocols.internet.ipv4.IPv4</i> method), 125
<code>_read_hip_para()</code>	(<i>pcap-kit.protocols.internet.hip.HIP</i> method), 49	<code>_read_ipv4_options()</code>	(<i>pcap-kit.protocols.internet.ipv4.IPv4</i> method), 126
<code>_read_hopopt_options()</code>	(<i>pcap-kit.protocols.internet.hopopt.HOPOPT</i> method), 104	<code>_read_ipv6_opts_options()</code>	(<i>pcap-kit.protocols.internet.ipv6_opts.IPv6_Opts</i> method), 141
<code>_read_http_body()</code>	(<i>pcap-kit.protocols.application.httpv1.HTTPv1</i> method), 205	<code>_read_ipx_address()</code>	(<i>pcap-kit.protocols.internet.ipx.IPX</i> method), 170
<code>_read_http_continuation()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 208	<code>_read_join_ack()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 178
<code>_read_http_data()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 209	<code>_read_join_syn()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 179
<code>_read_http_goaway()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 209	<code>_read_join_synack()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 179
<code>_read_http_header()</code>	(<i>pcap-kit.protocols.application.httpv1.HTTPv1</i> method), 205	<code>_read_mac_addr()</code>	(<i>pcap-kit.protocols.link.ethernet.Ethernet</i> method), 35
<code>_read_http_headers()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 210	<code>_read_mode_acopt()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 180
<code>_read_http_none()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 210	<code>_read_mode_donone()</code>	(<i>pcap-kit.protocols.internet.ipv4.IPv4</i> method), 126
<code>_read_http_ping()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 211	<code>_read_mode_donone()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 180
<code>_read_http_priority()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 211	<code>_read_mode_mptcp()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 180
<code>_read_http_push_promise()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 212	<code>_read_mode_pocsp()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 181
<code>_read_http_rst_stream()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 212	<code>_read_mode_qs()</code>	(<i>pcap-kit.protocols.internet.ipv4.IPv4</i> method), 126
<code>_read_http_settings()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 213	<code>_read_mode_qsopt()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP</i> method), 181
<code>_read_http_window_update()</code>	(<i>pcap-kit.protocols.application.httpv2.HTTPv2</i> method), 213	<code>_read_mode_route()</code>	(<i>pcap-kit.protocols.internet.ipv4.IPv4</i> method), 127
<code>_read_id_numbers()</code>	(<i>pcap-kit.protocols.link.ospf.OSPF</i> method), 39	<code>_read_mode_rsralt()</code>	(<i>pcap-kit.protocols.internet.ipv4.IPv4</i> method), 127
<code>_read_ip_addr()</code>	(<i>pcap-kit.protocols.internet.ipv6.IPv6</i> method),		

<code>_read_mode_sec()</code> <i>kit.protocols.internet.ipv4.Ipv4</i> 127	(pcap- method),	<code>_read_opt_home()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 105	(pcap-
<code>_read_mode_tcpao()</code> <i>kit.protocols.transport.tcp.TCP</i> 181	(pcap- method),	<code>_read_opt_home()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 142	(pcap-
<code>_read_mode_tr()</code> <i>kit.protocols.internet.ipv4.Ipv4</i> 128	(pcap- method),	<code>_read_opt_ilnp()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 105	(pcap-
<code>_read_mode_ts()</code> <i>kit.protocols.internet.ipv4.Ipv4</i> 128	(pcap- method),	<code>_read_opt_ilnp()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 142	(pcap-
<code>_read_mode_tsopt()</code> <i>kit.protocols.transport.tcp.TCP</i> 182	(pcap- method),	<code>_read_opt_ip_dff()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 106	(pcap-
<code>_read_mode_unpack()</code> <i>kit.protocols.internet.ipv4.Ipv4</i> 129	(pcap- method),	<code>_read_opt_ip_dff()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 142	(pcap-
<code>_read_mode_unpack()</code> <i>kit.protocols.transport.tcp.TCP</i> 182	(pcap- method),	<code>_read_opt_jumbo()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 106	(pcap-
<code>_read_mode_utopt()</code> <i>kit.protocols.transport.tcp.TCP</i> 182	(pcap- method),	<code>_read_opt_jumbo()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 143	(pcap-
<code>_read_mptcp_add()</code> <i>kit.protocols.transport.tcp.TCP</i> 183	(pcap- method),	<code>_read_opt_lio()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 106	(pcap-
<code>_read_mptcp_capable()</code> <i>kit.protocols.transport.tcp.TCP</i> 183	(pcap- method),	<code>_read_opt_lio()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 143	(pcap-
<code>_read_mptcp_dss()</code> <i>kit.protocols.transport.tcp.TCP</i> 184	(pcap- method),	<code>_read_opt_mpl()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 107	(pcap-
<code>_read_mptcp_fail()</code> <i>kit.protocols.transport.tcp.TCP</i> 184	(pcap- method),	<code>_read_opt_mpl()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 143	(pcap-
<code>_read_mptcp_fastclose()</code> <i>kit.protocols.transport.tcp.TCP</i> 185	(pcap- method),	<code>_read_opt_none()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 107	(pcap-
<code>_read_mptcp_join()</code> <i>kit.protocols.transport.tcp.TCP</i> 185	(pcap- method),	<code>_read_opt_none()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 144	(pcap-
<code>_read_mptcp_prio()</code> <i>kit.protocols.transport.tcp.TCP</i> 185	(pcap- method),	<code>_read_opt_pad()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 107	(pcap-
<code>_read_mptcp_remove()</code> <i>kit.protocols.transport.tcp.TCP</i> 186	(pcap- method),	<code>_read_opt_pad()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 144	(pcap-
<code>_read_opt_calipso()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 104	(pcap-	<code>_read_opt_pdm()</code> <i>kit.protocols.internet.hopopt.HOPOPT</i> method), 108	(pcap-
<code>_read_opt_calipso()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 141	(pcap-	<code>_read_opt_pdm()</code> <i>kit.protocols.internet.ipv6_opts.Ipv6_Opts</i> method), 145	(pcap-

<code>_read_opt_qs()</code>	(<i>pcap-kit.protocols.internet.hopopt.HOPOPT method</i>), 108	<code>_read_para_echo_request_unsigned()</code>	(<i>pcapkit.protocols.internet.hip.HIP method</i>), 52
<code>_read_opt_qs()</code>	(<i>pcap-kit.protocols.internet.ipv6_opts.IPv6_Opts method</i>), 145	<code>_read_para_echo_response_signed()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 53
<code>_read_opt_ra()</code>	(<i>pcap-kit.protocols.internet.hopopt.HOPOPT method</i>), 109	<code>_read_para_echo_response_unsigned()</code>	(<i>pcapkit.protocols.internet.hip.HIP method</i>), 53
<code>_read_opt_ra()</code>	(<i>pcap-kit.protocols.internet.ipv6_opts.IPv6_Opts method</i>), 146	<code>_read_para_encrypted()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 54
<code>_read_opt_rpl()</code>	(<i>pcap-kit.protocols.internet.hopopt.HOPOPT method</i>), 109	<code>_read_para_esp_info()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 54
<code>_read_opt_rpl()</code>	(<i>pcap-kit.protocols.internet.ipv6_opts.IPv6_Opts method</i>), 146	<code>_read_para_esp_transform()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 55
<code>_read_opt_smf_dpd()</code>	(<i>pcap-kit.protocols.internet.hopopt.HOPOPT method</i>), 110	<code>_read_para_from()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 56
<code>_read_opt_smf_dpd()</code>	(<i>pcap-kit.protocols.internet.ipv6_opts.IPv6_Opts method</i>), 146	<code>_read_para_hip_cipher()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 56
<code>_read_opt_tun()</code>	(<i>pcap-kit.protocols.internet.hopopt.HOPOPT method</i>), 110	<code>_read_para_hip_mac()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 57
<code>_read_opt_tun()</code>	(<i>pcap-kit.protocols.internet.ipv6_opts.IPv6_Opts method</i>), 147	<code>_read_para_hip_mac_2()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 57
<code>_read_opt_type()</code>	(<i>pcap-kit.protocols.internet.hopopt.HOPOPT method</i>), 111	<code>_read_para_hip_signature()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 58
<code>_read_opt_type()</code>	(<i>pcap-kit.protocols.internet.ipv4.IPv4 method</i>), 129	<code>_read_para_hip_signature_2()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 58
<code>_read_opt_type()</code>	(<i>pcap-kit.protocols.internet.ipv6_opts.IPv6_Opts method</i>), 147	<code>_read_para_hip_transform()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 59
<code>_read_packet()</code>	(<i>pcap-kit.protocols.protocol.Protocol method</i>), 229	<code>_read_para_hip_transport_mode()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 60
<code>_read_para_ack()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 49	<code>_read_para_hit_suite_list()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 60
<code>_read_para_ack_data()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 49	<code>_read_para_host_id()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 61
<code>_read_para_cert()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 50	<code>_read_para_locator_set()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 61
<code>_read_para_dh_group_list()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 51	<code>_read_para_nat_traversal_mode()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 62
<code>_read_para_diffie_hellman()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 51	<code>_read_para_notification()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 63
<code>_read_para_echo_request_signed()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 52	<code>_read_para_overlay_id()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 64
		<code>_read_para_overlay_ttl()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 64
		<code>_read_para_payload_mic()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 65
		<code>_read_para_puzzle()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 65
		<code>_read_para_r1_counter()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 66
		<code>_read_para_reg_failed()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 66
		<code>_read_para_reg_from()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 67

<code>_read_para_reg_info()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 68	<code>_reasm</code>	(<i>pcapkit.foundation.extraction.Extractor attribute</i>), 6
<code>_read_para_reg_request()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 68	<code>_receipt</code>	(<i>pcapkit.protocols.application.httpv1.HTTPv1 attribute</i>), 206
<code>_read_para_reg_response()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 69	<code>_replace()</code>	(<i>pcapkit.corekit.version.VersionInfo method</i>), 247
<code>_read_para_relay_from()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 70	<code>_request()</code>	(<i>pcapkit.vendor.default.Vendor method</i>), 363
<code>_read_para_relay_hmac()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 70	<code>_run_dpkt()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 11
<code>_read_para_relay_to()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 71	<code>_run_pipeline()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 11
<code>_read_para_route_dst()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 71	<code>_run_pyshark()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 12
<code>_read_para_route_via()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 72	<code>_run_scapy()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 12
<code>_read_para_rvs_hmac()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 73	<code>_run_server()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 12
<code>_read_para_seq()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 74	<code>_scapy_read_frame()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 13
<code>_read_para_seq_data()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 74	<code>_seekset</code>	(<i>pcapkit.protocols.protocol.Protocol attribute</i>), 231
<code>_read_para_solution()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 75	<code>_server_analyse_frame()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 13
<code>_read_para_transaction_id()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 75	<code>_server_extract_frame()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 14
<code>_read_para_transaction_pacing()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 76	<code>_sigterm</code>	(<i>pcapkit.protocols.protocol.Protocol attribute</i>), 232
<code>_read_para_transport_format_list()</code>	(<i>pcapkit.protocols.internet.hip.HIP method</i>), 76	<code>_stream</code>	(<i>pcapkit.foundation.traceflow.TraceFlow attribute</i>), 20
<code>_read_para_unassigned()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 77	<code>_strflg</code>	(<i>pcapkit.reassembly.reassembly.Reassembly attribute</i>), 234
<code>_read_para_via_rvs()</code>	(<i>pcap-kit.protocols.internet.hip.HIP method</i>), 78	<code>_syn</code>	(<i>pcapkit.protocols.transport.tcp.TCP attribute</i>), 178
<code>_read_proto_resolve()</code>	(<i>pcap-kit.protocols.link.arp.ARP method</i>), 33	<code>_tcp</code>	(<i>pcapkit.foundation.extraction.Extractor attribute</i>), 6
<code>_read_protos()</code>	(<i>pcap-kit.protocols.internet.internet.Internet method</i>), 175	<code>_tcp_frag_check()</code>	(in module <i>pcap-kit.utilities.validations</i>), 261
<code>_read_protos()</code>	(<i>pcapkit.protocols.link.link.Link method</i>), 45	<code>_trace</code>	(<i>pcapkit.foundation.extraction.Extractor attribute</i>), 6
<code>_read_protos()</code>	(<i>pcap-kit.protocols.pcap.header.Header method</i>), 25	<code>_type</code>	(<i>pcapkit.foundation.extraction.Extractor attribute</i>), 7
<code>_read_protos()</code>	(<i>pcap-kit.protocols.protocol.Protocol method</i>), 229	<code>_update_eof()</code>	(<i>pcap-kit.foundation.extraction.Extractor method</i>), 14
<code>_read_tcp_options()</code>	(<i>pcap-kit.protocols.transport.tcp.TCP method</i>), 186	<code>_vfunc</code>	(<i>pcapkit.foundation.extraction.Extractor at-</i>
<code>_read_unpack()</code>	(<i>pcap-kit.protocols.protocol.Protocol method</i>), 230		

- tribute), 6
- `_vinfo` (`pcapkit.foundation.extraction.Extractor` attribute), 6
- ## A
- `A_N` (`pcapkit.const.reg.transtype.TransType` attribute), 326
- `ac` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ACOPT` attribute), 192
- `ACK` (`pcapkit.const.hip.parameter.Parameter` attribute), 282
- `ACK` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2_FLAGS` attribute), 220
- `ACK` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2_SETTINGS_FLAGS` attribute), 219
- `ack` (`pcapkit.protocols.internet.hip.DataType_Param_ACK_Data` attribute), 95
- `ack` (`pcapkit.protocols.transport.tcp.DataType_TCP` attribute), 189
- `ack` (`pcapkit.protocols.transport.tcp.DataType_TCP_Flags` attribute), 190
- `ack` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Data` attribute), 199
- `ACK_DATA` (`pcapkit.const.hip.parameter.Parameter` attribute), 282
- `ack_len` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Flags` attribute), 199
- `ack_pre` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Flags` attribute), 199
- `action` (`pcapkit.protocols.internet.hopopt.DataType_Option_Type` attribute), 114
- `action` (`pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts_Type` attribute), 150
- `add_addr` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ADD_ADDR` attribute), 200
- `ADDEXT` (`pcapkit.const.ipv4.option_number.OptionNumber` attribute), 292
- `addr` (`pcapkit.protocols.internet.ipx.DataType_IPX_Address` attribute), 171
- `addr` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ADD_ADDR` attribute), 200
- `addr_id` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ADD_ADDR_Data` attribute), 200
- `addr_id` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYNACK_IPV6_Data` attribute), 197
- `addr_id` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYNACK_IPV6_Data` attribute), 197
- `addr_id` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYNACK_IPV6_Data` attribute), 201
- `addr_id` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_REMOVE_ADDR_Data` attribute), 200
- `Address_Resolution_Protocol` (`pcapkit.const.reg.ethertype.EtherType` attribute), 318
- `Aeonic_Systems` (`pcapkit.const.reg.ethertype.EtherType` attribute), 318
- `AES_128_CBC` (`pcapkit.const.hip.cipher.Cipher` attribute), 274
- `AES_128_CBC_with_HMAC_SHA1` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AES_128_CBC_with_HMAC_SHA_256` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AES_128_GCM` (`pcapkit.const.hip.cipher.Cipher` attribute), 274
- `AES_128_GCM_with_HMAC_SHA_256` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AES_CBC_with_HMAC_SHA1` (`pcapkit.const.hip.suite.Suite` attribute), 287
- `AES_CCM_16` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AES_CCM_8` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AES_CMAC_96` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AES_GCM_with_a_16_octet_ICV` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AES_GCM_with_an_8_octet_ICV` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AES_GMAC` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` attribute), 276
- `AETHER` (`pcapkit.const.arp.hardware.Hardware` attribute), 266
- `Aggregated_Reservation_Nesting_Level_0` (`pcapkit.const.ipv4.router_alert.RouterAlert` attribute), 294
- `Aggregated_Reservation_Nesting_Level_0` (`pcapkit.const.ipv6.router_alert.RouterAlert` attribute), 302
- `Aggregated_Reservation_Nesting_Level_1` (`pcapkit.const.ipv4.router_alert.RouterAlert` attribute), 294
- `Aggregated_Reservation_Nesting_Level_1` (`pcapkit.const.ipv6.router_alert.RouterAlert` attribute), 302
- `Aggregated_Reservation_Nesting_Level_10` (`pcapkit.const.ipv4.router_alert.RouterAlert` attribute), 302
- `Aggregated_Reservation_Nesting_Level_10` (`pcapkit.const.ipv6.router_alert.RouterAlert` attribute), 302
- `Aggregated_Reservation_Nesting_Level_11`

[illegible]

- (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_28 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 303
- Aggregated_Reservation_Nesting_Level_29 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_29 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 303
- Aggregated_Reservation_Nesting_Level_3 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_3 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 303
- Aggregated_Reservation_Nesting_Level_30 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_30 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 303
- Aggregated_Reservation_Nesting_Level_31 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_31 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 303
- Aggregated_Reservation_Nesting_Level_4 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_4 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 303
- Aggregated_Reservation_Nesting_Level_5 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_5 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 303
- Aggregated_Reservation_Nesting_Level_6 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_6 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 304
- Aggregated_Reservation_Nesting_Level_7 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 295
- Aggregated_Reservation_Nesting_Level_7 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 304
- Aggregated_Reservation_Nesting_Level_8 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 296
- Aggregated_Reservation_Nesting_Level_8 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 304
- Aggregated_Reservation_Nesting_Level_9 (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 296
- Aggregated_Reservation_Nesting_Level_9 (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 304
- AH (*class in pcapkit.protocols.internet.ah*), 45
- AH (*pcapkit.const.ipv6.extension_header.ExtensionHeader attribute*), 299
- AH (*pcapkit.const.reg.transtype.TransType attribute*), 326
- alert (*pcapkit.protocols.internet.hopopt.DataType_Opt_RA attribute*), 116
- alert (*pcapkit.protocols.internet.ipv4.DataType_Opt_RouterAlert attribute*), 138
- alert (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_RA attribute*), 152
- algorithm (*pcapkit.protocols.internet.hip.DataType_Param_Host_ID attribute*), 88
- algorithm (*pcapkit.protocols.internet.hip.DataType_Param_Signature attribute*), 99
- algorithm (*pcapkit.protocols.internet.hip.DataType_Param_Signature_2 attribute*), 99
- alias() (*pcapkit.corekit.protochain.ProtoChain property*), 245
- alias() (*pcapkit.protocols.application.httpv1.HTTPv1 property*), 206
- alias() (*pcapkit.protocols.application.httpv2.HTTPv2 property*), 215
- alias() (*pcapkit.protocols.internet.hip.HIP property*), 79
- alias() (*pcapkit.protocols.internet.ipv6_frag.IPv6_Frag property*), 139
- alias() (*pcapkit.protocols.internet.ipv6_opts.IPv6_Opts property*), 148
- alias() (*pcapkit.protocols.internet.ipv6_route.IPv6_Route property*), 164
- alias() (*pcapkit.protocols.link.arp.ARP property*), 33
- alias() (*pcapkit.protocols.link.ospf.OSPF property*), 40
- alias() (*pcapkit.protocols.link.vlan.VLAN property*), 43
- alias() (*pcapkit.protocols.protocol.Protocol property*), 232
- Alpha_Micro (*pcapkit.const.reg.ethertype.EtherType attribute*), 319
- ALTSVC (*pcapkit.const.http.frame.Frame attribute*), 289
- Amateur_Radio_AX_25 (*pcapkit.const.arp.hardware.Hardware attribute*), 266

analyse() (in module *pcapkit.foundation.analysis*), 4
 analyse() (in module *pcapkit.interface*), 22
 anonymous (*pcapkit.protocols.internet.hip.DataType_Connect* attribute), 80
 any_0_hop_protocol (*pcapkit.const.reg.transtype.TransType* attribute), 333
 any_distributed_file_system (*pcapkit.const.reg.transtype.TransType* attribute), 333
 any_host_internal_protocol (*pcapkit.const.reg.transtype.TransType* attribute), 333
 any_local_network (*pcapkit.const.reg.transtype.TransType* attribute), 333
 any_private_encryption_scheme (*pcapkit.const.reg.transtype.TransType* attribute), 333
 AO (*pcapkit.const.tcp.option.Option* attribute), 334
 Apollo_Computer (*pcapkit.const.reg.ethertype.EtherType* attribute), 319
 Apollo_Domain (*pcapkit.const.reg.ethertype.EtherType* attribute), 319
 APPLE_IP_OVER_IEEE1394 (*pcapkit.const.reg.linktype.LinkType* attribute), 312
 Appletalk (*pcapkit.const.reg.ethertype.EtherType* attribute), 319
 AppleTalk_AARP (*pcapkit.const.reg.ethertype.EtherType* attribute), 319
 Application (class in *pcapkit.protocols.application.application*), 222
 Applitek_Corporation (*pcapkit.const.reg.ethertype.EtherType* attribute), 319
 ARAI_Bunkichi (*pcapkit.const.reg.ethertype.EtherType* attribute), 318
 ARCNET (*pcapkit.const.arp.hardware.Hardware* attribute), 266
 ARCNET_BSD (*pcapkit.const.reg.linktype.LinkType* attribute), 312
 ARCNET_LINUX (*pcapkit.const.reg.linktype.LinkType* attribute), 312
 area_id (*pcapkit.protocols.link.ospf.DataType_OSPF* attribute), 41
 arg (*pcapkit.protocols.application.ftp.DataType_FTP_Request* attribute), 204
 arg (*pcapkit.protocols.application.ftp.DataType_FTP_Response* attribute), 204
 ARGUS (*pcapkit.const.reg.transtype.TransType* attribute), 326
 ARIS (*pcapkit.const.reg.transtype.TransType* attribute), 326
 ARP (class in *pcapkit.protocols.link.arp*), 32
 ARP_NAK (*pcapkit.const.arp.operation.Operation* attribute), 268
 ARPSec (*pcapkit.const.arp.hardware.Hardware* attribute), 266
 Asynchronous_Transmission_Mode_16 (*pcapkit.const.arp.hardware.Hardware* attribute), 266
 Asynchronous_Transmission_Mode_19 (*pcapkit.const.arp.hardware.Hardware* attribute), 266
 Asynchronous_Transmission_Mode_21 (*pcapkit.const.arp.hardware.Hardware* attribute), 266
 AT_T_0x8008 (*pcapkit.const.reg.ethertype.EtherType* attribute), 318
 AT_T_0x8046 (*pcapkit.const.reg.ethertype.EtherType* attribute), 318
 AT_T_0x8047 (*pcapkit.const.reg.ethertype.EtherType* attribute), 318
 AT_T_0x8069 (*pcapkit.const.reg.ethertype.EtherType* attribute), 318
 ATM_RFC1483 (*pcapkit.const.reg.linktype.LinkType* attribute), 312
 ATOMIC (*pcapkit.const.reg.ethertype.EtherType* attribute), 318
 ATSC_ALP (*pcapkit.const.reg.linktype.LinkType* attribute), 312
 AttributeWarning, 265
 auth (*pcapkit.protocols.link.ospf.DataType_OSPF* attribute), 41
 Authentication (class in *pcapkit.const.ospf.authentication*), 310
 Authentication (class in *pcapkit.vendor.ospf.authentication*), 358
 AUTHENTICATION_FAILED (*pcapkit.const.hip.notify_message.NotifyMessage* attribute), 279
 Autonet_Short_Address (*pcapkit.const.arp.hardware.Hardware* attribute), 267
 Autophon (*pcapkit.const.reg.ethertype.EtherType* attribute), 319
 autype (*pcapkit.protocols.link.ospf.DataType_OSPF* attribute), 41
 AX25 (*pcapkit.const.reg.linktype.LinkType* attribute), 312
 AX25_KISS (*pcapkit.const.reg.linktype.LinkType* attribute), 312
 AX25 (*pcapkit.const.reg.transtype.TransType* attribute), 326

B

- `backup` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYN_Data` attribute), 197
- `backup` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYNACK_Data` attribute), 197
- `backup` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_DATA` attribute), 201
- `BACNET_MS_TP` (`pcapkit.const.reg.linktype.LinkType` attribute), 312
- `Bad_certificate` (`pcapkit.const.hip.registration_failure.RegistrationFailure` attribute), 286
- `Banyan_Systems_0x80C4` (`pcapkit.const.reg.ethertype.EtherType` attribute), 319
- `Banyan_Systems_0x80C5` (`pcapkit.const.reg.ethertype.EtherType` attribute), 319
- `Banyan_VINES` (`pcapkit.const.reg.ethertype.EtherType` attribute), 319
- `BaseError`, 258
- `BaseWarning`, 265
- `BBN_RCC_MON` (`pcapkit.const.reg.transtype.TransType` attribute), 326
- `BBN_Simnet` (`pcapkit.const.reg.ethertype.EtherType` attribute), 319
- `BBN_VITAL_LanBridge_cache` (`pcapkit.const.reg.ethertype.EtherType` attribute), 319
- `BE` (`pcapkit.const.vlan.priority_level.PriorityLevel` attribute), 337
- `beholder()` (in module `pcapkit.utilities.decorators`), 257
- `beholder_ng()` (in module `pcapkit.utilities.decorators`), 257
- `Berkeley_Trailer_nego` (`pcapkit.const.reg.ethertype.EtherType` attribute), 319
- `BIIN_0x814D` (`pcapkit.const.reg.ethertype.EtherType` attribute), 319
- `BIIN_0x814E` (`pcapkit.const.reg.ethertype.EtherType` attribute), 319
- `binary()` (in module `pcapkit.vendor.ipv4.classification_level`), 347
- `binary()` (in module `pcapkit.vendor.ipv4.option_class`), 347
- `Binding_Acknowledgement` (`pcapkit.const.mh.packet.Packet` attribute), 309
- `Binding_Error` (`pcapkit.const.mh.packet.Packet` attribute), 309
- `Binding_Refresh_Request` (`pcapkit.const.mh.packet.Packet` attribute), 309
- `Binding_Revocation_Message` (`pcapkit.const.mh.packet.Packet` attribute), 309
- `Binding_Update` (`pcapkit.const.mh.packet.Packet` attribute), 309
- `bitmap` (`pcapkit.protocols.internet.hopopt.DataType_Opt_CALIPSO` attribute), 117
- `bitmap` (`pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_CALIPSO` attribute), 153
- `BK` (`pcapkit.const.vlan.priority_level.PriorityLevel` attribute), 337
- `BLOCKED_BY_POLICY` (`pcapkit.const.hip.notify_message.NotifyMessage` attribute), 279
- `BLOWFISH_CBC_with_HMAC_SHA1` (`pcapkit.const.hip.suite.Suite` attribute), 287
- `BLUETOOTH_BREDR_BB` (`pcapkit.const.reg.linktype.LinkType` attribute), 312
- `BLUETOOTH_HCI_H4` (`pcapkit.const.reg.linktype.LinkType` attribute), 312
- `BLUETOOTH_HCI_H4_WITH_PHDR` (`pcapkit.const.reg.linktype.LinkType` attribute), 312
- `BLUETOOTH_LE_LL` (`pcapkit.const.reg.linktype.LinkType` attribute), 312
- `BLUETOOTH_LE_LL_WITH_PHDR` (`pcapkit.const.reg.linktype.LinkType` attribute), 312
- `BLUETOOTH_LINUX_MONITOR` (`pcapkit.const.reg.linktype.LinkType` attribute), 312
- `BNA` (`pcapkit.const.reg.transtype.TransType` attribute), 326
- `body` (`pcapkit.protocols.application.httpv1.DataType_HTTP` attribute), 207
- `body` (`pcapkit.protocols.application.httpv1.DataType_HTTP_Raw` attribute), 207
- `bool_check()` (in module `pcapkit.utilities.validations`), 262
- `BoolError`, 258
- `BR_SAT_MON` (`pcapkit.const.reg.transtype.TransType` attribute), 326
- `Bubba` (`pcapkit.const.tcp.option.Option` attribute), 334
- `bytearray_check()` (in module `pcapkit.utilities.validations`), 262
- `BytearrayError`, 258
- `byteorder` (`pcapkit.protocols.pcap.header.DataType_MagicNumber` attribute), 27
- `byteorder()` (`pcapkit.protocols.pcap.header.Header` property), 26
- `bytes_check()` (in module `pcapkit.utilities.validations`), 262
- `BytesError`, 258

C

- C_HDLC (*pcapkit.const.reg.linktype.LinkType* attribute), 312
- C_HDLC_WITH_DIR (*pcapkit.const.reg.linktype.LinkType* attribute), 313
- CA (*pcapkit.const.vlan.priority_level.PriorityLevel* attribute), 337
- Cabletron (*pcapkit.const.reg.ethertype.EtherType* attribute), 319
- CALIPSO (*pcapkit.const.ipv6.option.Option* attribute), 300
- CallableError, 258
- CAN_SOCKETCAN (*pcapkit.const.reg.linktype.LinkType* attribute), 312
- CANCEL (*pcapkit.const.http.error_code.ErrorCode* attribute), 288
- cap_len (*pcapkit.protocols.pcap.frame.DataType_Frame* attribute), 31
- capable (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABLE* attribute), 195
- Care_of_Test (*pcapkit.const.mh.packet.Packet* attribute), 309
- Care_of_Test_Init (*pcapkit.const.mh.packet.Packet* attribute), 309
- CBT (*pcapkit.const.reg.transtype.TransType* attribute), 326
- CC (*pcapkit.const.tcp.option.Option* attribute), 334
- CCECHO (*pcapkit.const.tcp.option.Option* attribute), 334
- CCNEW (*pcapkit.const.tcp.option.Option* attribute), 334
- CE (*pcapkit.const.ipv4.tos_ecn.ToSECN* attribute), 298
- CERT (*pcapkit.const.hip.parameter.Parameter* attribute), 282
- cert_type (*pcapkit.protocols.internet.hip.DataType_Param_Cert* attribute), 90
- Certificate (class in *pcapkit.const.hip.certificate*), 273
- Certificate (class in *pcapkit.vendor.hip.certificate*), 339
- certificate (*pcapkit.protocols.internet.hip.DataType_Param_Cert* attribute), 90
- Certificate_expired (*pcapkit.const.hip.registration_failure.RegistrationFailure* attribute), 286
- Certificate_other (*pcapkit.const.hip.registration_failure.RegistrationFailure* attribute), 286
- CFTP (*pcapkit.const.reg.transtype.TransType* attribute), 327
- chain() (*pcapkit.corekit.protochain.ProtoChain* property), 245
- change (*pcapkit.protocols.internet.hopopt.DataType_Option_Type* attribute), 114
- change (*pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts_Option_Type* attribute), 150
- Chaos (*pcapkit.const.arp.hardware.Hardware* attribute), 267
- CHAOS (*pcapkit.const.reg.transtype.TransType* attribute), 327
- Chaosnet (*pcapkit.const.reg.ethertype.EtherType* attribute), 319
- check() (*pcapkit.foundation.extraction.Extractor* method), 14
- Checksum (class in *pcapkit.const.tcp.checksum*), 334
- Checksum (class in *pcapkit.vendor.tcp.checksum*), 361
- checksum (*pcapkit.protocols.internet.ipv4.DataType_IPv4* attribute), 131
- checksum (*pcapkit.protocols.transport.tcp.DataType_TCP* attribute), 189
- checksum (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Data* attribute), 199
- checksum (*pcapkit.protocols.transport.udp.DataType_UDP* attribute), 177
- Checksum_16_bit_Fletcher_s_algorithm (*pcapkit.const.tcp.checksum.Checksum* attribute), 334
- Checksum_8_bit_Fletcher_s_algorithm (*pcapkit.const.tcp.checksum.Checksum* attribute), 334
- CHECKSUM_FAILED (*pcapkit.const.hip.notify_message.NotifyMessage* attribute), 279
- CHKREQ (*pcapkit.const.tcp.option.Option* attribute), 334
- CHKSUM (*pcapkit.const.tcp.option.Option* attribute), 334
- chksum (*pcapkit.protocols.internet.hip.DataType_HIP* attribute), 80
- chksum (*pcapkit.protocols.internet.hopopt.DataType_Opt_CALIPSO* attribute), 117
- chksum (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_CALIPSO* attribute), 153
- chksum (*pcapkit.protocols.internet.ipx.DataType_IPX* attribute), 171
- chksum (*pcapkit.protocols.internet.mh.DataType_MH* attribute), 174
- chksum (*pcapkit.protocols.link.ospf.DataType_OSPF* attribute), 41
- Cipher (class in *pcapkit.const.hip.cipher*), 274
- Cipher (class in *pcapkit.vendor.hip.cipher*), 340
- CIPSO (*pcapkit.const.ipv4.option_number.OptionNumber* attribute), 292
- class (*pcapkit.protocols.internet.ipv4.DataType_IPv4_Option_Type* attribute), 133
- class (*pcapkit.protocols.internet.ipv6.DataType_IPv6* attribute), 169
- ClassificationLevel (class in *pcapkit.const.ipv4.classification_level*), 290
- ClassificationLevel (class in *pcapkit.const.ipv6.classification_level*), 290

Index 397

CODE_632 (<i>pcapkit.const.ftp.return_code.ReturnCode attribute</i>), 273	count (<i>pcapkit.protocols.internet.hip.DataType_Param_Cert attribute</i>), 90
CODE_633 (<i>pcapkit.const.ftp.return_code.ReturnCode attribute</i>), 273	count (<i>pcapkit.protocols.internet.hip.DataType_Param_R1_Counter attribute</i>), 82
ComDesign (<i>pcapkit.const.reg.ethertype.EtherType attribute</i>), 319	count (<i>pcapkit.protocols.internet.ipx.DataType_IPX attribute</i>), 171
Command (<i>class in pcapkit.vendor.ftp.command</i>), 338	count () (<i>pcapkit.corekit.protochain._AliasList method</i>), 246
Command (<i>in module pcapkit.const.ftp.command</i>), 270	count () (<i>pcapkit.corekit.protochain.ProtoChain method</i>), 244
command (<i>pcapkit.protocols.application.ftp.DataType_FTP_Request attribute</i>), 204	count () (<i>pcapkit.reassembly.reassembly.Reassembly property</i>), 234
Compaq_Peer (<i>pcapkit.const.reg.transtype.TransType attribute</i>), 327	count () (<i>pcapkit.vendor.default.Vendor method</i>), 364
ComparisonError, 258	count () (<i>pcapkit.vendor.ftp.return_code.ReturnCode method</i>), 339
complex_check () (<i>in module pcapkit.utilities.validations</i>), 262	count () (<i>pcapkit.vendor.ipv4.classification_level.ClassificationLevel method</i>), 346
ComplexError, 258	count () (<i>pcapkit.vendor.ipv4.option_class.OptionClass method</i>), 347
COMPRESSION_ERROR (<i>pcapkit.const.http.error_code.ErrorCode attribute</i>), 288	count () (<i>pcapkit.vendor.ipv4.option_number.OptionNumber method</i>), 347
Computgraphic_Corp (<i>pcapkit.const.reg.ethertype.EtherType attribute</i>), 319	count () (<i>pcapkit.vendor.ipv4.protection_authority.ProtectionAuthority method</i>), 348
CONF (<i>in module pcapkit.vendor.ftp.command</i>), 338	count () (<i>pcapkit.vendor.ipv4.qs_function.QSFunction method</i>), 349
Confidential (<i>pcapkit.const.ipv4.classification_level.ClassificationLevel attribute</i>), 291	count () (<i>pcapkit.vendor.ipv4.tos_del.ToSDelay method</i>), 350
CONNECT_ERROR (<i>pcapkit.const.http.error_code.ErrorCode attribute</i>), 288	count () (<i>pcapkit.vendor.ipv4.tos_ecn.ToSECN method</i>), 350
connection (<i>pcapkit.protocols.transport.tcp.DataType_TCP_Option_MP_Comp attribute</i>), 196	count () (<i>pcapkit.vendor.ipv4.tos_pre.ToSPrecedence method</i>), 351
CONNECTIVITY_CHECKS_FAILED (<i>pcapkit.const.hip.notify_message.NotifyMessage attribute</i>), 280	count () (<i>pcapkit.vendor.ipv4.tos_rel.ToSReliability method</i>), 352
contents (<i>pcapkit.protocols.internet.hip.DataType_Param_Unassigned attribute</i>), 81	count () (<i>pcapkit.vendor.ipv4.tos_thr.ToSThroughput method</i>), 352
context () (<i>pcapkit.vendor.default.Vendor method</i>), 363	count () (<i>pcapkit.vendor.ipv6.extension_header.ExtensionHeader method</i>), 353
context () (<i>pcapkit.vendor.ftp.command.Command method</i>), 338	count () (<i>pcapkit.vendor.ipv6.option.Option method</i>), 354
context () (<i>pcapkit.vendor.ftp.return_code.ReturnCode method</i>), 339	count () (<i>pcapkit.vendor.ipv6.qs_function.QSFunction method</i>), 354
context () (<i>pcapkit.vendor.ipv6.extension_header.ExtensionHeader method</i>), 353	count () (<i>pcapkit.vendor.ipv6.seed_id.SeedID method</i>), 356
CONTINUATION (<i>pcapkit.const.http.frame.Frame attribute</i>), 289	count () (<i>pcapkit.vendor.ipx.packet.Packet method</i>), 357
control (<i>pcapkit.const.ipv4.option_class.OptionClass attribute</i>), 291	count () (<i>pcapkit.vendor.ipx.socket.Socket method</i>), 357
control (<i>pcapkit.protocols.internet.hip.DataType_HIP attribute</i>), 80	count () (<i>pcapkit.vendor.reg.ethertype.EtherType method</i>), 360
copy (<i>pcapkit.protocols.internet.ipv4.DataType_IPv4_Option_Type attribute</i>), 133	count () (<i>pcapkit.vendor.reg.linktype.LinkType method</i>), 359
Corruption_experienced (<i>pcapkit.const.tcp.option.Option attribute</i>), 335	count () (<i>pcapkit.vendor.reg.transtype.TransType method</i>), 360
	count () (<i>pcapkit.vendor.tcp.checksum.Checksum method</i>), 360

`method`), 361
`count()` (`pcapkit.vendor.tcp.option.Option` `method`), 362
`count()` (`pcapkit.vendor.vlan.priority_level.PriorityLevel` `method`), 362
`counter` (`pcapkit.foundation.extraction.Extractor_mpk` `attribute`), 7
`Counterpoint_Computers` (`pcapkit.const.reg.ethertype.EtherType` `attribute`), 319
`CPHB` (`pcapkit.const.reg.transtype.TransType` `attribute`), 327
`CPNX` (`pcapkit.const.reg.transtype.TransType` `attribute`), 327
`CREDENTIALS_REQUIRED` (`pcapkit.const.hip.notify_message.NotifyMessage` `attribute`), 280
`CRITIC_ECP` (`pcapkit.const.ipv4.tos_pre.ToSPrecedence` `attribute`), 298
`critical` (`pcapkit.protocols.internet.hip.DataType_Parameters` `attribute`), 80
`Cronus_Direct` (`pcapkit.const.reg.ethertype.EtherType` `attribute`), 319
`Cronus_VLN` (`pcapkit.const.reg.ethertype.EtherType` `attribute`), 320
`CRTP` (`pcapkit.const.reg.transtype.TransType` `attribute`), 327
`CRUDP` (`pcapkit.const.reg.transtype.TransType` `attribute`), 327
`Cryptographic_authentication` (`pcapkit.const.ospf.authentication.Authentication` `attribute`), 311
`Cryptographic_Authentication_with_Extended_Security_Mechanism` (`pcapkit.const.ospf.authentication.Authentication` `attribute`), 311
`current` (`pcapkit.foundation.extraction.Extractor_mpk` `attribute`), 7
`curve` (`pcapkit.protocols.internet.hip.DataType_Host_ID_ECDSA_Curve` `attribute`), 88
`curve` (`pcapkit.protocols.internet.hip.DataType_Host_ID_ECDSA_LowCurve` `attribute`), 89
`Customer_VLAN_Tag_Type` (`pcapkit.const.reg.ethertype.EtherType` `attribute`), 320
`cwr` (`pcapkit.protocols.transport.tcp.DataType_TCP_Flags` `attribute`), 190

D
`Dansk_Data_Elektronik` (`pcapkit.const.reg.ethertype.EtherType` `attribute`), 320
`DATA` (in module `pcapkit.vendor.ipv4.classification_level`), 347
`DATA` (in module `pcapkit.vendor.ipv4.option_class`), 347
`DATA` (in module `pcapkit.vendor.ipv4.protection_authority`), 348
`DATA` (in module `pcapkit.vendor.ipv4.qs_function`), 349
`DATA` (in module `pcapkit.vendor.ipv4.tos_del`), 350
`DATA` (in module `pcapkit.vendor.ipv4.tos_ecn`), 351
`DATA` (in module `pcapkit.vendor.ipv4.tos_pre`), 351
`DATA` (in module `pcapkit.vendor.ipv4.tos_rel`), 352
`DATA` (in module `pcapkit.vendor.ipv4.tos_thr`), 353
`DATA` (in module `pcapkit.vendor.ipv6.option`), 354
`DATA` (in module `pcapkit.vendor.ipv6.qs_function`), 355
`DATA` (in module `pcapkit.vendor.ipv6.seed_id`), 356
`DATA` (in module `pcapkit.vendor.tcp.checksum`), 361
`DATA` (in module `pcapkit.vendor.tcp.option`), 362
`DATA` (`pcapkit.const.http.frame.Frame` `attribute`), 289
`data` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2_DATA` `attribute`), 216
`data` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2_GOAWAY` `attribute`), 221
`data` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2_PING` `attribute`), 220
`data` (`pcapkit.protocols.internet.hip.DataType_Param_Echo_Request_Signature` `attribute`), 90
`data` (`pcapkit.protocols.internet.hip.DataType_Param_Echo_Request_Unsigned` `attribute`), 99
`data` (`pcapkit.protocols.internet.hip.DataType_Param_Echo_Response_Signature` `attribute`), 93
`data` (`pcapkit.protocols.internet.hip.DataType_Param_Echo_Response_Unsigned` `attribute`), 100
`data` (`pcapkit.protocols.internet.hip.DataType_Param_Notification` `attribute`), 90
`data` (`pcapkit.protocols.internet.hip.DataType_Param_Payload_MIC` `attribute`), 95
`data` (`pcapkit.protocols.internet.hopopt.DataType_Opt_None` `attribute`), 114
`data` (`pcapkit.protocols.internet.hopopt.DataType_Opt_RPL` `attribute`), 120
`data` (`pcapkit.protocols.internet.ipv4.DataType_Opt_Do_None` `attribute`), 134
`data` (`pcapkit.protocols.internet.ipv4.DataType_Opt_Route_Data` `attribute`), 135
`data` (`pcapkit.protocols.internet.ipv4.DataType_Opt_TimeStamp` `attribute`), 136
`data` (`pcapkit.protocols.internet.ipv4.DataType_Opt_Unpack` `attribute`), 134
`data` (`pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_None` `attribute`), 151
`data` (`pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_RPL` `attribute`), 156
`data` (`pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_None` `attribute`), 165
`data` (`pcapkit.protocols.internet.mh.DataType_MH` `attribute`), 174
`data` (`pcapkit.protocols.pcap.header.DataType_MagicNumber` `attribute`), 174

attribute), 27
 data (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DONONE Dest_Opt_PadN (class in pcap-
 attribute), 191 kit.protocols.internet.ipv6_opts), 152
 data (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN Dest_Opt_PDM (class in pcap-
 attribute), 196 kit.protocols.internet.ipv6_opts), 155
 data (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MPTCP Dest_Opt_QS (class in pcap-
 attribute), 194 kit.protocols.internet.ipv6_opts), 155
 data (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_LINPACK Dest_Opt_RA (class in pcap-
 attribute), 191 kit.protocols.internet.ipv6_opts), 152
 data () (pcapkit.corekit.protochain._AliasList prop- DataType_Dest_Opt_RPL (class in pcap-
 erty), 246 kit.protocols.internet.ipv6_opts), 156
 data () (pcapkit.corekit.protochain._ProtoList prop- DataType_Dest_Opt_SMF_H_PDP (class in pcap-
 erty), 247 kit.protocols.internet.ipv6_opts), 154
 data () (pcapkit.protocols.protocol.Protocol property), DataType_Dest_Opt_SMF_I_PDP (class in pcap-
 232 kit.protocols.internet.ipv6_opts), 153
 data_pre (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DS_Flags Dest_Opt_TUN (class in pcap-
 attribute), 199 kit.protocols.internet.ipv6_opts), 152
 Database_Description (pcap- DataType_DS_Field (class in pcap-
 kit.const.ospf.packet.Packet attribute), 311 kit.protocols.internet.ipv4), 132
 datagram () (pcapkit.reassembly.reassembly.Reassembly DataType_Ethernet (class in pcap-
 property), 234 kit.protocols.link.ethernet), 36
 Datagram_contains_a_Multicast_Listener_DataType_Message (class in pcap-
 (pcapkit.const.ipv6.router_alert.RouterAlert kit.protocols.internet.hip), 97
 attribute), 304 DataType_Flags (class in pcap-
 Datagram_contains_an_Active_Networks_message kit.protocols.link.l2tp), 38
 (pcapkit.const.ipv6.router_alert.RouterAlert DataType_Frame (class in pcap-
 attribute), 304 kit.protocols.pcap.frame), 31
 Datagram_contains_RSVP_message (pcap- DataType_FrameInfo (class in pcap-
 kit.const.ipv6.router_alert.RouterAlert at- kit.protocols.pcap.frame), 31
 tribute), 304 DataType_FTP_Request (class in pcap-
 DataType_AH (class in pcapkit.protocols.internet.ah), kit.protocols.application.ftp), 204
 47
 DataType_ARP (class in pcapkit.protocols.link.arp), 34
 DataType_Auth (class in pcapkit.protocols.link.ospf), 41
 DataType_Control (class in pcap- DataType_HIP (class in pcap-
 kit.protocols.internet.hip), 80 kit.protocols.internet.hip), 80
 DataType_Dest_Opt_CALIPSO (class in pcap- DataType_HOPOPT (class in pcap-
 kit.protocols.internet.ipv6_opts), 153 kit.protocols.internet.hopopt), 113
 DataType_Dest_Opt_Home (class in pcap- DataType_Host_ID_ECDSA_Curve (class in pcap-
 kit.protocols.internet.ipv6_opts), 159 kit.protocols.internet.hip), 88
 DataType_Dest_Opt_ILNP (class in pcap- DataType_Host_ID_ECDSA_LOW_Curve (class in
 kit.protocols.internet.ipv6_opts), 158 pcapkit.protocols.internet.hip), 88
 DataType_Dest_Opt_IP_DFF (class in pcap- DataType_HTTP (class in pcap-
 kit.protocols.internet.ipv6_opts), 160 kit.protocols.application.httpv1), 207
 DataType_Dest_Opt_Jumbo (class in pcap- DataType_HTTP_Raw (class in pcap-
 kit.protocols.internet.ipv6_opts), 159 kit.protocols.application.httpv1), 207
 DataType_Dest_Opt_LIO (class in pcap- DataType_HTTP_Request_Header (class in pcap-
 kit.protocols.internet.ipv6_opts), 158 kit.protocols.application.httpv1), 207
 DataType_Dest_Opt_MPL (class in pcap- DataType_HTTP_Request_Header_Meta (class
 kit.protocols.internet.ipv6_opts), 157 in pcapkit.protocols.application.httpv1), 207
 DataType_Dest_Opt_None (class in pcap- DataType_HTTP_Response_Header (class in
 kit.protocols.internet.ipv6_opts), 151 pcapkit.protocols.application.httpv1), 207
 DataType_Dest_Opt_Pad1 (class in pcap- DataType_HTTP_Response_Header_Meta (class

in pcapkit.protocols.application.httpv1), 208
 DataType_HTTPv2 (class in *pcapkit.protocols.application.httpv2*), 215
 DataType_HTTPv2_CONTINUATION (class in *pcapkit.protocols.application.httpv2*), 222
 DataType_HTTPv2_CONTINUATION_Flags (class in *pcapkit.protocols.application.httpv2*), 222
 DataType_HTTPv2_DATA (class in *pcapkit.protocols.application.httpv2*), 216
 DataType_HTTPv2_DATA_Flags (class in *pcapkit.protocols.application.httpv2*), 216
 DataType_HTTPv2_Frame (class in *pcapkit.protocols.application.httpv2*), 215
 DataType_HTTPv2_GOAWAY (class in *pcapkit.protocols.application.httpv2*), 221
 DataType_HTTPv2_HEADERS (class in *pcapkit.protocols.application.httpv2*), 217
 DataType_HTTPv2_HEADERS_Flags (class in *pcapkit.protocols.application.httpv2*), 217
 DataType_HTTPv2_PING (class in *pcapkit.protocols.application.httpv2*), 220
 DataType_HTTPv2_PING_Flags (class in *pcapkit.protocols.application.httpv2*), 220
 DataType_HTTPv2_PRIORITY (class in *pcapkit.protocols.application.httpv2*), 218
 DataType_HTTPv2_PUSH_PROMISE (class in *pcapkit.protocols.application.httpv2*), 219
 DataType_HTTPv2_PUSH_PROMISE_Flags (class in *pcapkit.protocols.application.httpv2*), 220
 DataType_HTTPv2_RST_STREAM (class in *pcapkit.protocols.application.httpv2*), 218
 DataType_HTTPv2_SETTINGS (class in *pcapkit.protocols.application.httpv2*), 219
 DataType_HTTPv2_SETTINGS_Flags (class in *pcapkit.protocols.application.httpv2*), 219
 DataType_HTTPv2_Unassigned (class in *pcapkit.protocols.application.httpv2*), 216
 DataType_HTTPv2_WINDOW_UPDATE (class in *pcapkit.protocols.application.httpv2*), 221
 DataType_IP_DFF_Flags (class in *pcapkit.protocols.internet.hopopt*), 123
 DataType_IP_DFF_Flags (class in *pcapkit.protocols.internet.ipv6_opts*), 160
 DataType_IPv4 (class in *pcapkit.protocols.internet.ipv4*), 131
 DataType_IPv4_DSCP (class in *pcapkit.protocols.internet.ipv4*), 132
 DataType_IPv4_Flags (class in *pcapkit.protocols.internet.ipv4*), 132
 DataType_IPv4_OPT (class in *pcapkit.protocols.internet.ipv4*), 132
 DataType_IPv4_Option_Type (class in *pcapkit.protocols.internet.ipv4*), 133
 DataType_IPv6 (class in *pcapkit.protocols.internet.ipv6*), 169
 DataType_IPv6_Frag (class in *pcapkit.protocols.internet.ipv6_frag*), 140
 DataType_IPv6_Opts (class in *pcapkit.protocols.internet.ipv6_opts*), 149
 DataType_IPv6_Opts_Option_Type (class in *pcapkit.protocols.internet.ipv6_opts*), 150
 DataType_IPv6_Route (class in *pcapkit.protocols.internet.ipv6_route*), 164
 DataType_IPv6_Route_2 (class in *pcapkit.protocols.internet.ipv6_route*), 166
 DataType_IPv6_Route_None (class in *pcapkit.protocols.internet.ipv6_route*), 165
 DataType_IPv6_Route_RPL (class in *pcapkit.protocols.internet.ipv6_route*), 166
 DataType_IPv6_Route_Source (class in *pcapkit.protocols.internet.ipv6_route*), 165
 DataType_IPX (class in *pcapkit.protocols.internet.ipx*), 171
 DataType_IPX_Address (class in *pcapkit.protocols.internet.ipx*), 171
 DataType_L2TP (class in *pcapkit.protocols.link.l2tp*), 38
 DataType_Lifetime (class in *pcapkit.protocols.internet.hip*), 91
 DataType_Locator (class in *pcapkit.protocols.internet.hip*), 82
 DataType_Locator_Dict (class in *pcapkit.protocols.internet.hip*), 83
 DataType_MagicNumber (class in *pcapkit.protocols.pcap.header*), 27
 DataType_MH (class in *pcapkit.protocols.internet.mh*), 173
 DataType_MPL_Flags (class in *pcapkit.protocols.internet.hopopt*), 121
 DataType_MPL_Flags (class in *pcapkit.protocols.internet.ipv6_opts*), 157
 DataType_Opt (class in *pcapkit.protocols.internet.ipv4*), 132
 DataType_Opt_1_Byte (class in *pcapkit.protocols.internet.ipv4*), 133
 DataType_Opt_CALIPSO (class in *pcapkit.protocols.internet.hopopt*), 116
 DataType_Opt_Do_None (class in *pcapkit.protocols.internet.ipv4*), 134
 DataType_Opt_Home (class in *pcapkit.protocols.internet.hopopt*), 123
 DataType_Opt_ILNP (class in *pcapkit.protocols.internet.hopopt*), 121
 DataType_Opt_IP_DFF (class in *pcapkit.protocols.internet.hopopt*), 123
 DataType_Opt_Jumbo (class in *pcapkit.protocols.internet.hopopt*), 122
 DataType_Opt_LIO (class in *pcapkit*), 122

<i>kit.protocols.internet.hopopt</i>), 122		<i>kit.protocols.internet.hip</i>), 86	
DataType_Opt_MPL (class in <i>kit.protocols.internet.hopopt</i>), 121	pcap-	DataType_Param_Deffie_Hellman (class in <i>pcapkit.protocols.internet.hip</i>), 85	
DataType_Opt_None (class in <i>kit.protocols.internet.hopopt</i>), 114	pcap-	DataType_Param_DH_Group_List (class in <i>pcapkit.protocols.internet.hip</i>), 85	
DataType_Opt_Pad1 (class in <i>kit.protocols.internet.hopopt</i>), 115	pcap-	DataType_Param_Echo_Request_Signed (class in <i>pcapkit.protocols.internet.hip</i>), 90	
DataType_Opt_PadN (class in <i>kit.protocols.internet.hopopt</i>), 115	pcap-	DataType_Param_Echo_Request_Unsigned (class in <i>pcapkit.protocols.internet.hip</i>), 99	
DataType_Opt_PDM (class in <i>kit.protocols.internet.hopopt</i>), 118	pcap-	DataType_Param_Echo_Response_Signed (class in <i>pcapkit.protocols.internet.hip</i>), 93	
DataType_Opt_Permission (class in <i>kit.protocols.internet.ipv4</i>), 134	pcap-	DataType_Param_Echo_Response_Unsigned (class in <i>pcapkit.protocols.internet.hip</i>), 100	
DataType_Opt_QS (class in <i>kit.protocols.internet.hopopt</i>), 119	pcap-	DataType_Param_Encrypted (class in <i>pcapkit.protocols.internet.hip</i>), 88	
DataType_Opt_QuickStart (class in <i>kit.protocols.internet.ipv4</i>), 135	pcap-	DataType_Param_ESP_Info (class in <i>pcapkit.protocols.internet.hip</i>), 81	
DataType_Opt_RA (class in <i>kit.protocols.internet.hopopt</i>), 116	pcap-	DataType_Param_ESP_Transform (class in <i>pcapkit.protocols.internet.hip</i>), 94	
DataType_Opt_Route_Data (class in <i>kit.protocols.internet.ipv4</i>), 135	pcap-	DataType_Param_From (class in <i>pcapkit.protocols.internet.hip</i>), 102	
DataType_Opt_RouterAlert (class in <i>kit.protocols.internet.ipv4</i>), 138	pcap-	DataType_Param_HIT_Suite_List (class in <i>pcapkit.protocols.internet.hip</i>), 89	
DataType_Opt_RPL (class in <i>kit.protocols.internet.hopopt</i>), 120	pcap-	DataType_Param_HMAC (class in <i>pcapkit.protocols.internet.hip</i>), 98	
DataType_Opt_Security_Info (class in <i>pcapkit.protocols.internet.ipv4</i>), 137	pcap-	DataType_Param_HMAC_2 (class in <i>pcapkit.protocols.internet.hip</i>), 98	
DataType_Opt_SMF_H_PDP (class in <i>pcapkit.protocols.internet.hopopt</i>), 118	pcap-	DataType_Param_Host_ID (class in <i>pcapkit.protocols.internet.hip</i>), 88	
DataType_Opt_SMF_I_PDP (class in <i>pcapkit.protocols.internet.hopopt</i>), 117	pcap-	DataType_Param_Locator_Set (class in <i>pcapkit.protocols.internet.hip</i>), 82	
DataType_Opt_TimeStamp (class in <i>pcapkit.protocols.internet.ipv4</i>), 136	pcap-	DataType_Param_NET_Traversal_Mode (class in <i>pcapkit.protocols.internet.hip</i>), 87	
DataType_Opt_Traceroute (class in <i>pcapkit.protocols.internet.ipv4</i>), 137	pcap-	DataType_Param_Notification (class in <i>pcapkit.protocols.internet.hip</i>), 90	
DataType_Opt_TUN (class in <i>kit.protocols.internet.hopopt</i>), 116	pcap-	DataType_Param_Overlay_ID (class in <i>pcapkit.protocols.internet.hip</i>), 96	
DataType_Opt_Unpack (class in <i>pcapkit.protocols.internet.ipv4</i>), 134	pcap-	DataType_Param_Overlay_TTL (class in <i>pcapkit.protocols.internet.hip</i>), 101	
DataType_Option (class in <i>kit.protocols.internet.hopopt</i>), 113	pcap-	DataType_Param_Payload_MIC (class in <i>pcapkit.protocols.internet.hip</i>), 95	
DataType_Option (class in <i>kit.protocols.internet.ipv6_opts</i>), 150	pcap-	DataType_Param_Puzzle (class in <i>pcapkit.protocols.internet.hip</i>), 83	
DataType_Option_Type (class in <i>kit.protocols.internet.hopopt</i>), 114	pcap-	DataType_Param_R1_Counter (class in <i>pcapkit.protocols.internet.hip</i>), 82	
DataType_OSPF (class in <i>pcapkit.protocols.link.ospf</i>), 41		DataType_Param_Reg_Failed (class in <i>pcapkit.protocols.internet.hip</i>), 92	
DataType_Param_ACK (class in <i>pcapkit.protocols.internet.hip</i>), 85	pcap-	DataType_Param_Reg_From (class in <i>pcapkit.protocols.internet.hip</i>), 93	
DataType_Param_ACK_Data (class in <i>pcapkit.protocols.internet.hip</i>), 95	pcap-	DataType_Param_Reg_Info (class in <i>pcapkit.protocols.internet.hip</i>), 91	
DataType_Param_Cert (class in <i>pcapkit.protocols.internet.hip</i>), 89	pcap-	DataType_Param_Reg_Request (class in <i>pcapkit.protocols.internet.hip</i>), 91	
DataType_Param_Cipher (class in <i>pcap-</i>		DataType_Param_Reg_Response (class in <i>pcap-</i>	

kit.protocols.internet.hip), 92
 DataType_Param_Relay_From (class in *pcap-kit.protocols.internet.hip*), 100
 DataType_Param_Relay_HMAC (class in *pcap-kit.protocols.internet.hip*), 103
 DataType_Param_Relay_To (class in *pcap-kit.protocols.internet.hip*), 101
 DataType_Param_Route_Dst (class in *pcap-kit.protocols.internet.hip*), 96
 DataType_Param_Route_Via (class in *pcap-kit.protocols.internet.hip*), 102
 DataType_Param_RVS_HMAC (class in *pcap-kit.protocols.internet.hip*), 103
 DataType_Param_SEQ (class in *pcap-kit.protocols.internet.hip*), 84
 DataType_Param_SEQ_Data (class in *pcap-kit.protocols.internet.hip*), 94
 DataType_Param_Signature (class in *pcap-kit.protocols.internet.hip*), 99
 DataType_Param_Signature_2 (class in *pcap-kit.protocols.internet.hip*), 98
 DataType_Param_Solution (class in *pcap-kit.protocols.internet.hip*), 84
 DataType_Param_Transaction_ID (class in *pcapkit.protocols.internet.hip*), 96
 DataType_Param_Transaction_Pacing (class in *pcapkit.protocols.internet.hip*), 87
 DataType_Param_Transform (class in *pcap-kit.protocols.internet.hip*), 86
 DataType_Param_Transform_Format_List (class in *pcapkit.protocols.internet.hip*), 94
 DataType_Param_Transport_Mode (class in *pcapkit.protocols.internet.hip*), 97
 DataType_Param_Unassigned (class in *pcap-kit.protocols.internet.hip*), 81
 DataType_Param_Via_RVS (class in *pcap-kit.protocols.internet.hip*), 103
 DataType_Parameter (class in *pcap-kit.protocols.internet.hip*), 80
 DataType_Raw (class in *pcapkit.protocols.raw*), 224
 DataType_RPL_Flags (class in *pcap-kit.protocols.internet.hopopt*), 120
 DataType_RPL_Flags (class in *pcap-kit.protocols.internet.ipv6_opts*), 156
 DataType_SEC_Flags (class in *pcap-kit.protocols.internet.ipv4*), 137
 DataType_TCI (class in *pcapkit.protocols.link.vlan*), 44
 DataType_TCP (class in *pcap-kit.protocols.transport.tcp*), 189
 DataType_TCP_Flags (class in *pcap-kit.protocols.transport.tcp*), 189
 DataType_TCP_OPT (class in *pcap-kit.protocols.transport.tcp*), 190
 DataType_TCP_Opt (class in *pcap-kit.protocols.transport.tcp*), 190
 DataType_TCP_Opt_ACOPT (class in *pcap-kit.protocols.transport.tcp*), 192
 DataType_TCP_Opt_ADD_ADDR (class in *pcap-kit.protocols.transport.tcp*), 199
 DataType_TCP_Opt_ADD_ADDR_Data (class in *pcapkit.protocols.transport.tcp*), 200
 DataType_TCP_Opt_DONONE (class in *pcap-kit.protocols.transport.tcp*), 191
 DataType_TCP_Opt_DSS (class in *pcap-kit.protocols.transport.tcp*), 198
 DataType_TCP_Opt_DSS_Data (class in *pcap-kit.protocols.transport.tcp*), 199
 DataType_TCP_Opt_DSS_Flags (class in *pcap-kit.protocols.transport.tcp*), 199
 DataType_TCP_Opt_MP_CAPABLE (class in *pcap-kit.protocols.transport.tcp*), 195
 DataType_TCP_Opt_MP_CAPABLE_Data (class in *pcapkit.protocols.transport.tcp*), 195
 DataType_TCP_Opt_MP_CAPABLE_Flags (class in *pcapkit.protocols.transport.tcp*), 195
 DataType_TCP_Opt_MP_FAIL (class in *pcap-kit.protocols.transport.tcp*), 201
 DataType_TCP_Opt_MP_FAIL_Data (class in *pcapkit.protocols.transport.tcp*), 201
 DataType_TCP_Opt_MP_FASTCLOSE (class in *pcapkit.protocols.transport.tcp*), 202
 DataType_TCP_Opt_MP_FASTCLOSE_Data (class in *pcapkit.protocols.transport.tcp*), 202
 DataType_TCP_Opt_MP_JOIN (class in *pcap-kit.protocols.transport.tcp*), 196
 DataType_TCP_Opt_MP_JOIN_ACK (class in *pcap-kit.protocols.transport.tcp*), 198
 DataType_TCP_Opt_MP_JOIN_ACK_Data (class in *pcapkit.protocols.transport.tcp*), 198
 DataType_TCP_Opt_MP_JOIN_Data (class in *pcapkit.protocols.transport.tcp*), 196
 DataType_TCP_Opt_MP_JOIN_SYN (class in *pcap-kit.protocols.transport.tcp*), 196
 DataType_TCP_Opt_MP_JOIN_SYN_Data (class in *pcapkit.protocols.transport.tcp*), 196
 DataType_TCP_Opt_MP_JOIN_SYNACK (class in *pcapkit.protocols.transport.tcp*), 197
 DataType_TCP_Opt_MP_JOIN_SYNACK_Data (class in *pcapkit.protocols.transport.tcp*), 197
 DataType_TCP_Opt_MP_PRIO (class in *pcap-kit.protocols.transport.tcp*), 201
 DataType_TCP_Opt_MP_PRIO_Data (class in *pcapkit.protocols.transport.tcp*), 201
 DataType_TCP_Opt_MPTCP (class in *pcap-kit.protocols.transport.tcp*), 194
 DataType_TCP_Opt_POCSPP (class in *pcap-kit.protocols.transport.tcp*), 192

<code>DataType_TCP_Opt_QSOPT</code> (class in <code>pcapkit.protocols.transport.tcp</code>), 193	320
<code>DataType_TCP_Opt_REMOVE_ADDR</code> (class in <code>pcapkit.protocols.transport.tcp</code>), 200	<code>DEC_MOP_Remote_Console</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320
<code>DataType_TCP_Opt_REMOVE_ADDR_Data</code> (class in <code>pcapkit.protocols.transport.tcp</code>), 200	<code>DEC_Unassigned_0x6000</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320
<code>DataType_TCP_Opt_TCPAO</code> (class in <code>pcapkit.protocols.transport.tcp</code>), 194	<code>DEC_Unassigned_0x803E</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320
<code>DataType_TCP_Opt_TS</code> (class in <code>pcapkit.protocols.transport.tcp</code>), 191	<code>decode()</code> (<code>pcapkit.protocols.protocol.Protocol</code> static method), 230
<code>DataType_TCP_Opt_UNPACK</code> (class in <code>pcapkit.protocols.transport.tcp</code>), 191	<code>DEFAULT</code> (<code>pcapkit.const.hip.transport.Transport</code> attribute), 287
<code>DataType_TCP_Opt_UTOPT</code> (class in <code>pcapkit.protocols.transport.tcp</code>), 193	<code>DEFAULT</code> (<code>pcapkit.const.ipv6.tagger_id.TaggerID</code> attribute), 307
<code>DataType_UDP</code> (class in <code>pcapkit.protocols.transport.udp</code>), 177	<code>defaultInfo</code> (class in <code>pcapkit.const.ftp.command</code>), 270
<code>DataType_VLAN</code> (class in <code>pcapkit.protocols.link.vlan</code>), 44	<code>dei</code> (<code>pcapkit.protocols.link.vlan.DataType_TCI</code> attribute), 44
<code>DBUS</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 313	<code>del</code> (<code>pcapkit.protocols.internet.ipv4.DataType_IPv4_DSCP</code> attribute), 132
<code>DCCP</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 327	<code>Delta_Controls</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320
<code>DCN_MEAS</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 327	<code>deltatlr</code> (<code>pcapkit.protocols.internet.hopopt.DataType_Opt_PDM</code> attribute), 119
<code>DDP</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 327	<code>deltatlr</code> (<code>pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PDM</code> attribute), 155
<code>DDX</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 327	<code>deltatls</code> (<code>pcapkit.protocols.internet.hopopt.DataType_Opt_PDM</code> attribute), 119
<code>debugging_and_measurement</code> (<code>pcapkit.const.ipv4.option_class.OptionClass</code> attribute), 291	<code>deltatls</code> (<code>pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PDM</code> attribute), 155
<code>DEC_Customer_Protocol</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	<code>DEPRECATED</code> (<code>pcapkit.const.ipv6.option.Option</code> attribute), 300
<code>DEC_DECNET_Phase_IV_Route</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	<code>Deprecated</code> (<code>pcapkit.const.ipv6.option.Option</code> attribute), 300
<code>DEC_Diagnostic_Protocol</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	<code>DEPRECATED_2</code> (<code>pcapkit.const.hip.esp_transform_suite.ESPTransformSuite</code> attribute), 276
<code>DEC_Ethernet_Encryption</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	<code>DEPRECATED_3</code> (<code>pcapkit.const.hip.esp_transform_suite.ESPTransformSuite</code> attribute), 276
<code>DEC_LAN_Traffic_Monitor</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	<code>DEPRECATED_4</code> (<code>pcapkit.const.hip.esp_transform_suite.ESPTransformSuite</code> attribute), 276
<code>DEC_LANBridge</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	<code>DEPRECATED_5</code> (<code>pcapkit.const.hip.esp_transform_suite.ESPTransformSuite</code> attribute), 276
<code>DEC_LAT</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	<code>DEPRECATED_6</code> (<code>pcapkit.const.hip.esp_transform_suite.ESPTransformSuite</code> attribute), 276
<code>DEC_LAVC_SCA</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	<code>deps</code> (<code>pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEADERS</code> attribute), 217
<code>DEC_MOP_Dump_Load</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 320	

deps (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_PRIORITY* attribute), 218
 desc (*pcapkit.protocols.internet.hopopt.DataType_Option* domain attribute), 113
 desc (*pcapkit.protocols.internet.ipv4.DataType_IPv4_OPTdomain_id* attribute), 133
 desc (*pcapkit.protocols.internet.ipv6_opts.DataType_Option* down attribute), 150
 desc (*pcapkit.protocols.transport.tcp.DataType_TCP_OPT* down attribute), 190
 DEVMODE (in module *pcapkit.utilities.exceptions*), 261
 DevModeWarning, 265
 df (*pcapkit.protocols.internet.ipv4.DataType_IPv4_Flags* attribute), 132
 DGP (*pcapkit.const.reg.transtype.TransType* attribute), 327
 DH_GROUP_LIST (*pcapkit.const.hip.parameter.Parameter* attribute), 282
 di_len (*pcapkit.protocols.internet.hip.DataType_Param_Host_ID* attribute), 88
 di_type (*pcapkit.protocols.internet.hip.DataType_Param_Host_ID* attribute), 88
 Diagnostic_Packet (*pcapkit.const.ipx.socket.Socket* attribute), 308
 dict_check() (in module *pcapkit.utilities.validations*), 262
 DictError, 258
 DIFFIE_HELLMAN (*pcapkit.const.hip.parameter.Parameter* attribute), 282
 DigitError, 259
 DISPLAYPORT_AUX (*pcapkit.const.reg.linktype.LinkType* attribute), 313
 Distinguished_Name_of_X_509_v3 (*pcapkit.const.hip.certificate.Certificate* attribute), 273
 DITypes (class in *pcapkit.const.hip.di*), 274
 DITypes (class in *pcapkit.vendor.hip.di*), 340
 dl_len (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Data* attribute), 199
 DLOG_0x0660 (*pcapkit.const.reg.ethertype.EtherType* attribute), 320
 DLOG_0x0661 (*pcapkit.const.reg.ethertype.EtherType* attribute), 320
 DOCS (*pcapkit.vendor.default.Vendor* attribute), 365
 DOCSIS (*pcapkit.const.reg.linktype.LinkType* attribute), 313
 DOCSIS31_XRA31 (*pcapkit.const.reg.linktype.LinkType* attribute), 313
 DOE (*pcapkit.const.ipv4.protection_authority.ProtectionAuthority* attribute), 293
 dpd_type (*pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_H_PD* attribute), 118
 dpd_type (*pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_I_PD* attribute), 117
 dpd_type (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_SMF_I_PD* attribute), 154
 dpd_type (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_SMF_I_PD* attribute), 154
 DPKTWarning, 265
 dss (*pcapkit.const.ipv4.option_number.OptionNumber* attribute), 292
 DSS_Error (*pcapkit.const.arp.operation.Operation* attribute), 268
 DRARP_Reply (*pcapkit.const.arp.operation.Operation* attribute), 269
 DRARP_Request (*pcapkit.const.arp.operation.Operation* attribute), 269
 DSA (*pcapkit.const.hip.hi_algorithm.HIAlgorithm* attribute), 278
 DSA_TAG_BRCM (*pcapkit.const.reg.linktype.LinkType* attribute), 313
 DSA_TAG_BRCM_PREPEND (*pcapkit.const.reg.linktype.LinkType* attribute), 313
 DSA_TAG_DSA (*pcapkit.const.reg.linktype.LinkType* attribute), 313
 DSA_TAG_EDSA (*pcapkit.const.reg.linktype.LinkType* attribute), 313
 dscp (*pcapkit.protocols.internet.ipv4.DataType_DS_Field* attribute), 132
 dsfield (*pcapkit.protocols.internet.ipv4.DataType_IPv4* attribute), 131
 dsn (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Data* attribute), 199
 dsn (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_FAIL_Data* attribute), 201
 dsn_len (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Flag* attribute), 199
 DSR (*pcapkit.const.reg.transtype.TransType* attribute), 327
 dss (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS* attribute), 198
 dst (*pcapkit.protocols.internet.ipv4.DataType_IPv4* at-

- tribute), 131
 - dst (*pcapkit.protocols.internet.ipv6.DataType_IPv6 attribute*), 169
 - dst (*pcapkit.protocols.internet.ipx.DataType_IPX attribute*), 171
 - dst (*pcapkit.protocols.link.ethernet.DataType_Ethernet attribute*), 36
 - dst () (*pcapkit.protocols.internet.ip.IP property*), 124
 - dst () (*pcapkit.protocols.internet.ipsec.IPsec property*), 125
 - dst () (*pcapkit.protocols.internet.ipx.IPX property*), 170
 - dst () (*pcapkit.protocols.link.arp.ARP property*), 33
 - dst () (*pcapkit.protocols.link.ethernet.Ethernet property*), 35
 - dst () (*pcapkit.protocols.transport.tcp.TCP property*), 187
 - dst () (*pcapkit.protocols.transport.udp.UDP property*), 177
 - dstport (*pcapkit.protocols.transport.tcp.DataType_TCP attribute*), 189
 - dstport (*pcapkit.protocols.transport.udp.DataType_UDPECMA attribute*), 177
 - dump () (*pcapkit.foundation.traceflow.TraceFlow method*), 19
 - dup (*pcapkit.protocols.internet.hopopt.DataType_IP_DFF_Flags attribute*), 124
 - dup (*pcapkit.protocols.internet.ipv6_opts.DataType_IP_DFF_Flags attribute*), 160
 - DVB_CI (*pcapkit.const.reg.linktype.LinkType attribute*), 313
- ## E
- E_SEC (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
 - EBHSCR (*pcapkit.const.reg.linktype.LinkType attribute*), 313
 - ECDSA (*pcapkit.const.hip.hi_algorithm.HIAlgorithm attribute*), 278
 - ECDSA_LOW (*pcapkit.const.hip.hi_algorithm.HIAlgorithm attribute*), 278
 - ECDSA_LOW_SHA_1 (*pcapkit.const.hip.hit_suite.HITSuite attribute*), 278
 - ECDSA_SHA_384 (*pcapkit.const.hip.hit_suite.HITSuite attribute*), 279
 - ECDSACurve (*class in pcapkit.const.hip.ecdsa_curve*), 275
 - ECDSACurve (*class in pcapkit.vendor.hip.ecdsa_curve*), 340
 - ECDSALowCurve (*class in pcapkit.const.hip.ecdsa_low_curve*), 275
 - ECDSALowCurve (*class in pcapkit.vendor.hip.ecdsa_low_curve*), 341
 - ece (*pcapkit.protocols.transport.tcp.DataType_TCP_Flags attribute*), 190
 - ECHO (*pcapkit.const.tcp.option.Option attribute*), 335
 - Echo_Packet (*pcapkit.const.ipx.packet.Packet attribute*), 307
 - Echo_Protocol_Packet (*pcapkit.const.ipx.socket.Socket attribute*), 308
 - ECHO_REQUEST_SIGNED (*pcapkit.const.hip.parameter.Parameter attribute*), 282
 - ECHO_REQUEST_UNSIGNED (*pcapkit.const.hip.parameter.Parameter attribute*), 282
 - ECHO_RESPONSE_SIGNED (*pcapkit.const.hip.parameter.Parameter attribute*), 282
 - ECHO_RESPONSE_UNSIGNED (*pcapkit.const.hip.parameter.Parameter attribute*), 283
 - ECHORE (*pcapkit.const.tcp.option.Option attribute*), 335
 - ecn (*pcapkit.protocols.internet.ipv4.DataType_DS_Field attribute*), 132
 - ecr (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_TS attribute*), 192
 - ECT_0b01 (*pcapkit.const.ipv4.tos_ecn.ToSECN attribute*), 298
 - ECT_0b10 (*pcapkit.const.ipv4.tos_ecn.ToSECN attribute*), 298
 - EE (*pcapkit.const.vlan.priority_level.PriorityLevel attribute*), 337
 - EGP (*pcapkit.const.reg.transtype.TransType attribute*), 327
 - EIGRP (*pcapkit.const.reg.transtype.TransType attribute*), 327
 - EIP (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
 - ELEE (*pcapkit.const.reg.linktype.LinkType attribute*), 313
 - EMCON (*pcapkit.const.reg.transtype.TransType attribute*), 327
 - ENABLE_PUSH (*pcapkit.const.http.setting.Setting attribute*), 290
 - ENCAP (*pcapkit.const.reg.transtype.TransType attribute*), 327
 - ENCODE (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
 - ENCRYPTED (*pcapkit.const.hip.parameter.Parameter attribute*), 283
 - ENCRYPTION_FAILED (*pcapkit.const.hip.notify_message.NotifyMessage attribute*), 280
 - Encryption_Negotiation (*pcap-*

kit.const.tcp.option.Option attribute), 335
 end (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_POCS attribute*), 299
attribute), 192
 END_HEADERS (*pcap- kit.protocols.application.httpv2.DataType_HTTPv2_HEADERS attribute*), 222
 END_HEADERS (*pcap- kit.protocols.application.httpv2.DataType_HTTPv2_HEADERS attribute*), 217
 END_HEADERS (*pcap- kit.protocols.application.httpv2.DataType_HTTPv2_PUSH_PROMISE attribute*), 220
 END_STREAM (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_DATA attribute*), 216
 END_STREAM (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEADERS attribute*), 217
 EndianError, 259
 engine () (*pcapkit.foundation.extraction.Extractor property*), 16
 EngineWarning, 265
 ENHANCE_YOUR_CALM (*pcap- kit.const.http.error_code.ErrorCode attribute*), 288
 enum_check () (*in module pcap- kit.utilities.validations*), 262
 EnumError, 259
 environment variable
 PCAPKIT_HTTP_PROXY, 365
 PCAPKIT_HTTPS_PROXY, 365
 eof (*pcapkit.foundation.extraction.Extractor._mpkit attribute*), 7
 EOOL (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
 EOOL (*pcapkit.const.tcp.option.Option attribute*), 335
 EPON (*pcapkit.const.reg.linktype.LinkType attribute*), 313
 ERF (*pcapkit.const.reg.linktype.LinkType attribute*), 313
 error (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_GOAWAY attribute*), 221
 error (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_RST_STREAM attribute*), 218
 error (*pcapkit.protocols.pcap.frame.DataType_Frame attribute*), 31
 error (*pcapkit.protocols.raw.DataType_Raw attribute*), 224
 Error_Handling_Packet (*pcap- kit.const.ipx.socket.Socket attribute*), 308
 Error_Packet (*pcapkit.const.ipx.packet.Packet attribute*), 307
 ErrorCode (*class in pcapkit.const.http.error_code*), 288
 ErrorCode (*class in pcapkit.vendor.http.error_code*), 345
 ESP (*pcapkit.const.hip.transport.Transport attribute*), 287
 ESP (*pcapkit.const.ipv6.extension_header.ExtensionHeader attribute*), 299
 ESP (*pcapkit.const.reg.transtype.TransType attribute*), 327
 ESP_CONTINUE (*pcapkit.const.hip.parameter.Parameter attribute*), 283
 ESP_TCP (*pcapkit.const.hip.transport.Transport attribute*), 287
 ESP_TRANSFORM (*pcap- kit.const.hip.parameter.Parameter attribute*), 287
 ESPTransformSuite (*class in pcap- kit.const.hip.parameter.Parameter attribute*), 287
 ESPTransformSuite (*class in pcap- kit.const.hip.parameter.Parameter attribute*), 341
 ETHERIP (*pcapkit.const.reg.transtype.TransType attribute*), 327
 Ethernet (*class in pcapkit.protocols.link.ethernet*), 34
 Ethernet (*pcapkit.const.arp.hardware.Hardware attribute*), 267
 ETHERNET (*pcapkit.const.reg.linktype.LinkType attribute*), 313
 Ethernet (*pcapkit.const.reg.transtype.TransType attribute*), 327
 ETHERNET_MPACKE (*pcap- kit.const.reg.linktype.LinkType attribute*), 313
 EtherType (*class in pcapkit.const.reg.ethertype*), 318
 EtherType (*class in pcapkit.vendor.reg.ethertype*), 360
 EtherType_3Com_loop_detect (*pcap- kit.const.reg.ethertype.EtherType attribute*), 321
 EtherType_3Com_TCP_IP_Sys (*pcap- kit.const.reg.ethertype.EtherType attribute*), 320
 EtherType_3Com_XNS_Sys_Mgmt (*pcap- kit.const.reg.ethertype.EtherType attribute*), 320
 Evans_Sutherland (*pcap- kit.const.reg.ethertype.EtherType attribute*), 321
 Excelan (*pcapkit.const.reg.ethertype.EtherType attribute*), 321
 exclusive (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEADERS attribute*), 217
 exclusive (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_PUSH_PROMISE attribute*), 218
 EXP_158 (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
 EXP_222 (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
 EXP_30 (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292

- attribute*), 292
- EXP_94 (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
- ExperData (*pcapkit.const.reg.ethertype.EtherType attribute*), 321
- Experimental_Ethernet (*pcapkit.const.arp.hardware.Hardware attribute*), 267
- Experimental_Mobility_Header (*pcapkit.const.mh.packet.Packet attribute*), 309
- ext (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MIP_CAPABLE_Flags attribute*), 195
- ExtensionHeader (*class in pcapkit.const.ipv6.extension_header*), 299
- ExtensionHeader (*class in pcapkit.vendor.ipv6.extension_header*), 353
- extract () (*in module pcapkit.interface*), 21
- Extractor (*class in pcapkit.foundation.extraction*), 4
- F**
- F (*in module pcapkit.vendor.tcp.option*), 362
- fail (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MIP_CAPABLE_Flags attribute*), 201
- Fast_Binding_Acknowledgment (*pcapkit.const.mh.packet.Packet attribute*), 309
- Fast_Binding_Update (*pcapkit.const.mh.packet.Packet attribute*), 309
- Fast_Neighbor_Advertisement (*pcapkit.const.mh.packet.Packet attribute*), 309
- fastclose (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MIP_CAPABLE_Flags attribute*), 202
- FASTOPEN (*pcapkit.const.tcp.option.Option attribute*), 335
- FC (*pcapkit.const.reg.transtype.TransType attribute*), 328
- FC_2 (*pcapkit.const.reg.linktype.LinkType attribute*), 313
- FC_2_WITH_FRAME_DELIMS (*pcapkit.const.reg.linktype.LinkType attribute*), 313
- FDDI (*pcapkit.const.reg.linktype.LinkType attribute*), 313
- fetch () (*pcapkit.reassembly.reassembly.Reassembly method*), 233
- Fibre_Channel (*pcapkit.const.arp.hardware.Hardware attribute*), 267
- Field_Termination_Indicator (*pcapkit.const.ipv4.protection_authority.ProtectionAuthority attribute*), 293
- FileError, 259
- FileExists, 259
- FileNotFound, 259
- FileWarning, 265
- filler (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_POCSPP_ATTRIBUTE attribute*), 192
- fin (*pcapkit.protocols.transport.tcp.DataType_TCP_Flags attribute*), 190
- fin (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Flags attribute*), 199
- FINN (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
- FIRE (*pcapkit.const.reg.transtype.TransType attribute*), 328
- flag (*pcapkit.protocols.internet.ipv4.DataType_IPv4_OPT_ATTRIBUTE attribute*), 133
- flag (*pcapkit.protocols.internet.ipv4.DataType_Opt_Permission attribute*), 134
- flag (*pcapkit.protocols.internet.ipv4.DataType_Opt_TimeStamp attribute*), 136
- flag (*pcapkit.protocols.transport.tcp.DataType_TCP_OPT_ATTRIBUTE attribute*), 190
- FLAG (*pcapkit.vendor.arp.hardware.Hardware attribute*), 337
- FLAG (*pcapkit.vendor.arp.operation.Operation attribute*), 338
- FLAG (*pcapkit.vendor.default.Vendor attribute*), 365
- FLAG_FAIL (*pcapkit.vendor.ftp.return_code.ReturnCode attribute*), 339
- FLAG (*pcapkit.vendor.hip.certificate.Certificate attribute*), 339
- FLAG (*pcapkit.vendor.hip.cipher.Cipher attribute*), 340
- FLAG (*pcapkit.vendor.hip.di.DITypes attribute*), 340
- FLAG (*pcapkit.vendor.hip.ecdsa_curve.ECDSACurve attribute*), 340
- FLAG (*pcapkit.vendor.hip.ecdsa_low_curve.ECDSALowCurve attribute*), 341
- FLAG (*pcapkit.vendor.hip.esp_transform_suite.ESPTransformSuite attribute*), 341
- FLAG (*pcapkit.vendor.hip.group.Group attribute*), 341
- FLAG (*pcapkit.vendor.hip.hi_algorithm.HIAlgorithm attribute*), 342
- FLAG (*pcapkit.vendor.hip.hit_suite.HITSuite attribute*), 342
- FLAG (*pcapkit.vendor.hip.nat_traversal.NATTraversal attribute*), 342
- FLAG (*pcapkit.vendor.hip.notify_message.NotifyMessage attribute*), 342
- FLAG (*pcapkit.vendor.hip.packet.Packet attribute*), 343
- FLAG (*pcapkit.vendor.hip.parameter.Parameter attribute*), 343
- FLAG (*pcapkit.vendor.hip.registration.Registration attribute*), 343
- FLAG (*pcapkit.vendor.hip.registration_failure.RegistrationFailure attribute*), 344
- FLAG (*pcapkit.vendor.hip.suite.Suite attribute*), 344
- FLAG (*pcapkit.vendor.hip.transport.Transport attribute*), 344
- FLAG (*pcapkit.vendor.http.error_code.ErrorCode attribute*), 345

- FLAG (*pcapkit.vendor.http.frame.Frame* attribute), 345
- FLAG (*pcapkit.vendor.http.setting.Setting* attribute), 346
- FLAG (*pcapkit.vendor.ipv4.classification_level.ClassificationLevel* attribute), 346
- FLAG (*pcapkit.vendor.ipv4.option_class.OptionClass* attribute), 347
- FLAG (*pcapkit.vendor.ipv4.option_number.OptionNumber* attribute), 348
- FLAG (*pcapkit.vendor.ipv4.protection_authority.ProtectionAuthority* attribute), 348
- FLAG (*pcapkit.vendor.ipv4.qs_function.QSFunction* attribute), 349
- FLAG (*pcapkit.vendor.ipv4.router_alert.RouterAlert* attribute), 349
- FLAG (*pcapkit.vendor.ipv4.tos_del.ToSDelay* attribute), 350
- FLAG (*pcapkit.vendor.ipv4.tos_ecn.ToSECN* attribute), 351
- FLAG (*pcapkit.vendor.ipv4.tos_pre.ToSPrecedence* attribute), 351
- FLAG (*pcapkit.vendor.ipv4.tos_rel.ToSReliability* attribute), 352
- FLAG (*pcapkit.vendor.ipv4.tos_thr.ToSThroughput* attribute), 353
- FLAG (*pcapkit.vendor.ipv6.option.Option* attribute), 354
- FLAG (*pcapkit.vendor.ipv6.qs_function.QSFunction* attribute), 355
- FLAG (*pcapkit.vendor.ipv6.router_alert.RouterAlert* attribute), 355
- FLAG (*pcapkit.vendor.ipv6.routing.Routing* attribute), 355
- FLAG (*pcapkit.vendor.ipv6.seed_id.SeedID* attribute), 356
- FLAG (*pcapkit.vendor.ipv6.tagger_id.TaggerID* attribute), 356
- FLAG (*pcapkit.vendor.ipx.packet.Packet* attribute), 357
- FLAG (*pcapkit.vendor.ipx.socket.Socket* attribute), 358
- FLAG (*pcapkit.vendor.mh.packet.Packet* attribute), 358
- FLAG (*pcapkit.vendor.ospf.authentication.Authentication* attribute), 358
- FLAG (*pcapkit.vendor.ospf.packet.Packet* attribute), 359
- FLAG (*pcapkit.vendor.reg.ethertype.EtherType* attribute), 360
- FLAG (*pcapkit.vendor.reg.linktype.LinkType* attribute), 359
- FLAG (*pcapkit.vendor.reg.transtype.TransType* attribute), 361
- FLAG (*pcapkit.vendor.tcp.checksum.Checksum* attribute), 361
- FLAG (*pcapkit.vendor.tcp.option.Option* attribute), 362
- FLAG (*pcapkit.vendor.vlan.priority_level.PriorityLevel* attribute), 363
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_CONTENT_LENGTH* attribute), 222
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_DATA* attribute), 216
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_GOAWAY* attribute), 221
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEADER* attribute), 217
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_PING* attribute), 220
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_PRIORITY* attribute), 218
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_PUSH_PROMISE* attribute), 219
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_RST_STREAM* attribute), 218
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_SETTING_COOKIE* attribute), 219
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_Unassigned* attribute), 216
- flags (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_WINDOW_UPDATE* attribute), 221
- flags (*pcapkit.protocols.internet.hip.DataType_Param_Route_Dst* attribute), 97
- flags (*pcapkit.protocols.internet.hip.DataType_Param_Route_Via* attribute), 102
- flags (*pcapkit.protocols.internet.hopopt.DataType_Opt_IP_DFF* attribute), 123
- flags (*pcapkit.protocols.internet.hopopt.DataType_Opt_MPL* attribute), 121
- flags (*pcapkit.protocols.internet.hopopt.DataType_Opt_RPL* attribute), 120
- flags (*pcapkit.protocols.internet.ipv4.DataType_IPv4* attribute), 131
- flags (*pcapkit.protocols.internet.ipv4.DataType_Opt_Security_Info* attribute), 137
- flags (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_IP_DFF* attribute), 160
- flags (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_MPL* attribute), 157
- flags (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_RPL* attribute), 156
- flags (*pcapkit.protocols.link.l2tp.DataType_L2TP* attribute), 38
- flags (*pcapkit.protocols.transport.tcp.DataType_TCP* attribute), 189
- flags (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Data* attribute), 199
- flags (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABLE* attribute), 195
- Flash (*pcapkit.const.ipv4.tos_pre.ToSPrecedence* attribute), 298
- Flash_Override (*pcapkit.const.ipv4.tos_pre.ToSPrecedence* attribute), 298
- Flow_Binding_Message (*pcapkit.const.ipv4.tos_pre.ToSPrecedence* attribute), 298

`kit.const.mh.packet.Packet` attribute), 310
`FLOW_CONTROL_ERROR` (`pcap-kit.const.http.error_code.ErrorCode` attribute), 288
`format()` (`pcapkit.foundation.extraction.Extractor` property), 16
`FormatError`, 259
`FormatWarning`, 265
`FQDN` (`pcapkit.const.hip.di.DITypes` attribute), 274
`frag` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2_CONTINUATION` attribute), 222
`frag` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEADERS` attribute), 217
`frag` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2_PUSH_PROMISE` attribute), 220
`frag_check()` (in module `pcap-kit.utilities.validations`), 263
`frag_offset` (`pcap-kit.protocols.internet.ipv4.DataType_IPv4` attribute), 131
`FragmentError`, 259
`Frame` (class in `pcapkit.const.http.frame`), 289
`Frame` (class in `pcapkit.protocols.pcap.frame`), 27
`Frame` (class in `pcapkit.vendor.http.frame`), 345
`frame()` (`pcapkit.foundation.extraction.Extractor` property), 16
`frame_info` (`pcapkit.protocols.pcap.frame.DataType_Frame` attribute), 31
`Frame_Relay` (`pcapkit.const.arp.hardware.Hardware` attribute), 267
`Frame_Relay_ARP` (`pcap-kit.const.reg.ethertype.EtherType` attribute), 321
`FRAME_SIZE_ERROR` (`pcap-kit.const.http.error_code.ErrorCode` attribute), 288
`frames` (`pcapkit.foundation.extraction.Extractor._mpkit` attribute), 7
`FRELAY` (`pcapkit.const.reg.linktype.LinkType` attribute), 313
`FRELAY_WITH_DIR` (`pcap-kit.const.reg.linktype.LinkType` attribute), 313
`FROM` (`pcapkit.const.hip.parameter.Parameter` attribute), 283
`FTP` (class in `pcapkit.protocols.application.ftp`), 203
`func` (`pcapkit.protocols.internet.hopopt.DataType_Opt_QS` attribute), 119
`func` (`pcapkit.protocols.internet.ipv4.DataType_Opt_QuickStart` attribute), 135
`func` (`pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_QS` attribute), 156
`func` (`pcapkit.protocols.transport.tcp.DataType_TCP_OPT` attribute), 190
`fwd_error` (`pcapkit.protocols.internet.hopopt.DataType_RPL_Flags` attribute), 120
`fwd_error` (`pcapkit.protocols.internet.ipv6_opts.DataType_RPL_Flags` attribute), 157

G

`General_Dynamics` (`pcap-kit.const.reg.ethertype.EtherType` attribute), 321
`General_Switched_Management_Protocol` (`pcapkit.const.reg.ethertype.EtherType` attribute), 321
`GENSER` (`pcapkit.const.ipv4.protection_authority.ProtectionAuthority` attribute), 293
`GeoNetworking_as_defined_in_ETSI_EN_302_636_4_1` (`pcapkit.const.reg.ethertype.EtherType` attribute), 321
`get()` (`pcapkit.const.arp.hardware.Hardware` static method), 266
`get()` (`pcapkit.const.arp.operation.Operation` static method), 268
`get()` (`pcapkit.const.ftp.return_code.ReturnCode` static method), 270
`get()` (`pcapkit.const.hip.certificate.Certificate` static method), 273
`get()` (`pcapkit.const.hip.cipher.Cipher` static method), 274
`get()` (`pcapkit.const.hip.di.DITypes` static method), 274
`get()` (`pcapkit.const.hip.ecdsa_curve.ECDSACurve` static method), 275
`get()` (`pcapkit.const.hip.ecdsa_low_curve.ECDSALowCurve` static method), 275
`get()` (`pcapkit.const.hip.esp_transform_suite.ESPTransformSuite` static method), 276
`get()` (`pcapkit.const.hip.group.Group` static method), 277
`get()` (`pcapkit.const.hip.hi_algorithm.HIAAlgorithm` static method), 278
`get()` (`pcapkit.const.hip.hit_suite.HITSuite` static method), 278
`get()` (`pcapkit.const.hip.nat_traversal.NATTraversal` static method), 279
`get()` (`pcapkit.const.hip.notify_message.NotifyMessage` static method), 279
`get()` (`pcapkit.const.hip.packet.Packet` static method), 281
`get()` (`pcapkit.const.hip.parameter.Parameter` static method), 282
`get()` (`pcapkit.const.hip.registration.Registration` static method), 285
`get()` (`pcapkit.const.hip.registration_failure.RegistrationFailure` static method), 286
`get()` (`pcapkit.const.hip.suite.Suite` static method), 286

<code>get () (pcapkit.const.hip.transport.Transport static method), 287</code>	<code>get () (pcapkit.const.reg.ethertype.EtherType static method), 318</code>
<code>get () (pcapkit.const.http.error_code.ErrorCode static method), 288</code>	<code>get () (pcapkit.const.reg.linktype.LinkType static method), 312</code>
<code>get () (pcapkit.const.http.frame.Frame static method), 289</code>	<code>get () (pcapkit.const.reg.transtype.TransType static method), 326</code>
<code>get () (pcapkit.const.http.setting.Setting static method), 290</code>	<code>get () (pcapkit.const.tcp.checksum.Checksum static method), 334</code>
<code>get () (pcapkit.const.ipv4.classification_level.ClassificationLevel static method), 291</code>	<code>get () (pcapkit.const.tcp.option.Option static method), 334</code>
<code>get () (pcapkit.const.ipv4.option_class.OptionClass static method), 291</code>	<code>get () (pcapkit.const.vlan.priority_level.PriorityLevel static method), 336</code>
<code>get () (pcapkit.const.ipv4.option_number.OptionNumber static method), 291</code>	<code>get_parser () (in module pcapkit.vendor.__main__), 365</code>
<code>get () (pcapkit.const.ipv4.protection_authority.ProtectionAuthority static method), 293</code>	<code>get_proxies () (in module pcapkit.vendor.default), 365</code>
<code>get () (pcapkit.const.ipv4.qs_function.QSFunction static method), 294</code>	<code>GGP (pcapkit.const.reg.transtype.TransType attribute), 328</code>
<code>get () (pcapkit.const.ipv4.router_alert.RouterAlert static method), 294</code>	<code>GMTP (pcapkit.const.reg.transtype.TransType attribute), 328</code>
<code>get () (pcapkit.const.ipv4.tos_del.ToSDelay static method), 297</code>	<code>GOAWAY (pcapkit.const.http.frame.Frame attribute), 289</code>
<code>get () (pcapkit.const.ipv4.tos_ecn.ToSECN static method), 298</code>	<code>GPF_F (pcapkit.const.reg.linktype.LinkType attribute), 314</code>
<code>get () (pcapkit.const.ipv4.tos_pre.ToSPrecedence static method), 298</code>	<code>GPF_T (pcapkit.const.reg.linktype.LinkType attribute), 314</code>
<code>get () (pcapkit.const.ipv4.tos_rel.ToSReliability static method), 299</code>	<code>GPRS_LLC (pcapkit.const.reg.linktype.LinkType attribute), 314</code>
<code>get () (pcapkit.const.ipv4.tos_thr.ToSThroughput static method), 299</code>	<code>granularity (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_UTOPT attribute), 193</code>
<code>get () (pcapkit.const.ipv6.extension_header.ExtensionHeader static method), 299</code>	<code>GRE (pcapkit.const.reg.transtype.TransType attribute), 328</code>
<code>get () (pcapkit.const.ipv6.option.Option static method), 300</code>	<code>Group (class in pcapkit.const.hip.group), 277</code>
<code>get () (pcapkit.const.ipv6.qs_function.QSFunction static method), 302</code>	<code>Group (class in pcapkit.vendor.hip.group), 341</code>
<code>get () (pcapkit.const.ipv6.router_alert.RouterAlert static method), 302</code>	<code>group (pcapkit.protocols.internet.hip.DataType_Param_Cert attribute), 89</code>
<code>get () (pcapkit.const.ipv6.routing.Routing static method), 306</code>	<code>Group_1536_bit_MODP_group (pcapkit.const.hip.group.Group attribute), 277</code>
<code>get () (pcapkit.const.ipv6.seed_id.SeedID static method), 306</code>	<code>Group_2048_bit_MODP_group (pcapkit.const.hip.group.Group attribute), 277</code>
<code>get () (pcapkit.const.ipv6.tagger_id.TaggerID static method), 307</code>	<code>Group_3072_bit_MODP_group (pcapkit.const.hip.group.Group attribute), 277</code>
<code>get () (pcapkit.const.ipx.packet.Packet static method), 307</code>	<code>Group_384_bit_group (pcapkit.const.hip.group.Group attribute), 277</code>
<code>get () (pcapkit.const.ipx.socket.Socket static method), 308</code>	<code>Group_6144_bit_MODP_group (pcapkit.const.hip.group.Group attribute), 277</code>
<code>get () (pcapkit.const.mh.packet.Packet static method), 309</code>	<code>Group_8192_bit_MODP_group (pcapkit.const.hip.group.Group attribute), 277</code>
<code>get () (pcapkit.const.ospf.authentication.Authentication static method), 310</code>	H
<code>get () (pcapkit.const.ospf.packet.Packet static method), 311</code>	<code>Handover_Acknowledge_Message (pcapkit.const.mh.packet.Packet attribute), 310</code>
	<code>Handover_Initiate_Message (pcapkit.const.mh.packet.Packet attribute), 310</code>

Hardware (class in *pcapkit.const.arp.hardware*), 266
 Hardware (class in *pcapkit.vendor.arp.hardware*), 337
 Hash_and_URL_of_X_509_v3 (*pcapkit.const.hip.certificate.Certificate* attribute), 273
 hav (*pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_H_PDP* attribute), 118
 hav (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_SMF_H_PDP* attribute), 154
 Hayes_Microcomputers (*pcapkit.const.reg.ethertype.EtherType* attribute), 321
 HDLC (*pcapkit.const.arp.hardware.Hardware* attribute), 267
 hdr_len (*pcapkit.protocols.internet.ipv4.DataType_IPv4* attribute), 131
 hdr_len (*pcapkit.protocols.transport.tcp.DataType_TCP* attribute), 189
 HDRR (*pcapkit.const.hip.packet.Packet* attribute), 281
 Header (class in *pcapkit.protocols.pcap.header*), 24
 header (*pcapkit.protocols.application.httpv1.DataType_HTTP* attribute), 207
 header (*pcapkit.protocols.application.httpv1.DataType_HTTP_Raw* attribute), 207
 header () (*pcapkit.foundation.extraction.Extractor* property), 17
 HEADER_TABLE_SIZE (*pcapkit.const.http.setting.Setting* attribute), 290
 HEADERS (*pcapkit.const.http.frame.Frame* attribute), 289
 Heartbeat_Message (*pcapkit.const.mh.packet.Packet* attribute), 310
 Hello (*pcapkit.const.ospf.packet.Packet* attribute), 311
 hexlify () (in module *pcapkit.vendor.http.error_code*), 345
 hexlify () (in module *pcapkit.vendor.http.frame*), 345
 hexlify () (in module *pcapkit.vendor.http.setting*), 346
 HFI (*pcapkit.const.arp.hardware.Hardware* attribute), 267
 HIAAlgorithm (class in *pcapkit.const.hip.hi_algorithm*), 278
 HIAAlgorithm (class in *pcapkit.vendor.hip.hi_algorithm*), 342
 HIGH (*pcapkit.const.ipv4.tos_rel.ToSReliability* attribute), 299
 HIGH (*pcapkit.const.ipv4.tos_thr.ToSThroughput* attribute), 299
 HIP (class in *pcapkit.protocols.internet.hip*), 48
 HIP (*pcapkit.const.ipv6.extension_header.ExtensionHeader* attribute), 299
 HIP (*pcapkit.const.reg.transtype.TransType* attribute), 328
 HIP_CIPHER (*pcapkit.const.hip.parameter.Parameter* attribute), 283
 HIP_DATA (*pcapkit.const.hip.packet.Packet* attribute), 281
 HIP_MAC (*pcapkit.const.hip.parameter.Parameter* attribute), 283
 HIP_MAC_2 (*pcapkit.const.hip.parameter.Parameter* attribute), 283
 HIP_MAC_FAILED (*pcapkit.const.hip.notify_message.NotifyMessage* attribute), 280
 HIP_SIGNATURE (*pcapkit.const.hip.parameter.Parameter* attribute), 283
 HIP_SIGNATURE_2 (*pcapkit.const.hip.parameter.Parameter* attribute), 283
 HIP_TRANSFORM (*pcapkit.const.hip.parameter.Parameter* attribute), 283
 HIP_TRANSPORT_MODE (*pcapkit.const.hip.parameter.Parameter* attribute), 283
 HIPARP (*pcapkit.const.arp.hardware.Hardware* attribute), 267
 HIPPI_FP_encapsulation (*pcapkit.const.reg.ethertype.EtherType* attribute), 321
 HIT_SUITE_LIST (*pcapkit.const.hip.parameter.Parameter* attribute), 283
 HITSuite (class in *pcapkit.const.hip.hit_suite*), 278
 HITSuite (class in *pcapkit.vendor.hip.hit_suite*), 342
 hlen (*pcapkit.protocols.link.arp.DataType_ARP* attribute), 34
 hmac (*pcapkit.protocols.internet.hip.DataType_Param_HMAC* attribute), 98
 hmac (*pcapkit.protocols.internet.hip.DataType_Param_HMAC_2* attribute), 98
 hmac (*pcapkit.protocols.internet.hip.DataType_Param_Relay_HMAC* attribute), 104
 hmac (*pcapkit.protocols.internet.hip.DataType_Param_RVS_HMAC* attribute), 103
 hmac (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_AC* attribute), 198
 hmac (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SY* attribute), 197
 HMP (*pcapkit.const.reg.transtype.TransType* attribute), 328
 HOME (*pcapkit.const.ipv6.option.Option* attribute), 300
 Home_Agent_Switch_Message (*pcapkit.const.mh.packet.Packet* attribute), 310
 Home_Test (*pcapkit.const.mh.packet.Packet* attribute), 310
 Home_Test_Init (*pcapkit.const.mh.packet.Packet* attribute), 310

HOPOPT (class in pcapkit.protocols.internet.hopopt), 104
 HOPOPT (pcapkit.const.ipv6.extension_header.ExtensionHeader attribute), 300
 HOPOPT (pcapkit.const.reg.transtype.TransType attribute), 328
 HOST_ID (pcapkit.const.hip.parameter.Parameter attribute), 283
 host_id (pcapkit.protocols.internet.hip.DataType_Param_Host_ID attribute), 88
 HP_Probe (pcapkit.const.reg.ethertype.EtherType attribute), 321
 hsa (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABILITY attribute), 195
 HTTP (class in pcapkit.protocols.application.http), 204
 HTTP_1_1_REQUIRED (pcapkit.const.http.error_code.ErrorCode attribute), 288
 HTTP_METHODS (in module pcapkit.protocols.application.httpv1), 206
 HTTPv1 (class in pcapkit.protocols.application.httpv1), 205
 HTTPv2 (class in pcapkit.protocols.application.httpv2), 208
 htype (pcapkit.protocols.link.arp.DataType_ARP attribute), 34
 HW_EXP1 (pcapkit.const.arp.hardware.Hardware attribute), 267
 HW_EXP2 (pcapkit.const.arp.hardware.Hardware attribute), 267
 Hyperchannel (pcapkit.const.arp.hardware.Hardware attribute), 267
 I
 I1 (pcapkit.const.hip.packet.Packet attribute), 282
 I2 (pcapkit.const.hip.packet.Packet attribute), 282
 I2_ACKNOWLEDGEMENT (pcapkit.const.hip.notify_message.NotifyMessage attribute), 280
 I_NLSP (pcapkit.const.reg.transtype.TransType attribute), 329
 IATP (pcapkit.const.reg.transtype.TransType attribute), 328
 IBM_SNA_Service_on_Ether (pcapkit.const.reg.ethertype.EtherType attribute), 321
 IC (pcapkit.const.vlan.priority_level.PriorityLevel attribute), 337
 ICE_STUN_UDP (pcapkit.const.hip.nat_traversal.NATTraversal attribute), 279
 ICMP (pcapkit.const.reg.transtype.TransType attribute), 328
 icv (pcapkit.protocols.internet.ah.DataType_AH attribute), 48
 id (pcapkit.protocols.internet.hip.DataType_Param_ACK attribute), 85
 id (pcapkit.protocols.internet.hip.DataType_Param_Cert attribute), 90
 id (pcapkit.protocols.internet.hip.DataType_Param_Cipher attribute), 86
 id (pcapkit.protocols.internet.hip.DataType_Param_Deffie_Hellman attribute), 86
 id (pcapkit.protocols.internet.hip.DataType_Param_DH_Group_List attribute), 85
 id (pcapkit.protocols.internet.hip.DataType_Param_ESP_Transform attribute), 94
 id (pcapkit.protocols.internet.hip.DataType_Param_HIT_Suite_List attribute), 89
 id (pcapkit.protocols.internet.hip.DataType_Param_NET_Traversal_Mode attribute), 87
 id (pcapkit.protocols.internet.hip.DataType_Param_Overlay_ID attribute), 96
 id (pcapkit.protocols.internet.hip.DataType_Param_SEQ attribute), 84
 id (pcapkit.protocols.internet.hip.DataType_Param_Transaction_ID attribute), 96
 id (pcapkit.protocols.internet.hip.DataType_Param_Transform attribute), 86
 id (pcapkit.protocols.internet.hip.DataType_Param_Transport_Mode attribute), 97
 id (pcapkit.protocols.internet.hopopt.DataType_Opt_RPL attribute), 120
 id (pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_I_PDP attribute), 117
 id (pcapkit.protocols.internet.ipv4.DataType_IPv4 attribute), 131
 id (pcapkit.protocols.internet.ipv4.DataType_Opt_Traceroute attribute), 137
 id (pcapkit.protocols.internet.ipv6_frag.DataType_IPv6_Frag attribute), 140
 id (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_RPL attribute), 156
 id (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_SMF_I_PDP attribute), 154
 id() (pcapkit.protocols.application.http.HTTP class method), 204
 id() (pcapkit.protocols.application.httpv1.HTTPv1 class method), 206
 id() (pcapkit.protocols.application.httpv2.HTTPv2 class method), 214
 id() (pcapkit.protocols.internet.ah.AH class method), 46
 id() (pcapkit.protocols.internet.ip.IP class method), 124
 id() (pcapkit.protocols.internet.ipsec.IPsec class method), 124

<code>id()</code> (<code>pcapkit.protocols.internet.ipv4.IPv4</code> class method), 129	<code>IEEE_Std_802_1AB_Link_Layer_Discovery_Protocol</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321
<code>id()</code> (<code>pcapkit.protocols.internet.ipv6.Ipv6</code> class method), 167	<code>IEEE_Std_802_1AE_Media_Access_Control_Security</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321
<code>id()</code> (<code>pcapkit.protocols.link.arp.ARP</code> class method), 33	<code>IEEE_Std_802_1Q_Multiple_Multicast_Registration_Protocol</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321
<code>id()</code> (<code>pcapkit.protocols.link.rarp.RARP</code> class method), 42	<code>IEEE_Std_802_1Q_Multiple_VLAN_Registration_Protocol</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321
<code>id()</code> (<code>pcapkit.protocols.protocol.Protocol</code> class method), 230	<code>IEEE_Std_802_1Q_Service_VLAN_tag_identifier</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321
<code>id_len</code> (<code>pcapkit.protocols.internet.hip.DataType_Param_HostID</code> attribute), 88	<code>IEEE_Std_802_1Qbe_Multiple_I_SID_Registration_Protocol</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321
<code>IDPR</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 328	<code>IEEE_Std_802_1Qbg_ECP_Protocol</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321
<code>IDPR_CMTF</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 328	<code>IEEE_Std_802_1X_Port_based_network_access_control</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 322
<code>IDRP</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 328	<code>IEEE_Std_802_21_Media_Independent_Handover_Protocol</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 322
<code>IEEE802_11</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>IEEE_Std_802_3_Ethernet_Passive_Optical_Network</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 322
<code>IEEE802_11_AVS</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>IEEE_Std_802_Local_Experimental_Ethertype_0x88B5</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 322
<code>IEEE802_11_PRISM</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>IEEE_Std_802_Local_Experimental_Ethertype_0x88B6</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 322
<code>IEEE802_11_RADIOTAP</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>IEEE_Std_802_OUI_Extended_Ethertype</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 322
<code>IEEE802_15_4_NOFCS</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>IFMP</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 328
<code>IEEE802_15_4_NONASK_PHY</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>IGMP</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 328
<code>IEEE802_15_4_TAP</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>IGP</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 328
<code>IEEE802_15_4_WITHFCS</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>IL</code> (<code>pcapkit.const.reg.transtype.TransType</code> attribute), 328
<code>IEEE802_5</code> (<code>pcapkit.const.reg.linktype.LinkType</code> attribute), 314	<code>ILNP</code> (<code>pcapkit.const.ipv6.option.Option</code> attribute), 300
<code>IEEE_1394_1995</code> (<code>pcapkit.const.arp.hardware.Hardware</code> attribute), 267	<code>IMITD</code> (<code>pcapkit.const.ipv4.option_number.OptionNumber</code> attribute), 292
<code>IEEE_802_Networks</code> (<code>pcapkit.const.arp.hardware.Hardware</code> attribute), 267	<code>Immediate</code> (<code>pcapkit.const.ipv4.tos_pre.ToSPrecedence</code> attribute), 298
<code>IEEE_Std_802_11_Fast_Roaming_Remote_Request</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321	<code>import_test()</code> (<code>pcapkit.foundation.extraction.Extractor</code> static method), 14
<code>IEEE_Std_802_11_Pre_Authentication</code> (<code>pcapkit.const.reg.ethertype.EtherType</code> attribute), 321	

- INADEQUATE_SECURITY (pcap-kit.const.http.error_code.ErrorCode attribute), 288
- InARP_Reply (pcapkit.const.arp.operation.Operation attribute), 269
- InARP_Request (pcap-kit.const.arp.operation.Operation attribute), 269
- incl_len (pcapkit.protocols.pcap.frame.DataType_Frame attribute), 31
- index (pcapkit.protocols.internet.hip.DataType_Param_ESP_Info attribute), 81
- index () (pcapkit.corekit.protochain._AliasList method), 246
- index () (pcapkit.corekit.protochain.ProtoChain method), 244
- index () (pcapkit.foundation.traceflow.TraceFlow property), 20
- index () (pcapkit.protocols.pcap.frame.Frame method), 29
- index () (pcapkit.reassembly.reassembly.Reassembly method), 233
- IndexNotFound, 259
- InfiniBand (pcapkit.const.arp.hardware.Hardware attribute), 267
- INFINIBAND (pcapkit.const.reg.linktype.LinkType attribute), 314
- Info (class in pcapkit.corekit.infoclass), 243
- INFO (in module pcapkit.const.ftp.return_code), 273
- info () (pcapkit.foundation.extraction.Extractor property), 17
- info () (pcapkit.protocols.protocol.Protocol property), 232
- info2dict () (pcapkit.corekit.infoclass.Info method), 243
- info_check () (in module pcap-kit.utilities.validations), 263
- InfoError, 259
- INITIAL_WINDOW_SIZE (pcap-kit.const.http.setting.Setting attribute), 290
- input () (pcapkit.foundation.extraction.Extractor property), 17
- Insufficient_resources (pcap-kit.const.hip.registration_failure.RegistrationFailure attribute), 286
- int_check () (in module pcapkit.utilities.validations), 263
- INTERNAL_ERROR (pcap-kit.const.http.error_code.ErrorCode attribute), 288
- Internet (class in pcapkit.protocols.internet.internet), 174
- Internet_Protocol_version_4 (pcap-kit.const.reg.ethertype.EtherType attribute), 322
- Internet_Protocol_version_6 (pcap-kit.const.reg.ethertype.EtherType attribute), 322
- Internetwork_Control (pcap-kit.const.ipv4.tos_pre.ToSPrecedence attribute), 298
- IntError, 259
- INVALID_CERTIFICATE (pcap-kit.const.hip.notify_message.NotifyMessage attribute), 280
- Invalid_certificate (pcap-kit.const.hip.registration_failure.RegistrationFailure attribute), 286
- INVALID_DH_CHOSEN (pcap-kit.const.hip.notify_message.NotifyMessage attribute), 280
- INVALID_ESP_TRANSFORM_CHOSEN (pcap-kit.const.hip.notify_message.NotifyMessage attribute), 280
- INVALID_HIP_CIPHER_CHOSEN (pcap-kit.const.hip.notify_message.NotifyMessage attribute), 280
- INVALID_HIT (pcap-kit.const.hip.notify_message.NotifyMessage attribute), 280
- INVALID_SYNTAX (pcap-kit.const.hip.notify_message.NotifyMessage attribute), 280
- InvalidVendorWarning, 265
- io_check () (in module pcapkit.utilities.validations), 263
- IOAM_TEMPORARY_registered_2020_04_16_expires_2021_04_16 (pcapkit.const.ipv6.option.Option attribute), 300
- IOAM_TEMPORARY_registered_2020_04_16_expires_2021_04_16 (pcapkit.const.ipv6.option.Option attribute), 300
- IOObjError, 259
- IP (class in pcapkit.protocols.internet.ip), 124
- ip (pcapkit.protocols.internet.hip.DataType_Locator_Dict attribute), 83
- ip (pcapkit.protocols.internet.hip.DataType_Param_From attribute), 102
- ip (pcapkit.protocols.internet.hip.DataType_Param_Reg_From attribute), 93
- ip (pcapkit.protocols.internet.hip.DataType_Param_Relay_From attribute), 100
- ip (pcapkit.protocols.internet.hip.DataType_Param_Relay_To attribute), 101
- ip (pcapkit.protocols.internet.hip.DataType_Param_Route_Dst attribute), 97
- ip (pcapkit.protocols.internet.hip.DataType_Param_Route_Via attribute), 102

ip (*pcapkit.protocols.internet.hip.DataType_Param_Via_RV* *TM* (*pcapkit.const.reg.transtype.TransType* attribute), attribute), 103 329
ip (*pcapkit.protocols.internet.hopopt.DataType_Opt_HomeIPv4* (class in *pcapkit.protocols.internet.ipv4*), 125 attribute), 123 IPv4 (*pcapkit.const.ipv6.tagger_id.TaggerID* attribute),
ip (*pcapkit.protocols.internet.ipv4.DataType_Opt_TimeStamp* 307 attribute), 136 IPv4 (*pcapkit.const.reg.linktype.LinkType* attribute), 314
ip (*pcapkit.protocols.internet.ipv4.DataType_Opt_TracerouteIPv4* (*pcapkit.const.reg.transtype.TransType* attribute), attribute), 137 329
ip (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_HomeBuffer*, 236 attribute), 159 ipv4.datagram, 236
ip (*pcapkit.protocols.internet.ipv6_route.DataType_IPv6_RouteIPv4* *Route* packet, 236 attribute), 166 IPv4_Reassembly (class in *pcapkit.reassembly.ipv4*),
ip (*pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_RPI* 236 attribute), 166 ipv4_reassembly() (in module *pcap-*
ip (*pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_SourceIPv4* *Source* *toolkit.default*), 250 attribute), 165 ipv4_reassembly() (in module *pcap-*
IP_and_ARP_over_ISO_7816_3 (*pcap-* *kit.const.arp.hardware.Hardware* attribute), *ip* (*pcapkit.const.arp.hardware.Hardware* attribute), 267 ipv4_reassembly() (in module *pcap-*
IP_Autonomous_Systems (*pcap-* *kit.const.reg.ethertype.EtherType* attribute), 322 IPv6 (class in *pcapkit.protocols.internet.ipv6*), 167
ip_check() (in module *pcapkit.utilities.validations*), 263 IPv6 (*pcapkit.const.reg.linktype.LinkType* attribute), 314
IP_DFF (*pcapkit.const.ipv6.option.Option* attribute), 301 IPv6 (*pcapkit.const.reg.transtype.TransType* attribute), 329
IP_OVER_FC (*pcapkit.const.reg.linktype.LinkType* attribute), 314 ipv6.buffer, 238
IP_Reassembly (class in *pcapkit.reassembly.ip*), 235 ipv6.datagram, 237
ip_ver (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ADD_IPv6_Frag* *IPv6_Frag* *data* *internet.ipv6_frag*), 138 attribute), 200 IPv6_Frag (*pcapkit.const.ipv6.extension_header.ExtensionHeader* attribute), 300
IPComp (*pcapkit.const.reg.transtype.TransType* attribute), 328 IPv6_Frag (*pcapkit.const.reg.transtype.TransType* attribute), 329
IPCV (*pcapkit.const.reg.transtype.TransType* attribute), 328 ipv6_hdr_len() (in module *pcapkit.toolkit.dpkt*), 251
IPError, 259
IPIP (*pcapkit.const.reg.transtype.TransType* attribute), 328 IPv6_ICMP (*pcapkit.const.reg.transtype.TransType* attribute), 329
IPLT (*pcapkit.const.reg.transtype.TransType* attribute), 328 IPv6_NoNxt (*pcapkit.const.reg.transtype.TransType* attribute), 329
IPMB_LINUX (*pcapkit.const.reg.linktype.LinkType* attribute), 314 IPv6_Opts (class in *pcapkit.protocols.internet.ipv6_opts*), 140
IPMI_HPM_2 (*pcapkit.const.reg.linktype.LinkType* attribute), 314 IPv6_Opts (*pcapkit.const.ipv6.extension_header.ExtensionHeader* attribute), 300
IPNET (*pcapkit.const.reg.linktype.LinkType* attribute), 314 IPv6_Opts (*pcapkit.const.reg.transtype.TransType* attribute), 329
IPOIB (*pcapkit.const.reg.linktype.LinkType* attribute), 314 IPv6_Reassembly (class in *pcapkit.reassembly.ipv6*), 238
IPPC (*pcapkit.const.reg.transtype.TransType* attribute), 329 ipv6_reassembly() (in module *pcap-*
IPsec (class in *pcapkit.protocols.internet.ipsec*), 124 *ip* (*pcapkit.const.arp.hardware.Hardware* attribute), 267 ipv6_reassembly() (in module *pcap-*
IPsec_tunnel (*pcap-* *kit.const.arp.hardware.Hardware* attribute), 267 ipv6_reassembly() (in module *pcap-*
ip (*pcapkit.const.arp.hardware.Hardware* attribute), 267 *kit.toolkit.scapy*), 254

IPv6_Route (class in pcap-
kit.protocols.internet.ipv6_route), 160

IPv6_Route (pcapkit.const.ipv6.extension_header.ExtensionHeader attribute), 300

IPv6_Route (pcapkit.const.reg.transtype.TransType attribute), 329

IPV6_SOURCE_ADDRESS (pcap-
kit.const.ipv6.seed_id.SeedID attribute), 306

IPX (class in pcapkit.protocols.internet.ipx), 169

IPX (pcapkit.const.ipx.socket.Socket attribute), 308

IPX_in_IP (pcapkit.const.reg.transtype.TransType attribute), 329

IPXF (pcapkit.const.ipx.socket.Socket attribute), 308

IRTP (pcapkit.const.reg.transtype.TransType attribute), 329

ISIS_over_IPv4 (pcap-
kit.const.reg.transtype.TransType attribute), 329

ISO_14443 (pcapkit.const.reg.linktype.LinkType attribute), 314

ISO_IP (pcapkit.const.reg.transtype.TransType attribute), 329

ISO_TP4 (pcapkit.const.reg.transtype.TransType attribute), 329

IterableError, 260

J

join (pcapkit.protocols.transport.tcp.DataType_TCP_Option attribute), 196

JUMBO (pcapkit.const.ipv6.option.Option attribute), 301

K

key_id (pcapkit.protocols.link.ospf.DataType_Auth attribute), 41

key_id (pcapkit.protocols.transport.tcp.DataType_TCP_Option attribute), 194

KIND (in module pcapkit.const.ftp.return_code), 273

KIND (in module pcapkit.vendor.ftp.command), 338

kind (pcapkit.protocols.internet.ipv4.DataType_Opt attribute), 132

kind (pcapkit.protocols.transport.tcp.DataType_TCP_Option attribute), 190

kind() (pcapkit.dumpkit.NotImplementedIO property), 249

kind() (pcapkit.dumpkit.PCAP property), 249

KRYPTOLAN (pcapkit.const.reg.transtype.TransType attribute), 329

L

L2_IS_IS (pcapkit.const.reg.ethertype.EtherType attribute), 322

L2TP (class in pcapkit.protocols.link.l2tp), 36

L2TP (pcapkit.const.reg.transtype.TransType attribute), 329

L2TP (pcapkit.protocols.internet.ipv6.DataType_IPv6 attribute), 169

Lanstar (pcapkit.const.arp.hardware.Hardware attribute), 267

LAPB_WITH_DIR (pcapkit.const.reg.linktype.LinkType attribute), 315

LAPD (pcapkit.const.reg.linktype.LinkType attribute), 315

LARP (pcapkit.const.reg.transtype.TransType attribute), 329

last_sid (pcapkit.protocols.application.httpv2.DataType_HTTPv2_GOA attribute), 221

layer() (pcapkit.protocols.application.application.Application property), 223

layer() (pcapkit.protocols.internet.internet.Internet property), 175

layer() (pcapkit.protocols.link.link.Link property), 45

layer() (pcapkit.protocols.transport.transport.Transport property), 202

LAYER_LIST (in module pcap-
kit.foundation.extraction), 17

LayerWarning, 265

LDAP_URL_of_X_509_v3 (pcap-
kit.const.hip.certificate.Certificate attribute), 273

LEAF_1 (pcapkit.const.reg.transtype.TransType attribute), 329

LEAF_JOIN (pcapkit.const.reg.transtype.TransType attribute), 329

len (pcapkit.protocols.internet.ipv4.DataType_IPv4 attribute), 131

len (pcapkit.protocols.internet.ipx.DataType_IPX attribute), 171

len (pcapkit.protocols.link.l2tp.DataType_Flags attribute), 38

len (pcapkit.protocols.link.ospf.DataType_Auth attribute), 41

len (pcapkit.protocols.link.ospf.DataType_OSPF attribute), 41

len (pcapkit.protocols.pcap.frame.DataType_Frame attribute), 31

len (pcapkit.protocols.transport.udp.DataType_UDP attribute), 177

length (pcapkit.protocols.application.httpv2.DataType_HTTPv2 attribute), 215

length (pcapkit.protocols.internet.ah.DataType_AH attribute), 47

length (pcapkit.protocols.internet.hip.DataType_HIP attribute), 80

length (pcapkit.protocols.internet.hip.DataType_Locator attribute), 83

length (pcapkit.protocols.internet.hip.DataType_Parameter attribute), 80

`length (pcapkit.protocols.internet.hopopt.DataType_HOPOPT attribute), 113`
`length (pcapkit.protocols.internet.hopopt.DataType_Opt_Pad attribute), 115`
`length (pcapkit.protocols.internet.hopopt.DataType_Opt_Id attribute), 113`
`length (pcapkit.protocols.internet.ipv4.DataType_Opt attribute), 132`
`length (pcapkit.protocols.internet.ipv4.DataType_Opt_1_Byte attribute), 133`
`length (pcapkit.protocols.internet.ipv4.DataType_Opt_Permission attribute), 134`
`length (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_Rad attribute), 151`
`length (pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts attribute), 149`
`length (pcapkit.protocols.internet.ipv6_opts.DataType_Option attribute), 150`
`length (pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route attribute), 164`
`length (pcapkit.protocols.internet.mh.DataType_MH attribute), 173`
`length (pcapkit.protocols.link.l2tp.DataType_L2TP attribute), 38`
`length (pcapkit.protocols.transport.tcp.DataType_TCP_Opt attribute), 190`
`length () (pcapkit.foundation.extraction.Extractor property), 17`
`length () (pcapkit.protocols.application.ftp.FTP property), 203`
`length () (pcapkit.protocols.application.http.HTTP property), 205`
`length () (pcapkit.protocols.internet.ah.AH property), 47`
`length () (pcapkit.protocols.internet.hip.HIP property), 79`
`length () (pcapkit.protocols.internet.hopopt.HOPOPT property), 111`
`length () (pcapkit.protocols.internet.ipv4.IPv4 property), 130`
`length () (pcapkit.protocols.internet.ipv6.IPv6 property), 168`
`length () (pcapkit.protocols.internet.ipv6_frag.IPv6_Frag property), 139`
`length () (pcapkit.protocols.internet.ipv6_opts.IPv6_Opts property), 148`
`length () (pcapkit.protocols.internet.ipv6_route.IPv6_Route property), 164`
`length () (pcapkit.protocols.internet.ipx.IPX property), 170`
`length () (pcapkit.protocols.internet.mh.MH property), 173`
`length () (pcapkit.protocols.link.arp.ARP property), 33`
`length () (pcapkit.protocols.link.ethernet.Ethernet property), 35`
`length () (pcapkit.protocols.link.l2tp.L2TP property), 37`
`length () (pcapkit.protocols.link.ospf.OSPF property), 40`
`length () (pcapkit.protocols.link.vlan.VLAN property), 43`
`length () (pcapkit.protocols.null.NoPayload property), 225`
`length () (pcapkit.protocols.pcap.frame.Frame property), 30`
`length () (pcapkit.protocols.pcap.header.Header property), 26`
`length () (pcapkit.protocols.protocol.Protocol property), 232`
`length () (pcapkit.protocols.raw.Raw property), 224`
`length () (pcapkit.protocols.transport.tcp.TCP property), 187`
`length () (pcapkit.protocols.transport.udp.UDP property), 177`
`level (pcapkit.protocols.internet.hopopt.DataType_Opt_CALIPSO attribute), 117`
`level (pcapkit.protocols.internet.ipv4.DataType_Opt_Security_Info attribute), 137`
`level (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_CALIPSO attribute), 153`
`lid (pcapkit.protocols.internet.hopopt.DataType_Opt_LIO attribute), 122`
`lid (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_LIO attribute), 158`
`lid_len (pcapkit.protocols.internet.hopopt.DataType_Opt_LIO attribute), 122`
`lid_len (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_LIO attribute), 158`
`lifetime (pcapkit.protocols.internet.hip.DataType_Locator attribute), 83`
`lifetime (pcapkit.protocols.internet.hip.DataType_Param_Puzzle attribute), 83`
`lifetime (pcapkit.protocols.internet.hip.DataType_Param_Reg_Failed attribute), 93`
`lifetime (pcapkit.protocols.internet.hip.DataType_Param_Reg_Info attribute), 91`
`lifetime (pcapkit.protocols.internet.hip.DataType_Param_Reg_Request attribute), 92`
`lifetime (pcapkit.protocols.internet.hip.DataType_Param_Reg_Response attribute), 92`
`lifetime (pcapkit.protocols.internet.hip.DataType_Param_Solution attribute), 84`
`limit (pcapkit.protocols.internet.hopopt.DataType_Opt_TUN attribute), 116`
`limit (pcapkit.protocols.internet.ipv6.DataType_IPv6 attribute), 169`
`limit (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_TUN attribute), 169`

- attribute), 152
- LINK () (in module *pcapkit.vendor.default*), 365
- LINK () (in module *pcapkit.vendor.ftp.command*), 338
- LINK () (in module *pcapkit.vendor.ftp.return_code*), 339
- LINK () (in module *pcapkit.vendor.ipv6.extension_header*), 353
- Link (class in *pcapkit.protocols.link.link*), 44
- LINK (*pcapkit.vendor.arp.hardware.Hardware* attribute), 337
- LINK (*pcapkit.vendor.arp.operation.Operation* attribute), 338
- LINK (*pcapkit.vendor.default.Vendor* attribute), 365
- LINK (*pcapkit.vendor.ftp.command.Command* attribute), 338
- LINK (*pcapkit.vendor.ftp.return_code.ReturnCode* attribute), 339
- LINK (*pcapkit.vendor.hip.certificate.Certificate* attribute), 339
- LINK (*pcapkit.vendor.hip.cipher.Cipher* attribute), 340
- LINK (*pcapkit.vendor.hip.di.DITypes* attribute), 340
- LINK (*pcapkit.vendor.hip.ecdsa_curve.ECDSACurve* attribute), 340
- LINK (*pcapkit.vendor.hip.ecdsa_low_curve.ECDSALowCurve* attribute), 341
- LINK (*pcapkit.vendor.hip.esp_transform_suite.ESPTransformSuite* attribute), 341
- LINK (*pcapkit.vendor.hip.group.Group* attribute), 341
- LINK (*pcapkit.vendor.hip.hi_algorithm.HIAAlgorithm* attribute), 342
- LINK (*pcapkit.vendor.hip.hit_suite.HITSuite* attribute), 342
- LINK (*pcapkit.vendor.hip.nat_traversal.NATTraversal* attribute), 342
- LINK (*pcapkit.vendor.hip.notify_message.NotifyMessage* attribute), 342
- LINK (*pcapkit.vendor.hip.packet.Packet* attribute), 343
- LINK (*pcapkit.vendor.hip.parameter.Parameter* attribute), 343
- LINK (*pcapkit.vendor.hip.registration.Registration* attribute), 343
- LINK (*pcapkit.vendor.hip.registration_failure.RegistrationFailure* attribute), 344
- LINK (*pcapkit.vendor.hip.suite.Suite* attribute), 344
- LINK (*pcapkit.vendor.hip.transport.Transport* attribute), 344
- LINK (*pcapkit.vendor.http.error_code.ErrorCode* attribute), 345
- LINK (*pcapkit.vendor.http.frame.Frame* attribute), 345
- LINK (*pcapkit.vendor.http.setting.Setting* attribute), 346
- LINK (*pcapkit.vendor.ipv4.option_number.OptionNumber* attribute), 348
- LINK (*pcapkit.vendor.ipv4.router_alert.RouterAlert* attribute), 349
- LINK (*pcapkit.vendor.ipv6.extension_header.ExtensionHeader* attribute), 353
- LINK (*pcapkit.vendor.ipv6.option.Option* attribute), 354
- LINK (*pcapkit.vendor.ipv6.router_alert.RouterAlert* attribute), 355
- LINK (*pcapkit.vendor.ipv6.routing.Routing* attribute), 355
- LINK (*pcapkit.vendor.ipv6.tagger_id.TaggerID* attribute), 356
- LINK (*pcapkit.vendor.ipx.packet.Packet* attribute), 357
- LINK (*pcapkit.vendor.ipx.socket.Socket* attribute), 358
- LINK (*pcapkit.vendor.mh.packet.Packet* attribute), 358
- LINK (*pcapkit.vendor.ospf.authentication.Authentication* attribute), 358
- LINK (*pcapkit.vendor.ospf.packet.Packet* attribute), 359
- LINK (*pcapkit.vendor.reg.ethertype.EtherType* attribute), 360
- LINK (*pcapkit.vendor.reg.linktype.LinkType* attribute), 359
- LINK (*pcapkit.vendor.reg.transtype.TransType* attribute), 361
- LINK (*pcapkit.vendor.tcp.option.Option* attribute), 362
- LINK (*pcapkit.vendor.vlan.priority_level.PriorityLevel* attribute), 363
- Link_State_Ack (*pcapkit.const.ospf.packet.Packet* attribute), 311
- Link_State_Request (*pcapkit.const.ospf.packet.Packet* attribute), 311
- Link_State_Update (*pcapkit.const.ospf.packet.Packet* attribute), 311
- LinkType (class in *pcapkit.const.reg.linktype*), 312
- LinkType (class in *pcapkit.vendor.reg.linktype*), 359
- LINUX_IRDA (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- LINUX_LAPD (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- LINUX_SLL (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- LINUX_SLL2 (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- LIO (*pcapkit.const.ipv6.option.Option* attribute), 301
- Load_check () (in module *pcapkit.utilities.validations*), 264
- ListError, 260
- Little_Machines (*pcapkit.const.reg.ethertype.EtherType* attribute), 322
- Localized_Routing_Acknowledgment (*pcapkit.const.mh.packet.Packet* attribute), 310
- Localized_Routing_Initiation (*pcapkit.const.mh.packet.Packet* attribute), 310
- LocalNet (*pcapkit.const.arp.hardware.Hardware* attribute), 267
- LocalTalk (*pcapkit.const.arp.hardware.Hardware* attribute), 267

locator (*pcapkit.protocols.internet.hip.DataType_Parameter attribute*), 82

locator_set (*pcapkit.protocols.internet.ipx.IPX method*), 170

LOCATOR_SET (*pcapkit.const.hip.parameter.Parameter attribute*), 283

LOCATOR_TYPE_UNSUPPORTED (*pcapkit.const.hip.notify_message.NotifyMessage attribute*), 280

Logiccraft (*pcapkit.const.reg.ethertype.EtherType attribute*), 322

LOOP (*pcapkit.const.reg.linktype.LinkType attribute*), 315

Loopback (*pcapkit.const.reg.ethertype.EtherType attribute*), 322

LORATAP (*pcapkit.const.reg.linktype.LinkType attribute*), 315

LOW (*pcapkit.const.ipv4.tos_del.ToSDelay attribute*), 297

LoWPAN_encapsulation (*pcapkit.const.reg.ethertype.EtherType attribute*), 322

LSR (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292

LTALK (*pcapkit.const.reg.linktype.LinkType attribute*), 315

M

mac (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_TCPO attribute*), 194

magic_number (*pcapkit.protocols.pcap.header.DataType_Header attribute*), 27

main() (*in module pcapkit.vendor.__main__*), 365

major (*pcapkit.corekit.version.VersionInfo attribute*), 247

make() (*in module pcapkit.vendor.ftp.command*), 338

make() (*pcapkit.protocols.application.ftp.FTP method*), 203

make() (*pcapkit.protocols.application.httpv1.HTTPv1 method*), 206

make() (*pcapkit.protocols.application.httpv2.HTTPv2 method*), 214

make() (*pcapkit.protocols.internet.ah.AH method*), 46

make() (*pcapkit.protocols.internet.hip.HIP method*), 78

make() (*pcapkit.protocols.internet.hopopt.HOPOPT method*), 111

make() (*pcapkit.protocols.internet.ipv4.IPv4 method*), 129

make() (*pcapkit.protocols.internet.ipv6.IPv6 method*), 168

make() (*pcapkit.protocols.internet.ipv6_frag.IPv6_Frag method*), 139

make() (*pcapkit.protocols.internet.ipv6_opts.IPv6_Opts method*), 147

make() (*pcapkit.protocols.internet.ipv6_route.IPv6_Route method*), 163

make() (*pcapkit.protocols.internet.mh.MH method*), 172

make() (*pcapkit.protocols.link.arp.ARP method*), 33

make() (*pcapkit.protocols.link.ethernet.Ethernet method*), 35

make() (*pcapkit.protocols.link.l2tp.L2TP method*), 37

make() (*pcapkit.protocols.link.ospf.OSPF method*), 40

make() (*pcapkit.protocols.link.vlan.VLAN method*), 43

make() (*pcapkit.protocols.null.NoPayload method*), 225

make() (*pcapkit.protocols.pcap.frame.Frame method*), 30

make() (*pcapkit.protocols.pcap.header.Header method*), 25

make() (*pcapkit.protocols.protocol.Protocol method*), 231

make() (*pcapkit.protocols.raw.Raw method*), 223

make() (*pcapkit.protocols.transport.tcp.TCP method*), 186

make() (*pcapkit.protocols.transport.udp.UDP method*), 176

make_fout() (*pcapkit.foundation.traceflow.TraceFlow static method*), 19

make_name() (*pcapkit.foundation.extraction.Extractor class method*), 15

manet (*pcapkit.const.reg.transtype.TransType attribute*), 333

MAPOS (*pcapkit.const.arp.hardware.Hardware attribute*), 268

MAPOS_UNARP (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_GroupList_Reply (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_GroupList_Request (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_Join (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_Leave (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_MServ (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_Multi (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_NAK (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_Redirect_Map (*pcapkit.const.arp.operation.Operation attribute*), 269

MARS_Request (*pcapkit.const.arp.operation.Operation attribute*), 269

kit.const.arp.operation.Operation attribute), 269
MARS_SJoin (*pcapkit.const.arp.operation.Operation* attribute), 269
MARS_SLeave (*pcapkit.const.arp.operation.Operation* attribute), 269
MARS_Unserv (*pcapkit.const.arp.operation.Operation* attribute), 269
Matra (*pcapkit.const.reg.ethertype.EtherType* attribute), 322
max (*pcapkit.protocols.internet.hopopt.DataType_MPL_Flags* attribute), 121
max (*pcapkit.protocols.internet.ipv6_opts.DataType_MPL_Flags* attribute), 157
MAX_CONCURRENT_STREAMS (*pcapkit.const.http.setting.Setting* attribute), 290
MAX_FRAME_SIZE (*pcapkit.const.http.setting.Setting* attribute), 290
MAX_HEADER_LIST_SIZE (*pcapkit.const.http.setting.Setting* attribute), 290
maz (*pcapkit.protocols.internet.hip.DataType_Lifetime* attribute), 91
MERIT_INP (*pcapkit.const.reg.transtype.TransType* attribute), 329
Merit_Internodal (*pcapkit.const.reg.ethertype.EtherType* attribute), 322
MESSAGE_NOT_RELAYED (*pcapkit.const.hip.notify_message.NotifyMessage* attribute), 280
method (*pcapkit.protocols.application.httpv1.DataType_HTTP_Request_Headers_Max* attribute), 207
Metricom (*pcapkit.const.arp.hardware.Hardware* attribute), 268
mf (*pcapkit.protocols.application.ftp.DataType_FTP_Response* attribute), 204
mf (*pcapkit.protocols.internet.ipv4.DataType_IPv4_Flags* attribute), 132
mf (*pcapkit.protocols.internet.ipv6_frag.DataType_IPv6_Frag* attribute), 140
MFE_NSP (*pcapkit.const.reg.transtype.TransType* attribute), 330
MFR (*pcapkit.const.reg.linktype.LinkType* attribute), 315
MH (class in *pcapkit.protocols.internet.mh*), 172
MICP (*pcapkit.const.reg.transtype.TransType* attribute), 330
MIL_STD_188_220 (*pcapkit.const.arp.hardware.Hardware* attribute), 268
min (*pcapkit.protocols.internet.hip.DataType_Lifetime* attribute), 91
min_ta (*pcapkit.protocols.internet.hip.DataType_Param_Transaction_Pacing* attribute), 87
minor (*pcapkit.corekit.version.VersionInfo* attribute), 247
MOBILE (*pcapkit.const.reg.transtype.TransType* attribute), 330
Mobility_Header (*pcapkit.const.ipv6.extension_header.ExtensionHeader* attribute), 300
Mobility_Header (*pcapkit.const.reg.transtype.TransType* attribute), 330
module
 pcapkit, 3
 pcapkit.all, 366
 pcapkit.const, 266
 pcapkit.const.arp, 266
 pcapkit.const.arp.hardware, 266
 pcapkit.const.arp.operation, 268
 pcapkit.const.ftp, 270
 pcapkit.const.ftp.command, 270
 pcapkit.const.ftp.return_code, 270
 pcapkit.const.hip, 273
 pcapkit.const.hip.certificate, 273
 pcapkit.const.hip.cipher, 274
 pcapkit.const.hip.di, 274
 pcapkit.const.hip.ecdsa_curve, 275
 pcapkit.const.hip.ecdsa_low_curve, 275
 pcapkit.const.hip.esp_transform_suite, 275
 pcapkit.const.hip.group, 277
 pcapkit.const.hip.hi_algorithm, 278
 pcapkit.const.hip.hit_suite, 278
 pcapkit.const.hip.nat_traversal, 279
 pcapkit.const.hip.notify_message, 279
 pcapkit.const.hip.packet, 281
 pcapkit.const.hip.parameter, 282
 pcapkit.const.hip.registration, 285
 pcapkit.const.hip.registration_failure, 286
 pcapkit.const.hip.suite, 286
 pcapkit.const.hip.transport, 287
 pcapkit.const.http, 288
 pcapkit.const.http.error_code, 288
 pcapkit.const.http.frame, 289
 pcapkit.const.http.setting, 290
 pcapkit.const.ipv4, 290
 pcapkit.const.ipv4.classification_level, 290
 pcapkit.const.ipv4.option_class, 291
 pcapkit.const.ipv4.option_number, 291
 pcapkit.const.ipv4.protection_authority, 293
 pcapkit.const.ipv4.qs_function, 294

pcapkit.const.ipv4.router_alert, 294
pcapkit.const.ipv4.tos_del, 297
pcapkit.const.ipv4.tos_ecn, 298
pcapkit.const.ipv4.tos_pre, 298
pcapkit.const.ipv4.tos_rel, 299
pcapkit.const.ipv4.tos_thr, 299
pcapkit.const.ipv6, 299
pcapkit.const.ipv6.extension_header, 299
pcapkit.const.ipv6.option, 300
pcapkit.const.ipv6.qs_function, 302
pcapkit.const.ipv6.router_alert, 302
pcapkit.const.ipv6.routing, 306
pcapkit.const.ipv6.seed_id, 306
pcapkit.const.ipv6.tagger_id, 307
pcapkit.const.ipx, 307
pcapkit.const.ipx.packet, 307
pcapkit.const.ipx.socket, 308
pcapkit.const.mh, 309
pcapkit.const.mh.packet, 309
pcapkit.const.ospf, 310
pcapkit.const.ospf.authentication, 310
pcapkit.const.ospf.packet, 311
pcapkit.const.reg, 312
pcapkit.const.reg.ethertype, 318
pcapkit.const.reg.linktype, 312
pcapkit.const.reg.transtype, 326
pcapkit.const.tcp, 334
pcapkit.const.tcp.checksum, 334
pcapkit.const.tcp.option, 334
pcapkit.const.vlan, 336
pcapkit.const.vlan.priority_level, 336
pcapkit.corekit, 243
pcapkit.corekit.infoclass, 243
pcapkit.corekit.protochain, 243
pcapkit.corekit.version, 247
pcapkit.dumpkit, 248
pcapkit.foundation, 3
pcapkit.foundation.analysis, 3
pcapkit.foundation.extraction, 4
pcapkit.foundation.traceflow, 19
pcapkit.interface, 21
pcapkit.protocols, 23
pcapkit.protocols.application, 203
pcapkit.protocols.application.application, 222
pcapkit.protocols.application.ftp, 203
pcapkit.protocols.application.http, 204
pcapkit.protocols.application.httpv1, 205
pcapkit.protocols.application.httpv2, 208
pcapkit.protocols.internet, 45
pcapkit.protocols.internet.ah, 45
pcapkit.protocols.internet.hip, 48
pcapkit.protocols.internet.hopopt, 104
pcapkit.protocols.internet.internet, 174
pcapkit.protocols.internet.ip, 124
pcapkit.protocols.internet.ipsec, 124
pcapkit.protocols.internet.ipv4, 125
pcapkit.protocols.internet.ipv6, 167
pcapkit.protocols.internet.ipv6_frag, 138
pcapkit.protocols.internet.ipv6_opts, 140
pcapkit.protocols.internet.ipv6_route, 160
pcapkit.protocols.internet.ipx, 169
pcapkit.protocols.internet.mh, 172
pcapkit.protocols.link, 32
pcapkit.protocols.link.arp, 32
pcapkit.protocols.link.ethernet, 34
pcapkit.protocols.link.l2tp, 36
pcapkit.protocols.link.link, 44
pcapkit.protocols.link.ospf, 39
pcapkit.protocols.link.rarp, 42
pcapkit.protocols.link.vlan, 43
pcapkit.protocols.null, 225
pcapkit.protocols.pcap, 23
pcapkit.protocols.pcap.frame, 27
pcapkit.protocols.pcap.header, 24
pcapkit.protocols.raw, 223
pcapkit.protocols.transport, 176
pcapkit.protocols.transport.tcp, 178
pcapkit.protocols.transport.transport, 202
pcapkit.protocols.transport.udp, 176
pcapkit.reassembly, 232
pcapkit.reassembly.ip, 235
pcapkit.reassembly.ipv4, 236
pcapkit.reassembly.ipv6, 238
pcapkit.reassembly.reassembly, 233
pcapkit.reassembly.tcp, 242
pcapkit.toolkit, 250
pcapkit.toolkit.default, 250
pcapkit.toolkit.dpkt, 251
pcapkit.toolkit.pyshark, 253
pcapkit.toolkit.scapy, 254
pcapkit.utilities, 256
pcapkit.utilities.exceptions, 258
pcapkit.utilities.validations, 261

pcapkit.utilities.warnings, 265
 pcapkit.vendor, 337
 pcapkit.vendor.__main__, 365
 pcapkit.vendor.arp, 337
 pcapkit.vendor.arp.hardware, 337
 pcapkit.vendor.arp.operation, 338
 pcapkit.vendor.default, 363
 pcapkit.vendor.ftp, 338
 pcapkit.vendor.ftp.command, 338
 pcapkit.vendor.ftp.return_code, 339
 pcapkit.vendor.hip, 339
 pcapkit.vendor.hip.certificate, 339
 pcapkit.vendor.hip.cipher, 340
 pcapkit.vendor.hip.di, 340
 pcapkit.vendor.hip.ecdsa_curve, 340
 pcapkit.vendor.hip.ecdsa_low_curve, 341
 pcapkit.vendor.hip.esp_transform_suite, 341
 pcapkit.vendor.hip.group, 341
 pcapkit.vendor.hip.hi_algorithm, 342
 pcapkit.vendor.hip.hit_suite, 342
 pcapkit.vendor.hip.nat_traversal, 342
 pcapkit.vendor.hip.notify_message, 342
 pcapkit.vendor.hip.packet, 343
 pcapkit.vendor.hip.parameter, 343
 pcapkit.vendor.hip.registration, 343
 pcapkit.vendor.hip.registration_failure, 344
 pcapkit.vendor.hip.suite, 344
 pcapkit.vendor.hip.transport, 344
 pcapkit.vendor.http, 345
 pcapkit.vendor.http.error_code, 345
 pcapkit.vendor.http.frame, 345
 pcapkit.vendor.http.setting, 346
 pcapkit.vendor.ipv4, 346
 pcapkit.vendor.ipv4.classification_level, 346
 pcapkit.vendor.ipv4.option_class, 347
 pcapkit.vendor.ipv4.option_number, 347
 pcapkit.vendor.ipv4.protection_authority, 348
 pcapkit.vendor.ipv4.qs_function, 349
 pcapkit.vendor.ipv4.router_alert, 349
 pcapkit.vendor.ipv4.tos_del, 350
 pcapkit.vendor.ipv4.tos_ecn, 350
 pcapkit.vendor.ipv4.tos_pre, 351
 pcapkit.vendor.ipv4.tos_rel, 352
 pcapkit.vendor.ipv4.tos_thr, 352
 pcapkit.vendor.ipv6, 353
 pcapkit.vendor.ipv6.extension_header, 353
 pcapkit.vendor.ipv6.option, 354
 pcapkit.vendor.ipv6.qs_function, 354
 pcapkit.vendor.ipv6.router_alert, 355
 pcapkit.vendor.ipv6.routing, 355
 pcapkit.vendor.ipv6.seed_id, 356
 pcapkit.vendor.ipv6.tagger_id, 356
 pcapkit.vendor.ipx, 357
 pcapkit.vendor.ipx.packet, 357
 pcapkit.vendor.ipx.socket, 357
 pcapkit.vendor.mh, 358
 pcapkit.vendor.mh.packet, 358
 pcapkit.vendor.ospf, 358
 pcapkit.vendor.ospf.authentication, 358
 pcapkit.vendor.ospf.packet, 359
 pcapkit.vendor.reg, 359
 pcapkit.vendor.reg.ethertype, 360
 pcapkit.vendor.reg.linktype, 359
 pcapkit.vendor.reg.transtype, 360
 pcapkit.vendor.tcp, 361
 pcapkit.vendor.tcp.checksum, 361
 pcapkit.vendor.tcp.option, 362
 pcapkit.vendor.vlan, 362
 pcapkit.vendor.vlan.priority_level, 362
 ModuleNotFoundError, 260
 Motorola_Computer (pcapkit.const.reg.ethertype.EtherType attribute), 322
 MP (pcapkit.const.tcp.option.Option attribute), 335
 MPEG_2_TS (pcapkit.const.reg.linktype.LinkType attribute), 315
 MPL (pcapkit.const.ipv6.option.Option attribute), 301
 MPLS (pcapkit.const.reg.ethertype.EtherType attribute), 322
 MPLS_in_IP (pcapkit.const.reg.transtype.TransType attribute), 330
 MPLS_OAM (pcapkit.const.ipv6.router_alert.RouterAlert attribute), 304
 MPLS_with_upstream_assigned_label (pcapkit.const.reg.ethertype.EtherType attribute), 322
 msg_type (pcapkit.protocols.internet.hip.DataType_Param_Notification attribute), 90
 MSS (pcapkit.const.tcp.option.Option attribute), 335
 MTP (pcapkit.const.reg.transtype.TransType attribute), 330
 MTP2 (pcapkit.const.reg.linktype.LinkType attribute), 315
 MTP2_WITH_PHDR (pcapkit.const.reg.linktype.LinkType attribute),

- 315
- MTP3 (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- MTUP (*pcapkit.const.ipv4.option_number.OptionNumber* attribute), 292
- MTUR (*pcapkit.const.ipv4.option_number.OptionNumber* attribute), 292
- Multi_Topology (*pcapkit.const.reg.ethertype.EtherType* attribute), 322
- Multicast_Channel_Allocation_Protocol (*pcapkit.const.reg.ethertype.EtherType* attribute), 322
- must_follow (*pcapkit.protocols.internet.hip.DataType_Flags* attribute), 97
- MUX (*pcapkit.const.reg.transtype.TransType* attribute), 330
- MUX27010 (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- ## N
- NAI (*pcapkit.const.hip.di.DITypes* attribute), 274
- NAME (*pcapkit.vendor.default.Vendor* attribute), 365
- name () (*pcapkit.protocols.application.ftp.FTP* property), 203
- name () (*pcapkit.protocols.application.http.HTTP* property), 205
- name () (*pcapkit.protocols.internet.ah.AH* property), 47
- name () (*pcapkit.protocols.internet.hip.HIP* property), 79
- name () (*pcapkit.protocols.internet.hopopt.HOPOPT* property), 112
- name () (*pcapkit.protocols.internet.ipv4.IPv4* property), 130
- name () (*pcapkit.protocols.internet.ipv6.IPv6* property), 168
- name () (*pcapkit.protocols.internet.ipv6_frag.IPv6_Frag* property), 139
- name () (*pcapkit.protocols.internet.ipv6_opts.IPv6_Opts* property), 148
- name () (*pcapkit.protocols.internet.ipv6_route.IPv6_Route* property), 164
- name () (*pcapkit.protocols.internet.ipx.IPX* property), 170
- name () (*pcapkit.protocols.internet.mh.MH* property), 173
- name () (*pcapkit.protocols.link.arp.ARP* property), 33
- name () (*pcapkit.protocols.link.ethernet.Ethernet* property), 35
- name () (*pcapkit.protocols.link.l2tp.L2TP* property), 37
- name () (*pcapkit.protocols.link.ospf.OSPF* property), 40
- name () (*pcapkit.protocols.link.vlan.VLAN* property), 43
- name () (*pcapkit.protocols.null.NoPayload* property), 225
- name () (*pcapkit.protocols.pcap.frame.Frame* property), 30
- name () (*pcapkit.protocols.pcap.header.Header* property), 26
- name () (*pcapkit.protocols.protocol.Protocol* property), 232
- name () (*pcapkit.protocols.raw.Raw* property), 224
- name () (*pcapkit.protocols.transport.tcp.TCP* property), 187
- name () (*pcapkit.protocols.transport.udp.UDP* property), 177
- name () (*pcapkit.reassembly.ipv4.IPv4_Reassembly* property), 237
- name () (*pcapkit.reassembly.ipv6.IPv6_Reassembly* property), 238
- name () (*pcapkit.reassembly.reassembly.Reassembly* property), 234
- name () (*pcapkit.reassembly.tcp.TCP_Reassembly* property), 242
- nanosecond (*pcapkit.protocols.pcap.header.DataType_MagicNumber* attribute), 27
- nanosecond () (*pcapkit.protocols.pcap.header.Header* property), 26
- NARP (*pcapkit.const.reg.transtype.TransType* attribute), 330
- NAT_TRAVERSAL_MODE (*pcapkit.const.hip.parameter.Parameter* attribute), 283
- NATTraversal (class in *pcapkit.const.hip.nat_traversal*), 279
- NATTraversal (class in *pcapkit.vendor.hip.nat_traversal*), 342
- NBS_Internet (*pcapkit.const.reg.ethertype.EtherType* attribute), 323
- NC (*pcapkit.const.vlan.priority_level.PriorityLevel* attribute), 337
- NCP (*pcapkit.const.ipx.packet.Packet* attribute), 307
- Nestar (*pcapkit.const.reg.ethertype.EtherType* attribute), 323
- NETANALYZER (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- NETANALYZER_TRANSPARENT (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- NetBIOS (*pcapkit.const.ipx.socket.Socket* attribute), 308
- NETBLT (*pcapkit.const.reg.transtype.TransType* attribute), 330
- NETLINK (*pcapkit.const.reg.linktype.LinkType* attribute), 315
- NetWare_Core_Protocol (*pcapkit.const.ipx.socket.Socket* attribute), 308
- network (*pcapkit.protocols.internet.ipx.DataType_IPX_Address* attribute), 171

network (<i>pcapkit.protocols.pcap.header.DataType_Header</i> attribute), 27	<i>kit.const.hip.notify_message.NotifyMessage</i> attribute), 280
Network_Computing_Devices (<i>pcapkit.const.reg.ethertype.EtherType</i> attribute), 323	NO_ERROR (<i>pcapkit.const.http.error_code.ErrorCode</i> attribute), 288
Network_Control (<i>pcapkit.const.ipv4.tos_pre.ToSPrecedence</i> attribute), 298	NO_ESP_PROPOSAL_CHOSEN (<i>pcapkit.const.hip.notify_message.NotifyMessage</i> attribute), 280
new_spi (<i>pcapkit.protocols.internet.hip.DataType_Param_ESP_Info</i> attribute), 81	NO_HIP_PROPOSAL_CHOSEN (<i>pcapkit.const.hip.notify_message.NotifyMessage</i> attribute), 280
next (<i>pcapkit.protocols.internet.ah.DataType_AH</i> attribute), 47	NO_VALID_HIP_TRANSPORT_MODE (<i>pcapkit.const.hip.notify_message.NotifyMessage</i> attribute), 280
next (<i>pcapkit.protocols.internet.hip.DataType_HIP</i> attribute), 80	NO_VALID_NAT_TRAVERSAL_MODE_PARAMETER (<i>pcapkit.const.hip.notify_message.NotifyMessage</i> attribute), 280
next (<i>pcapkit.protocols.internet.hip.DataType_Param_Payload_MIC</i> attribute), 95	NO_VALID_PAYLOAD (<i>pcapkit.const.hip.notify_message.NotifyMessage</i> attribute), 280
next (<i>pcapkit.protocols.internet.hopopt.DataType_HOPOPT</i> attribute), 113	NO_VALID_PAYLOAD (<i>pcapkit.protocols.internet.ipx.DataType_IPX_Address</i> attribute), 171
next (<i>pcapkit.protocols.internet.ipv6.DataType_IPv6</i> attribute), 169	none_included (<i>pcapkit.const.hip.di.DITypes</i> attribute), 274
next (<i>pcapkit.protocols.internet.ipv6_frag.DataType_IPv6_Frag</i> attribute), 140	NO_PAYLOAD (<i>pcapkit.const.ipv4.option_number.OptionNumber</i> attribute), 292
next (<i>pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts</i> attribute), 149	NO_PAYLOAD (<i>pcapkit.const.tcp.option.Option</i> attribute), 335
next (<i>pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route</i> attribute), 164	NO_PAYLOAD (<i>pcapkit.const.tcp.option.Option</i> attribute), 225
next (<i>pcapkit.protocols.internet.mh.DataType_MH</i> attribute), 173	NO_PAYLOAD (<i>pcapkit.const.reg.linktype.LinkType</i> attribute), 316
NFC_LLCP (<i>pcapkit.const.reg.linktype.LinkType</i> attribute), 315	NORMAL (<i>pcapkit.const.ipv4.tos_del.ToSDelay</i> attribute), 297
NFLOG (<i>pcapkit.const.reg.linktype.LinkType</i> attribute), 315	NORMAL (<i>pcapkit.const.ipv4.tos_rel.ToSReliability</i> attribute), 299
NG40 (<i>pcapkit.const.reg.linktype.LinkType</i> attribute), 315	NORMAL (<i>pcapkit.const.ipv4.tos_thr.ToSThroughput</i> attribute), 299
Nimrod (<i>pcapkit.const.ipv6.routing.Routing</i> attribute), 306	Not_ECT (<i>pcapkit.const.ipv4.tos_ecn.ToSECN</i> attribute), 298
NIST_P_256 (<i>pcapkit.const.hip.ecdsa_curve.ECDSACurve</i> attribute), 275	NOTIFICATION (<i>pcapkit.const.hip.parameter.Parameter</i> attribute), 283
NIST_P_256 (<i>pcapkit.const.hip.group.Group</i> attribute), 277	NOTIFY (<i>pcapkit.const.hip.packet.Packet</i> attribute), 282
NIST_P_384 (<i>pcapkit.const.hip.ecdsa_curve.ECDSACurve</i> attribute), 275	NotifyMessage (class in <i>pcapkit.const.hip.notify_message</i>), 279
NIST_P_384 (<i>pcapkit.const.hip.group.Group</i> attribute), 277	NotifyMessage (class in <i>pcapkit.vendor.hip.notify_message</i>), 342
NIST_P_521 (<i>pcapkit.const.hip.group.Group</i> attribute), 277	NotImplementedIO (class in <i>pcapkit.dumpkit</i>), 249
Nixdorf (<i>pcapkit.const.reg.ethertype.EtherType</i> attribute), 323	nounce (<i>pcapkit.protocols.internet.hopopt.DataType_Opt_QS</i> attribute), 119
Nixdorf_Computers (<i>pcapkit.const.reg.ethertype.EtherType</i> attribute), 323	nounce (<i>pcapkit.protocols.internet.ipv4.DataType_Opt_QuickStart</i> attribute), 135
No_Authentication (<i>pcapkit.const.ospf.authentication.Authentication</i> attribute), 311	nounce (<i>pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_QS</i> attribute), 156
NO_DH_PROPOSAL_CHOSEN (<i>pcapkit.const.ospf.authentication.Authentication</i> attribute), 311	nounce (<i>pcapkit.protocols.transport.tcp.DataType_TCP_Opt_QSOPT</i> attribute), 193
	nr (<i>pcapkit.protocols.link.l2tp.DataType_L2TP</i> attribute), 38
	ns (<i>pcapkit.protocols.link.l2tp.DataType_L2TP</i> attribute), 38

- tribute), 38
- ns (*pcapkit.protocols.transport.tcp.DataType_TCP_Flags attribute*), 189
- NSA (*pcapkit.const.ipv4.protection_authority.ProtectionAuthority attribute*), 293
- NSFNET_IGP (*pcapkit.const.reg.transtype.TransType attribute*), 330
- NSH (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
- NSIS_NATFW_NSLP (*pcapkit.const.ipv4.router_alert.RouterAlert attribute*), 296
- NSIS_NATFW_NSLP (*pcapkit.const.ipv6.router_alert.RouterAlert attribute*), 304
- NULL (*pcapkit.const.ipv6.tagger_id.TaggerID attribute*), 307
- NULL (*pcapkit.const.reg.linktype.LinkType attribute*), 316
- NULL_ENCRYPT (*pcapkit.const.hip.cipher.Cipher attribute*), 274
- NULL_ENCRYPT (*pcapkit.const.hip.hi_algorithm.HIAAlgorithm attribute*), 278
- NULL_ENCRYPT_with_HMAC_MD5 (*pcapkit.const.hip.suite.Suite attribute*), 287
- NULL_ENCRYPT_with_HMAC_SHA1 (*pcapkit.const.hip.suite.Suite attribute*), 287
- NULL_with_HMAC_SHA_256 (*pcapkit.const.hip.esp_transform_suite.ESPTransformSuite attribute*), 276
- number (*pcapkit.protocols.internet.hip.DataType_Param_Puzzle attribute*), 83
- number (*pcapkit.protocols.internet.hip.DataType_Param_Solution attribute*), 84
- number (*pcapkit.protocols.internet.ipv4.DataType_IPv4_Option_Type attribute*), 133
- number (*pcapkit.protocols.pcap.frame.DataType_Frame attribute*), 31
- number_check () (in module *pcapkit.utilities.validations*), 264
- NVP_II (*pcapkit.const.reg.transtype.TransType attribute*), 330
- O**
- OAKLEY_well_known_group_1 (*pcapkit.const.hip.group.Group attribute*), 277
- object (*pcapkit.protocols.internet.hip.DataType_Locator attribute*), 83
- Obsoleted_2 (*pcapkit.const.hip.certificate.Certificate attribute*), 273
- Obsoleted_4 (*pcapkit.const.hip.certificate.Certificate attribute*), 273
- Obsoleted_6 (*pcapkit.const.hip.certificate.Certificate attribute*), 273
- Obsoleted_8 (*pcapkit.const.hip.certificate.Certificate attribute*), 273
- offset (*pcapkit.protocols.internet.ipv6_frag.DataType_IPv6_Frag attribute*), 140
- offset (*pcapkit.protocols.link.l2tp.DataType_Flags attribute*), 38
- offset (*pcapkit.protocols.link.l2tp.DataType_L2TP attribute*), 38
- ohc (*pcapkit.protocols.internet.ipv4.DataType_Opt_Traceroute attribute*), 137
- old_spi (*pcapkit.protocols.internet.hip.DataType_Param_ESP_Info attribute*), 81
- OP_EXP1 (*pcapkit.const.arp.operation.Operation attribute*), 269
- OP_EXP2 (*pcapkit.const.arp.operation.Operation attribute*), 269
- opaque (*pcapkit.protocols.internet.hip.DataType_Param_Puzzle attribute*), 83
- opaque (*pcapkit.protocols.internet.hip.DataType_Param_Solution attribute*), 84
- OPENVIZSLA (*pcapkit.const.reg.linktype.LinkType attribute*), 316
- oper (*pcapkit.protocols.link.arp.DataType_ARP attribute*), 34
- Operation (class in *pcapkit.const.arp.operation*), 268
- Operation (class in *pcapkit.vendor.arp.operation*), 338
- opt (*pcapkit.protocols.internet.ipv4.DataType_IPv4 attribute*), 132
- opt (*pcapkit.protocols.transport.tcp.DataType_TCP attribute*), 189
- Option (class in *pcapkit.const.ipv6.option*), 300
- Option (class in *pcapkit.const.tcp.option*), 334
- Option (class in *pcapkit.vendor.ipv6.option*), 354
- Option (class in *pcapkit.vendor.tcp.option*), 362
- OptionClass (class in *pcapkit.const.ipv4.option_class*), 291
- OptionClass (class in *pcapkit.vendor.ipv4.option_class*), 347
- OptionNumber (class in *pcapkit.const.ipv4.option_number*), 291
- OptionNumber (class in *pcapkit.vendor.ipv4.option_number*), 347
- options (*pcapkit.protocols.internet.hopopt.DataType_HOPOPT attribute*), 113
- options (*pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts attribute*), 150
- orig_len (*pcapkit.protocols.pcap.frame.DataType_FrameInfo attribute*), 31
- ORIGIN (*pcapkit.const.http.frame.Frame attribute*), 289
- OSPF (class in *pcapkit.protocols.link.ospf*), 39
- OSPF_IGP (*pcapkit.const.reg.transtype.TransType attribute*), 330
- output () (*pcapkit.foundation.extraction.Extractor*

property), 17

overflow (*pcapkit.protocols.internet.ipv4.DataType_Opt_TimeStamp* attribute), 166

attribute), 136

OVERLAY_ID (*pcapkit.const.hip.parameter.Parameter* attribute), 283

OVERLAY_TTL (*pcapkit.const.hip.parameter.Parameter* attribute), 283

OVERLAY_TTL_EXCEEDED (*pcapkit.const.hip.notify_message.NotifyMessage* attribute), 280

P

Pacer_Software (*pcapkit.const.reg.ethertype.EtherType* attribute), 323

Packet (class in *pcapkit.const.hip.packet*), 281

Packet (class in *pcapkit.const.ipx.packet*), 307

Packet (class in *pcapkit.const.mh.packet*), 309

Packet (class in *pcapkit.const.ospf.packet*), 311

Packet (class in *pcapkit.vendor.hip.packet*), 343

Packet (class in *pcapkit.vendor.ipx.packet*), 357

Packet (class in *pcapkit.vendor.mh.packet*), 358

Packet (class in *pcapkit.vendor.ospf.packet*), 359

packet (*pcapkit.protocols.application.httpv1.DataType_HTTP_Raw* attribute), 207

packet (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_Unassigned* attribute), 215

packet (*pcapkit.protocols.internet.hopopt.DataType_HOPOPT* attribute), 113

packet (*pcapkit.protocols.internet.ipv4.DataType_IPv4* attribute), 132

packet (*pcapkit.protocols.internet.ipv6.DataType_IPv6* attribute), 169

packet (*pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts* attribute), 150

packet (*pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_RPL* attribute), 164

packet (*pcapkit.protocols.pcap.frame.DataType_Frame* attribute), 31

packet (*pcapkit.protocols.raw.DataType_Raw* attribute), 224

packet (*pcapkit.protocols.transport.tcp.DataType_TCP* attribute), 189

packet2chain() (in module *pcapkit.toolkit.dpkt*), 252

packet2chain() (in module *pcapkit.toolkit.scapy*), 255

packet2dict() (in module *pcapkit.toolkit.dpkt*), 252

packet2dict() (in module *pcapkit.toolkit.pyshark*), 253

packet2dict() (in module *pcapkit.toolkit.scapy*), 255

PacketError, 260

PAD (*pcapkit.const.ipv6.option.Option* attribute), 301

pad (*pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route_RPL* attribute), 166

pad_len (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEAD* attribute), 217

pad_len (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_PUSH* attribute), 220

PADDED (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_DATA* attribute), 216

PADDED (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEAD* attribute), 217

PADDED (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_PUSH* attribute), 220

padding (*pcapkit.protocols.internet.hopopt.DataType_Opt_PadN* attribute), 115

padding (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PadN* attribute), 152

PADN (*pcapkit.const.ipv6.option.Option* attribute), 301

Parameter (class in *pcapkit.const.hip.parameter*), 282

Parameter (class in *pcapkit.vendor.hip.parameter*), 343

parameters (*pcapkit.protocols.internet.hip.DataType_HIP* attribute), 80

Path_MTU_Record_Option_TEMPORARY_registered_2019_01 (*pcapkit.const.ipv6.option.Option* attribute), 301

payload (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_Unassigned* attribute), 216

payload (*pcapkit.protocols.internet.ipv6.DataType_IPv6* attribute), 169

payload() (*pcapkit.protocols.internet.ah.AH* property), 47

payload() (*pcapkit.protocols.internet.hip.HIP* property), 79

payload() (*pcapkit.protocols.internet.hopopt.HOPOPT* property), 112

payload() (*pcapkit.protocols.internet.ipv6_frag.IPv6_Frag* property), 140

payload() (*pcapkit.protocols.internet.ipv6_opts.IPv6_Opts* property), 148

payload() (*pcapkit.protocols.internet.ipv6_route.IPv6_Route* property), 164

payload() (*pcapkit.protocols.internet.mh.MH* property), 173

payload() (*pcapkit.protocols.pcap.header.Header* property), 26

payload() (*pcapkit.protocols.protocol.Protocol* property), 232

payload_len (*pcapkit.protocols.internet.hopopt.DataType_Opt_Jumbo* attribute), 122

payload_len (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_Jumbo* attribute), 159

PAYLOAD_MIC (*pcapkit.const.hip.parameter.Parameter*

attribute), 283
PCAP (*class in pcapkit.dumpkit*), 248
pcapkit
 module, 3
pcapkit.all
 module, 366
pcapkit.const
 module, 266
pcapkit.const.arp
 module, 266
pcapkit.const.arp.hardware
 module, 266
pcapkit.const.arp.operation
 module, 268
pcapkit.const.ftp
 module, 270
pcapkit.const.ftp.command
 module, 270
pcapkit.const.ftp.return_code
 module, 270
pcapkit.const.hip
 module, 273
pcapkit.const.hip.certificate
 module, 273
pcapkit.const.hip.cipher
 module, 274
pcapkit.const.hip.di
 module, 274
pcapkit.const.hip.ecdsa_curve
 module, 275
pcapkit.const.hip.ecdsa_low_curve
 module, 275
pcapkit.const.hip.esp_transform_suite
 module, 275
pcapkit.const.hip.group
 module, 277
pcapkit.const.hip.hi_algorithm
 module, 278
pcapkit.const.hip.hit_suite
 module, 278
pcapkit.const.hip.nat_traversal
 module, 279
pcapkit.const.hip.notify_message
 module, 279
pcapkit.const.hip.packet
 module, 281
pcapkit.const.hip.parameter
 module, 282
pcapkit.const.hip.registration
 module, 285
pcapkit.const.hip.registration_failure
 module, 286
pcapkit.const.hip.suite
 module, 286
pcapkit.const.hip.transport
 module, 287
pcapkit.const.http
 module, 288
pcapkit.const.http.error_code
 module, 288
pcapkit.const.http.frame
 module, 289
pcapkit.const.http.setting
 module, 290
pcapkit.const.ipv4
 module, 290
pcapkit.const.ipv4.classification_level
 module, 290
pcapkit.const.ipv4.option_class
 module, 291
pcapkit.const.ipv4.option_number
 module, 291
pcapkit.const.ipv4.protection_authority
 module, 293
pcapkit.const.ipv4.qs_function
 module, 294
pcapkit.const.ipv4.router_alert
 module, 294
pcapkit.const.ipv4.tos_del
 module, 297
pcapkit.const.ipv4.tos_ecn
 module, 298
pcapkit.const.ipv4.tos_pre
 module, 298
pcapkit.const.ipv4.tos_rel
 module, 299
pcapkit.const.ipv4.tos_thr
 module, 299
pcapkit.const.ipv6
 module, 299
pcapkit.const.ipv6.extension_header
 module, 299
pcapkit.const.ipv6.option
 module, 300
pcapkit.const.ipv6.qs_function
 module, 302
pcapkit.const.ipv6.router_alert
 module, 302
pcapkit.const.ipv6.routing
 module, 306
pcapkit.const.ipv6.seed_id
 module, 306
pcapkit.const.ipv6.tagger_id
 module, 307
pcapkit.const.ipx
 module, 307
pcapkit.const.ipx.packet
 module, 307

pcapkit.const.ipx.socket
 module, 308
 pcapkit.const.mh
 module, 309
 pcapkit.const.mh.packet
 module, 309
 pcapkit.const.ospf
 module, 310
 pcapkit.const.ospf.authentication
 module, 310
 pcapkit.const.ospf.packet
 module, 311
 pcapkit.const.reg
 module, 312
 pcapkit.const.reg.ethertype
 module, 318
 pcapkit.const.reg.linktype
 module, 312
 pcapkit.const.reg.transtype
 module, 326
 pcapkit.const.tcp
 module, 334
 pcapkit.const.tcp.checksum
 module, 334
 pcapkit.const.tcp.option
 module, 334
 pcapkit.const.vlan
 module, 336
 pcapkit.const.vlan.priority_level
 module, 336
 pcapkit.corekit
 module, 243
 pcapkit.corekit.infoclass
 module, 243
 pcapkit.corekit.protochain
 module, 243
 pcapkit.corekit.version
 module, 247
 pcapkit.dumpkit
 module, 248
 pcapkit.foundation
 module, 3
 pcapkit.foundation.analysis
 module, 3
 pcapkit.foundation.extraction
 module, 4
 pcapkit.foundation.extraction.CPU_CNT
 (in module *pcapkit.foundation.extraction*), 17
 pcapkit.foundation.traceflow
 module, 19
 pcapkit.interface
 module, 21
 pcapkit.interface.APP (in module *pcap-kit.interface*), 23
 pcapkit.interface.DPKT (in module *pcap-kit.interface*), 23
 pcapkit.interface.INET (in module *pcap-kit.interface*), 23
 pcapkit.interface.JSON (in module *pcap-kit.interface*), 23
 pcapkit.interface.LINK (in module *pcap-kit.interface*), 23
 pcapkit.interface.MPPipeline (in module *pcapkit.interface*), 23
 pcapkit.interface.MPServer (in module *pcap-kit.interface*), 23
 pcapkit.interface.PCAP (in module *pcap-kit.interface*), 23
 pcapkit.interface.PCAPKit (in module *pcap-kit.interface*), 23
 pcapkit.interface.PLIST (in module *pcap-kit.interface*), 23
 pcapkit.interface.PyShark (in module *pcap-kit.interface*), 23
 pcapkit.interface.RAW (in module *pcap-kit.interface*), 23
 pcapkit.interface.Scapy (in module *pcap-kit.interface*), 23
 pcapkit.interface.TRANS (in module *pcap-kit.interface*), 23
 pcapkit.interface.TREE (in module *pcap-kit.interface*), 23
 pcapkit.protocols
 module, 23
 pcapkit.protocols.application
 module, 203
 pcapkit.protocols.application.application
 module, 222
 pcapkit.protocols.application.ftp
 module, 203
 pcapkit.protocols.application.http
 module, 204
 pcapkit.protocols.application.httpv1
 module, 205
 pcapkit.protocols.application.httpv2
 module, 208
 pcapkit.protocols.application.httpv2._HTTP_FUNC
 (in module *pcap-kit.protocols.application.httpv2*), 215
 pcapkit.protocols.internet
 module, 45
 pcapkit.protocols.internet.ah
 module, 45
 pcapkit.protocols.internet.hip
 module, 48
 pcapkit.protocols.internet.hopopt
 module, 104
 pcapkit.protocols.internet.hopopt._HOPOPT_ACT

```

        (in module pcapkit.protocols.internet.hopopt), pcapkit.protocols.link.link
112 module, 44
pcapkit.protocols.internet.hopopt._HOPOPT_NULL pcapkit.protocols.link.ospf
        (in module pcapkit.protocols.internet.hopopt), module, 39
112 pcapkit.protocols.link.rarp
pcapkit.protocols.internet.hopopt._HOPOPT_OPT module, 42
        (in module pcapkit.protocols.internet.hopopt), pcapkit.protocols.link.vlan
112 module, 43
pcapkit.protocols.internet.internet pcapkit.protocols.null
        module, 174 module, 225
pcapkit.protocols.internet.ip pcapkit.protocols.pcap
        module, 124 module, 23
pcapkit.protocols.internet.ipsec pcapkit.protocols.pcap.frame
        module, 124 module, 27
pcapkit.protocols.internet.ipv4 pcapkit.protocols.pcap.header
        module, 125 module, 24
pcapkit.protocols.internet.ipv4.IPv4_OPT pcapkit.protocols.raw
        (in module pcapkit.protocols.internet.ipv4), module, 223
130 pcapkit.protocols.transport
pcapkit.protocols.internet.ipv4.process_opt module, 176
        (in module pcapkit.protocols.internet.ipv4), pcapkit.protocols.transport.tcp
131 module, 178
pcapkit.protocols.internet.ipv6 pcapkit.protocols.transport.tcp.mptcp_opt
        module, 167 (in module pcapkit.protocols.transport.tcp),
pcapkit.protocols.internet.ipv6_frag module, 188
        module, 138 pcapkit.protocols.transport.tcp.process_opt
pcapkit.protocols.internet.ipv6_opts (in module pcapkit.protocols.transport.tcp),
        module, 140 188
pcapkit.protocols.internet.ipv6_opts._IPv6_OPTS_ACT pcapkit.protocols.transport.tcp.TCP_OPT
        (in module pcap- (in module pcapkit.protocols.transport.tcp),
        kit.protocols.internet.ipv6_opts), 148 187
pcapkit.protocols.internet.ipv6_opts._IPv6_OPTS_NULL pcapkit.protocols.transport.transport
        (in module pcap- module, 202
        kit.protocols.internet.ipv6_opts), 149 pcapkit.protocols.transport.udp
pcapkit.protocols.internet.ipv6_opts._IPv6_OPTS_IP module, 176
        (in module pcap- pcapkit.reassembly
        kit.protocols.internet.ipv6_opts), 149 module, 232
pcapkit.protocols.internet.ipv6_route pcapkit.reassembly.ip
        module, 160 module, 235
pcapkit.protocols.internet.ipv6_route._ROUTE_IP pcapkit.reassembly.ipv4
        (in module pcap- module, 236
        kit.protocols.internet.ipv6_route), 164 pcapkit.reassembly.ipv6
pcapkit.protocols.internet.ipx module, 238
        module, 169 pcapkit.reassembly.reassembly
pcapkit.protocols.internet.mh module, 233
        module, 172 pcapkit.reassembly.tcp
pcapkit.protocols.link module, 242
        module, 32 pcapkit.toolkit
pcapkit.protocols.link.arp module, 250
        module, 32 pcapkit.toolkit.default
pcapkit.protocols.link.ethernet module, 250
        module, 34 pcapkit.toolkit.dpkt
pcapkit.protocols.link.l2tp module, 251
        module, 36 pcapkit.toolkit.pyshark

```

- module, [253](#)
- pcapkit.toolkit.scapy
 - module, [254](#)
- pcapkit.utilities
 - module, [256](#)
- pcapkit.utilities.exceptions
 - module, [258](#)
- pcapkit.utilities.validations
 - module, [261](#)
- pcapkit.utilities.warnings
 - module, [265](#)
- pcapkit.vendor
 - module, [337](#)
- pcapkit.vendor.__main__
 - module, [365](#)
- pcapkit.vendor.arp
 - module, [337](#)
- pcapkit.vendor.arp.hardware
 - module, [337](#)
- pcapkit.vendor.arp.operation
 - module, [338](#)
- pcapkit.vendor.default
 - module, [363](#)
- pcapkit.vendor.ftp
 - module, [338](#)
- pcapkit.vendor.ftp.command
 - module, [338](#)
- pcapkit.vendor.ftp.return_code
 - module, [339](#)
- pcapkit.vendor.hip
 - module, [339](#)
- pcapkit.vendor.hip.certificate
 - module, [339](#)
- pcapkit.vendor.hip.cipher
 - module, [340](#)
- pcapkit.vendor.hip.di
 - module, [340](#)
- pcapkit.vendor.hip.ecdsa_curve
 - module, [340](#)
- pcapkit.vendor.hip.ecdsa_low_curve
 - module, [341](#)
- pcapkit.vendor.hip.esp_transform_suite
 - module, [341](#)
- pcapkit.vendor.hip.group
 - module, [341](#)
- pcapkit.vendor.hip.hi_algorithm
 - module, [342](#)
- pcapkit.vendor.hip.hit_suite
 - module, [342](#)
- pcapkit.vendor.hip.nat_traversal
 - module, [342](#)
- pcapkit.vendor.hip.notify_message
 - module, [342](#)
- pcapkit.vendor.hip.packet
 - module, [343](#)
- pcapkit.vendor.hip.parameter
 - module, [343](#)
- pcapkit.vendor.hip.registration
 - module, [343](#)
- pcapkit.vendor.hip.registration_failure
 - module, [344](#)
- pcapkit.vendor.hip.suite
 - module, [344](#)
- pcapkit.vendor.hip.transport
 - module, [344](#)
- pcapkit.vendor.http
 - module, [345](#)
- pcapkit.vendor.http.error_code
 - module, [345](#)
- pcapkit.vendor.http.frame
 - module, [345](#)
- pcapkit.vendor.http.setting
 - module, [346](#)
- pcapkit.vendor.ipv4
 - module, [346](#)
- pcapkit.vendor.ipv4.classification_level
 - module, [346](#)
- pcapkit.vendor.ipv4.option_class
 - module, [347](#)
- pcapkit.vendor.ipv4.option_number
 - module, [347](#)
- pcapkit.vendor.ipv4.protection_authority
 - module, [348](#)
- pcapkit.vendor.ipv4.qs_function
 - module, [349](#)
- pcapkit.vendor.ipv4.router_alert
 - module, [349](#)
- pcapkit.vendor.ipv4.tos_del
 - module, [350](#)
- pcapkit.vendor.ipv4.tos_ecn
 - module, [350](#)
- pcapkit.vendor.ipv4.tos_pre
 - module, [351](#)
- pcapkit.vendor.ipv4.tos_rel
 - module, [352](#)
- pcapkit.vendor.ipv4.tos_thr
 - module, [352](#)
- pcapkit.vendor.ipv6
 - module, [353](#)
- pcapkit.vendor.ipv6.extension_header
 - module, [353](#)
- pcapkit.vendor.ipv6.option
 - module, [354](#)
- pcapkit.vendor.ipv6.qs_function
 - module, [354](#)
- pcapkit.vendor.ipv6.router_alert
 - module, [355](#)
- pcapkit.vendor.ipv6.routing

module, 355
 pcapkit.vendor.ipv6.seed_id
 module, 356
 pcapkit.vendor.ipv6.tagger_id
 module, 356
 pcapkit.vendor.ipx
 module, 357
 pcapkit.vendor.ipx.packet
 module, 357
 pcapkit.vendor.ipx.socket
 module, 357
 pcapkit.vendor.mh
 module, 358
 pcapkit.vendor.mh.packet
 module, 358
 pcapkit.vendor.ospf
 module, 358
 pcapkit.vendor.ospf.authentication
 module, 358
 pcapkit.vendor.ospf.packet
 module, 359
 pcapkit.vendor.reg
 module, 359
 pcapkit.vendor.reg.ethertype
 module, 360
 pcapkit.vendor.reg.linktype
 module, 359
 pcapkit.vendor.reg.transtype
 module, 360
 pcapkit.vendor.tcp
 module, 361
 pcapkit.vendor.tcp.checksum
 module, 361
 pcapkit.vendor.tcp.option
 module, 362
 pcapkit.vendor.vlan
 module, 362
 pcapkit.vendor.vlan.priority_level
 module, 362
 PCAPKIT_HTTP_PROXY, 365
 PCAPKIT_HTTPS_PROXY, 365
 pcp (*pcapkit.protocols.link.vlan.DataType_TCI attribute*), 44
 PCS_Basic_Block_Protocol (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
 PDM (*pcapkit.const.ipv6.option.Option attribute*), 301
 PEP (*pcapkit.const.ipx.packet.Packet attribute*), 308
 PFLOG (*pcapkit.const.reg.linktype.LinkType attribute*), 316
 PGM (*pcapkit.const.reg.transtype.TransType attribute*), 330
 phrase (*pcapkit.protocols.application.httpv1.DataType_HTTP_Response_Header_Meta attribute*), 208
 pid (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_PUSH_PRO attribute*), 220
 PIM (*pcapkit.const.reg.transtype.TransType attribute*), 330
 PING (*pcapkit.const.http.frame.Frame attribute*), 289
 PIPE (*pcapkit.const.reg.transtype.TransType attribute*), 330
 pkt_check () (*in module pcapkit.utilities.validations*), 264
 PKTAP (*pcapkit.const.reg.linktype.LinkType attribute*), 316
 Planning_Research_Corp (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
 plen (*pcapkit.protocols.link.arp.DataType_ARP attribute*), 34
 PNNI (*pcapkit.const.reg.transtype.TransType attribute*), 330
 POC (*pcapkit.const.tcp.option.Option attribute*), 335
 POCSF (*pcapkit.const.tcp.option.Option attribute*), 335
 Point_to_Point_Protocol (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
 pointer (*pcapkit.protocols.internet.ipv4.DataType_Opt_Route_Data attribute*), 135
 pointer (*pcapkit.protocols.internet.ipv4.DataType_Opt_TimeStamp attribute*), 136
 pool (*pcapkit.foundation.extraction.Extractor._mpkit attribute*), 7
 port (*pcapkit.protocols.internet.hip.DataType_Param_Reg_From attribute*), 93
 port (*pcapkit.protocols.internet.hip.DataType_Param_Relay_From attribute*), 100
 port (*pcapkit.protocols.internet.hip.DataType_Param_Relay_To attribute*), 101
 port (*pcapkit.protocols.internet.hip.DataType_Param_Transport_Mode attribute*), 97
 port (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_ADD_ADDR attribute*), 200
 PPI (*pcapkit.const.reg.linktype.LinkType attribute*), 316
 PPP (*pcapkit.const.reg.linktype.LinkType attribute*), 316
 PPP_ETHER (*pcapkit.const.reg.linktype.LinkType attribute*), 316
 PPP_HDLC (*pcapkit.const.reg.linktype.LinkType attribute*), 316
 PPP_over_Ethernet_Discovery_Stage (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
 PPP_over_Ethernet_Session_Stage (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
 PPP_PPPD (*pcapkit.const.reg.linktype.LinkType attribute*), 316
 PPP_WITH_DIR (*pcapkit.const.reg.linktype.LinkType attribute*), 316

attribute), 316
 pre (pcapkit.protocols.internet.ipv4.DataType_IPv4_DSCPp
 attribute), 132
 preferred (pcapkit.protocols.internet.hip.DataType_Location
 attribute), 83
 prio (pcapkit.protocols.link.l2tp.DataType_Flags at-
 tribute), 38
 prio (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MB_Prio
 attribute), 201
 PRIORITY (pcapkit.const.http.frame.Frame attribute),
 289
 Priority (pcapkit.const.ipv4.tos_pre.ToSPrecedence
 attribute), 298
 PRIORITY (pcapkit.protocols.application.httpv2.DataType_HTTP2_HEADERS_Flags
 attribute), 217
 PriorityLevel (class in pcap-
 kit.const.vlan.priority_level), 336
 PriorityLevel (class in pcap-
 kit.vendor.vlan.priority_level), 362
 PRM (pcapkit.const.reg.transtype.TransType attribute),
 330
 proc (pcapkit.protocols.internet.ipv4.DataType_IPv4_OPTp
 attribute), 133
 proc (pcapkit.protocols.transport.tcp.DataType_TCP_OPTp
 attribute), 190
 process () (pcapkit.vendor.default.Vendor method),
 364
 process () (pcapkit.vendor.ftp.command.Command
 method), 338
 process () (pcapkit.vendor.ftp.return_code.ReturnCode
 method), 339
 process () (pcapkit.vendor.hip.group.Group method),
 341
 process () (pcapkit.vendor.hip.packet.Packet method),
 343
 process () (pcapkit.vendor.hip.parameter.Parameter
 method), 343
 process () (pcapkit.vendor.http.error_code.ErrorCode
 method), 345
 process () (pcapkit.vendor.http.frame.Frame method),
 345
 process () (pcapkit.vendor.http.setting.Setting
 method), 346
 process () (pcapkit.vendor.ipv4.classification_level.ClassificationLevel
 method), 346
 process () (pcapkit.vendor.ipv4.option_class.OptionClass
 method), 347
 process () (pcapkit.vendor.ipv4.option_number.OptionNumber
 method), 348
 process () (pcapkit.vendor.ipv4.protection_authority.ProtectionAuthority
 method), 348
 process () (pcapkit.vendor.ipv4.qs_function.QSFunction
 method), 349
 process () (pcapkit.vendor.ipv4.router_alert.RouterAlert
 method), 349
 process () (pcapkit.vendor.ipv4.tos_del.ToSDelay
 method), 350
 process () (pcapkit.vendor.ipv4.tos_ecn.ToSECN
 method), 350
 process () (pcapkit.vendor.ipv4.tos_pre.ToSPrecedence
 method), 351
 process () (pcapkit.vendor.ipv4.tos_rel.ToSReliability
 method), 352
 process () (pcapkit.vendor.ipv4.tos_thr.ToSThroughput
 method), 352
 process () (pcapkit.vendor.ipv6.extension_header.ExtensionHeader
 method), 353
 process () (pcapkit.vendor.ipv6.option.Option
 method), 354
 process () (pcapkit.vendor.ipv6.qs_function.QSFunction
 method), 354
 process () (pcapkit.vendor.ipv6.router_alert.RouterAlert
 method), 355
 process () (pcapkit.vendor.ipv6.routing.Routing
 method), 355
 process () (pcapkit.vendor.ipv6.seed_id.SeedID
 method), 356
 process () (pcapkit.vendor.ipv6.tagger_id.TaggerID
 method), 356
 process () (pcapkit.vendor.ipx.packet.Packet method),
 357
 process () (pcapkit.vendor.ipx.socket.Socket method),
 357
 process () (pcapkit.vendor.mh.packet.Packet method),
 358
 process () (pcapkit.vendor.reg.ethertype.EtherType
 method), 360
 process () (pcapkit.vendor.reg.linktype.LinkType
 method), 359
 process () (pcapkit.vendor.reg.transtype.TransType
 method), 361
 process () (pcapkit.vendor.tcp.checksum.Checksum
 method), 361
 process () (pcapkit.vendor.tcp.option.Option method),
 362
 process () (pcapkit.vendor.vlan.priority_level.PriorityLevel
 method), 362
 process () (pcapkit.const.reg.linktype.LinkType at-
 tribute), 316
 ProtectionAuthority (class in pcap-
 kit.const.ipv4.protection_authority), 293
 ProtectionAuthority (class in pcap-
 kit.vendor.ipv4.protection_authority), 348
 ProtectionAuthority (pcapkit.const.reg.ethertype.EtherType at-
 tribute), 323
 Proteon_ProNET_Token_Ring (pcap-
 kit.const.arp.hardware.Hardware attribute),
 268

proto (*pcapkit.protocols.internet.ipv4.DataType_IPv4 attribute*), 131
 proto() (*pcapkit.corekit.protochain.ProtoChain property*), 245
 PROTO_LIST (in module *pcapkit.foundation.extraction*), 17
 ProtoChain (class in *pcapkit.corekit.protochain*), 243
 protochain() (*pcapkit.protocols.pcap.header.Header property*), 26
 protochain() (*pcapkit.protocols.protocol.Protocol property*), 232
 Protocol (class in *pcapkit.protocols.protocol*), 226
 protocol (*pcapkit.protocols.internet.hip.DataType_Param_Reg_Error* attribute), 93
 protocol (*pcapkit.protocols.internet.hip.DataType_Param_Reg_Error* attribute), 100
 protocol (*pcapkit.protocols.internet.hip.DataType_Param_Reg_Error* attribute), 101
 protocol() (*pcapkit.foundation.extraction.Extractor property*), 17
 protocol() (*pcapkit.protocols.internet.ah.AH property*), 47
 protocol() (*pcapkit.protocols.internet.hip.HIP property*), 79
 protocol() (*pcapkit.protocols.internet.hopopt.HOPOPT property*), 112
 protocol() (*pcapkit.protocols.internet.ipv4.IPv4 property*), 130
 protocol() (*pcapkit.protocols.internet.ipv6.IPv6 property*), 168
 protocol() (*pcapkit.protocols.internet.ipv6_frag.IPv6_Frag property*), 140
 protocol() (*pcapkit.protocols.internet.ipv6_opts.IPv6_Opts property*), 148
 protocol() (*pcapkit.protocols.internet.ipv6_route.IPv6_Route property*), 164
 protocol() (*pcapkit.protocols.internet.ipx.IPX property*), 170
 protocol() (*pcapkit.protocols.internet.mh.MH property*), 173
 protocol() (*pcapkit.protocols.link.ethernet.Ethernet property*), 35
 protocol() (*pcapkit.protocols.link.vlan.VLAN property*), 43
 protocol() (*pcapkit.protocols.null.NoPayload property*), 226
 protocol() (*pcapkit.protocols.pcap.header.Header property*), 26
 protocol() (*pcapkit.protocols.protocol.Protocol property*), 232
 protocol() (*pcapkit.protocols.raw.Raw property*), 224
 protocol() (*pcapkit.reassembly.ipv4.IPv4_Reassembly property*), 237
 protocol() (*pcapkit.reassembly.ipv6.IPv6_Reassembly property*), 238
 protocol() (*pcapkit.reassembly.reassembly.Reassembly property*), 234
 protocol() (*pcapkit.reassembly.tcp.TCP_Reassembly property*), 242
 PROTOCOL_ERROR (*pcapkit.const.http.error_code.ErrorCode attribute*), 288
 ProtocolError, 260
 ProtocolNotFound, 260
 ProtocolNotImplemented, 260
 P_Relay_From (*pcapkit.protocols.pcap.frame.DataType_Frame attribute*), 31
 P_Relay_To, 260
 ProtocolWarning, 265
 P_Relay_To_Backbone_Bridging_Instance_tag (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
 psh (*pcapkit.protocols.transport.tcp.DataType_TCP_Flags attribute*), 190
 psnlr (*pcapkit.protocols.internet.hopopt.DataType_Opt_PDM attribute*), 119
 psnlr (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PDM attribute*), 155
 psntp (*pcapkit.protocols.internet.hopopt.DataType_Opt_PDM attribute*), 118
 psntp (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PDM attribute*), 155
 PTP (*pcapkit.const.reg.transtype.TransType attribute*), 330
 ptype (*pcapkit.protocols.link.arp.DataType_ARP attribute*), 34
 pub_len (*pcapkit.protocols.internet.hip.DataType_Param_Deffie_Hellman attribute*), 86
 pub_val (*pcapkit.protocols.internet.hip.DataType_Param_Deffie_Hellman attribute*), 86
 pubkey (*pcapkit.protocols.internet.hip.DataType_Host_ID_ECDSA_Curve attribute*), 88
 pubkey (*pcapkit.protocols.internet.hip.DataType_Host_ID_ECDSA_LOW attribute*), 89
 PUP (*pcapkit.const.reg.transtype.TransType attribute*), 330
 PUP_Addr_Trans_0x0201 (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
 PUP_Addr_Trans_0x0A01 (*pcapkit.const.reg.ethertype.EtherType attribute*), 323
 Pure_IP (*pcapkit.const.arp.hardware.Hardware attribute*), 268
 PUSH_PROMISE (*pcapkit.const.http.frame.Frame attribute*), 289

PUZZLE (*pcapkit.const.hip.parameter.Parameter* attribute), 283

PVP (*pcapkit.const.reg.transtype.TransType* attribute), 330

PySharkWarning, 265

Python Enhancement Proposals
PEP 557, 243

Q

QNX (*pcapkit.const.reg.transtype.TransType* attribute), 331

QoS_NSLP_Aggregation_Level_0 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_0 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_1 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_1 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_10 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_10 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_11 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_11 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_12 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_12 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_13 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_13 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_14 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_14 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_15 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_15 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_16 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_16 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_17 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_17 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_18 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_18 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_19 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_19 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 304

QoS_NSLP_Aggregation_Level_2 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_2 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 305

QoS_NSLP_Aggregation_Level_20 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_20 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 305

QoS_NSLP_Aggregation_Level_21 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_21 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 305

QoS_NSLP_Aggregation_Level_22 (*pcapkit.const.ipv4.router_alert.RouterAlert* attribute), 296

QoS_NSLP_Aggregation_Level_22 (*pcapkit.const.ipv6.router_alert.RouterAlert* attribute), 305

QoS_NSLP_Aggregation_Level_23 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 296	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_31 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_23 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_31 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_24 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 296	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_4 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_24 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_4 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_25 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_5 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_25 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_5 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_26 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_6 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_26 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_6 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_27 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_7 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_27 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_7 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_28 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_8 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_28 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_8 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_29 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_9 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_29 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>	QoS_NSLP_Aggregation_Level_9 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>
QoS_NSLP_Aggregation_Level_3 (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> <i>tribute</i>), 297	(<i>pcap-</i> <i>at-</i>	QS (<i>pcapkit.const.ipv4.option_number.OptionNumber</i> <i>at-</i> <i>tribute</i>), 292	
QoS_NSLP_Aggregation_Level_3 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> <i>tribute</i>), 305	(<i>pcap-</i> <i>at-</i>	QS (<i>pcapkit.const.ipv6.option.Option</i> <i>attribute</i>), 301	
		QS (<i>pcapkit.const.tcp.option.Option</i> <i>attribute</i>), 335	
		QSFunction (<i>class in pcapkit.const.ipv4.qs_function</i>), 294	
		QSFunction (<i>class in pcapkit.const.ipv6.qs_function</i>), 302	
		QSFunction (<i>class in pcap-</i> <i>kit.vendor.ipv4.qs_function</i>), 349	<i>pcap-</i>
		QSFunction (<i>class in pcap-</i> <i>kit.vendor.ipv6.qs_function</i>), 354	<i>pcap-</i>

Quick_Start_Request (pcap-kit.const.ipv4.qs_function.QSFunction attribute), 294

Quick_Start_Request (pcap-kit.const.ipv6.qs_function.QSFunction attribute), 302

R

R1 (pcapkit.const.hip.packet.Packet attribute), 282

R1_COUNTER (pcapkit.const.hip.parameter.Parameter attribute), 284

R1_Counter (pcapkit.const.hip.parameter.Parameter attribute), 284

R2 (pcapkit.const.hip.packet.Packet attribute), 282

r_next_key_id (pcap-kit.protocols.transport.tcp.DataType_TCP_Opt_TCPO attribute), 194

RA (pcapkit.const.ipv6.option.Option attribute), 301

rand_num (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYN_data attribute), 197

rand_num (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYN_data attribute), 197

random (pcapkit.protocols.internet.hip.DataType_Param_Piece attribute), 83

random (pcapkit.protocols.internet.hip.DataType_Param_Solution attribute), 84

rank (pcapkit.protocols.internet.hopopt.DataType_Opt_RPL attribute), 120

rank (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_RPL attribute), 156

rank_error (pcapkit.protocols.internet.hopopt.DataType_RPL attribute), 120

rank_error (pcapkit.protocols.internet.ipv6_opts.DataType_RPL attribute), 157

RARP (class in pcapkit.protocols.link.rarp), 42

rate (pcapkit.protocols.internet.hopopt.DataType_Opt_QS attribute), 119

rate (pcapkit.protocols.internet.ipv4.DataType_Opt_QuickStart attribute), 135

rate (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_QS attribute), 156

Rational_Corp (pcap-kit.const.reg.ethertype.EtherType attribute), 323

Raw (class in pcapkit.protocols.raw), 223

RAW (pcapkit.const.reg.linktype.LinkType attribute), 316

raw (pcapkit.protocols.application.ftp.DataType_FTP_Request attribute), 204

raw (pcapkit.protocols.application.ftp.DataType_FTP_Response attribute), 204

raw (pcapkit.protocols.application.httpv1.DataType_HTTP attribute), 207

raw (pcapkit.protocols.internet.hip.DataType_Param_Encrypted attribute), 88

Raw_Frame_Relay (pcap-kit.const.reg.ethertype.EtherType attribute), 323

RDP (pcapkit.const.reg.trans_type.TransType attribute), 331

RDS (pcapkit.const.reg.linktype.LinkType attribute), 316

read () (pcapkit.protocols.application.ftp.FTP method), 203

read () (pcapkit.protocols.application.httpv1.HTTPv1 method), 206

read () (pcapkit.protocols.application.httpv2.HTTPv2 method), 214

read () (pcapkit.protocols.internet.ah.AH method), 46

read () (pcapkit.protocols.internet.hip.HIP method), 78

read () (pcapkit.protocols.internet.hopopt.HOPOPT method), 111

read () (pcapkit.protocols.internet.ipv4.IPv4 method), 129

read () (pcapkit.protocols.internet.ipv6.IPv6 method), 168

read () (pcapkit.protocols.internet.ipv6_frag.IPv6_Frag method), 139

read () (pcapkit.protocols.internet.ipv6_opts.IPv6_Opts method), 147

read () (pcapkit.protocols.internet.ipv6_route.IPv6_Route method), 163

read () (pcapkit.protocols.internet.ipx.IPX method), 170

read () (pcapkit.protocols.internet.mh.MH method), 172

read () (pcapkit.protocols.link.arp.ARP method), 33

read () (pcapkit.protocols.link.ethernet.Ethernet method), 35

read () (pcapkit.protocols.link.l2tp.L2TP method), 37

read () (pcapkit.protocols.link.ospf.OSPF method), 40

read () (pcapkit.protocols.link.vlan.VLAN method), 43

read () (pcapkit.protocols.null.NoPayload method), 225

read () (pcapkit.protocols.pcap.frame.Frame method), 30

read () (pcapkit.protocols.pcap.header.Header method), 25

read () (pcapkit.protocols.protocol.Protocol method), 231

read () (pcapkit.protocols.raw.Raw method), 224

read () (pcapkit.protocols.transport.tcp.TCP method), 186

read () (pcapkit.protocols.transport.udp.UDP method), 176

read_check () (in module pcap-kit.utilities.validations), 264

RealError, 260

reassemble () (in module pcapkit.interface), 22

Reassembly (class in pcapkit.reassembly.reassembly), 233

reassembly (*pcapkit.foundation.extraction.Extractor_mpkit* attribute), 7
 reassembly () (*pcap-kit.foundation.extraction.Extractor* property), 17
 reassembly () (*pcapkit.reassembly.ip.IP_Reassembly* method), 235
 reassembly () (*pcap-kit.reassembly.reassembly.Reassembly* method), 233
 reassembly () (*pcap-kit.reassembly.tcp.TCP_Reassembly* method), 242
 receipt (*pcapkit.protocols.application.httpv1.DataType_HTTP* attribute), 207
 Record_Boundaries (*pcap-kit.const.tcp.option.Option* attribute), 335
 record_frames () (*pcap-kit.foundation.extraction.Extractor* method), 15
 record_header () (*pcap-kit.foundation.extraction.Extractor* method), 16
 Redundant_Checksum_Avoidance (*pcap-kit.const.tcp.checksum.Checksum* attribute), 334
 REFUSED_STREAM (*pcap-kit.const.http.error_code.ErrorCode* attribute), 288
 REG_FAILED (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 REG_FROM (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 REG_INFO (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 REG_REQUEST (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 REG_REQUIRED (*pcap-kit.const.hip.notify_message.NotifyMessage* attribute), 280
 REG_RESPONSE (*pcap-kit.const.hip.parameter.Parameter* attribute), 284
 reg_type (*pcapkit.protocols.internet.hip.DataType_Parameters* attribute), 93
 reg_type (*pcapkit.protocols.internet.hip.DataType_Parameters* attribute), 91
 reg_type (*pcapkit.protocols.internet.hip.DataType_Parameters* attribute), 92
 reg_type (*pcapkit.protocols.internet.hip.DataType_Parameters* attribute), 92
 Registration (class in *pcap-kit.const.hip.registration*), 285
 Registration (class in *pcap-kit.vendor.hip.registration*), 343
 Registration_requires_additional_credentials (*pcapkit.const.hip.registration_failure.RegistrationFailure* attribute), 286
 Registration_type_unavailable (*pcap-kit.const.hip.registration_failure.RegistrationFailure* attribute), 286
 RegistrationFailure (class in *pcap-kit.const.hip.registration_failure*), 286
 RegistrationFailure (class in *pcap-kit.vendor.hip.registration_failure*), 344
 rel (*pcapkit.protocols.internet.ipv4.DataType_IPv4_DSCP* attribute), 132
 relay (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 RELAY_HMAC (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 RELAY_TO (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 RELAY_UDP_HIP (*pcap-kit.const.hip.registration.Registration* attribute), 285
 remove_addr (*pcap-kit.protocols.transport.tcp.DataType_TCP_Opt_REMOVE_ADDR* attribute), 200
 rename () (*pcapkit.vendor.default.Vendor* method), 364
 rename () (*pcapkit.vendor.ipv4.tos_ecn.ToSECN* method), 350
 rename () (*pcapkit.vendor.reg.ethertype.EtherType* method), 360
 RENDEZVOUS (*pcapkit.const.hip.registration.Registration* attribute), 285
 REPLY (*pcapkit.const.arp.operation.Operation* attribute), 269
 reply_Reverse (*pcap-kit.const.arp.operation.Operation* attribute), 270
 Report_of_Approved_Rate (*pcap-kit.const.ipv4.qs_function.QSFunction* attribute), 294
 Report_of_Approved_Rate (*pcap-kit.const.ipv6.qs_function.QSFunction* attribute), 302
 Report_of_Failed (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABLE* attribute), 195
 Report_of_Life (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_QSOPT* attribute), 193
 Request (*pcapkit.const.arp.operation.Operation* attribute), 269
 Request (*pcapkit.protocols.application.httpv1.DataType_HTTP_Request* attribute), 207
 request () (*pcapkit.vendor.default.Vendor* method), 364
 request () (*pcapkit.vendor.ftp.return_code.ReturnCode* attribute), 364

<i>method</i>), 339	Reserved (<i>pcapkit.const.hip.notify_message.NotifyMessage</i> attribute), 281
<i>request () (pcapkit.vendor.ipv4.classification_level.ClassificationLevel</i> <i>method</i>), 346	Reserved (<i>pcapkit.const.hip.packet.Packet</i> attribute), 282
<i>request () (pcapkit.vendor.ipv4.option_class.OptionClass</i> <i>method</i>), 347	Reserved (<i>pcapkit.const.hip.suite.Suite</i> attribute), 287
<i>request () (pcapkit.vendor.ipv4.protection_authority.ProtectionAuthority</i> <i>method</i>), 348	Reserved (<i>pcapkit.const.hip.transport.Transport</i> attribute), 287
<i>request () (pcapkit.vendor.ipv4.qs_function.QSFunction</i> <i>method</i>), 349	Reserved (<i>pcapkit.const.http.setting.Setting</i> attribute), 290
<i>request () (pcapkit.vendor.ipv4.tos_del.ToSDelay</i> <i>method</i>), 350	Reserved (<i>pcapkit.const.ipv4.router_alert.RouterAlert</i> attribute), 297
<i>request () (pcapkit.vendor.ipv4.tos_ecn.ToSECN</i> <i>method</i>), 351	Reserved (<i>pcapkit.const.ipv6.routing.Routing</i> attribute), 306
<i>request () (pcapkit.vendor.ipv4.tos_pre.ToSPrecedence</i> <i>method</i>), 351	Reserved (<i>pcapkit.const.ospf.packet.Packet</i> attribute), 311
<i>request () (pcapkit.vendor.ipv4.tos_rel.ToSReliability</i> <i>method</i>), 352	Reserved (<i>pcapkit.const.reg.ethertype.EtherType</i> attribute), 323
<i>request () (pcapkit.vendor.ipv4.tos_thr.ToSThroughput</i> <i>method</i>), 352	Reserved (<i>pcapkit.const.reg.transtype.TransType</i> attribute), 331
<i>request () (pcapkit.vendor.ipv6.qs_function.QSFunction</i> <i>method</i>), 354	Reserved_0 (<i>pcapkit.const.arp.hardware.Hardware</i> attribute), 268
<i>request () (pcapkit.vendor.ipv6.seed_id.SeedID</i> <i>method</i>), 356	Reserved_0 (<i>pcapkit.const.arp.operation.Operation</i> attribute), 270
<i>request () (pcapkit.vendor.ipx.packet.Packet</i> <i>method</i>), 357	RESERVED_0 (<i>pcapkit.const.hip.cipher.Cipher</i> attribute), 274
<i>request () (pcapkit.vendor.ipx.socket.Socket</i> <i>method</i>), 357	Reserved_1 (<i>pcapkit.const.ipv4.classification_level.ClassificationLevel</i> attribute), 291
<i>request () (pcapkit.vendor.reg.linktype.LinkType</i> <i>method</i>), 359	Reserved_2 (<i>pcapkit.const.ipv4.classification_level.ClassificationLevel</i> attribute), 291
<i>request () (pcapkit.vendor.tcp.checksum.Checksum</i> <i>method</i>), 361	RESERVED_3 (<i>pcapkit.const.hip.cipher.Cipher</i> attribute), 274
<i>request () (pcapkit.vendor.vlan.priority_level.PriorityLevel</i> <i>method</i>), 363	Reserved_3 (<i>pcapkit.const.ipv4.classification_level.ClassificationLevel</i> attribute), 291
<i>request_Reverse (pcapkit.const.arp.operation.Operation</i> attribute), 270	Reserved_3 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> attribute), 305
<i>res (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABILITY</i> attribute), 195	Reserved_31 (<i>pcapkit.const.tcp.option.Option</i> attribute), 335
Reserved (<i>pcapkit.const.hip.certificate.Certificate</i> attribute), 273	Reserved_32 (<i>pcapkit.const.tcp.option.Option</i> attribute), 335
RESERVED (<i>pcapkit.const.hip.ecdsa_curve.ECDSACurve</i> attribute), 275	Reserved_33 (<i>pcapkit.const.tcp.option.Option</i> attribute), 335
RESERVED (<i>pcapkit.const.hip.ecdsa_low_curve.ECDSALowCurve</i> attribute), 275	Reserved_4 (<i>pcapkit.const.ipv4.classification_level.ClassificationLevel</i> attribute), 291
RESERVED (<i>pcapkit.const.hip.esp_transform_suite.ESPTransformSuite</i> attribute), 276	Reserved_65535 (<i>pcapkit.const.arp.hardware.Hardware</i> attribute), 268
Reserved (<i>pcapkit.const.hip.group.Group</i> attribute), 277	Reserved_65535 (<i>pcapkit.const.arp.operation.Operation</i> attribute), 270
RESERVED (<i>pcapkit.const.hip.hi_algorithm.HIAlgorithm</i> attribute), 278	Reserved_65535 (<i>pcapkit.const.ipv6.router_alert.RouterAlert</i> attribute), 306
RESERVED (<i>pcapkit.const.hip.hit_suite.HITSuite</i> attribute), 279	
Reserved (<i>pcapkit.const.hip.nat_traversal.NATTraversal</i> attribute), 279	Reserved_70 (<i>pcapkit.const.tcp.option.Option</i> attribute), 335

Reserved_76 (<i>pcapkit.const.tcp.option.Option attribute</i>), 335	RFC 5482, 188
Reserved_77 (<i>pcapkit.const.tcp.option.Option attribute</i>), 335	RFC 5570, 112, 149
Reserved_78 (<i>pcapkit.const.tcp.option.Option attribute</i>), 336	RFC 5925, 188
reserved_for_future_use_1 (<i>pcapkit.const.ipv4.option_class.OptionClass attribute</i>), 291	RFC 6028, 96
reserved_for_future_use_3 (<i>pcapkit.const.ipv4.option_class.OptionClass attribute</i>), 291	RFC 6247, 188
Reserved_for_HIPPI_6400_0x8182 (<i>pcapkit.const.reg.ethertype.EtherType attribute</i>), 323	RFC 6275, 112, 149, 164
Reserved_for_HIPPI_6400_0x8183 (<i>pcapkit.const.reg.ethertype.EtherType attribute</i>), 323	RFC 6553, 112, 149
RESPONDER_BUSY_PLEASE_RETRY (<i>pcapkit.const.hip.notify_message.NotifyMessage attribute</i>), 280	RFC 6554, 164
response (<i>pcapkit.protocols.application.httpv1.DataType</i> <i>HTTP_Response_Header attribute</i>), 207	RFC 6621, 112, 149
ret (<i>pcapkit.protocols.internet.hopopt.DataType_IP_DFF_Flag</i> <i>attribute</i>), 124	RFC 6744, 112, 149
ret (<i>pcapkit.protocols.internet.ipv6_opts.DataType_IP_DFF_Flag</i> <i>attribute</i>), 160	RFC 6788, 112, 149
Retix (<i>pcapkit.const.reg.ethertype.EtherType attribute</i>), 324	RFC 6814, 130
ReturnCode (<i>class in pcapkit.const.ftp.return_code</i>), 270	RFC 6824, 188
ReturnCode (<i>class in pcapkit.vendor.ftp.return_code</i>), 339	RFC 6971, 112, 149
Reverse_Address_Resolution_Protocol (<i>pcapkit.const.reg.ethertype.EtherType attribute</i>), 324	RFC 7323, 188
RFC	RFC 7413, 188
RFC 1063, 130	RFC 7731, 112, 113, 149
RFC 1072, 188	RFC 791, 130
RFC 1108, 130	RFC 793, 188
RFC 1146, 188	RFC 8200, 112, 149
RFC 1191, 130	RFC 8250, 112, 149
RFC 1385, 130	RFC 1063, 292
RFC 1393, 130	RFC 1072, 335
RFC 1693, 188	RFC 1108, 127, 137, 292, 293
RFC 2018, 188	RFC 1112, 328
RFC 2113, 130	RFC 1132, 171
RFC 2385, 188	RFC 1144, 324
RFC 2473, 112, 149	RFC 1146, 180, 192, 334, 335, 361
RFC 2675, 112, 149	RFC 1190, 332
RFC 2711, 112, 149	RFC 1191, 292
RFC 4727, 113, 149	RFC 1201, 266
RFC 4782, 112, 130, 149, 188	RFC 1241, 327
RFC 5095, 164	RFC 1385, 292
	RFC 1393, 293
	RFC 1577, 268
	RFC 1582, 308
	RFC 1583, 311, 330
	RFC 1644, 334
	RFC 1693, 181, 192, 335
	RFC 1701, 321–325
	RFC 1735, 330
	RFC 1819, 332
	RFC 1931, 32, 269
	RFC 2003, 329
	RFC 2018, 336
	RFC 2091, 308
	RFC 2113, 127, 138, 292
	RFC 2176, 268, 269
	RFC 2205, 331
	RFC 2225, 266
	RFC 2328, 39–41, 311, 330
	RFC 2385, 336
	RFC 2390, 32, 269

- RFC 2393, 328
RFC 2404, 276
RFC 2410, 276, 278
RFC 2460, 124, 168, 169
RFC 2460#section-4.1, 252
RFC 2460#section-4.3, 252
RFC 2460#section-4.4, 252
RFC 2460#section-4.5, 250, 252, 254
RFC 2460#section-4.6, 252
RFC 2473, 110, 115, 116, 147, 152, 302, 329
RFC 2516, 323
RFC 2661, 37
RFC 2675, 106, 122, 143, 159, 301
RFC 2710, 304
RFC 2711, 109, 116, 146, 152, 301, 304
RFC 2784, 328
RFC 3175, 294–296, 302–304, 331
RFC 3209, 331
RFC 3378, 327
RFC 3456, 267
RFC 3602, 276
RFC 3659, 270
RFC 3692, 300, 332
RFC 3828, 332
RFC 3931, 329
RFC 4023, 330
RFC 4106, 276
RFC 4302, 46, 47, 124, 299, 326
RFC 4303, 124, 299, 327
RFC 4309, 276
RFC 4338, 267
RFC 4340, 327
RFC 4391, 267
RFC 4493, 276
RFC 4494, 276
RFC 4543, 276
RFC 4727, 292, 301, 306, 335
RFC 4728, 327
RFC 4782, 108, 119, 126, 135, 145, 155, 181, 193, 292, 301, 335
RFC 4868, 276
RFC 5095, 161–165, 306
RFC 5096, 309
RFC 5142, 310
RFC 5201, 59, 65, 66, 75, 77, 78, 80–84, 86, 277, 283, 284, 287
RFC 5227, 269, 270
RFC 5332, 322
RFC 5340, 330
RFC 5350, 297, 306
RFC 5482, 182, 193, 336
RFC 5494, 266–270, 337, 338
RFC 5498, 333
RFC 5533, 300, 332
RFC 5568, 309, 310
RFC 5570, 105, 110, 116–118, 141, 146, 153, 154, 300
RFC 5709, 311
RFC 5770, 62, 67, 70, 71, 76, 87, 93, 100, 101, 103, 279, 280, 283–285
RFC 5798, 333
RFC 5840, 333
RFC 5846, 309
RFC 5847, 310
RFC 5858, 331
RFC 5925, 182, 194, 334
RFC 5973, 296, 304
RFC 5974, 296, 297, 304, 305
RFC 6028, 71, 72, 78, 97, 102, 103, 281, 284
RFC 6078, 49, 64, 65, 74, 75, 94–96, 101, 282–284
RFC 6079, 64, 96, 280, 283
RFC 6172, 328
RFC 6247, 180, 181, 192, 334, 335
RFC 6261, 60, 97, 280, 283, 287
RFC 6275, 105, 123, 142, 159, 161, 166, 172, 300, 306, 309, 310, 330
RFC 6325, 322, 324
RFC 6537, 281
RFC 6553, 109, 119, 120, 146, 156, 301
RFC 6554, 162, 166, 306
RFC 6621, 302, 307
RFC 6705, 310
RFC 6744, 105, 121, 122, 142, 158, 300
RFC 6788, 107, 122, 143, 158, 301
RFC 6814, 128, 136, 137, 292, 293
RFC 6824, 178–180, 183, 184, 186, 188, 194–202
RFC 6971, 106, 123, 142, 159, 160, 301
RFC 7042, 35, 44, 318, 320–323
RFC 7077, 310
RFC 7109, 310
RFC 7161, 310
RFC 7172, 324
RFC 7178, 324
RFC 7230, 204–207
RFC 7323, 182, 191, 336
RFC 7401, 49–54, 56–61, 63, 65, 66, 74–78, 80–90, 93, 94, 98–100, 274, 275, 277–284, 300, 328
RFC 7402, 54, 55, 81, 94, 276, 280, 283
RFC 741, 330
RFC 7413, 335
RFC 7474, 311
RFC 7506, 304
RFC 7540, 204, 208–222, 290
RFC 768, 176, 177, 332
RFC 7731, 107, 120, 121, 143, 157, 300, 301, 356
RFC 7761, 330
RFC 7868, 327

- RFC 791, 114, 124, 127–129, 131, 133, 135–137, 150, 234, 240, 292, 293
- RFC 792, 328
- RFC 793, 187, 189, 332, 335
- RFC 7973, 322
- RFC 8002, 273, 280, 282
- RFC 8003, 67–69, 91–93, 280, 284, 286
- RFC 8004, 56, 73, 102, 103, 283–285
- RFC 8046, 61, 82, 280, 283
- RFC 815, 232–234, 240, 366, 369
- RFC 8157, 325
- RFC 8200, 107, 108, 111, 113–115, 139, 140, 144, 147, 149, 151, 152, 161, 163–165, 300, 328, 329
- RFC 823, 328
- RFC 824, 320
- RFC 8250, 108, 118, 119, 145, 154–156, 301
- RFC 826, 32–34, 266, 268–270, 337, 338
- RFC 8300, 323
- RFC 8336, 289
- RFC 8377, 322
- RFC 8441, 290
- RFC 8547, 335
- RFC 8684, 335
- RFC 869, 328
- RFC 8754, 306
- RFC 888, 327
- RFC 903, 32, 270, 324
- RFC 905, 329
- RFC 908, 331
- RFC 938, 329
- RFC 959, 204
- RFC 969, 330
- RFC3692_style_Experiment_0x1E (*pcap-kit.const.ipv6.option.Option attribute*), 301
- RFC3692_style_Experiment_0x3E (*pcap-kit.const.ipv6.option.Option attribute*), 301
- RFC3692_style_Experiment_0x5E (*pcap-kit.const.ipv6.option.Option attribute*), 301
- RFC3692_style_Experiment_0x7E (*pcap-kit.const.ipv6.option.Option attribute*), 301
- RFC3692_style_Experiment_0x9E (*pcap-kit.const.ipv6.option.Option attribute*), 301
- RFC3692_style_Experiment_0xBE (*pcap-kit.const.ipv6.option.Option attribute*), 301
- RFC3692_style_Experiment_0xDE (*pcap-kit.const.ipv6.option.Option attribute*), 301
- RFC3692_style_Experiment_0xFE (*pcap-kit.const.ipv6.option.Option attribute*), 301
- RFC3692_style_Experiment_1 (*pcap-kit.const.ipv6.routing.Routing attribute*), 306
- RFC3692_style_Experiment_1 (*pcap-kit.const.tcp.option.Option attribute*), 335
- RFC3692_style_Experiment_2 (*pcap-kit.const.ipv6.routing.Routing attribute*), 306
- RFC3692_style_Experiment_2 (*pcap-kit.const.tcp.option.Option attribute*), 335
- rhc (*pcapkit.protocols.internet.ipv4.DataType_Opt_Traceroute attribute*), 137
- rhic (*pcapkit.protocols.internet.hip.DataType_HIP attribute*), 80
- RIP (*pcapkit.const.ipx.packet.Packet attribute*), 308
- rkey (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABLE attribute*), 195
- rkey (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_FASTCLO attribute*), 202
- ROHC (*pcapkit.const.reg.transtype.TransType attribute*), 331
- ROUTE_DST (*pcapkit.const.hip.parameter.Parameter attribute*), 284
- ROUTE_VIA (*pcapkit.const.hip.parameter.Parameter attribute*), 284
- router_id (*pcapkit.protocols.link.ospf.DataType_OSPF attribute*), 41
- RouterAlert (*class in pcap-kit.const.ipv4.router_alert*), 294
- RouterAlert (*class in pcap-kit.const.ipv6.router_alert*), 302
- RouterAlert (*class in pcap-kit.vendor.ipv4.router_alert*), 349
- RouterAlert (*class in pcap-kit.vendor.ipv6.router_alert*), 355
- Routine (*pcapkit.const.ipv4.tos_pre.ToSPrecedence attribute*), 298
- Routing (*class in pcapkit.const.ipv6.routing*), 306
- Routing (*class in pcapkit.vendor.ipv6.routing*), 355
- Routing_Information_Packet (*pcap-kit.const.ipx.socket.Socket attribute*), 308
- Routing_Information_Protocol (*pcap-kit.const.ipx.socket.Socket attribute*), 308
- RPL_0x63 (*pcapkit.const.ipv6.option.Option attribute*), 301
- RPL_Option_0x23 (*pcapkit.const.ipv6.option.Option attribute*), 301
- RPL_Source_Route_Header (*pcap-kit.const.ipv6.routing.Routing attribute*), 306
- RR (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 292
- RSA (*pcapkit.const.hip.hi_algorithm.HIAlgorithm attribute*), 278
- RSA_DSA_SHA_256 (*pcap-kit.const.hip.hit_suite.HITSuite attribute*), 279
- rst (*pcapkit.protocols.transport.tcp.DataType_TCP_Flags attribute*), 190

RST_STREAM (pcapkit.const.http.frame.Frame attribute), 289

RSVP (pcapkit.const.reg.transtype.TransType attribute), 331

RSVP_E2E_IGNORE (pcapkit.const.reg.transtype.TransType attribute), 331

RTAC_SERIAL (pcapkit.const.reg.linktype.LinkType attribute), 316

RTRALT (pcapkit.const.ipv4.option_number.OptionNumber attribute), 292

run() (in module pcapkit.vendor.__main__), 366

run() (pcapkit.foundation.extraction.Extractor method), 16

run() (pcapkit.reassembly.reassembly.Reassembly method), 233

RVD (pcapkit.const.reg.transtype.TransType attribute), 331

RVS_HMAC (pcapkit.const.hip.parameter.Parameter attribute), 284

S

SACK (pcapkit.const.tcp.option.Option attribute), 336

SACKPMT (pcapkit.const.tcp.option.Option attribute), 336

safe_name() (pcapkit.vendor.default.Vendor method), 364

SAT_EXPAK (pcapkit.const.reg.transtype.TransType attribute), 331

SAT_MON (pcapkit.const.reg.transtype.TransType attribute), 331

scaledtlr (pcapkit.protocols.internet.hopopt.DataType_Opt_PDM attribute), 118

scaledtlr (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PDM attribute), 155

scaledtls (pcapkit.protocols.internet.hopopt.DataType_Opt_PDM attribute), 118

scaledtls (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_PDM attribute), 155

ScapyWarning, 266

SCC_SP (pcapkit.const.reg.transtype.TransType attribute), 331

SCCP (pcapkit.const.reg.linktype.LinkType attribute), 316

SCI (pcapkit.const.ipv4.protection_authority.ProtectionAuthority attribute), 293

SCPS (pcapkit.const.reg.transtype.TransType attribute), 331

SCPS_Capabilities (pcapkit.const.tcp.option.Option attribute), 336

SCTP (pcapkit.const.reg.linktype.LinkType attribute), 316

SCTP (pcapkit.const.reg.transtype.TransType attribute), 331

SDB (pcapkit.const.ipv4.option_number.OptionNumber attribute), 292

SDLC (pcapkit.const.reg.linktype.LinkType attribute), 316

SDRP (pcapkit.const.reg.transtype.TransType attribute), 331

SEC (pcapkit.const.ipv4.option_number.OptionNumber attribute), 293

SECP160R1 (pcapkit.const.hip.ecdsa_low_curve.ECDSALowCurve attribute), 275

SECP160R1 (pcapkit.const.hip.group.Group attribute), 277

Secret (pcapkit.const.ipv4.classification_level.ClassificationLevel attribute), 291

SECTRA (pcapkit.const.reg.ethertype.EtherType attribute), 324

Secure_Data (pcapkit.const.reg.ethertype.EtherType attribute), 324

SECURE_VMTP (pcapkit.const.reg.transtype.TransType attribute), 331

seed_id (pcapkit.protocols.internet.hopopt.DataType_Opt_MPL attribute), 121

seed_id (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_MPL attribute), 157

seed_len (pcapkit.protocols.internet.hopopt.DataType_Opt_MPL attribute), 121

seed_len (pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_MPL attribute), 157

SeedID (class in pcapkit.const.ipv6.seed_id), 306

SeedID (class in pcapkit.vendor.ipv6.seed_id), 356

SEEDID_128_BIT_UNSIGNED_INTEGER (pcapkit.const.ipv6.seed_id.SeedID attribute), 306

SEEDID_16_BIT_UNSIGNED_INTEGER (pcapkit.const.ipv6.seed_id.SeedID attribute), 307

SEEDID_64_BIT_UNSIGNED_INTEGER (pcapkit.const.ipv6.seed_id.SeedID attribute), 307

seed_id (pcapkit.vendor.__main__ module pcapkit.utilities.decorators), 256

seed_id (pcapkit.vendor.ipv6.seed_id module pcapkit.utilities.decorators), 256

seed_id (pcapkit.vendor.ipv6.seed_id module pcapkit.utilities.decorators), 256

seed_id (pcapkit.vendor.ipv6.seed_id module pcapkit.utilities.decorators), 256

seed_id (pcapkit.vendor.ipv6.seed_id module pcapkit.utilities.decorators), 256

Segment_Routing_Header (pcapkit.const.ipv6.routing.Routing attribute), 306

Selective_Negative_Acknowledgements (pcapkit.const.tcp.option.Option attribute), 336

SEQ (pcapkit.const.hip.parameter.Parameter attribute), 284

seq (pcapkit.protocols.internet.ah.DataType_AH attribute), 48

seq (pcapkit.protocols.internet.hip.DataType_Param_SEQ_Data attribute), 95

seq (pcapkit.protocols.internet.hopopt.DataType_Opt_IP_DFF attribute), 123

seq (pcapkit.protocols.internet.hopopt.DataType_Opt_MPL attribute), 121

seq (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_IP_Deffer* attribute), 293
 attribute), 160
 seq (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_MPL* attribute), 215
 attribute), 157
 seq (*pcapkit.protocols.link.l2tp.DataType_Flags* attribute), 38
 seq (*pcapkit.protocols.link.ospf.DataType_Auth* attribute), 41
 seq (*pcapkit.protocols.transport.tcp.DataType_TCP* attribute), 189
 SEQ_DATA (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 Serial_Line (*pcapkit.const.arp.hardware.Hardware* attribute), 268
 Serialization_Packet (*pcapkit.const.ipx.socket.Socket* attribute), 308
 Service_Advertising_Protocol (*pcapkit.const.ipx.socket.Socket* attribute), 308
 sessionid (*pcapkit.protocols.link.l2tp.DataType_L2TP* attribute), 38
 Setting (class in *pcapkit.const.http.setting*), 290
 Setting (class in *pcapkit.vendor.http.setting*), 346
 SETTINGS (*pcapkit.const.http.frame.Frame* attribute), 289
 settings (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_SETTINGS* attribute), 219
 SETTINGS_ENABLE_CONNECT_PROTOCOL (*pcapkit.const.http.setting.Setting* attribute), 290
 SETTINGS_TIMEOUT (*pcapkit.const.http.error_code.ErrorCode* attribute), 288
 SGI_bounce_server (*pcapkit.const.reg.ethertype.EtherType* attribute), 324
 SGI_diagnostics (*pcapkit.const.reg.ethertype.EtherType* attribute), 324
 SGI_network_games (*pcapkit.const.reg.ethertype.EtherType* attribute), 324
 SGI_reserved (*pcapkit.const.reg.ethertype.EtherType* attribute), 324
 SGI_Time_Warner_prop (*pcapkit.const.reg.ethertype.EtherType* attribute), 324
 sha (*pcapkit.protocols.link.arp.DataType_ARP* attribute), 34
 Shim6 (*pcapkit.const.ipv6.extension_header.ExtensionHeader* attribute), 300
 Shim6 (*pcapkit.const.reg.transype.TransType* attribute), 332
 shit (*pcapkit.protocols.internet.hip.DataType_HIP* attribute), 80
 SID (*pcapkit.const.ipv4.option_number.OptionNumber* attribute), 160
 sid (*pcapkit.protocols.application.httpv2.DataType_HTTPv2* attribute), 215
 SIG (*pcapkit.const.tcp.option.Option* attribute), 336
 sigfigs (*pcapkit.protocols.pcap.header.DataType_Header* attribute), 27
 signature (*pcapkit.protocols.internet.hip.DataType_Param_Signature* attribute), 99
 signature (*pcapkit.protocols.internet.hip.DataType_Param_Signature_2* attribute), 99
 Simple_Password_Authentication (*pcapkit.const.ospf.authentication.Authentication* attribute), 311
 SIOP_ESI (*pcapkit.const.ipv4.protection_authority.ProtectionAuthority* attribute), 293
 SITA (*pcapkit.const.reg.linktype.LinkType* attribute), 316
 Skeeter (*pcapkit.const.tcp.option.Option* attribute), 336
 skey (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_CAPABLE* attribute), 195
 SKIP (*pcapkit.const.reg.transype.TransType* attribute), 331
 SLIP (*pcapkit.const.reg.linktype.LinkType* attribute), 316
 SM (*pcapkit.const.reg.transype.TransType* attribute), 331
 SMF_DPDP (*pcapkit.const.ipv6.option.Option* attribute), 301
 SMP (*pcapkit.const.reg.transype.TransType* attribute), 331
 SNAP (*pcapkit.const.tcp.option.Option* attribute), 336
 snaplen (*pcapkit.protocols.pcap.header.DataType_Header* attribute), 27
 SNMP (*pcapkit.const.reg.ethertype.EtherType* attribute), 324
 SNP (*pcapkit.const.reg.transype.TransType* attribute), 331
 Socket (class in *pcapkit.const.ipx.socket*), 308
 Socket (class in *pcapkit.vendor.ipx.socket*), 357
 socket (*pcapkit.protocols.internet.ipx.DataType_IPX_Address* attribute), 171
 SOLUTION (*pcapkit.const.hip.parameter.Parameter* attribute), 284
 solution (*pcapkit.protocols.internet.hip.DataType_Param_Solution* attribute), 84
 Source_Route (*pcapkit.const.ipv6.routing.Routing* attribute), 306
 spi (*pcapkit.protocols.internet.ah.DataType_AH* attribute), 47
 spi (*pcapkit.protocols.internet.hip.DataType_Locator_Dict* attribute), 83
 Spider_Systems_Ltd (*pcapkit.const.reg.ethertype.EtherType* attribute), 324

Sprite_RPC (*pcapkit.const.reg.transtype.TransType attribute*), 332
 SPS (*pcapkit.const.reg.transtype.TransType attribute*), 331
 SPX (*pcapkit.const.ipx.packet.Packet attribute*), 308
 src (*pcapkit.protocols.internet.ipv4.DataType_IPv4 attribute*), 131
 src (*pcapkit.protocols.internet.ipv6.DataType_IPv6 attribute*), 169
 src (*pcapkit.protocols.internet.ipx.DataType_IPX attribute*), 171
 src (*pcapkit.protocols.link.ethernet.DataType_Ethernet attribute*), 36
 src () (*pcapkit.protocols.internet.ip.IP property*), 124
 src () (*pcapkit.protocols.internet.ipsec.IPsec property*), 125
 src () (*pcapkit.protocols.internet.ipx.IPX property*), 170
 src () (*pcapkit.protocols.link.arp.ARP property*), 34
 src () (*pcapkit.protocols.link.ethernet.Ethernet property*), 35
 src () (*pcapkit.protocols.transport.tcp.TCP property*), 187
 src () (*pcapkit.protocols.transport.udp.UDP property*), 177
 srcport (*pcapkit.protocols.transport.tcp.DataType_TCP attribute*), 189
 srcport (*pcapkit.protocols.transport.udp.DataType_UDP attribute*), 177
 SRP (*pcapkit.const.reg.transtype.TransType attribute*), 331
 SSCOPMCE (*pcapkit.const.reg.transtype.TransType attribute*), 331
 ssn (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_DSS_Data attribute*), 199
 SSR (*pcapkit.const.ipv4.option_number.OptionNumber attribute*), 293
 ST (*pcapkit.const.reg.transtype.TransType attribute*), 332
 stacklevel () (in module *pcapkit.utilities.exceptions*), 261
 STANAG_5066_D_PDU (*pcapkit.const.reg.linktype.LinkType attribute*), 316
 Stanford_V_Kernel_exp (*pcapkit.const.reg.ethertype.EtherType attribute*), 324
 Stanford_V_Kernel_prod (*pcapkit.const.reg.ethertype.EtherType attribute*), 324
 start (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_POCSPT attribute*), 192
 status (*pcapkit.protocols.application.httpv1.DataType_HTTP_Response_Header_Meta attribute*), 208
 STP (*pcapkit.const.reg.transtype.TransType attribute*), 332
 STP_HIPPI_ST (*pcapkit.const.reg.ethertype.EtherType attribute*), 324
 str_check () (in module *pcapkit.utilities.validations*), 264
 STREAM_CLOSED (*pcapkit.const.http.error_code.ErrorCode attribute*), 288
 StringError, 260
 StructError, 260
 submit () (*pcapkit.foundation.traceflow.TraceFlow method*), 19
 submit () (*pcapkit.reassembly.ip.IP_Reassembly method*), 236
 submit () (*pcapkit.reassembly.reassembly.Reassembly method*), 233
 submit () (*pcapkit.reassembly.tcp.TCP_Reassembly method*), 242
 Subscription_Query (*pcapkit.const.mh.packet.Packet attribute*), 310
 Subscription_Response (*pcapkit.const.mh.packet.Packet attribute*), 310
 subtype (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MPTCP attribute*), 194
 Suite (class in *pcapkit.const.hip.suite*), 286
 Suite (class in *pcapkit.vendor.hip.suite*), 344
 Suite_3DES_CBC_with_HMAC_MD5 (*pcapkit.const.hip.suite.Suite attribute*), 287
 Suite_3DES_CBC_with_HMAC_SHA1 (*pcapkit.const.hip.suite.Suite attribute*), 287
 SUN_ND (*pcapkit.const.reg.transtype.TransType attribute*), 332
 SUNATM (*pcapkit.const.reg.linktype.LinkType attribute*), 317
 SWIPE (*pcapkit.const.reg.transtype.TransType attribute*), 332
 Symbolics_Private (*pcapkit.const.reg.ethertype.EtherType attribute*), 324
 symmetric (*pcapkit.protocols.internet.hip.DataType_Flags attribute*), 97
 syn (*pcapkit.protocols.transport.tcp.DataType_TCP_Flags attribute*), 190
 syn (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_ACK attribute*), 198
 syn (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYN attribute*), 196
 syn (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_SYN attribute*), 197
 T
 T (in module *pcapkit.vendor.tcp.option*), 362
 TaggerID (class in *pcapkit.const.ipv6.tagger_id*), 307
 TaggerID (class in *pcapkit.vendor.ipv6.tagger_id*), 356

target (*pcapkit.protocols.application.httpv1.DataType_HTTP_Request_Header_Meta* attribute), 207

TCF (*pcapkit.const.reg.transtype.TransType* attribute), 332

tci (*pcapkit.protocols.link.vlan.DataType_VLAN* attribute), 44

TCP (class in *pcapkit.protocols.transport.tcp*), 178

TCP (*pcapkit.const.reg.transtype.TransType* attribute), 332

tcp.buffer, 241

tcp.datagram, 241

tcp.packet, 240

TCP_checksum (*pcapkit.const.tcp.checksum.Checksum* attribute), 334

TCP_Compression_Filter (*pcapkit.const.tcp.option.Option* attribute), 336

TCP_IP_Compression (*pcapkit.const.reg.ethertype.EtherType* attribute), 324

TCP_over_IPXF (*pcapkit.const.ipx.socket.Socket* attribute), 309

TCP_Reassembly (class in *pcapkit.reassembly.tcp*), 242

tcp_reassembly() (in module *pcapkit.toolkit.default*), 250

tcp_reassembly() (in module *pcapkit.toolkit.dpkt*), 252

tcp_reassembly() (in module *pcapkit.toolkit.scapy*), 255

tcp_traceflow() (in module *pcapkit.toolkit.default*), 251

tcp_traceflow() (in module *pcapkit.toolkit.dpkt*), 253

tcp_traceflow() (in module *pcapkit.toolkit.pyshark*), 253

tcp_traceflow() (in module *pcapkit.toolkit.scapy*), 255

Technically_Elite_Concept (*pcapkit.const.reg.ethertype.EtherType* attribute), 324

tf_type (*pcapkit.protocols.internet.hip.DataType_Param_Transform_FormatList* attribute), 94

The_Ethertype_will_be_used_to_identify_a_packet_encapsulated_in_thiszone (class in *pcapkit.const.reg.ethertype.EtherType* attribute), 324

thiszone (*pcapkit.protocols.pcap.header.DataType_Header* attribute), 27

thr (*pcapkit.protocols.internet.ipv4.DataType_IPv4_DSCPTR* attribute), 132

TIA_102_Project_25_Common_Air_Interface (*pcapkit.const.arp.hardware.Hardware* attribute), 268

tid (*pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_I_PDP* attribute), 117

tid_len (*pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_I_PDP* attribute), 117

tid_len (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_SMF_I_PDP* attribute), 154

tid_type (*pcapkit.protocols.internet.hopopt.DataType_Opt_SMF_I_PDP* attribute), 117

tid_type (*pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_SMF_I_PDP* attribute), 154

Tigan_Inc (*pcapkit.const.reg.ethertype.EtherType* attribute), 325

time (*pcapkit.protocols.pcap.frame.DataType_Frame* attribute), 31

time_epoch (*pcapkit.protocols.pcap.frame.DataType_Frame* attribute), 31

TIMEOUT (*pcapkit.const.tcp.option.Option* attribute), 336

timeout (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_UTOPT* attribute), 193

timestamp (*pcapkit.protocols.internet.ipv4.DataType_Opt_TimeStamp* attribute), 136

TLS_RENEG_PERMITTED (*pcapkit.const.http.setting.Setting* attribute), 290

TLSP (*pcapkit.const.reg.transtype.TransType* attribute), 332

token (*pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_JOIN_S* attribute), 197

Top_Secret (*pcapkit.const.ipv4.classification_level.ClassificationLevel* attribute), 291

ToSDelay (class in *pcapkit.const.ipv4.tos_del*), 297

ToSDelay (class in *pcapkit.vendor.ipv4.tos_del*), 350

ToSECN (class in *pcapkit.const.ipv4.tos_ecn*), 298

ToSECN (class in *pcapkit.vendor.ipv4.tos_ecn*), 350

ToSPrecedence (class in *pcapkit.const.ipv4.tos_pre*), 298

ToSPrecedence (class in *pcapkit.vendor.ipv4.tos_pre*), 351

ToSReliability (class in *pcapkit.const.ipv4.tos_rel*), 299

ToSThroughput (class in *pcapkit.vendor.ipv4.tos_thr*), 352

TP (*pcapkit.const.reg.transtype.TransType* attribute), 332

trace (*pcapkit.foundation.extraction.Extractor_mpk* attribute), 7

trace() (in module *pcapkit.interface*), 22

tf_type (*pcapkit.foundation.extraction.Extractor_property*), 17

`trace()` (`pcapkit.foundation.traceflow.TraceFlow` method), 19
`trace.buffer`, 18
`trace.index`, 18
`trace.packet`, 18
`TraceFlow` (class in `pcapkit.foundation.traceflow`), 19
`traffic` (`pcapkit.protocols.internet.hip.DataType_Locator` attribute), 82
`Trailer_Checksum_Option` (`pcapkit.const.tcp.option.Option` attribute), 336
`Trans_Ether_Bridging` (`pcapkit.const.reg.ethertype.EtherType` attribute), 325
`TRANSACTION_ID` (`pcapkit.const.hip.parameter.Parameter` attribute), 284
`TRANSACTION_PACING` (`pcapkit.const.hip.parameter.Parameter` attribute), 284
`Transport` (class in `pcapkit.const.hip.transport`), 287
`Transport` (class in `pcapkit.protocols.transport.transport`), 202
`Transport` (class in `pcapkit.vendor.hip.transport`), 344
`TRANSPORT_FORMAT_LIST` (`pcapkit.const.hip.parameter.Parameter` attribute), 284
`TransType` (class in `pcapkit.const.reg.transtype`), 326
`TransType` (class in `pcapkit.vendor.reg.transtype`), 360
`TransType_3PC` (`pcapkit.const.reg.transtype.TransType` attribute), 332
`TRILL` (`pcapkit.const.reg.ethertype.EtherType` attribute), 324
`TRILL_Fine_Grained_Labeling` (`pcapkit.const.reg.ethertype.EtherType` attribute), 324
`TRILL_RBridg_Channel` (`pcapkit.const.reg.ethertype.EtherType` attribute), 324
`TRUNK_1` (`pcapkit.const.reg.transtype.TransType` attribute), 332
`TRUNK_2` (`pcapkit.const.reg.transtype.TransType` attribute), 332
`TS` (`pcapkit.const.ipv4.option_number.OptionNumber` attribute), 293
`TS` (`pcapkit.const.tcp.option.Option` attribute), 336
`ts_sec` (`pcapkit.protocols.pcap.frame.DataType_FrameInfoType` attribute), 31
`ts_usec` (`pcapkit.protocols.pcap.frame.DataType_FrameInfoType` attribute), 31
`ttl` (`pcapkit.protocols.internet.hip.DataType_Param_Overlay` attribute), 101
`ttl` (`pcapkit.protocols.internet.hopopt.DataType_Opt_QS` attribute), 119
`ttl` (`pcapkit.protocols.internet.ipv4.DataType_IPv4` attribute), 131
`ttl` (`pcapkit.protocols.internet.ipv4.DataType_Opt_QuickStart` attribute), 135
`ttl` (`pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_QS` attribute), 156
`ttl_diff` (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_QSOPT` attribute), 193
`TTP` (`pcapkit.const.reg.transtype.TransType` attribute), 332
`TUN` (`pcapkit.const.ipv6.option.Option` attribute), 302
`tunnelid` (`pcapkit.protocols.link.l2tp.DataType_L2TP` attribute), 38
`tuple` (`pcapkit.corekit.protochain.ProtoChain` attribute), 245
`tuple_check()` (in module `pcapkit.utilities.validations`), 264
`TupleError`, 260
`Twinaxial` (`pcapkit.const.arp.hardware.Hardware` attribute), 268
`Tymshare` (`pcapkit.const.reg.ethertype.EtherType` attribute), 325
`type` (`pcapkit.protocols.application.ftp.DataType_FTP_Request` attribute), 204
`type` (`pcapkit.protocols.application.ftp.DataType_FTP_Response` attribute), 204
`type` (`pcapkit.protocols.application.httpv2.DataType_HTTPv2` attribute), 215
`type` (`pcapkit.protocols.internet.hip.DataType_HIP` attribute), 80
`type` (`pcapkit.protocols.internet.hip.DataType_Locator` attribute), 82
`type` (`pcapkit.protocols.internet.hip.DataType_Parameter` attribute), 80
`type` (`pcapkit.protocols.internet.hopopt.DataType_Option` attribute), 113
`type` (`pcapkit.protocols.internet.ipv4.DataType_Opt` attribute), 132
`type` (`pcapkit.protocols.internet.ipv6_opts.DataType_Option` attribute), 150
`type` (`pcapkit.protocols.internet.ipv6_route.DataType_IPv6_Route` attribute), 164
`type` (`pcapkit.protocols.internet.ipx.DataType_IPX` attribute), 171
`type` (`pcapkit.protocols.internet.mh.DataType_MH` attribute), 173
`type` (`pcapkit.protocols.link.ethernet.DataType_Ethernet` attribute), 36
`type` (`pcapkit.protocols.link.l2tp.DataType_Flags` attribute), 38
`type` (`pcapkit.protocols.link.ospf.DataType_OSPF` attribute), 41
`type` (`pcapkit.protocols.link.vlan.DataType_VLAN` attribute), 44

<code>type()</code> (<i>pcapkit.protocols.link.arp.ARP</i> property), 34	
<code>type()</code> (<i>pcapkit.protocols.link.l2tp.L2TP</i> property), 37	
<code>type()</code> (<i>pcapkit.protocols.link.ospf.OSPF</i> property), 40	
<code>Type_2_Routing_Header</code> (<i>pcap-kit.const.ipv6.routing.Routing</i> attribute), 306	
U	
<code>UDP</code> (class in <i>pcapkit.protocols.transport.udp</i>), 176	
<code>UDP</code> (<i>pcapkit.const.reg.transtype.TransType</i> attribute), 332	
<code>UDP_ENCAPSULATION</code> (<i>pcap-kit.const.hip.nat_traversal.NATTraversal</i> attribute), 279	
<code>UDP_over_IPXF</code> (<i>pcapkit.const.ipx.socket.Socket</i> attribute), 309	
<code>UDPLite</code> (<i>pcapkit.const.reg.transtype.TransType</i> attribute), 332	
<code>Ultra_link</code> (<i>pcapkit.const.arp.hardware.Hardware</i> attribute), 268	
<code>UMP</code> (<i>pcapkit.const.ipv4.option_number.OptionNumber</i> attribute), 293	
<code>Unassigned</code> (<i>pcapkit.const.hip.registration.Registration</i> attribute), 285	
<code>Unassigned</code> (<i>pcapkit.const.http.frame.Frame</i> attribute), 289	
<code>Unassigned</code> (<i>pcapkit.const.http.setting.Setting</i> attribute), 290	
<code>Unassigned</code> (<i>pcapkit.const.tcp.option.Option</i> attribute), 336	
<code>Unassigned_150</code> (<i>pcap-kit.const.ipv4.option_number.OptionNumber</i> attribute), 293	
<code>Unassigned_2</code> (<i>pcap-kit.const.hip.hi_algorithm.HIAAlgorithm</i> attribute), 278	
<code>Unassigned_25</code> (<i>pcap-kit.const.hip.notify_message.NotifyMessage</i> attribute), 281	
<code>Unassigned_27</code> (<i>pcap-kit.const.hip.notify_message.NotifyMessage</i> attribute), 281	
<code>Unassigned_4</code> (<i>pcap-kit.const.hip.hi_algorithm.HIAAlgorithm</i> attribute), 278	
<code>Unassigned_41</code> (<i>pcap-kit.const.hip.notify_message.NotifyMessage</i> attribute), 281	
<code>Unassigned_43</code> (<i>pcap-kit.const.hip.notify_message.NotifyMessage</i> attribute), 281	
<code>Unassigned_45</code> (<i>pcap-kit.const.hip.notify_message.NotifyMessage</i> attribute), 281	
<code>Unassigned_47</code> (<i>pcap-kit.const.hip.notify_message.NotifyMessage</i> attribute), 281	
<code>Unassigned_49</code> (<i>pcap-kit.const.hip.notify_message.NotifyMessage</i> attribute), 281	
<code>Unassigned_5</code> (<i>pcap-kit.const.ipv4.protection_authority.ProtectionAuthority</i> attribute), 293	
<code>Unassigned_512</code> (<i>pcap-kit.const.hip.parameter.Parameter</i> attribute), 284	
<code>Unassigned_578</code> (<i>pcap-kit.const.hip.parameter.Parameter</i> attribute), 284	
<code>Unassigned_6</code> (<i>pcap-kit.const.hip.hi_algorithm.HIAAlgorithm</i> attribute), 278	
<code>Unassigned_6</code> (<i>pcap-kit.const.ipv4.protection_authority.ProtectionAuthority</i> attribute), 293	
<code>Unassigned_609</code> (<i>pcap-kit.const.hip.parameter.Parameter</i> attribute), 285	
<code>Unassigned_65499</code> (<i>pcap-kit.const.hip.parameter.Parameter</i> attribute), 285	
<code>Unassigned_65501</code> (<i>pcap-kit.const.hip.parameter.Parameter</i> attribute), 285	
<code>Unassigned_8</code> (<i>pcap-kit.const.hip.hi_algorithm.HIAAlgorithm</i> attribute), 278	
<code>Unassigned_931</code> (<i>pcap-kit.const.hip.parameter.Parameter</i> attribute), 285	
<code>Unassigned_933</code> (<i>pcap-kit.const.hip.parameter.Parameter</i> attribute), 285	
<code>Unassigned_935</code> (<i>pcap-kit.const.hip.parameter.Parameter</i> attribute), 285	
<code>Unclassified</code> (<i>pcap-kit.const.ipv4.classification_level.ClassificationLevel</i> attribute), 291	
<code>Ungermann_Bass_dia_loop</code> (<i>pcap-kit.const.reg.ethertype.EtherType</i> attribute), 325	
<code>Ungermann_Bass_download</code> (<i>pcap-kit.const.reg.ethertype.EtherType</i> attribute), 325	
<code>Ungermann_Bass_net_debugr</code> (<i>pcap-kit.const.reg.ethertype.EtherType</i> attribute), 325	

Univ_of_Mass_Amherst_0x8065 (pcap-kit.const.reg.ethertype.EtherType attribute), 300
 325
 Univ_of_Mass_Amherst_0x8066 (pcap-kit.const.reg.ethertype.EtherType attribute), 325
 Unknown (pcapkit.const.ipx.packet.Packet attribute), 308
 Unknown_CA (pcapkit.const.hip.registration_failure.RegistrationFailure attribute), 286
 UNKNOWN_NEXT_HOP (pcap-kit.const.hip.notify_message.NotifyMessage attribute), 281
 unquote() (pcapkit.protocols.protocol.Protocol static method), 231
 Unsupported_certificate (pcap-kit.const.hip.registration_failure.RegistrationFailure attribute), 286
 UNSUPPORTED_CRITICAL_PARAMETER_TYPE (pcapkit.const.hip.notify_message.NotifyMessage attribute), 281
 UNSUPPORTED_HIT_SUITE (pcap-kit.const.hip.notify_message.NotifyMessage attribute), 281
 UnsupportedCall, 261
 UPDATE (pcapkit.const.hip.packet.Packet attribute), 282
 Update_Notification (pcap-kit.const.mh.packet.Packet attribute), 310
 Update_Notification_Acknowledgement (pcapkit.const.mh.packet.Packet attribute), 310
 urg (pcapkit.protocols.transport.tcp.DataType_TCP_Flags attribute), 190
 urgent_pointer (pcap-kit.protocols.transport.tcp.DataType_TCP attribute), 189
 USB_2_0 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USB_DARWIN (pcapkit.const.reg.linktype.LinkType attribute), 317
 USB_LINUX (pcapkit.const.reg.linktype.LinkType attribute), 317
 USB_LINUX_MMAPPED (pcap-kit.const.reg.linktype.LinkType attribute), 317
 USBPCAP (pcapkit.const.reg.linktype.LinkType attribute), 317
 Use_for_experimentation_and_testing_253 (pcapkit.const.ipv6.extension_header.ExtensionHeader attribute), 300
 Use_for_experimentation_and_testing_253 (pcapkit.const.reg.transtype.TransType attribute), 332
 Use_for_experimentation_and_testing_254 (pcapkit.const.ipv6.extension_header.ExtensionHeader attribute), 300
 Use_for_experimentation_and_testing_254 (pcapkit.const.reg.transtype.TransType attribute), 332
 Used_by_Novell_NetWare_Client (pcap-kit.const.ipx.socket.Socket attribute), 309
 USER_0 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_10 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_11 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_12 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_13 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_14 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_15 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_2 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_3 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_4 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_5 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_6 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_7 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_8 (pcapkit.const.reg.linktype.LinkType attribute), 317
 USER_9 (pcapkit.const.reg.linktype.LinkType attribute), 318
 UTI (pcapkit.const.reg.transtype.TransType attribute), 332

V

val (pcapkit.protocols.transport.tcp.DataType_TCP_Opt_TS attribute), 191
 Valid_Systems (pcap-kit.const.reg.ethertype.EtherType attribute), 325
 value (pcapkit.protocols.internet.hip.DataType_Param_Payload_MIC attribute), 95
 value (pcapkit.protocols.internet.hopopt.DataType_Opt_ILNP attribute), 122
 value (pcapkit.protocols.internet.hopopt.DataType_Opt_RA attribute), 116

value (`pcapkit.protocols.internet.hopopt.DataType_Option_Type` Laboratory_Systems (pcap-
 attribute), 114 kit.const.reg.ethertype.EtherType attribute),
 value (`pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_ILNP5`
 attribute), 158 VI (pcapkit.const.vlan.priority_level.PriorityLevel
 value (`pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_RAattribute`), 337
 attribute), 152 VIA_RVS (pcapkit.const.hip.parameter.Parameter at-
 value (`pcapkit.protocols.internet.ipv6_opts.DataType_IPv6_Opts_Option_Type85`
 attribute), 150 vid (pcapkit.protocols.link.vlan.DataType_TCI at-
 Varian_Associates (pcap-tribute), 44
 kit.const.reg.ethertype.EtherType attribute), VINES (pcapkit.const.reg.transtype.TransType attribute),
 325 332
 Veeco_Integrated_Auto (pcap- VINES_Echo (pcapkit.const.reg.ethertype.EtherType at-
 kit.const.reg.ethertype.EtherType attribute), tribute), 325
 325 VINES_Loopback (pcap-
 Vendor (class in `pcapkit.vendor.default`), 363 kit.const.reg.ethertype.EtherType attribute),
 VendorNotImplemented, 261 325
 VendorRequestWarning, 266 VISA (pcapkit.const.ipv4.option_number.OptionNumber
 VendorRuntimeWarning, 266 attribute), 293
 verification (pcap- VISA (pcapkit.const.reg.transtype.TransType attribute),
 kit.protocols.internet.hopopt.DataType_MPL_Flags 332
 attribute), 121 Vitalink_TransLAN_III (pcap-
 verification (pcap- kit.const.reg.ethertype.EtherType attribute),
 kit.protocols.internet.ipv6_opts.DataType_MPL_Flags 325
 attribute), 157 VLAN (class in `pcapkit.protocols.link.vlan`), 43
 version (`pcapkit.protocols.application.httpv1.DataType_HTTP_Request_Header_Meta` attribute),
 attribute), 208 333
 version (`pcapkit.protocols.application.httpv1.DataType_HTTP_Response_Header_Meta` attribute), 337
 attribute), 208 VPP_DISPATCH (pcapkit.const.reg.linktype.LinkType
 version (`pcapkit.protocols.internet.hip.DataType_HIP` attribute), 318
 attribute), 80 VPP_DISPATCH (pcapkit.const.reg.transtype.TransType attribute),
 version (`pcapkit.protocols.internet.hopopt.DataType_Option_Type85` attribute), 333
 attribute), 123 VSOCK (pcapkit.const.reg.linktype.LinkType attribute),
 version (`pcapkit.protocols.internet.ipv4.DataType_IPv4` attribute), 318
 attribute), 131
 version (`pcapkit.protocols.internet.ipv6.DataType_IPv6` attribute), 169
 version (`pcapkit.protocols.internet.ipv6_opts.DataType_Dest_Opt_ILNP5` attribute), 160
 attribute), 160 kit.const.reg.linktype.LinkType attribute),
 version (`pcapkit.protocols.link.l2tp.DataType_L2TP` attribute), 38 318
 attribute), 38 WB_EXPAP (pcapkit.const.reg.transtype.TransType at-
 version (`pcapkit.protocols.link.ospf.DataType_OSPF` attribute), 333
 attribute), 41 WB_MON (pcapkit.const.reg.transtype.TransType at-
 version (`pcapkit.protocols.transport.tcp.DataType_TCP_Opt_MP_GARBLE3Data` attribute), 195
 attribute), 195 weight (pcapkit.protocols.application.httpv2.DataType_HTTPv2_HEADE
 version() (pcapkit.protocols.pcap.header.Header attribute), 217
 property), 26 weight (pcapkit.protocols.application.httpv2.DataType_HTTPv2_PRIORI
 version_major (pcap-tribute), 218
 kit.protocols.pcap.header.DataType_Header Wellfleet_Communications (pcap-
 attribute), 27 kit.const.reg.ethertype.EtherType attribute),
 version_minor (pcap- 325
 kit.protocols.pcap.header.DataType_Header WESP (pcapkit.const.reg.transtype.TransType attribute),
 attribute), 27 333
 VersionError, 261 Wiegand_Interface (pcap-
 VersionInfo (class in `pcapkit.corekit.version`), 247 kit.const.arp.hardware.Hardware attribute),

268
 window (*pcapkit.protocols.application.httpv2.DataType_HTTPv2_WINDOW_UPDATE*
attribute), 221
 window_size (*pcap-*
kit.protocols.transport.tcp.DataType_TCP
attribute), 189
 WINDOW_UPDATE (*pcapkit.const.http.frame.Frame* *at-*
tribute), 289
 wrap_comment() (*pcapkit.vendor.default.Vendor*
static method), 364
 WS (*pcapkit.const.tcp.option.Option* *attribute*), 336
 WSN (*pcapkit.const.reg.transtype.TransType* *attribute*),
 333

X

X_25_Level_3 (*pcapkit.const.reg.ethertype.EtherType*
attribute), 326
 X_509_v3 (*pcapkit.const.hip.certificate.Certificate* *at-*
tribute), 273
 X_75_Internet (*pcap-*
kit.const.reg.ethertype.EtherType *attribute*),
 326
 Xerox_IEEE802_3_PUP (*pcap-*
kit.const.reg.ethertype.EtherType *attribute*),
 326
 XEROX_NS_IDP (*pcapkit.const.reg.ethertype.EtherType*
attribute), 325
 XEROX_PUP (*pcapkit.const.reg.ethertype.EtherType* *at-*
tribute), 325
 XNET (*pcapkit.const.reg.transtype.TransType* *attribute*),
 333
 XNS_Compatibility (*pcap-*
kit.const.reg.ethertype.EtherType *attribute*),
 326
 XNS_IDP (*pcapkit.const.reg.transtype.TransType* *at-*
tribute), 333
 XTP (*pcapkit.const.reg.ethertype.EtherType* *attribute*),
 326
 XTP (*pcapkit.const.reg.transtype.TransType* *attribute*),
 333

Z

Z_WAVE_SERIAL (*pcapkit.const.reg.linktype.LinkType*
attribute), 318
 ZSU (*pcapkit.const.ipv4.option_number.OptionNumber*
attribute), 293
 ZWAVE_R1_R2 (*pcapkit.const.reg.linktype.LinkType* *at-*
tribute), 318
 ZWAVE_R3 (*pcapkit.const.reg.linktype.LinkType* *at-*
tribute), 318